

Scanning - Shortwave - Ham Radio - Equipment
Internet Streaming - Computers - Antique Radio

Monitoring Times

A Publication of Grove Enterprises

Volume 28,
No. 11
November
2009

U.S. \$6.95

MT Special:

Radio Buyer's Guide Issue

In this issue:

- Ham Radio Transceivers
- Shortwave Radios
- Scanners
- Antennas
- Also: Weather Radios, CBs, FRS/GMRS and Portable Shortwave



**NOW
AVAILABLE**

AR-ONE

Communications Receiver

The AR-ONE gives law enforcement and government professionals total command of frequencies, modes, tuning steps and more. It is possible to tune in increments of one Hz.

**FOR
PROFESSIONAL
USE ONLY**



**Monitor Any Frequency
from 10 KHz to 3.3 GHz**

**Ultra-stable reference
frequency oscillator (0.1ppm)**

**The AR-ONE is a
new beginning for
wide-range monitors.**

The AR-ONE is designed to support computer controlled operation. Link up to 99 receivers for control by a single PC. The AR-ONE can be used for mobile or fixed monitoring operations.

Surveillance operations are enhanced. Monitoring multiple frequencies is easier and faster. Computer control gives you maximum flexibility and unleashes the many features found in this advanced technology receiver.

The AR-ONE is the right choice for the new world we now monitor.

- Super wide coverage: 10 KHz ~ 3.3 GHz
- 1000 memory channels
- 10 VFOs
- Monitor AM, NFM, WFM, USB, LSB, CW, Data
- Ultra-stable reference frequency oscillator
- Two RS-232C ports
- Control up to 99 AR-ONE Units with one PC
- Triple conversion superheterodyne front end
- Antenna input level readout
- Adjustable BFO
- High intercept +2dBm (-1 dBm above 2.5 GHz)
- Multi IF signal output (10.7 MHz or 455 KHz)
- Excellent sensitivity

The AR-ONE is designed for use by the monitoring professional. The AR-ONE is so advanced, you'll be thinking of new applications for its powerful capabilities.



Authority on Radio
Communications

**The Serious Choice in Advanced
Technology Receivers™**

AOR U.S.A., Inc.
20655 S. Western Ave., Suite 112, Torrance, CA 90501, USA
Tel: 310-787-8615 Fax: 310-787-8619
info@aorusa.com • www.aorusa.com

*Available only to authorized users in the USA.
Documentation required.*

WSS-420 HRPT/CHRPT Weather Satellite System



WiNRADiO has added a new product to its large range of innovative receivers and radio monitoring and surveillance systems: The WSS-420 turn-key weather satellite monitoring system.

The WSS-420 system is a fully integrated package, including an antenna dish, rotator, down-converter, receiver and automatic tracking software. This is complemented by an optional image-processing software application which provides a number of meteorological products such as standard NOAA Contrast Enhancement Curves, Sea Surface Temperature (SST), Land Surface Temperature (LST), Normalized Differential Vegetation Index (NDVI), RGB Mixers and others.

Individual parts of this system are also available for third-party integration. Check out for example our rugged, reliable EL-AZ antenna rotator with ± 0.5 degree positioning accuracy and its compact, USB-interfaced control unit.

- Fully-integrated hardware/software weather satellite solution
- Compact stand-alone system
- Robust, heavy-duty rotator and tripod
- Easy installation, calibration and configuration
- Automatic satellite dish positioning
- Automatic real-time orbital satellite tracking
- Automatic reception scheduling and image storage
- Full support for multi-spectral AVHRR data
- Full support for NOAA (HRPT) and Feng Yun-1D (CHRPT) satellites
- Advanced image-processing software application
- Automatic updating of satellite tracking data from the Internet
- Automatic clock synchronization from the Internet
- AVHRR data export in NOAA Level 1B (HRPT) file format



MT Special: Radio Buyer's Guide Issue

With the Christmas season just around the corner, many readers are considering what they'd *really* like to see under the tree. To help with this, *MT* offers a special Radio Buyer's Guide written by hams who have tested and reviewed radio-related products for many years.

On Our Cover: *Some of the finest radios on the market. But which one is right for you? This issue will help you decide!*

C O N T E N T S

Buying a Ham Radio Transceiver 8 By Kirk Kleinschmidt NT0Z

Former QST assistant editor, current amateur radio columnist for Popular Communications, and a ham for 32 years, Kirk has handled, tested, and reviewed, more ham gear than most of us can imagine. Now, you get the benefit of his experience as he walks you through the purchase of your next amateur radio transceiver.

MT's Guide to Buying a Used Receiver 11 By Bob Grove W8JHD

Bob Grove knows shortwave radios, he's been reviewing them for decades, and he's seen and used them all. If you're looking for a portable, table-top set or software defined radio, Bob tells you how to look for the best deal among all the great used models now on the used radio market.

Expert's Guide to Buying a Scanner Radio 12 By Larry Van Horn N5FPW

Digital technology has put public service monitoring in a state of flux across the U.S. So, when it comes to choosing the kind of scanner that will be the most useful where you live, you could use a little expert advice. Nobody knows scanners like *MT's* own Larry Van Horn. Listen up!

Trends in Radio 13 By Ken Reitz KS4ZR

There's a whole world of radios that we use every day: Weather Radios, CB sets, FRS/GMRS radios and pocket-sized portable shortwave sets. Ken details the pluses and minuses of some of the most well-known brands. He also looks at trends among the major manufacturers so you'll know what to look for before you buy.

Expert's Guide to Buying an Antenna 15 By Bob Grove W8JHD

Bob has been designing and building antennas for HF, VHF and UHF for decades. He's used nearly every type of antenna made and now you don't have to "Ask Bob." He'll tell you!

A Life in Service to Amateur Radio 18 By Harry Dannels W2HD

The former 5-time ARRL president, and past president of QCWA, reflects on a life of service to amateur radio that took him around the U.S. and the world representing American hams during his 10 year term. Harry helped forge policies and regulations that gave us, among other things, the WARC bands (30, 17 and 12 meters). He may not look like the kind of guy who would jump off a garage roof to swing from a rope on a tree but then, maybe you don't know W2HD.



Photo by Ken Reitz KS4ZR

Reviews

Uniden BCD996XT
21st Century Scanner
Technology



TABLE OF CONTENTS

Departments:

| | |
|------------------------|----|
| Letters | 4 |
| Communications | 6 |
| Stock Exchange..... | 76 |
| Advertisers Index..... | 76 |

First Departments

Getting Started

| | |
|---|----|
| Beginners Corner | 20 |
| <i>How to Beat the Dismal Sunspot Cycle: Go Digital</i> | |
| Global Nett | 22 |
| <i>Looking for South Africa? Try the Internet!</i> | |

| | |
|--------------------------|----|
| Scanning Report | 24 |
| <i>Taming Talkgroups</i> | |

| | |
|---|----|
| Ask Bob | 27 |
| <i>Atomic clocks; coax cable lifespan; Slinky® antennas and more.</i> | |

| | |
|--|----|
| Utility World | 28 |
| <i>Around the bands: Odds and Ends</i> | |

| | |
|--------------------------------------|----|
| Digital Digest..... | 31 |
| <i>Marine Listening with SITOR-B</i> | |

| | |
|------------------------------------|----|
| Programming Spotlight..... | 32 |
| <i>Everything Old is New Again</i> | |

| | |
|---|----|
| QSL Report | 34 |
| <i>Radio St. Helena's Annual "Party-on-the-Air"</i> | |

| | |
|----------------------------|----|
| English Language SWG | 35 |
|----------------------------|----|

| | |
|--------------------------------|----|
| MTXtra Spanish Schedules | 48 |
|--------------------------------|----|

Second Departments

| | |
|---|----|
| Milcom | 52 |
| <i>North American Aerial Refueling Frequencies</i> | |
| Fed Files | 54 |
| <i>2009 Fed Files Wrap-up</i> | |
| Boats, Planes, Trains..... | 56 |
| <i>"Black Boxes": Cockpit Voice and Flight Data Recorders</i> | |
| Below 500 kHz | 58 |
| <i>LF Receiving Antennas, Part II</i> | |
| Outer Limits..... | 59 |
| <i>The Filipino Monkey - Malicious Unlicensed Jamming</i> | |
| On the Ham Bands..... | 60 |
| <i>Transversion Conversion and Other Diversions</i> | |

Technical Departments

| | |
|--|----|
| Antenna Topics | 62 |
| <i>Build Your Antenna Library; an Easy VHF-UHF Antenna</i> | |
| Radio Restorations..... | 64 |
| <i>An S-20 R "S" Meter and Introducing the BC314/BC-344</i> | |
| On the Bench..... | 66 |
| <i>"Sky-Wires and Inhalers" Part 2: From Antenna to Receiver</i> | |
| Sky Surfing | 68 |
| <i>Amateur Radio Satellite Report</i> | |
| First Look..... | 70 |
| <i>Uniden BC996XT :21st Century Scanner Technology</i> | |
| What's New | 74 |
| <i>New Products from MP Antennas</i> | |



MONITORING TIMES
(ISSN: 0889-5341;
Publishers Mail Agree-
ment #1253492) is
published monthly by
Grove Enterprises, Inc.,
Brasstown, North Caro-
lina, USA.

Copyright © 2009 Grove Enterprises, Inc. Periodicals postage paid at Brasstown, NC, and additional mailing offices. Short excerpts may be reprinted with appropriate credit. Complete articles may not be reproduced without permission.

Address: 7540 Highway 64 West,
Brasstown, NC 28902-0098
Telephone: (828) 837-9200
Fax: (828) 837-2216 (24 hours)
Internet Address: www.grove-ent.com or
www.monitoringtimes.com
Editorial e-mail: editor@monitoringtimes.com
Subscriptions: order@grove-ent.com

Subscription Rates: \$32.95 in US; \$42.95 Canada; and \$58.95 foreign elsewhere, US funds. Label indicates number of issues left. Renewal notice is cover sheet 3 months before expiration. See page 76 for subscription information.

WRITE FOR MONITORING TIMES:

See how at
www.monitoringtimes.com/html/write_for_mt.html or
write to editor@monitoringtimes.com

Postmaster:
Send address changes to *Monitoring Times*,
7540 Highway 64 West, Brasstown, NC
28902-0098.

Disclaimer:

While *Monitoring Times* makes an effort to ensure the information it publishes is accurate, it cannot be held liable for the contents. The reader assumes any risk for performing modification or construction projects published in *Monitoring Times*. Opinion or conclusions expressed are not necessarily the view of *Monitoring Times* or Grove Enterprises. Unsolicited manuscripts are accepted. SASE if material is to be returned.

Subscription Questions?
belinda@grove-ent.com

Owners

Bob and Judy Grove
judy@grove-ent.com

Publisher

Bob Grove, W8JHD
bobgrove@monitoringtimes.com

Managing Editor

Rachel Baughn, KE4OPD
editor@monitoringtimes.com

Assistant and Reviews Editor

Larry Van Horn, N5FPW
larryvanhorn@monitoringtimes.com

Features Editor

Ken Reitz
kenreitz@monitoringtimes.com

Art Director

Bill Grove


Advertising Svcs.

Beth Leinbach
(828) 389-4007
bethleinbach@monitoringtimes.com

EDITORIAL STAFF Email firstlast@monitoringtimes.com

TJ "Skip" AreyOn the Ham Bands
Rachel BaughnLetters to the Editor
Kevin Carey.....Below 500 kHz
Mike Chace.....Digital Digest
Marc EllisRadio Restorations
Bob Grove.....Ask Bob
Jeffrey Lichtman.....Sky Surfing
Chris Parris.....Fed Files
Ken ReitzFeatures Editor
.....Beginners Corner
.....Communications
Iden RogersPlanes
Clem SmallAntenna Topics
Doug SmithAmerican Bandscan

Hugh StegmanUtility World
Ernest RoblTrains
Gayle Van Horn.....Frequency Manager
.....QSL Corner
Larry Van HornMilcom
.....Reviews Editor
.....What's New?
Loyd Van Horn.....GlobalNet
Dan Veeneman.....Scanning Report
Ron WalshBoats
Fred WatererProgramming
.....Spotlight
George ZellerOuter Limits



LETTERS

editor@monitoringtimes.com

September's Mystery Antenna

In December 2008, when my husband Harry Baughn and I were visiting San Diego, we took a trolley ride to Coronado Island for lunch. However, when our return trolley failed to show up on time, we discovered that the Coronado Bay Bridge had been closed because two people were on the bridge threatening to jump. The evening's rush hour traffic and our friendly trolley driver were detoured around the bay on the Silver Strand highway, which took us past the wonderful Wullenweber array just at sunset that I posted in September's *Letters*.

Fifteen people correctly identified the type and the location of this antenna: Dave Anderson, Bruce Ames, Dave Billeci, Deon, Gary, Rick Herndon, Donald Kalinowski, Jeff Lee, Bruce Oltman, Rich Ortloff, Denny Reeves, Gordon Schlesinger, Gary Shapiro, Tim W6TWR, and Dave Wilcox (winner of the 3 months' subscription to *MT Express*). Congratulations!

Gordon Schlesinger, W6LBV, is a local resident who remembers the bridge closing – fortunately, a rare event. He adds, “The Wullenweber is an HF direction finding system usually constructed and used by the U.S. Navy. The two concentric circles of vertical dipole antennas that can be seen in the picture give it utility on two different portions of the HF band... There's some good background information on the Wullenweber and similar DFing arrays in: www.mapability.com/ei8ic/rhombic/wullen.php”

Jeff Lee claims the antenna was even featured in a couple of episodes in the first season of “John From Cincinnati.”

A couple of other locals wrote, as did readers who had been stationed in the area years ago. Deon said “Of course this antenna being in my backyard, I was very curious when I first moved here. This is the Imperial Beach Radio Receiving Facility, CA. The antenna is an AN/FRD-10 HFDF Wullenweber array (aka “Elephant Cage”). The array was for receiving signals in the 2-30MHz range operated by the NCTC and NSGD Dept. (Built in 1964 and used till 1999).”

Tim W6TWR, wrote: “I just went to this facility two weeks ago and asked the Main Gate security if there were tours available of the facility and got the standard answer of ‘I don't know.’”

Everyone enjoyed reminiscing about these rhombic direction-finding antennas, even those who weren't sure of the location. Derek Helling attached a picture of “the one at RAF Chicksands in Bedfordshire, UK, taken in the 1960s, I believe. ... I used to see this antenna regularly as my parents lived in nearby Biggleswade, and

my grandmother lived in Shefford. The local nickname was ‘Elephant Cage.’”



There was a lot of speculation about how many antennas with this configuration still stand and how many are still being used. Readers mentioned operating or seeing similar antennas at other locations, such as Homestead AFB, FL; Misawa, Japan; San Vito dei Normanni Air Station, Italy and Edzell, Scotland; Goodfellow AFB, San Angelo; Elmendorf AFB Alaska; Bramstedtlund, Germany; Scaggs Island, California; Oahu and Honolulu, Hawaii.

Dave Anderson, Bruce Ames, and others doubt this particular antenna is being used, even though cars were present at the center building. Dave says that this one “is located on the Silver Strand Training Complex, which is a principal area for training special forces, though the antenna is no longer used. There are apparently two of these still in use at Elmendorf, Alaska, and at Misawa, Japan. Most of the others have become landmarks. I once was stationed in Augsburg, Germany where we used one of these – it's still there, surrounded by what looks like an industrial park.

“A particularly unique use of one is in the Philippines, where they've made it into an amphitheatre.” (photo below)

Frank McJunkins said he had the pleasure of using the antenna at Clark AFB in the Philippines. He also said, “I heard the FCC had been using the one at Bellingham, WA prior to its



<http://static.panoramio.com/photos/original/5414611.jpg>

being torn down a few years back, so maybe that is who the current tenant is.”

Francois Michaud said, “I had the chance to visit the one in Corea, Maine. It is very impressive in size.” However, that antenna was demolished in August of 2001.

Canadian Jon Huneault, VE1FTL, of Nova Scotia says, “Well I'll be darned! That's an AN/FRD-10 Circularly Disposed Antenna Array (CDA) affectionately known to the military as a ‘Fred-ten,’ and to techies as a Wullenweber Array.

“I worked at both of Canada's sites in Gander (Newfoundland) and Masset (BC) while I was in the Canadian Forces ... Both our sites had nicknames: Masset was known as the ‘Elephant Trap’ and Gander was the ‘Turkey Farm.’”

Bruce Ames confesses to being a former “NSA spook,” living California. Of course he nailed it, and included some other interesting information:

“The antenna in question is used for ‘huff-duff’ (HFDF) High Frequency Direction Finding and they were used by virtually all branches of the Department of Defense intelligence agencies during the cold war reporting to NSA (National Security Agency). The FRD-10 was code named ‘Classic Bullseye’ ...

“I was a Cryptologic Technician (maintenance) at many places around the world during the cold war. I worked on the equipment on the Wullenweber system at Naval Security Group Sabana Seca Puerto Rico, which was roughly thirty miles west of San Juan, in the mid-'70s.”

As to whether any sites are still active, Bruce says, “Nope, per my Crypto contacts all of the Wullenwebers have been de-established and just about every one of them has been taken down. There is a story that one may still be operating in Japan; however, that has never been verified. They were used only for receiving and would always be located far away from any transmitters.

“Because the Wullenwebers were so sensitive, periodic tests were done by other Crypto techs using test gear at the side of the access road to the [PR] site measuring any radiated electrical noise from a vehicle. If your vehicle was above a certain very low threshold, your vehicle was not allowed on the site and one had to hoof it.”

That's all we have room for in this discussion of our mystery antenna. We have lots more information links and memories of other Wullenweber sites worldwide, which we will post for your further reading. Just go to the *MT* homepage at www.monitoringtimes.com for the link.

Universal Radio — Quality equipment since 1942.

YAESU VR-5000



The **Yaesu VR-5000** provides sophisticated wideband reception. Coverage is from 100 kHz to 2600 MHz (2.6 GHz) less cellular, in AM, FM-N, FM-W, LSB, USB and CW. This radio features a real-time bandscope and you get 2000 alphanumeric memories grouped into 100 banks. Optional aids such as a DSP unit, voice synthesizer and digital voice recorder are available. Jacks on the back panel include: Mute, 13.8 VDC input, External Speaker, 10.7 MHz IF Output, Antenna Input A (SO-239 50 ohm) & B (Hi Z 450 ohm), CAT Interface Jack (4800/9600/57600 bps). The VR-5000 comes with the PA28B 117 VAC adapter and a DC power cord. This radio is only 7.1 x 2.75 x 8 inches 4.2 Lbs. Please visit our website for full specifications, color photos and current price.


ACCESSORIES

- #3545 **DSP-1** DSP Notch/NR/Bandp. \$119.95
- #0560 **DVS-4** Digital Voice Recorder 49.95

YAESU

HANDI-TALKIE EMERGENCY GO-BAG

FREE HT *Go-Bag* with the purchase of any new Yaesu HT from Universal Radio for a limited time.




This orange insulated bag is great for creating an HT "Emergency Go Bag" for your Yaesu handi-talkie. There is plenty of room for your radio, batteries, accessories, *Repeater Directory* and more. The top is zippered and it has a carry strap plus an open pocket on the front panel. 8 x 6 x 5 inches. Orange with Yaesu logo. Radio and directory shown are not included. This carry bag will be included **FREE** with your purchase of any new Yaesu HT transceiver from Universal Radio for a limited time.

This case may also be purchased separately. Order #0429 \$7.95

YAESU

VR-500 PKG




The **Yaesu VR-500** is the first to provide wideband coverage plus single sideband capability in such a small and capable package. Coverage is solid from 100 kHz to 1300 MHz (1.3 GHz) less cellular, in AM, FM-N, FM-W, LSB, USB and CW. You get 1000 regular memories (10x100) plus tuning steps from 50 Hz to 100 kHz. Other features include: backlit keypad, priority, power-off timers, adjustable battery saver, 60 channel bandscope, attenuator, dual watch, alphanumeric recall, bank scanning Smart Search™. The VR-500 operates from two AA cells. Includes BNC antenna, hand strap and belt clip. This new **Yaesu VR-500 "PKG"** configuration also includes the NiCd battery and wall charger. Only 2.3 x 3.7 x 1" 8 oz. Please call or visit our website for more information and current price.

ACCESSORIES

- #4037 **ADMS3** Win Software & PC cable \$37.95
- #4035 **CSC72** Carry Case 19.95
- #1693 **EDC5B** DC Cable +Cigar Plug 23.95
- #3116 **EDC6** DC Cable 6.95
- #0353 **FNB79** NiCad Batt 2.4V 9.95
- #0594 **NC60B** AC Adapter 13.95

YAESU

FT-857D



FREE Yaesu orange mug with FT-857D/897D.



The **Yaesu FT-857D** is the world's smallest HF/VHF/UHF multimode amateur transceiver covering 160 m to 70 cm with 100 watts on HF. Now with 60 meters and DSP2 built-in.

FT-897D



The **Yaesu FT-897D** is a multi-mode high-power base/mobile transceiver covering 160 m to 70 cm including 60 meters. Now with TCXO.

FT-817ND



FREE Yaesu canvas urban case with FT-817ND.

The **Yaesu FT-817ND** is an improved, deluxe version of the hugely popular FT-817. It includes 60 meter coverage plus the new high capacity FNB-85 battery. This radio has an excellent shortwave receiver built-in and is a fully self-contained, battery-powered, low power amateur MF/HF/VHF/UHF QRP transceiver.



Universal Radio, Inc.
6830 Americana Pkwy.
Reynoldsburg, Ohio
43068-4113 U.S.A.

☎ 800 431-3939 Orders & Prices
☎ 614 866-4267 Information
☎ 614 866-2339 FAX Line
✉ dx@universal-radio.com

www.universal-radio.com

◆ Visit our website for more exciting new and used shortwave radios.

- Visa
- MasterCard
- Discover
- JCB
- Prices and specs. are subject to change.
- Special offers are subject to change.
- Returns subject to a 15% restocking fee.
- Prices shown do not include shipping.



COMMUNICATIONS

by Ken Reitz

"Communications" is compiled by Ken Reitz KS4ZR (kenreitz@monitoringtimes.com) from news clippings and links supplied by our readers. Many thanks to this month's fine reporters: Anonymous, Rachel Baughn, Ralph Johnson, and Larry Van Horn

SHORTWAVE/AMATEUR RADIO

Tale of Two Ham Antenna Companies

Last month signaled the end of the road for GLA Systems, maker of the Texas BugCatcher mobile ham antenna. In a statement posted on his website, owner Henry Allen K5BUG said, "It's been a fun 30 years, but it is time to hang it up. I would like to thank everyone who has made this experience possible...it has been a great trip down a long road."

The posting gave a timetable for the company's final months: "All orders received before October 31, 2009 will be filled. Effective November 1, 2009, only orders for items that are in stock at the time will be accepted. Effective December 31, 2009, the toll free line 800-588-2841, will be discontinued."

Meanwhile, long-time amateur radio antenna manufacturer Cushcraft was purchased July 31, 2009 by MFJ Enterprises, Inc. of Starkville, Mississippi. A statement released by the new owner, Martin F. Jue, president and founder of MFJ, stated that, "We are excited to have the Cushcraft amateur radio antennas product line alongside our other five companies."

MFJ had previously bought Hy-gain antennas in 2000 and produces a line of MJF-branded antennas as well. Cushcraft's line of 50 antenna products, ranging from HF through UHF and including verticals as well as horizontal beams, will be added to the MFJ catalog. Mr. Jue stated that Cushcraft models would continue to be made in Manchester, New Hampshire.

FCC Grants Experimental Licenses

The FCC was busy back in September issuing experimental licenses for various operations, including the Boeing Company, "for testing the radiated field effects of PEDs [Personal Electronic Devices] on aircraft electronic components and systems...and a ground cellular system on board commercial aircraft." Lockheed Martin received an experimental license "for identifying and geo-locating low power and high ground based signals."

While you may not have heard of L-3 Communications, the company is on the Fortune 500 list and receives a lot of money from the Pentagon for various high-tech, missile-related programs. The company received the call sign WE3XYO to operate in 902-928 MHz to test and evaluate command and control of an unmanned aerial vehicle.

Powerwave Technologies, Inc. received a license to operate in 2541.5-2561.5 MHz and 2630.5-2650.5 MHz for "testing WiMax mobile user handover and coverage operability in a network configuration."

And, the University of Puerto Rico at

Mayaguez received a number of licenses at 9.410 GHz for testing lower-tropospheric weather radar to study rainfall.

AM/FM/TV BROADCASTING

KHCM-AM Goes CRI

An article in the Honolulu *Star-Bulletin* from September 4, explained the story of two seemingly strange bed-fellows: local AM station, KHCM 880 kHz (owned by Christian broadcasting conglomerate Salem Communications) and China Radio International (CRI), a radio service controlled by the Communist Party of the People's Republic of China. The agreement brings CRI's full schedule of programs in Chinese, English, Korean and Japanese to the 24/7 station, operating under an agreement between Salem and California-based R & C Productions.



Paradise and CRI Too: KHCM-AM 880 Switches to China Radio International for programming. (Courtesy: KHCM-AM)

The article quoted CRI officials, at a gathering to promote the programming change, as saying that China does not prevent listeners in China from hearing VOA and BBC shortwave broadcasts; and a senior company official from Salem described CRI broadcasts as "not intensely political." It turns out that the whole deal is simply a commercial venture; CRI is merely buying all of KHCM-AM's broadcast time. Meanwhile, sister station KHCM-FM continues its flag-waving, all-American, all-country format under the red, white and blue "Country 97.5" logo.

Pirate Cat Radio Gets City Approval

It's hard to imagine a city where the local pirate radio station is not only taken for granted by local citizens, but publicly praised by city officials. But then, San Francisco is not an ordinary city. The San Francisco *Chronicle*, in its on-line site www.sfgate.com, reports that a member of the local board of supervisors dropped by the radio station/coffee house a couple of months ago to present the station with a certificate of



Pirate Cat Radio gets approval from San Francisco officials, but will the FCC pet the nice kitty? (Courtesy: Pirate Cat Radio)

commendation, on behalf of the whole board, for, among other things, "[Pirate Cat Radio's] trailblazing efforts toward freeing the airwaves from corporate control, providing the community with training in radio broadcasting skills, [and] empowering voices ignored by traditional media outlets..."

Cal. TV Station Can Air 20 Channels

A report on [TV Technology.com](http://TVTechnology.com) from early September details how a low-powered community TV station in San Jose, California, KAXT-CA, is using available technology to allow it to broadcast up to twenty MPEG2 video and audio channels within its allotted 19.39 Mbps signal. The commercial-supported station's main intent is to provide more alternative programming, including multicultural content, expected by the area's diversified population, within the station's limited budget. The station believes the concept can be a business model for similar low-power TV stations nationwide.

The station currently programs 12 video channels and 4 audio channels including Cool Music Network (world music videos), Que Dong (Vietnamese), Tempos Finales (Spanish Christian), Bahia TV (Brazilian Portuguese), Colours TV (multi-cultural), i2TV (Internet to TV), Jewelry TV (jewelry shopping), Peanut TV (pet care), Coastal TV (California coastal tourism channel), and Corner Store TV (shopping).

Eco-Terrorists Blamed in Downed Towers

Many media outlets reported the toppling of two of four radio towers belonging to KRKO-AM in Snohomish, Washington in early September. Most articles, including those written by the Associated Press, blamed "eco-terrorists," specifically, a group calling itself Earth Liberation Front (ELF) for the act. And, why not? A large banner left at the site indicated ELF was behind the attack.

But, the *Seattle Times*' staff reporter Sara Jean Green, dug a little deeper. Even though a web site, purporting to speak for the ELF claimed responsibility for the attack, the *Times* quoted the general manager of the family-owned, sports-format radio station as being in doubt. He said he suspected "disgruntled locals" who had just recently lost a court case against the station's tower site which is located on farm land.

The manager told the *Times* that the family will replace the towers and "accelerate plans to add several more." The towers had been brought down with the aid of a large piece of earth-moving machinery that had been left at the site, apparently part of the new construction plans.

According to the *Times* article, there were plenty of local people annoyed with the installation and the fact that the family had just received permission from the FCC to construct a second 50kW AM station at the site. Residents, according to the article, had been complaining of all manner of RF interference they blamed on the station including sportscasts coming in on a local church's PA system and electric garage and car doors randomly opening.

BusRadio? What Next!

Because school buses are already a terrible place to be stuck for 30 or 50 minutes twice a day for everyone involved, why not make it even worse by piping kid-oriented programming over the buses' loudspeaker systems? That's been the trial run for a company calling itself BusRadio which features not just pop music, commercials, public service announcements and games, but offers prizes and cash to students for texting answers to quizzes. Another fun feature is texting a "shout-out" to your bus driver, girlfriend or secret heartthrob. It makes riding the bus just like a fun-filled TV sitcom.



BusRadio: Games, Prizes, Music...It's like being at home with 80 of your closest friends and enemies. (Courtesy: BusRadio)

Now, with all the data in (including a little-publicized public comment period from the FCC, a raft of scornful comments from a Harvard-based organization called Campaign for a Commercial-Free Childhood, and high praise from various bus drivers who might rather lash the little darlings to their seats) the FCC is weighing the chance for the "service" to go nationwide. Since BusRadio is the only company with such a plan, it hopes to enjoy a monopoly on taxpayer-funded school transportation. So, what's next? BusTV, of course!

SATELLITES

Chinese Space Debris Haunts ISS

Remember that non-functioning Chinese weather satellite that they used for target practice in space back in 2007? The International Space Station is routinely haunted by debris from that event and other accidents and ineptitudes while NASA tries to maintain a no-junk zone around the ISS that extends out to 15 miles around it, in addition to a one-half mile zone above and below it. Still, Space.com reports that "...part of a three year-old slab of a European rocket body," was said to have come within one mile of ISS recently.

Cash-strapped City Taxes Dish Viewers

Omaha, Nebraska, like most American municipalities these days is strapped for cash. Falling property values have depleted the tax base, operating costs continue to rise, and budget decisions need to be made. What to do? The



Omaha wants to take a bite out of DISH and DirecTV viewers. (Courtesy: DISH Network and DirecTV)

friendly folks at the National Cable Telecommunications Association (NCTA), cable-TV's national lobbying group, had a brilliant idea: tax satellite-TV viewers! One city councilman is fronting the scheme that proposes a \$50/year fee that, he estimates, would raise \$2 million in much needed revenue.

The Satellite Broadcasting and Communications Association (SBCA), the nation's satellite-TV lobbying group, was not amused. Citing FCC exemption from special taxes, the SBCA warned the city council that they would fight the tax. Omaha, seeking to slither around the FCC's exemption, is calling the tax a "safety inspection fee." Stay tuned for the showdown in Omaha.

The NCTA apparently went door-to-door to states and municipalities trying to drum up taxes for satellite-TV viewers. They were in Sacramento, California, in early September, asking state legislators to tax the state's estimated 3.6 million satellite-TV customers, citing the mouth-watering figure of \$170 million that could flow into the state's empty treasury. But, the scheme ran out of time when it failed to get on the legislative calendar within the legal time limit.

New GPS Sat Goes Live

Lockheed Martin announced September 3, the operational status of the last in a series of eight modernized GPS satellites for global military and civilian use. Dubbed GPS IIR-21 (M), the satellite was launched by the Air Force August, 17. According to a press release by the company, the program is on track to launch the first GPS IIIA satellite in 2014. It must be time to finally bury the hysteria generated a few months back about the nation's GPS constellation going down.



Lockheed Martin GPS IIRM (Courtesy: Lockheed Martin Corp.)

PUBLIC SERVICE

San Antonio Scanner Channels Restored

The city of San Antonio, Texas, hatched a plan to bar the media from listening in to dispatches from the fire department and Emergency Medical Services (EMS). Reason given was so that the city could comply with provisions in the Federal Health Insurance Portability and Accountability Act of 1996. The theory was that the identity of individual patients would be compromised through in-the-clear transmissions.

But, according to an editorial in the San Antonio *Express-News*, the city found a way to keep the dispatch channels open to the press while keeping patient information private through the use of channels that are blocked to public reception. The paper had expressed a fear that closing all dispatch channels to the press would have "made it seem as though the city was trying to avoid scrutiny of its emergency services, scrutiny that in recent years has resulted in controversy and a review of EMS protocol."

Scientific American Examines Interoperability

The September issue of *Scientific American*, available on line at www.scientificamerican.com, examined the difficulties of developing a nationwide system of radios for first responders. The article noted that even though it's been eight years since 9/11, there are few local systems capable of allowing police and fire/rescue services to talk with one another, let alone any such nationwide system in place. The excellent article spells out the problem of having only one company so far, with a design that meets the criteria for such a system as set by the Department of Homeland Security.

It further examined the slow pace of the transfer of the former analog TV band to be developed as the place for such communications and the fact that commercial ventures bidding for the space wanted to be granted priority over public service agencies, even during an emergency, for its use.

7,432 Cell-phone Drivers Ticketed in NYC

The Washington *Post* noted that one day this past summer New York City police staged a 24 hour crackdown on violators of the city's law against driving and using a cell phone that is not a hands-free device. While on an average day the NYPD issues 580 such tickets, during this particular day they wrote 7,432 tickets which, at \$130 a pop, brought the city nearly \$1 million in revenue. Omaha and California, take note!

Bug-Killer Radio

Finally, *Radio World* on-line reported August 12 that KroneHit Radio, in Vienna, Austria was transmitting more than the usual radio fare this past summer. The station is said to have imbedded a 14.850 Hz tone (the 27th harmonic of a mosquitoes buzz), intending to imitate the buzz of a female mosquito, in its audio signal aimed at driving away all mosquitoes within a 5 meter radius of the radio. The station apparently warned that the effect does not work if the listener is wearing headphones.

Expert's Guide to Buying an HF Transceiver

By Kirk A. Kleinschmidt, NTOZ

Big or small? DC-to-daylight or HF only? New or used? Kit-built or manufactured? Base or mobile? Ham-bands only or SWL, too? Standalone or PC required? These days, buying the right rig can be amazingly complicated. Here's some advice on making the best choice.

Finding My Way

As a teenager in the late 1970s, choosing my first rig was a lot simpler than it is today. The internet, in its infancy, was "military only" and the worldwide web was more than a decade away. Like computers, radios were much more expensive (see sidebar) and my \$3 an hour after-school job had to pay for gas and non-radio goodies.

Information about radios – used and new – came from magazines (*QST*, *CQ*, *73* and *Ham Radio*); your Elmer, if you had one, and your ham radio buddies and fellow club members. These are still good resources today, despite the fact that the number of available radios and potential information sources has skyrocketed.

In an era with a Morse code requirement for HF access and unpublished exam questions, learning to be a ham seemed to require more one-on-one instruction. So, most followed the lead of their Elmers. Consequently, if your Elmer was a VHF guy, you were a VHF guy. If he was a DXer, you were a DXer. And so on.

Buying radio gear followed suit. I'm sure more than a few hams lusted after their Elmer's gear. I know I did! My first Elmer had a Swan 350 HF transceiver and a tri-band beam. Although its performance is eclipsed by the least expensive transceivers available today, I will never forget the sounds of faraway DX stations coming from the speaker and the eerie, warm glow of the dial lamps.

My second Elmer was an Old-Timer and a real techie. He had a pair of Drake Twins and, later, a Drake TR-7/R-7 setup with every option. After he switched to the TR-7, he lent me his Twins so I could operate split-frequency mode on 40-meter SSB during DX contests, something my trusty Tempo One couldn't do without an accessory VFO.

Made by Yaesu, and a veritable clone of the FT-101, the Tempo One was my first real radio. I worked all summer landscaping the huge lawn at our new house, and my Dad surprised me with the Tempo in the fall of that year. Although its sale did pay my tuition for one semester at college, I wish I still had it for the sake of nostalgia!

Reminiscing aside, how can you choose a suitable radio today? Even when accounting for

the vastly expanded selection and rapidly evolving technology, the basics of buying a radio are surprisingly similar. Whether it's generated by a vacuum tube and a 1930s crystal oscillator or a newfangled software-defined radio (SDR), the essence of radio is still radio. So let's get started!

Define Your Interests

Before you reach for your VISA card, be sure to actually think about your interests – what they are now and what they're likely to be in the near future. At the most basic level, if you're simply interested in chatting with your friends on the local repeater, looking at contest-grade HF transceivers isn't necessary, and vice-versa. On a subtler level, however, you should be as detailed as possible when surveying your interests. Make a list so you don't forget when you're mesmerized by the shiny chrome and the blinking lights when you get to the showroom!

Do you have a home shack, or will hassles with the neighborhood association force you to operate portable or mobile? And, if you can reasonably operate from home, does your desire to operate from your camper suggest a compact portable transceiver that can also be easily hooked up at home? If you're not expecting to do a lot of Morse code work, whether a rig has silky smooth, full-break-in CW isn't really relevant. You get the idea.

Think about bands and modes, too. If HF and SWLing are your main interests, an HF transceiver that has a general-coverage receiver will do nicely and save you the expense and complexity of buying an HF rig that also covers VHF and up. Conversely, if you need a single rig that does everything, a compact dc-to-daylight transceiver is probably in your future.

If you require certain features such as a rig that can transmit RTTY with a dedicated FSK keying input (as opposed to the audio from your PC) or provisions for separate receive antennas (good for low-frequency reception or contest operation), be sure to note them in your shopping checklist because some features are difficult or impossible to add later.

Price and Relative Performance

When discussing buying a "starter radio," most of us tend to think about price, specifically, buying a starter radio that will work well enough to get started without breaking the bank. However, some hams are fortunate enough to "start" with a \$10,000 transceiver...or a \$3,000 transceiver...whatever. If that's your reality,

lucky you! The really interesting thing is that radio gear has never been more affordable and performance has never been better! Regardless of price, today's radios offer enough features and performance to get the job done. They're all stable and they all produce clean, usable signals.



Icom 718: Great "starter" rig for new hams with plenty of room to grow. List price: \$812, discounts bring it down to \$579. (Courtesy: Icom America)

There's quite a range between the price of the most affordable HF transceiver and the most expensive. Using ICOM's lineup as a guide (just because I'm familiar with it), the entry-level IC-718 – full-featured, with general-coverage receive and plenty of bells and whistles – can be purchased for \$579 new. The IC-7800, ICOM's flagship radio, costs about \$10,500! One's a Toyota Corolla, the other's an Aston Martin – but both are cars that do essentially the same things. The 7800 offers better performance and some extra bells and whistles but, thanks to today's technology and manufacturing practices, there are few contacts that couldn't be completed by hams using either rig.



Icom 7800: For the ham who has/wants everything. List price: \$14,000, discounts bring it down to \$10,500. (Courtesy: Icom America) (Courtesy: www.w4rt.com)

When it comes to making your decision you'll have to evaluate your budget and any additional specific requirements and interests. If you're truly just getting started and need to explore the wide world of Amateur Radio – a little of this, a little of that, a friendly ragchew here, a little DXing there – any modern entry-level radio will work like a champ. If you're starting out with a competitive bent and want to dive deeply into every weekend contest

you can find, a competition-grade rig – with a competition-grade price – may be necessary.

You can't beat the Aston Martin in a cross-continent race with a Corolla, but you can certainly drive from coast to coast while thoroughly enjoying the ride! And, if you only have \$600 to spend, the choice is easy!

Gathering Information

Before we get into some specifics, let's take a look at the process of finding information on, and getting input about, which radio to buy. In my experience, most hams are pretty good at this part – maybe a little too good!

It's a rare ham who won't chime in when someone asks for advice about radios! These folks will also probably offer opportunities to actually see or use a radio or two, which can be invaluable when you're just starting out.

Just remember that every ham carries the mark of his personal bias when it comes to which aspects of the hobby he finds interesting and which types and brands of gear to recommend. A Kenwood guy isn't likely to recommend a Yaesu radio, a low-band DXer may not know beans about weak-signal VHF work, and an Old-Timer who keeps paper logs won't necessarily know about the importance of computer control and computerized contest logging, etc. It's not a big deal – just remember to keep it in mind so you can read between the lines!

Even in the internet age, ham radio magazines are still excellent sources of information when it comes to choosing a radio, new or used. In addition to dozens of ads showcasing the latest and greatest offerings, most ham magazines have regular product reviews, some more thorough than others. When it comes to detailed technical and operational reviews with lots of numbers, charts, tests and actual measurements, the Product Review section of *QST* is the hands-down winner. It's the Consumer Reports of Amateur Radio evaluation.

QST's detailed product evaluations got into high gear in the 1970s, so there's an excellent chance that every mainstream radio you might be interested in – unless it's too new – has been reviewed in one issue or another. A complete list of *QST* product reviews can be found at www.arrl.org/tis/info/prodrev.html. ARRL members can download write-ups from 1980 onward right from the web site. If you're serious about finding the right radio, the \$39 annual membership fee via www.arrl.org is a bargain. If your ham club doesn't have back issues, your local library might. Many *QST* Product Reviews end up on the internet by hook or by crook, so it also pays to Google around.

Speaking of the internet, it's a staggering resource when it comes to searching for tidbits about your soon-to-be favorite radio. In addition to manufacturer's web sites, complete with juicy pictures and detailed specs on everything they make, the 'net has a lot of nooks and crannies full of rig specs, modifications, workarounds, service info and photos. Google away, but be sure to point your browser to www.eham.net, which has a great classifieds section and a treasure trove of equipment reviews submitted by users.

Specific Features

Now that we've looked at how to start the overall process, let's look at some specific considerations.

Bands:

Almost every modern transceiver covers 160 through 10 meters, including the "WARC" bands. Not every modern rig covers 60 meters, however, so if you need to work ham radio's only "channelized" band, make sure the radio in question covers 5 MHz.

Many modern rigs also add multimode coverage of 50, 144 and 420 MHz – a true "station in a box!" Whether base or mobile, these dc-to-daylight super radios do just about everything reasonably well and were essentially unheard of before the mid '90s.

Although some older HF rigs cover 6 meters, most do not have any VHF/UHF coverage unless you're willing to add transverters to the mix, which is fine for performance but not necessarily recommended for beginners.

Most older radios don't cover 60 meters, and some don't even cover 160 meters! But most ops never use those bands, so it may not be a factor in your decision tree.

Size:

I used to think of this category as "mobile vs. base," but, because most modern mobile, compact radios are quite capable of being used at home, the distinction is more about size and convenience than ever before.

During the past decade we've seen a real trend toward compact, do-everything, dc-to-daylight radios that offer an amazing range of features and frequency coverage in the tiniest of packages. However, the added convenience sometimes has a price when it comes to absolute performance and functionality. For example, although a radio in this class can work SSB and CW on 6 and 2 meters, its weak-signal performance is certainly not best-in-class. Similarly, the radio can also work through VHF/UHF FM repeaters, but its ease of use when considering frequency splits, memories, etc, keeps it from truly competing with dedicated mobile FM rigs that are expressly designed for that service. But when it comes to "bang for the buck" and maximizing your ability to explore just about every aspect of ham radio in a compact, capable package, there's nothing better.

Base station radios are "big," and are generally designed for use in the shack instead of a 4X4 pickup. They generally perform better than their more-compact cousins and offer extra options and added operating convenience. The larger size means more circuitry, more features, more filters, more connectors and more switches and controls. They may seem more complicated to use at first, but after you get the hang of it, using a base station rig is generally easier than a compact one.

Usability:

In a related sense, big radios have larger displays and plenty of front-panel controls. That means no squinting and no digging through potentially complicated and layered menus and multifunction controls. If you need to switch on

THE GOOD OLD (EXPENSIVE) DAYS

Despite our embattled economy, when adjusted for inflation, amateur radio gear has never been more affordable. To see for yourself, check out the equipment ads in ham magazines from the '40s through the '60s. Separate receivers and transmitters made by Collins, National, Drake, etc, had stellar price tags to match their stunning appearances. A premium receiver might have set you back \$1,000 or more and you could add a transmitter for about the same! Even in the late '60s you could buy a new car with all the extras for less than it cost to buy a Collins transmitter/receiver combo!

Don't believe me? A 1968 Camaro SS cost a measly \$2,588. A '66 Ford pickup was a paltry \$1,795. In 1968, a Collins 51S-1 ham/shortwave receiver cost more than \$2,000. Drake's more affordable R4 still cost \$600, but worked on ham bands only. Even Swan's 350 – considered a real budget transceiver, complete with scary TV sweep tubes as finals – cost about \$500.

So, adjusting for inflation, a radio that cost \$500 in 1968 would cost a whopping \$2,917 in 2006 (the latest year I could find data for)! That Collins 51S-1 would cost \$11,600 today – the same cost of ICOM's top of the line IC-7800 transceiver today!

It's interesting that top-of-the-line equals top-of-the-line, then and now, but what about performance and overall value? Does the venerable 51S-1 offer the ultimate performance and value of ICOM's 7800? Not hardly, though more than a few Collins collectors might sharply disagree with me!

Inflation works the other way, too. After a small rebate, ICOM's IC-718, arguably the most affordable full-featured HF transceiver available today, costs about \$525 new and as little as \$475 for a factory refurbished unit (online). In 1968 dollars, that's an amazing \$90! Not bad for a radio that does stuff that a 1968 radio couldn't even dream of. With due respect to collectors everywhere, today's gear performs twice as well at a tenth the cost. – NT0Z

the speech compressor, for example, on a big radio you just push a button. On a compact radio you might have to push a sequence of several buttons – and remember that sequence the next time you need it. Both radios may have similar functions, but big radios generally offer more operating convenience, especially for older or visually impaired users.

Extended Receiver Coverage:

Once a premium on HF transceivers, most radios now receive from 100 kHz to at least 30 MHz. Radios that also cover VHF/UHF bands typically have extended receiver coverage at least to the top of the highest ham band on which the rig can transmit. Be sure to check the specs of the rig in question, though, because gaps in VHF/UHF coverage are the norm, and the radios are definitely not as functional as scanners or "VHF communications receivers."

Modern HF rigs typically offer good to excellent performance as SWL receivers, but may lack versatility in AM filter bandwidths, sensitivity below 1.8 MHz, and advanced options such as synchronous detectors. Still, unless you're used to high-end SWL receivers, a typical HF rig more than gets the job done and runs rings around inexpensive shortwave radios.

It's interesting to note that the highest-performing "enthusiast-grade" ham transceivers do not feature SWL receive coverage. When it's necessary to boost receive performance by the final smidgen, a general coverage front end goes out the window!

Computer control:

Most – but not all – modern HF radios have computer-control interfaces. Although not needed to get on the air, they are necessary to take advantage of computerized logging, PC control and lots of automated goodness. The older a radio is, the less likely it has a PC interface.

Filters:

To simplify a complex topic, there are two main types of bandwidth (IF) filters in modern radios: crystal filters and digital filters created by a rig's digital signal processor (DSP). Most rigs use one or the other while some have both. Although exceptions exist, generally, big radios have bigger, better filters than those found in compact radios. Better crystal filters and better DSP units. After all, that extra space has to count for something!



W4RT add-on, inboard Collins Mechanical Filter for Icom 718 \$114 if you install it yourself. (Courtesy: www.w4rt.com)

Again, generally, DSP filters offer more bandwidths and more flexibility, while crystal filters tend to offer better ultimate performance. Actually, the combination tends to offer the best of both worlds. For a starter radio, it's important to simply have (or have the option to add) filter bandwidths necessary to work the bands and modes you're interested in.

Another important tidbit to remember is that the filters in most entry level radios can be updated by purchasing new (or better) filters from the manufacturer or from a third party. My handy little ICOM IC-718, for example, has just about every feature a ham could want – except good-performing IF filters! A \$500 radio has to cut a few corners and, because filters are expensive, guess what got cut? Don't get me wrong: the radio works just fine with its inexpensive Murata filters, but by upgrading the SSB filter and adding a CW filter, the performance goes way up, as does the radio's value. I prefer adding Collins mechanical filters from www.w4rt.com instead of those offered by ICOM. If you're

considering a compact ICOM or Yaesu radio, the W4RT filters are less expensive and perform better.

VFOs:

Most modern rigs have dual VFOs, allowing you to listen on one frequency and transmit on another. This is especially useful for contesting and working DX pileups that require split-frequency operation to handle the sheer volume of calls. Some older rigs don't have this feature (remember my Tempo One?) though on some you can add an external VFO. Dual VFOs also offer a handy "memory scratchpad" function. When you tune across an interesting signal, push the button that sets VFO A equal to VFO B, then continue tuning up or down the band. To check in on your memorized frequency, simply switch to VFO B. Nifty!

Other goodies:

The list of goodies that can be found on modern radios is exhaustive. We're talking keyers, digital voice recorders, speech processors, RTTY decoders – you name it. While you're compiling your list of potential radios, make sure your candidates have the goodies you're interested in. Or make sure they can be added internally or "outboard" after the fact.

New or Used? Dealer or Individual?

Buying from a dealer – whether the rig's new or used – can be safer than buying from an individual. In addition to hardware, dealers offer information, service and a bit of security. Make sure the dealer you choose has a reasonable return period (a modest restocking fee is acceptable), and try to purchase your rig with a credit card, if possible. You'll be protected if the rig turns out to be a lemon.

Buying from individuals (hamfests, the internet, classified ads) is where the bargains can be found – but only if you're an experienced buyer, skillful in ham radio service or repair, or know someone who is who's also willing to assist you! As any horse trader will tell you, it's possible to find fabulous deals at such outlets, but it's also possible to come home with wretched doorstops that look great on the outside.

When a seller says a particular radio "works great!" he might be telling the truth, or he might be pulling your leg. If you're inexperienced or you can't fix the rig's "little problem," you could be stuck with the thing. Caveat Emptor even applies to ham radio!

There are dozens and dozens of used HF rigs that will still work well today (assuming that they're in good working condition). There's not nearly enough space here to list them, but a lengthy list and follow-on discussion can be found at www.eham.net/articles/4140.

The Future is Now

By now we're all familiar with computer-controlled radios. They make scanning and SWLing lots of fun and enable computerized logging and other nifty, high-tech features. The

real future of ham radio isn't "computer control," however, it's "computer defined." More precisely, the newest ham radios are "software



Wave of the future: Flex-3000 Software Defined Radio (\$1,600). (Courtesy: Flex-Radio)

defined radios," SDR for short.

In an SDR, the front end is conventional and uses coils, capacitors and filters to prepare RF signals for transition into the digital domain. From that point on, all processing, demodulating, filtering, signal generation, etc, is done by the rig's digital signal processor. Essentially, the radio is a computer, and vice-versa! To add modes or other capabilities simply update the "radio's" firmware or software.

SDRs offer very advanced features such as graphical display of received signals (panoramic-type displays), the ability to demodulate extremely weak signals, very high dynamic range and receiver performance, etc. The potential downside is that SDRs require PCs and PC monitors to function (even if the PC is built into the SDR's cabinet). SDRs don't yet offer conventional front panel controls, etc, so some users are put off by the PC requirement. Operating SDR software and logging or PSK31 software, for example, can be quite a trick. Still, dollar for dollar, nothing beats an SDR when it comes to ultimate performance. To check out the future, see www.flex-radio.com.

Conclusion

As I wrap this up I can't help but wonder how many of you are peeved that I didn't tell you exactly which radio to buy! Well, it doesn't work that way. One size doesn't fit all! What I hope you understand is that choosing a rig is a process of identifying your interests, examining your budget, talking with hams in your circle of friends, researching information and specifications in person and online, putting your hands on a rig at a friend's shack or at a dealer (if possible), and so on.

As you gain experience, choosing a rig will become less mysterious – but probably no less frustrating! New gear is introduced every year, and most hams trade their stuff in for newer versions every few years. You probably will, too. It's all part of the fun! Your first rig – or your next rig – probably won't be your last, so work your process, get a radio, get on the air, and good luck!

About the Author:

Kirk Kleinschmidt, NT0Z, a ham since 1977, was licensed at age 15 and is still slinging dits to this day. Kirk was *QST's* assistant managing editor from 1988 to 1994, is the Amateur Radio columnist for *Popular Communications*, wrote *Stealth Amateur Radio* and wrote features for *Satellite Times*, an MT sister publication, in the late '90s. He lives in Rochester, Minnesota, and can't wait to move back to a more rural setting so he can put up some real antennas. He can be reached at kirk@cloudnet.com.



MT'S GUIDE TO BUYING A USED RECEIVER

By Bob Grove W8JHD

Radio receivers have had a long, progressive evolution. In the earliest days, simple coherers and galena crystals were attached to an antenna and an earth ground to detect radio signals generated by spark-gap transmitters.

Eventually, tuned circuits, vacuum-tube amplifiers, regeneration and super-regeneration, heterodyne and superheterodyne refinements led to vastly-superior radio receiving equipment by the 1930s.

The second World War added impetus to the development of the final phases of vacuum-tube radio, with famous brand names like Hammarlund, National and Hallicrafters offering advanced designs and handsome packaging to the serious listener.

When transistors were first incorporated into radio circuits in the 1950s, their performance left much to be desired; vacuum-tube models still led the field. But, along came field-effect transistors, integrated circuits and other solid-state devices which finally competed with the old tube sets. Now vacuum tubes are virtually extinct, manufactured for replacement purposes, audiophiles, and specialized industrial/scientific/medical applications.

So what about buying one of those classics?

If it were possible to obtain a new model of the old radios, we would be initially impressed by their performance, but would soon observe their limitations like frequency drift, crystal-filter distortion, heat generation, and other subtleties that have been overcome by modern design techniques.

Worse, age has taken its toll on these fine, old receivers, and finding original replacement parts is not always possible. Capacitors have become "leaky," allowing voltage to pass through them like resistors; resistors have changed tolerance, changing as well the performance of the circuits of which they are part; potentiometers have decomposed, becoming noisy and erratic; RF and IF transformer potting compounds have taken on moisture, losing their crisp tuning ability, referred to as "Q".

These old sets deserve respect, even reverence for the period they represent, but they best serve as gentle reminders of our past; collectibles for nostalgic hobbyists and restorers.

But weren't early transistor sets also prone to poor performance?

Indeed they were, just like early vacuum-tube sets were. Both eras went through giant evolutionary periods. But more modern, solid-state receivers and transceivers from revered companies like ICOM, JRC, Drake, Ten-Tec, Kenwood, and Yaesu, as well as the more recent introductions by innovators like WiNRADiO, Perseus, AOR, and RF Space, offer extraordinary improvements in sensitivity, selectivity, memory, autoscans, frequency stability, readout accuracy, and noise reduction.

What about portables?

There isn't a portable on the market that can match the performance of today's desktop receivers. Portables offer only one advantage: portability. Their small size and battery operation make them valuable as secondary and emergency radios, but they aren't primary receiving sets for serious applications.

Are there restorers around who can fix an old receiver?

Indeed there are. Probably the best source on these is Antique Radio Classified, published by John Terrey, and available on line at www.antiqueradio.com.

A local hobbyist has offered to sell me a used receiver; what should I look for?

Does it work? If not, unless you possess diagnostic and repair skills, don't buy it! It could have missing, weak, shorted, or burned-out tubes; shorted or open windings on power, audio, or IF transformers; leaky capacitors ("condensers"); out-of-tolerance resistors; frozen, dirty or decomposed adjustable components like the variable tuning capacitor and front-panel controls (RF gain, volume, tone, selectivity, switches, etc.).

There is also the daunting possibility that it has been improperly modified. Look for stray wires, extra holes, knobs, components, or switches and solder globs that are different from the rest of the chassis connections.

Except for the tubes part, these precautions apply to modern, solid-state radios as well.

It seems to be working just fine; how can I test its performance?

Attach an antenna, 20 feet of wire is just fine, preferably running out a window. Turn it on and tune in a signal with the SSB or CW mode switched on. Turn the frequency control, stopping on a signal. Does the tone drift in pitch? This is typical for older, vacuum-tube sets, but shouldn't happen on solid-state radios. In any case, drift will mean constantly readjusting the tuning on sideband, CW and digital signals.

Tap (don't slam!) the sides of the radio; does the pitch change erratically? If so, this indicates either flimsy design or possibly loose or worn components.

Fine-tune the received station; does the tone smoothly change, or does it jump erratically? Erratic tuning is a sign of an dirty, corroded or worn variable capacitor in an older set, or a defective encoder in a modern receiver.

Change bands or frequency ranges and listen for signals, especially above 10 megahertz (MHz) at the higher frequencies during the daytime. Even with the low sunspot cycle, broadcasters should be heard up through at least 15-18 MHz.

It's working great; how do I know a radio is a good value?

The quick answer is that if you can get it for less than you'd have to pay somewhere else, it's a good deal! As a practical matter, however, you can see how much that model and similar models are selling for at chain radio stores like Ham Radio Outlet and Amateur Radio Supply; individual outlets like Universal Radio and Grove Enterprises; and on line from specialty sites and eBay. Consider shipping costs, too, and availability of a warranty.

HOW TO TEST THAT USED SCANNER BEFORE YOU BUY IT

Folks sell their personal scanners for a variety of reasons:

1. They are no longer interested in listening.
2. They wish to step up to a more recent, more functional model.
3. They have too many scanners.
4. They are forced to sell because of the economy.
5. Their wives have said, "Either that scanner goes, or I go!"
6. It doesn't work well anymore.

It's that last reason that should give you pause, so test it before you buy it! Here's how: First, examine it carefully. Scratches may indicate rough handling, even dropping on hard surfaces. If it's a portable, be sure that the battery connectors aren't corroded. If you don't know the seller, get his guarantee that he has made no modifications and has not tampered with the circuitry or alignment.

Press all the keys multiple times to reassure you that all the keys work dependably, and watch the display to be sure that all LCD segments are functional, and that there aren't any black spots forming. If it has a back light, does it still work?

Attach a whip antenna and tune in a local weather channel; wiggle the base of the antenna slightly to determine that the connector is not loose, and that the center pin is connecting firmly – a loose connection would be revealed by an erratic change in signal strength.

Search for signals on several frequency ranges – 118-137, 144-163, 450-470, and 854-868 MHz. Be sure that the antenna is correct for that model, and hope for an operating manual. Some manufacturers post their owner's manuals on-line. Radio Shack has the owner's manuals for over 100 different RS scanners listed here:

http://support.radioshack.com/productinfo/ProductResults.asp?Name=Radio_Scanners&ID=004001001 Uniden has more than 50 scanner manuals here: www.uniden.com/index/manuals_results.cfm?cat=3

If the price is right, these simple steps should ease your mind.

Expert's Guide to Buying a Scanner Radio

What Kind of VHF/UHF Scanner Should I Buy?

By Larry Van Horn, MT Assistant/Review Editor

wish I had a nickel for every time someone has asked me that question. To be honest, there is no easy answer so I usually answer this question with another question, "What services do you want to monitor?" That will certainly dictate the type of scanner you will want to buy.

Digital V. Analog/Trunk V. Conventional

If you are interested in monitoring public safety services, (e.g., police, fire, and EMS), you can narrow your purchase options to a couple of considerations – analog vs. digital, and conventional vs. trunk systems. I recommend that the first thing you do is to conduct a survey of the agencies you are interested in monitoring in your local area. You can do that at an Internet website such as RadioReference.com (www.radioreference.com).

For example, let's use the monitoring area around here in Brasstown, North Carolina. We are a rural area so the majority of the public safety radio systems we monitor will be conventional and analog. If that was the extent of it, I would recommend one of the inexpensive, conventional scanners such as a Uniden BC-346T or the GRE PSR-100/200 radios.

A closer examination of the RadioReference database reveals I have one important public safety trunk radio system in the area. This system is a statewide mixed mode (P16) 800 MHz trunk radio system known as "VIPER." It carries both analog and digital voice traffic. If I want to monitor this public safety trunk system, I will have to step up to a higher dollar scanner that, at a minimum, can follow a trunk radio system.

Even though the VIPER system mentioned above does have digital talk groups, if I want to monitor only analog talk groups, I have a wide variety of choices available to me.

- Uniden - BC245XLT BC246T BC346XT BC780XLT BC895XLT BC898T BCT8 BCT15 BCT15X BR330T
- GRE - PSR-300 PSR-400
- Radio Shack - PRO-51 PRO-90 PRO-91 PRO-92 PRO-93 PRO-94 PRO-95 PRO-97 PRO-160 PRO-162 PRO-163 PRO-164

- PRO-433 PRO-528 PRO-2050 PRO-2051 PRO-2052 PRO-2053 PRO-2055 PRO-2066 PRO-2067

There is one caveat that you should be aware of when purchasing some of the older trunk scanners. The following scanners will no longer correctly track most Motorola systems after 800 MHz rebanding takes place and cannot be updated. They are the Uniden BC245XLT, BC895XLT, and BC780XLT. If you need to follow an EDACS or LTR trunk system, the scanners below will work fine when the new rebanded 800 MHz frequencies are programmed.

If you are looking for additional information on rebanding, I have covered the topic extensively on my personal BTown Monitoring Post blog at monitor-post.blogspot.com/2006/06/800-mhz-rebanding-and-uniden-scanners.html

If I want to monitor the digital talk groups on the VIPER system or the new 380-390 MHz P25 trunk radio system in my area I will need to step up in price again and purchase one of the newer digital scanners.

- Here is a list of scanners that I would consider.
- Uniden - BC250D BC296D BCD396T BCD396XT BC785D BC796D BCD996T BCD996XT
- GRE - PSR-500 PSR-600
- Radio Shack - PRO-96 PRO-106 PRO-197 PRO-2096

The BC250 and 785 require the use of an optional BC25i digital card to enable digital trunking/decoding and they are becoming very hard to find. Even with the BC25i card, the only digital systems these two scanners will track are marked analog and APCO-25 Common Air Interface in the RadioReference website database. This means that these two scanners cannot track Project 25 trunking systems (9600 baud control channel); they can only track Motorola Type II systems (3600 baud control channel) that may use Project 25 common air interface (digital voice) for some (or all) of their voice channels.

At the Track and in the Air

If you are a NASCAR fan, any of the low end scanners in the marketplace will be just the ticket to let you monitor your favorite driver at the track. You can get complete details on monitoring races by downloading the Race Scanning Tips and Hints pdf from www.midwestracingfrequencies.com/tips.pdf

If you want to monitor other types of communications such as marine, aeronautical, railroad, and business, just about any analog style scanner will serve you well. While most of these

specialties use analog communications, there is a slow migration to digital for all the above except the aeronautical bands. So, at some time in the future, a digital scanner might be needed to monitor some of the services I have mentioned above.

If you are an air show buff, the analog scanner playing field changes just a bit. While an analog scanner will let you hear most of the action, some scanners currently being marketed and most older scanners on the used market are not suited for air show monitoring. There are certain requirements your air show radio has to meet in order to successfully monitor the two major military aerial demonstration teams – the U.S. Navy's Blue Angels and the U.S. Air Force's Thunderbirds.

If you are going to a T-birds show, you will need a scanner that can monitor the 138-150 MHz military land mobile band in the AM mode. Most of the older Uniden scanners cannot be used for air show monitoring due to their lack of independent transmission mode selection.

You also need a scanner that has the 225-400 MHz military aeronautical band in it. Most of the action (especially the Blues) will be heard in this military UHF portion of the spectrum. Adding this criterion to the mix of possible radios again narrows our choice for air show scanners even further. You can get a comprehensive list of scanners we recommend for air show monitoring in the March issue of *Monitoring Times* in our exclusive, Annual Air Show Guide.

There are more radio manufacturers than the ones we listed above that have radios with VHF/UHF coverage. Names such as Alinco, AOR, Icom, Yaesu, and WinRadio also make radios that will let you catch activity in the VHF/UHF frequencies.

If you want further advice on purchasing a scanner, I recommend that you stop by the Monitoring Times or Grove Enterprises website. We have reviews and other background information to help you select a scanner that fits your monitoring needs. Also be sure to also visit our Trunk Scanner page at www.monitoringtimes.com/html/trunkedscanners.html for specific scanner information.



AOR AR-8200 MKII (\$630)
500 kHz to 3 GHz tuning range (less cellular), all-mode hand-held scanner. (Courtesy: Grove Enterprises)



RADIO TRENDS: A Look at What Top Radio Manufacturers are Currently Offering

By Ken Reitz KS4ZR

Across the vast landscape of consumer electronics are many radios that we use every day: Weather radios, CB radios, FRS/GMRS two-way sets, and portable short-wave radios. These radios exist in a fiercely competitive world where one manufacturer often makes most of the components if not the finished products of competing lines. Still, this system has brought some interesting innovations to the market place. *MT* takes a look at current radio trends among these specialty radios.

Weather Radios

Weather radios have been added to CB sets, scanners, Family Radio Service (FRS) hand-talkies, and there are dozens of stand-alone models. But, not all weather radios are all that useful. Look for sets that are Specific Area Message Encoding (S.A.M.E.)-capable, showing the "Public Alert" logo. Public Alert certification was developed between the Consumer Electronics Association (CEA) and the National Weather Service (NWS) to provide a standard for features that consumers could rely on.

To be Public Alert certified a radio must include S.A.M.E. capability (to sound an alarm not only for severe weather but as many as 80 other selectable events such as a hazardous waste spill, Amber Alert or nuclear power plant "incident" near you); selectable alerting of events (the consumer can instruct the receiver not to turn on if there's an event that may not be a concern); battery backup that automatically engages when the main power is interrupted; external antenna jack, and external warning device jack (to enable a strobe light for the hearing impaired, for example).

S.A.M.E.-capable radios come in three types: desk-top, portable and emergency crank-powered portables. Midland Radio offers five such desk-top models that range in price from \$40–100, but you should avoid desk-top sets with built-in clocks, AM/FM radios and

bright displays. In an emergency such features help deplete the backup batteries. Sima Products is a company that makes many private-labeled weather radios. Their First Alert sets such as the WX-200 (\$80) take rechargeable AA batteries (not included) that are trickle-charged while the unit is plugged into the wall. These batteries are widely available from \$10–15 for four. I found the WX-200 at Ambient Weather.com for \$44.

Portable S.A.M.E.-capable sets range in price from \$20–60. Many are not Public Alert certified and most have inadequate antennas good only for reception within in a relatively small radius of your local NOAA weather radio station. You would probably be better off using the weather radio feature on your portable scanner.

Crank-up S.A.M.E.-capable sets suffer from the same problems that portables do. There are no Public Alert crank-up models and, if you've ever actually used a crank-up radio, you know that the cranking stops being fun about two minutes into the job. That means that during an emergency, if a weather alert is sent and you fell asleep at the crank, you'll never know what hit you.

CB Radios

The biggest change in CB sets in decades has been the introduction of hand-held CBs, such as Midland Radio's 75-822 and Cobra's 75WX-ST. Some sets actually look like 2 meter HTs. But, as expected, these units have a few drawbacks, not the least of which is that, inside a car, they need help from an external antenna. You'll get poor reception inside the car without one and your transmission will never be heard without an external antenna.

CB manufacturers have had no real reason to upgrade their products: they're still limited to 40 channels; 4 watts output, and have little hope

of being heard outside of a 3 to 5 mile radius. Even so, if you're on the road that may be all you need if you want to avoid speed traps, accident-generated "parking lots," or help when your cell phone runs out of juice.

A welcome addition to many CBs models today is the inclusion of all 10 weather radio frequencies used in the U.S. and Canada. Other features you wouldn't have found on Smokey-and-the-Bandit-era CBs: Last channel memory, scanning function, 5 memory channels, Bluetooth connection to your cell phone, and hand-held portability. Even "full sized" sets look more like ham gear. They are smaller, with less chrome, and designed to fit in the smaller interiors of today's cars.

Two other things consumers will notice: the number of models has been greatly reduced while the prices have not. Midland's HH Road Trip hand-held CB set retails for \$110, while Midland's more versatile 75-822, retails for \$125. Substantial discounts can be found at many on-line retailers.

Full-sized "trucker" style CB sets, such as Cobra's 29 WX NWBT with NOAA channels and Bluetooth® wireless technology (\$210) are even more expensive. The cheapest full-sized CB set I found was Midland Radio's 1001z (\$45). More traditional chromed plastic sets such as Midland's 5001z (\$110) and Cobra's 29 LTD Classic (\$120) look like they are right out of 1975.

Regardless of what CB set you buy, you'll need a mobile mag-mount antenna. Mag-mount CB antennas are not what they used to be, especially from The Shack. Their mag-mount CB antenna (cat.#21-989) has an inadequate magnet base, poor construction and cheap coax that add up to emergency-side-of-the-road-use only. I found an old-fashioned Wilson "Little Will" mag-mount CB antenna at Overstock.com for \$39 that will probably outperform anything from The Shack and can be trimmed to use on the 10 meter ham band. At least it will stay on the car at highway speeds!



This Oregon Scientific WR-602 hand-held weather radio is portable and handy, but it's also pricey (\$80 at The Shack), the dinky antenna will not let you go far from a NOAA station, but at least it has a rechargeable battery and recharging cradle, some don't. (Courtesy: Oregon Scientific)



Sima Products' WX-200 (\$80) is a small, full-function S.A.M.E. weather radio featuring a rechargeable battery that trickle-charges while the radio is plugged into the wall. (Courtesy: Sima Products)



Midland Radio 75-822 (\$125) is a microphone-sized, full-featured CB with NOAA weather radio, but it's useless without an external antenna. (Courtesy: Midland Radio)

FRS/GMRS Radios

When the FCC first authorized the Family Radio Service (FRS) it was hoped that it would be the new Citizens Band, offering essentially the same range with dozens more channels and privacy unknown on old-fashioned CB sets. And, the service has been wildly successful. Tens of millions of these two-way radio sets have been sold over the last decade. Families use them on trips and vacations; children use them at play; hunters and fisherman use them in the woods and on the water. They're packed with features CB sets never imagined in a size that truly fits in a shirt pocket. Some models include NOAA weather radio reception, many offer hands-free VOX operation, Direct Call, and privacy codes to allow you thousands of channels to choose from.

Midland Radio's GXT1000VP4 (\$80/pair) is a top-quality FRS/GMRS HT set. Ignore the mileage claims and check out the features: rechargeable batteries/charging cradle, boom/mics for hands-free VOX operation and plenty of privacy channels. (Courtesy: Midland Radio)



There is one feature on all of these radios that's totally bogus: mileage. The smallest sets claim communications are capable up to 16 miles while the best claim up to 36 miles. Most hams know that, in theory, your five watt 2 meter HT is perfectly capable of contacting the International Space Station some 200 miles in the sky. Conditions have to be just right but, it can be done. Still, you don't see ham radio HT manufacturers plastering that claim on their sets. But, the FRS industry somehow found itself in a mileage war and, once it started, no one wanted to quit.

The fact is, that under perfect circumstances, as performed by the manufacturer's engineers, such mileage claims can be verified, but, as with EPA car mileage claims: your mileage will vary. Most units will not be able to achieve intelligent communications beyond a 3 mile limit regardless of their packaging claim unless you're out on the water or on a very high mountain looking over a vast desert.

Since mileage claims can be dismissed, shop for the features you want. All sets are sold in pairs. Better sets come with rechargeable batteries and recharging cradles. Look for sets that include headset boom-mics for hands-free VOX operating and NOAA weather radio reception with S.A.M.E. capability.

In addition to the FRS frequencies, most sets include General Mobile Radio Service (GMRS) frequencies as well. There is no license requirement to use FRS channels, but the FCC does require a license to operate GMRS frequencies (\$80). The trouble is that, even though it's so stated in all the manuals, hardly any of the tens of millions who have bought these sets have applied for the GMRS license. Though it's unlikely that you would be caught by the FCC for using those channels, if you were, it could result in a fine of \$10,000. The real problem occurs when businesses use these radios regularly without a

license and interfere with companies that are also using the same frequencies, but have a license. Once the FCC is brought in, fines will ensue.

One company of note, Tri-Square, offers two-way hand-held sets that are not technically FRS because they operate at 900 MHz. Their TSX300R 2VP (\$80) has slightly less range, due to less power output than FRS units, but includes built-in NOAA weather radio and uses digital transmissions to achieve "10 billion channels." Their units also include boom/mics and rechargeable batteries/cradle.

Portable Shortwave Radios

This is without doubt the "golden age" of portable shortwave radios. Surface mount and LCD technologies have made portable shortwave sets more sensitive, more versatile and certainly more capable. The trend here is smaller, better quality, more features, and at lower prices than ever before. Gone are the clunky, oversized, under-performing, power-sucking sets of the past. New models feature built-in NiMH rechargeable batteries with the charger built-in; on most you can use an "old-school" tuning knob or direct-entry frequency tuning, and nearly all offer more memory than you will probably use.

Long-time radio manufacturers Grundig/Eton, Sony and Sangean still dominate the portable shortwave market. But, Kaito has brought innovative sets to the market. Their KA1121 and ever-popular KA1103, are driving trends toward features serious shortwave listeners want, including lower prices. Other models such as the Kaito 1123 appear to push the limits in size while still maintaining performance and features reserved previously for more expensive and much larger portables. While sets like the 1123 have notable drawbacks: inconvenient tuning and front-end overloading, their size and price make them attractive.

What shortwave listeners are waiting for, though, is a portable DRM receiver. Such a receiver is said to be on the way from Uni-Wave dubbed the Di-Wave 100. Promotional material touts features that would bring shortwave listening from the Cold War era into the 21st century. It's difficult to know what the performance of such a radio will be, let alone the price, but once it is available look for prices to fall as competing models appear out of China.

The biggest question for consumers regarding today's miracle minis is longevity. My Uniden 2021 all-band shortwave portable with LCD display was purchased new in 1983 and it's been in daily use since. How long will today's LCD displays hold out? How well will today's wafer-thin circuitry wear?



Kaito's KA1103 gets great reviews every time out in MT. Size, price and performance makes this radio attractive to serious listeners on a budget. But, how will it hold up over time? (Courtesy: Kaito U.S.A.)

One last note about trends from these specialty radio manufacturers: Today's fashion is the heavy promotion of Internet radios. The market is awash with Sony, Sangean, C. Crane, and Kaito Internet radio sets. Many previously unheard of brands such as Grace, iLuv, and Tangent have joined the fray. And now, even Cobra Electronics, long-time CB radio maker, is in on the rush to Internet riches. The trouble is that these radios are not cheap, typically \$100-300, they're certainly not portable, and, to be useful, require consumers to have high-speed Internet service with a wireless network router in the home.

MT

MTX PRESS

The Real Deal

The best tool for today's internet-savvy radio listener is our bargain-priced pdf version of *Monitoring Times*. Saving \$13 off the cost of the print magazine, you receive:

- Prompt delivery,
- Clickable internet and email links,
- Full color photos, and
- The ability to print out as much of the magazine as you want.

It's the real deal at a steal at only \$19.95. Call 1-800-438-8155, go to our website, or e-mail order@grove-ent.com to start your *MT Express* subscription today!

MTX PRESS

www.grove-ent.com

The Expert's Guide to Buying an Antenna

By Bob Grove W8JHD

While all antennas serve the same basic purpose, to emit or accept signal voltages at radio frequencies, the "devil is in the details." Are we interested in directivity – favoring a particular compass direction? Is the required frequency range narrow or wide? Can the antenna be elevated or mounted at ground level? What frequencies are particularly important? Will the antenna be transmitting a signal or only receiving? Is an outdoor antenna out of the picture? Is the application portable? Mobile? Fixed? And, how about coaxial cable; are they all the same?

The radio marketplace bristles with antenna designs for virtually every application, but how do you make the best choice? Let's take a look at some typical questions – and the answers.

Q. I live in a condominium with restrictions against outdoor antennas. I can remember reading that years ago shortwave listeners hooked their radios to bedsprings, rotary-telephone finger stops, and even through a capacitor to the house wiring. Are these contrivances still valid

alternatives to an outdoor antenna?

A. No. While all of these make-shift antennas work to some degree, the prevalence of modern household electric and electronic appliances produce enormous quantities of radio interference, especially at shortwave frequencies. Additionally, metallic obstructions like heating/air ducting, reinforcement rods/screen in walls, metalized Mylar insulation, and aluminum siding reflect and block radio signals. You will hear most major international broadcasters and some ham and utility shortwave stations, but they'll be heard amidst a mire of noise.

Q. I enjoy scanner monitoring of local police, fire and ambulance calls. Is the attachable whip that came with my scanner going to be all I need?

A. For the local repeaters up to several miles away, yes. In that case, it's best to put the scanner near a window on the side facing the activity. However, if you're at all serious and want to


hear some distance away, especially listening to mobiles and hand-held radios, you'll need a good outdoor antenna.

While it's tempting to mount the antenna in an attic space, that's still not quite as good as being outdoors away from electrical wiring, ducting and other metallic surfaces and shields. Additionally, a higher location guarantees greater distances because of the curvature of the earth as well as the reduced likelihood of natural and man-made blockages between you and the target.

Q. What about the line that connects the outdoor antenna to my receiver or scanner; can I use just about any type of coaxial cable?

A. For receiving purposes, the impedance (50 or 75 ohm) is not important; what is important is the characteristic loss, the signal drop from absorption by the cable itself over a long length.

For shortwave applications (under 30 MHz), you can use any type of coaxial cable that's convenient – RG-58/U, RG-8/U, even TV-style



2010 EDITION WORLD RADIO TV HANDBOOK

This information-packed reference for professional monitoring stations and serious shortwave listeners bulges with station information, staff listings, contact information, worldwide mediumwave and shortwave frequencies, and schedules for programs in all languages.

A special English language program section makes station selection a breeze. Includes non-U.S. TV and FM broadcasters as well!

Available December 2009.

Shipping to Canada & Mexico, \$8/book by Global Priority Mail.
Other Countries are \$14/book Air Mail.

Order BOK03-10

\$29⁹⁵

plus \$3 First
Class Mail

www.grove-ent.com

GROVE

800-438-8155

828-837-9200; FAX 828-837-2216 7540 Highway 64 West, Brasstown, NC 28902 email: order@grove-ent.com

RG-59/U and RG-6/U (my particular favorite). The worst cable is teensy RG-174/U, which is intended for short runs, and very lossy.

Remember, the higher the frequency, the greater the signal loss in the cable. For scanner listening at VHF (under 300 MHz), don't use RG-58/U for more than 50 feet. A much better choice is RG-59/U and the best of the four is RG-6/U. If you're really critical, operating at high UHF (450-1000 MHz), and your installation requires at least 100 feet, try a premium cable like LMR-400 (roughly \$127 for 100 feet).

Q. I've heard long-time hams talk about "ladder line"; what is it?

A. It's like the old-style, flat, TV ribbon wire, only bigger and thicker! It has most of its insulation between the two parallel wire conductors punched out to reduce resistive losses when transmitters are hooked to it. This leaves a small rung of insulation connected between those wires every few inches, giving it the "ladder" look. The beauty of ladder line is that it's extremely low loss and allows a transmitter to be poorly matched to the antenna without losing its power heating up the insulation of the cable as it does with coax.



300 ohm and 450 ohm ladder line (\$17-19 per 100' roll) used in construction of amateur radio HF antennas. (Courtesy: Universal Radio)

Q. Are antennas designed for transmitting also good receiving antennas?

A. Absolutely. But the converse isn't true; just because an antenna receives well doesn't mean it is the best choice for transmitting. The reason is that transmitting antennas are meticulously adjusted for the best impedance match with the transmitter/transceiver, but just because you hear signals well on a randomly-designed antenna doesn't mean it will properly match a transmitter.

Q. I'm only interested in listening to distant shortwave signals. What's the least expensive way to design an antenna for this application?

A. Any kind of wire (stranded or solid, thick or thin, insulated or uninsulated, aluminum clothesline, steel or copper). Yes, I can hear it now: "Aluminum corrodes, steel rusts, and thin wire breaks!" That's true, but all of them receive the

FlexWeave 14 gauge stranded copper antenna wire (\$20 for 100')



is strong, easy to work with, and makes a great shortwave or amateur radio wire antenna. (Courtesy: Universal Radio)

same! For best results, use 40-50 feet of convenient, reasonably strong copper wire; locate it away from your house and away from power lines; elevate it as high as practical; position it so that its sides face the target direction; and feed it with RG-58/U coax to your receiver.

Q. I have a chance to buy a used antenna that's presently on a tower for only a fraction of its original cost; is that a good investment?

A. Only if it isn't corroded or weather-beaten. Check it thoroughly for signs of abuse, repair, rust and other corrosion. Generally speaking, antennas near saltwater beaches corrode faster than those farther inland. If it passes the test, have at it! But, safety first: To remove an antenna from a tower may require you to rent a "cherry picker" or hire experienced tower climbers with appropriate safety gear to do a safe removal. Consider those potential costs as additional to the "asking" price.

Q. I've noticed that several scanner antennas, and even some HF (shortwave) antennas, are advertised as having very wide frequency ranges. Does this mean that they transmit as well as receive over these wide spans?

A. No. If an antenna is designed for reception purposes, little attention is paid to impedance matching, so if you try transmitting with it, it is likely to have high reflected power which translates to losses in the coax transmission line. Reputable manufacturers will specify the recommended, and usually reduced, transmit-frequency range as well as the receive range on their antennas.

Q. There are many brands of antennas out there that have been around for quite a while. Which ones are best?

A. Actually, if the antennas have been marketed for several years, they probably have a good track record. Decide which antenna will do what you need for the lowest price, then, buy it from an established dealer.

Q. I want to hear stations from the greatest distance over the widest frequency range on my scanner; what kind of antenna do I want?

A. For that demand, you'll need a log-periodic dipole array (LPDA) and a rotator on a tower, connected to your scanner with low-loss cable. Two of the most popular beams are the Create 5130-2N and the Grove Scanner Beam, both of




VHF-UHF Log periodic dipole array (LPDA) receives 105-1,300 MHz (17 elements on a 4' boom): \$300. (Courtesy: Create Antennas)

which cover roughly the same frequency range. The Create is sturdier, but at a considerably higher price. For antennas of this size, a small TV-style antenna rotator will suffice.

Q. For VHF/UHF scanner listening, do I want a vertical antenna or a horizontal antenna?

A. Vertical. If you note the transmitting antennas on base locations, they are vertical, as are the receiving antennas on mobile units. Even a handy-talkie works more reliably when held in a vertical position, matching the units with which it is communicating.

Wide-band HF antennas, such as this MFJ-1796 40-2 meter vertical (\$230) could be the solution for hams with little or no real estate. It's 12' high and takes up only 24 square inches of patio, lawn or balcony space. But, safety first: make sure people and pets can't come into contact with the radiator. (Courtesy: MFJ Enterprises)




Q. How about shortwave listening and HF transmitting? Vertical or horizontal?

A. Now you've opened a can of worms! There are devotees to both polarizations. Over the considerable distances of shortwave signal propagation, signals have a tendency to mix and blend in both polarizations regardless of the original polarization of the transmitting antenna that you are trying to receive; thus, the polarization is unimportant.

More important are your real estate limitations. A horizontal wire must be suspended high; even a sloper must have one end high. This requires a high mounting point or points – a tower, mast, tree, or dwelling peak.

When properly installed in the open, and high above the ground, a horizontal wire has two directions for transmitting and receiving – at right angles to the axis of the wire. It is virtually deaf directly off the ends. A vertical antenna in the clear has an omnidirectional (circular) pattern for transmitting and receiving and can be secured on the ground.



A VHF-UHF scanner antenna such as this Hustler DCX vertical (\$25) might be a good omni-directional transmitting antenna for 2 meters and 70 cm as well, but keep the power output low. (Courtesy: Universal Radio)

Big Savings on Radio Scanners

Uniden® SCANNERS



Bearcat® 796DGV Trunk Tracker IV with free scanner headset

Manufacturers suggested list price \$799.95
CEI Special Price \$519.95

1,000 Channels • 10 banks • CTCSS/DCS • S Meter
 Size: 6¹⁵/₁₆" Wide x 6⁹/₁₆" Deep x 2³⁸/₆₄" High

Frequency Coverage: 25,000-512,000 MHz., 806,000-956,000 MHz. (excluding the cellular & UHF TV band), 1,240,000-1,300,000 MHz.

When you buy your Bearcat 796DGV TrunkTracker package deal from Communications Electronics, you get more. The GV means "Great Value." With your BC796DGV scanner purchase, you also get a **free deluxe scanner headphone** designed for home or race track use. Headset features independent volume controls and 3.5 mm gold right angle plug. The 1,000 channel Bearcat 796DGV is packed with features to track Motorola Type I/II/III Hybrid, EDACS, LTR Analog Trunk Systems and Motorola APCO 25 Phase I digital scanner including 9,600 Baud C4FM and CQPSK. Also features control channel only mode to allow you to automatically trunk many systems by simply programming the control channel, S.A.M.E. weather alert, full-frequency display and backlit controls, built-in CTCSS/DCS to assign analog and digital subaudible tone codes to a specific frequency in memory, PC Control and programming with RS232C 9 pin port (cable not supplied), Beep Alert, Record function, VFO control, menu-driven design, total channel control and much more. Our CEI package deal includes telescopic antenna, AC adapter, cigarette lighter cord, DC cord, mobile mounting bracket with screws, owner's manual, trunking frequency guide and one-year limited Uniden factory warranty. For maximum scanning enjoyment, order magnetic mount antenna part number ANTMBCNC for \$29.95. For complete details, download the owners manual from the www.usascan.com web site. For fastest delivery, order on-line at www.usascan.com.

Bearcat® BCT8 Trunk Tracker III

Manufacturer suggested list price \$299.95

CEI Special Price \$169.95
 250 Channels • 5 banks • PC Programmable

Size: 7.06" Wide x 6.10" Deep x 2.44" High
 Frequency Coverage: 25,000-54,000 MHz., 108,000-174,000 MHz., 400,000-512,000 MHz., 806,000-823,995 MHz., 849,0125-868,995 MHz., 894,0125-956,000 MHz.

The Bearcat BCT8 scanner, licensed by NASCAR, is a superb preprogrammed 800 MHz trunked highway patrol system scanner. Featuring TrunkTracker III, PC Programming, 250 Channels with unique BearTracker warning system to alert you to activity on highway patrol link frequencies. Preprogrammed service searches makes finding interesting active frequencies even easier and include preprogrammed police, fire and emergency medical, news agency, weather, CB band, air band, railroad, marine band and department of transportation service searches. The BCT8 also has preprogrammed highway patrol alert frequencies by state to help you quickly find frequencies likely to be active when you are driving. The BCT8 includes AC adapter, DC power cable, cigarette lighter adapter plug, telescopic antenna, window mount antenna, owner's manual, one year limited Uniden warranty, frequency guide and free mobile mounting bracket. For maximum scanning enjoyment, also order the following optional accessories: External speaker ESP20 with mounting bracket & 10 feet of cable with plug attached \$19.95. Magnetic Mount mobile antenna ANTMBCNC for \$29.95.



Bearcat® BCD396T Trunk Tracker IV

Suggested list price \$799.95/CEI price \$519.95

APCO 25 9,600 baud compact digital ready handheld TrunkTracker IV scanner featuring Fire Tone Out Paging, Close Call and Dynamically Allocated Channel Memory (up to 6,000 channels), SAME Weather Alert, CTCSS/DCS, Alpha Tagging. Size: 2.40" Wide x 1.22" Deep x 5.35" High

Frequency Coverage:

25,000-512,000 MHz., 764,000-775,987.5 MHz., 794,000-823,987.5 MHz., 849,0125-868,8765 MHz., 894,0125-956,000 MHz., 1,240,000 MHz.-1,300,000 MHz.

The handheld BCD396T scanner was designed for National Security/Emergency Preparedness (NS/EP) and homeland security use with new features such as **Fire Tone Out Decoder**. This feature lets you set the BCD396T to alert if your selected two-tone sequential paging tones are received. Ideal for on-call firefighters, emergency response staff and for activating individual scanners used for incident management and population attack warning.



Close Call Radio Frequency Capture - Bearcat exclusive technology locks onto nearby radio transmissions, even if you haven't programmed anything into your scanner. Useful for intelligence agencies for use at events where you don't have advance notice or knowledge of the radio communications systems and assets you need to intercept. The BCD396T scanner is designed to track Motorola Type I, Type II, Hybrid, SMARTNET, PRIVACY PLUS, LTR and EDACS analog trunking systems on any band. Now, follow UHF High Band, UHF 800/900 MHz trunked public safety and public service systems just as if conventional two-way communications were used. **Dynamically Allocated Channel Memory** - The BCD396T scanner's memory is

organized so that it more closely matches how radio systems actually work. Organize channels any way you want, using Uniden's exclusive dynamic memory management system. 3,000 channels are typical but **over 6,000 channels are possible** depending on the scanner features used. You can also easily determine how much memory you have used and how much memory you have left. **Preprogrammed Systems** - The BCD396T is preprogrammed with over 400 channels covering police, fire and ambulance operations in the 25 most populated counties in the United States, plus the most popular digital systems. **3 AA NIMH or Alkaline battery operation and Charger** - 3 AA battery operation - The BCD396T includes 3 premium 2,300 mAh Nickel Metal Hydride AA batteries to give you the most economical power option available. You may also operate the BCD396T using 3 AA alkaline batteries. **Unique Data Skip** - Allows your scanner to skip unwanted data transmissions and reduces unwanted birdies. **Memory Backup** - If the battery completely discharges or if power is disconnected, the frequencies programmed in the BCD396T scanner are retained in memory. **Manual Channel Access** - Go directly to any channel. **LCD Back Light** - A blue LCD light remains on when the back light key is pressed. **Autolight** - Automatically turns the blue LCD backlight on when your scanner stops on a transmission. **Battery Save** - In manual mode, the BCD396T automatically reduces its power requirements to extend the battery's charge. **Attenuator** - Reduces the signal strength to help prevent signal overload. The BCD396T also works as a conventional scanner to continuously monitor many radio conversations even though the message is switching frequencies. The BCD396T comes with AC adapter, 3 AA nickel metal hydride batteries, belt clip, flexible rubber antenna, wrist strap, SMA/BNC adapter, RS232C cable, Trunk Tracker frequency guide, owner's manual and one year limited Uniden warranty. Not compatible with AGEIS, ASTRO or ESAS systems. Order on-line at www.usascan.com or call 1-800-USA-SCAN.

More Radio Products

Save even more on radio scanners when purchased directly from CEI. Price includes delivery in the continental USA excluding Alaska.

| | |
|---|------------|
| Bearcat 898T 500 channel TrunkTracker III base/mobile..... | \$209.95 |
| Bearcat 796DGV 1,000 channel TrunkTracker III base/mobile..... | \$519.95 |
| Bearcat BCD396T APCO 25 Digital scanner with Fire Tone Out..... | \$519.95 |
| Bearcat 246T up to 2,500 ch. TrunkTracker III handheld scanner..... | \$214.95 |
| Bearcat Sportcat 230 alpha display handheld sports scanner..... | \$184.95 |
| Bearcat 278CLT 100 channel AM/FM/SAME WX alert scanner..... | \$129.95 |
| Bearcat 248CLT 50 channel base AM/FM/weather alert scanner..... | \$104.95 |
| Bearcat 92XLT 200 channel handheld scanner..... | \$109.95 |
| Bearcat 72XLT 100 channel handheld scanner..... | \$99.95 |
| Bearcat BR330T up to 2,500 ch. TrunkTracker III with Tone out..... | \$274.95 |
| Bearcat BCT8 250 channel information mobile scanner..... | \$169.95 |
| Bearcat 350C 50 channel desktop/mobile scanner..... | \$104.95 |
| AOR AR16BQ Wide Band scanner with quick charger..... | \$199.95 |
| AOR AR3000AB Wide Band base/mobile receiver..... | \$1,079.95 |
| AOR AR5000A+3B Wide Band 10 KHz to 3 GHz receiver..... | \$2,599.95 |
| AOR AR8200 Mark III Wide Band handheld scanner..... | \$594.95 |
| AOR AR8600 Mark II Wide Band receiver..... | \$899.95 |
| AOR AR-ONE Government/Export sales only 10 KHz-3 GHz..... | \$4,489.95 |
| Scantcat Gold For Windows Software..... | \$99.95 |
| Scantcat Gold for Windows Surveillance Edition..... | \$159.95 |

Bearcat® BC246T Trunk Tracker III

Suggested list price \$399.95/CEI price \$214.95
 Compact professional handheld TrunkTracker III scanner featuring Close Call and Dynamically Allocated Channel Memory (up to 2,500 channels), SAME Weather Alert, CTCSS/DCS, Alpha Tagging. Size: 2.72" Wide x 1.26" Deep x 4.6" High

Frequency Coverage:

25,000-54,000 MHz., 108,000-174,000 MHz., 216,000-224,980 MHz., 400,000-512,000 MHz., 806,000-823,987.5 MHz., 849,0125-868,987.5 MHz., 894,0125-956,000 MHz., 1,240,000 MHz.-1,300,000 MHz.

The handheld BC246T TrunkTracker scanner has so many features, we recommend you visit our web site at www.usascan.com and download the free owner's manual. Popular features include **Close Call Radio Frequency Capture** - Bearcat exclusive technology locks onto nearby radio transmissions, even if you haven't programmed anything into your scanner. **Dynamically Allocated Channel Memory** - Organize channels any way you want, using Uniden's exclusive dynamic memory management system. 1,600 channels are typical but **over 2,500 channels are possible** depending on the scanner features used. You can also easily determine how much memory is used. **Preprogrammed Service Search (10)** - Makes it easy to find interesting frequencies used by public safety, news media TV broadcast audio, Amateur (ham) radio, CB radio, Family Radio Service, special low power, railroad, aircraft, marine, racing and weather frequencies. **Quick Keys** - allow you to select systems and groups by pressing a single key. **Text Tagging** - Name each system, group, channel, talk group



ID, custom search range, and S.A.M.E. group using 16 characters per name. **Memory Backup** - When power is lost or disconnected, your BC246T retains the frequencies that were programmed in memory. **Unique Data Skip** - Allows the BC246T to skip over unwanted data transmissions and birdies. **Attenuator** - You can set the BC246T attenuator to reduce the input strength of strong signals by about 18 dB. **Duplicate Frequency Alert** - Alerts you if you try to enter a duplicate name or frequency already stored in the scanner. **22 Bands** - with aircraft and 800 MHz. The BC246T comes with AC adapter, 2 AA 1,800 mAh nickel metal hydride batteries, belt clip, flexible rubber antenna, wrist strap, RS232C cable, Trunk Tracker frequency guide, owner's manual and one year limited Uniden warranty. For more fun, order our optional deluxe racing headset part #HF24RS for \$29.95. Order now at www.usascan.com or call 1-800-USA-SCAN.

Buy with Confidence

Order on-line and get big savings

For over 36 years, millions of communications specialists and enthusiasts worldwide have trusted Communications Electronics for their mission critical communications needs. It's easy to order. For fastest delivery, order on-line at www.usascan.com. Mail orders to: Communications Electronics Inc., P.O. Box 1045, Ann Arbor, Michigan 48106 USA. Price includes \$30.00 UPS Ground shipping/handling/insurance per scanner to a street address in the continental USA excluding Alaska. Add \$20.00 shipping for all accessories. For shipments to Canada, Puerto Rico, Hawaii, Alaska, Guam, P.O. Box, APO/FPO, USPS Priority Mail or UPS 2 business day delivery, add \$30.00. Michigan residents add sales tax. No COD's. For Bearcat scanners your satisfaction is guaranteed or return item in unused condition in original packaging within 61 days for refund, less shipping charges. 10% surcharge for net 10 billing to qualified accounts. All sales are subject to availability, acceptance and verification. Prices, terms and specifications are subject to change without notice. We welcome your Discover, Visa, American Express, MasterCard, IMPAC or Eurocard. Order toll free, call 1-800-USA-SCAN or 1-734-996-8888 if outside Canada or the USA. FAX anytime, dial 1-734-663-8888. Dealer and international inquiries invited. Order your radio scanners from Communications Electronics today.

For credit card orders call
1-800-USA-SCAN

e-mail: cei@usascan.com

www.usascan.com

PO Box 1045, Ann Arbor, Michigan 48106-1045 USA
 For information call 734-996-8888 or FAX 734-663-8888

COMMUNICATIONS ELECTRONICS INC.
 Emergency Operations Center

Visit WWW.USASCAN.COM • 1-800-USA-SCAN

A Life of Service in Amateur Radio



Photo by Ken Reitz KS4ZR

This story begins many decades ago when a young lad of ten fell from a garage roof while trying to catch a swinging rope and hit the ground on his stomach. As it turned out, no injuries were sustained, but the parents of this fellow put him on house restriction and no more catching of ropes hanging from a tree!

What to do about this parental decision? Obviously, it was the end of all the fun, but was it? As a diversion from this outside activity, our young lad turned to his best friend and they decided to learn the Morse code (CW) together using little buzzer units connected by wire from room to room. It wasn't long before both boys became code proficient with increasing speeds.



Harry Dannals as W2TUK in 1947 at age 19 in the station he shared with his dad, W2GG, using an ARC-5 converted military transmitter for 80 meters and a BC-779 (WWII version of the Hammerlund Super Pro). (Courtesy: Harry Dannals W2HD)

Before long the young lad was listening to CW on the amateur radio receiver that his dad, W2GG had, and a life-long interest in ham radio quickly developed. As you now certainly know, that person was your writer and a wonderful and fascinating life began that has covered seven decades. The story continues today and what follows are highlights of that time.

Budding Ham Career Interrupted

As a twelve year-old I would often help my dad, the commanding officer at his Naval Communications Reserve group on Long Island, by sending CW to Navy trainees. Sometimes, when dad was on a distant assignment, "bootleg" radio contacts were made on CW between my dad and

mom. Mom would read my code copy over my shoulder and tell me what to send.

A year later I found myself riding in a National Guard half-track in Clearfield, Pennsylvania, as the radioman, relaying our position in CW to the other half-track on maneuvers whose radioman was my dad. I got the job because the actual operator had called in sick. My dad told the National Guard Commander that I could do the job and he said, "But, isn't he just a kid?" My dad said, "Yes, but he's a better operator than anyone else here."

Dad was called to active duty in early 1941, assigned to Norfolk, Virginia and, unfortunately, study for my ham radio license took a step backward because moving required school changes and keeping up with school work was very important. Dad was then sent to the Panama Canal Zone as Officer-In-Charge of a radio receiving site. World War II started just weeks later. By then the federal government had banned all amateur radio activities and the ham bands went silent. My plans for a license had to be put on hold.

After graduation from Balboa High School, in the Canal Zone, my Navy life began for real. My dad was my first commanding officer, something never to be recommended! There was no "boot camp," so my first assignment was washing dishes while attending radio classes on the local base. The classes were easy because my code speed was now more than 25 words per minute.

Since Navy operating procedure had been part of my early life with my dad, all that was necessary was learning to type. I began standing radio watch at the receiving site at the age of 17 and another phase of my life began with my entry into a career in electronics, radio, and communications.

Learning quickly about the operation of our radio equipment and, having a deep interest in naval communications, led to early promotions. Eventually I became the supervisor of more than 20 radiomen and support personnel. Radio Balboa, with the call sign NBA, was one of the Navy's key radio stations and it was an honor to be the youngest Watch Supervisor at that time at the age of 18.

Another Try at a Ham Ticket

Discharge from the Navy came in mid-1946 and I found myself back in the U.S. after almost



W2TUK in the attic shack at his first home with his wife Kay in Bethpage, on New York's Long Island. On the bench: a Johnson Viking II transmitter with VFO, a Collins 75A4 receiver, and Johnson MatchBox that fed a 40 meter dipole. (Courtesy: Harry Dannals W2HD)

five years away. I was ready for another phase in life; one that I hoped would include a return to studying for an amateur radio license. I had enrolled at Polytechnic Institute of Brooklyn (now Polytechnic Institute of New York University), majoring in electrical engineering with an emphasis on electronics. I was eager to learn as much as I could about the fast changing world of electronics.

College work required a lot of time, but I found a way to prepare for my amateur license by doing a research paper for an English class using amateur radio as a resource. Among my references was the American Radio Relay League's (ARRL) *Radio Amateur's Handbook* with the latest ARRL license manual on the side! It worked, and my call sign, W2TUK, was received that year with a great deal of joy by me and my dad.

My early days as a licensed ham started with the handling of messages on the air, something that had been a major part of my Navy career. This also began my association with the ARRL, an organization which has been a very important part of my ham radio involvement.

Graduation from college in 1950 was a milestone that led to my employment at the Sperry Corporation where I worked in radar and other engineering programs. But, Sperry, too, had a connection with ham radio. During almost



In 1964 at the New York World's Fair, Dannals was trustee for K2US, the official U.S. amateur radio station. Here he's at the key of an all-Hallicrafters station. (Courtesy: Harry Dannals W2HD)

40 years of my employment there, the company provided a club station, W2YKQ, which was on the air during lunch periods, a fact that made the more than 200 ham radio operators that worked at Sperry very happy.

But, let's get back to the days after graduation. Another avenue had been opened when I applied for a direct commission as a naval officer which resulted in a new Ensign being added to the ranks. The Naval Security Group program was anxious to have qualified applicants and a new naval career for me soon followed. The final result of several decades of service as commanding officer of two highly rated Security Group divisions and an association with the communications world, ended with my retirement from the Navy as a full Commander in 1987.

Kay Enters the Scene

Before returning to my association with the ARRL, there is a very important part of my life that must be told. It involves meeting a very pretty, pleasant employee at Sperry whose carpool had busted up with a change in overtime work hours. She was in this carpool with another rider who needed a ride and he was, of all things, one of the Sperry hams. He approached me for a ride and that was OK. Then he said there was another person who needed a ride from the same pick-up point. My answer was simply that, while he was an old friend, someone else was going to be a newcomer to me and was questionable as a passenger. However, he was convincing and the gal who has been my wife for almost six decades



Mid 1990s W2HD is at the key for Field Day at WA4TFZ, club station for the Albemarle Amateur Radio Club (Charlottesville, VA). (Courtesy: Harry Dannals W2HD)

was that passenger!

Kay and I have had a wonderful, busy life with four kids (two boys and two girls); twelve grand-children, and three great-grandchildren. Without her support for my involvement in amateur radio, there would simply be no story to tell. I thank Kay many times over for enabling my amateur radio activity.

As part of this story of ham radio and family, it should be mentioned that I am the son of a ham (K4GG when he became a Silent Key); the brother of three hams: Frank (W2DRL) and two who have become Silent Keys. And, I'm the father of two hams, Bob (W2GG, my dad's old call) and Tom (W2TUK, my old call). It's fun to have ham radio as a bonding tool.

The League Beckons

And now, back to the ARRL. During my direct involvement with the League, I have held many offices at various levels. As part of the League's field organization, I received appointments as Official Relay Station (ORS); Official Phone Station (OPS); Official Observer (OO), and Emergency Coordinator (EC). In the area of elected office I have been Section Communications Manager (SCM), the vice-director and director of the ARRL Hudson Division.

I was elected League president by the ARRL Board in 1972 and returned for a total of five two-year terms ending in 1982. It was my pleasure to serve the Amateur Radio Service which had given me so much over the years.

While, presiding over meetings of the Board and the Executive Committee was the responsibility of the office, to me, there was a message to be delivered to the League's membership and also to those hams who were not members.

This message is simple: Amateur radio is a service organization established with a basis and purpose as set forth by the Federal Communications Commission (FCC) in simple terms with the following key points: It is a voluntary, noncommercial, communication service, particularly with respect to providing emergency communications; to demonstrate a proven ability to contribute to the advancement of the radio art; to provide for advancing skills in both the communication and technical phases of the art; to provide trained operators, technicians and electronics experts; and finally, the extension of the amateur's unique ability to enhance international goodwill.

That was the key message I brought with me as I visited all fifty of the United States during my ten years in office. Many of my addresses to the assembled groups started out with the words, "I am proud to be a radio amateur because we continue to be responsive to our basis and purpose."

In addition to the visits to all 50 States, trips were made to the Canal Zone, Puerto Rico, Canada, Mexico, Chile, Peru, the Bahamas, Bermuda and the United Kingdom. Many of the visits to the countries beyond our borders were made as the U.S. representative to Region II of the International Amateur Radio Union (IARU). It was interesting to note as I traveled abroad that the ARRL and U.S. amateur radio was well respected and looked to for leadership in our mutual interest.

The Politics of Ham Radio.

One of the key events during my presidency was the preparation for the World Administrative Radio Conference (WARC) of 1979. The future of our radio frequency bands was of prime importance with retention and possible expansion as goals. ARRL staffers as well as volunteers were deeply involved with this effort. The concept of an additional band or more to bridge the gap between the existing Amateur Radio assignments had been set forth by A. Prose Walker of the FCC.

He envisioned having new bands between 40 and 20 meters; between 20 and 15 meters, and between 15 and 10 meters. The League took the concept into its workload by preparing details and promoting the idea with other countries seeking their support at the WARC level.

Vic Clark, W4KFC, then ARRL First Vice President (now a Silent Key), was asked to visit and work closely with IARU Region II countries in South and Central America plus the Caribbean islands. He performed this task with tremendous success and all of the countries in Region II voted in support at the WARC. All their efforts paid off with very successful results. The 30, 17 and 12 meter bands were approved with small, but foothold, assignments.

During my tenure, I made frequent visits to FCC offices in Washington to discuss ham radio repeater issues, possible expansion of Citizen Band (CB) frequencies, and other points. The CB subject ended with a congressional hearing on a Class "E" service taking the 220 MHz band from ham use to CB. My appearance before the hearing committee was to defend the continuation of the ham radio assignment and we were successful at that time. Subsequently, however, 40 percent of the band was lost to others (not CB) due to our lack of use. The remainder of the band is presently in use by hams for repeaters, links and other activities.

Another appearance before a Congressional Committee was concerned with radio frequency interference (RFI) to devices in the TV and audio field. Ham radio was successful here also; making the point that interference was not due to our equipment, but the lack of adequate filtering in the external device.

Without question, the time devoted to ARRL matters, working with the very capable and dedicated staff, and my association with the board of directors was a wonderful experience. Each year was punctuated by new developments for ham radio. A volume of great memories will never be forgotten.

Another chapter in my life began with the Quarter Century Wireless Association (QCWA) as a director and then president from 1989 to 1994. It is interesting to note that this was the first time that one person had held both offices.

As a licensee for 63 years, I am still active every day on the ham bands from my home in Charlottesville, Virginia and, if you tune to 14.291 MHz, you can hear me daily on the Sperry Net.

It has been a very interesting life. The challenges of new avenues in communication are wonderful to observe and, I believe, will keep amateur radio alive and well for decades ahead. I hope to meet you there!

MT

How to Beat the Dismal Sunspot Cycle: Go Digital

Several years ago, like most hams, I was bemoaning the state of the sunspot cycle, – or more properly, the non-sunspot cycle – occurring just when I had been bitten by the DX bug. It just didn't seem fair. Then one day a casual mention from *MT* assistant editor, Larry Van Horn N5FPW sent me scurrying to the friendly confines of the more popular digital modes: PSK31 and RTTY. It was so much fun that I've operated almost exclusively in those modes since.

❖ The Many Modes of Digital Operating

I had heard of RTTY (short for radioteletype) many years before. The term mostly conjured images of old-time Associated Press Teletype machines clacking away in the back rooms of radio stations and newspaper offices. Large boxes of continuous-fold AP copy paper spooled up into the machine's constant chatter and dropped neatly printed with the latest news into a box to be culled by various editors. But, that's an image from a half century ago.

The RTTY now used by hams is merely one of several software programs that can be downloaded into your computer (usually for free) and interfaced to your HF transceiver. The interface can be one of many manufactured units such as the Tigertronics Signalink USB (see photo), but shortwave listeners can tune in these digital conversations by simply taking the audio output of your receiver and plugging it into the microphone input of your computer's soundcard: no need for an external interface. Adjusting the volume on the receiver will help get good copy: too much volume will distort the signal, too little will make the signal unreadable.



West Mountain Radio offers a wide range of products such as the RIGblasterPlus and RIGblasterPro that interface between your computer and your radio with prices ranging from \$120-350. (Courtesy: West Mountain Radio)



Tigertronics' Signalink USB (\$100) is a compact digital interface that comes with a CD of software for the most popular digital modes including PSK31, SSTV, CW, RTTY, AMTOR, and Packet. (Courtesy: Tigertronics)

Current digital mode software programs are not just for RTTY, but typically handle most other digital modes, including the oldest digital mode of them all: CW (Morse code). They can also do PSK31 (Phase Shift Keying at 31 baud); Slow Scan TV (SSTV, a painfully slow way to transmit a still TV image); Packet transmissions (also common at VHF or UHF frequencies, using repeaters or amateur satellites), and a few other lesser used modes. The bulk of most HF digital mode operating is done with PSK31 and RTTY.

❖ Slow but Sure

PSK31 and RTTY are relatively slow modes that don't offer Forward Error Cor-

rection (FEC) or allow big chunks of data to be exchanged quickly. Letters are sent as they are typed on the computer keyboard. To speed things up, as in CW, a "code" of abbreviations is often used: "BTU = Back To You," "TNX FB QSO = Thanks for the Fine Business (great) QSO (conversation)," etc. A QSO can go as fast as you can type.

Digital mode operators typically transmit at under 25 watts, many at far less than that, for two reasons. First, the nature of the narrowband transmission, especially PSK31, makes this mode a DX mode. It is seemingly immune to the vagaries of poor band conditions, static, fading and other forms of interference, so there's no need to run high power. Second, increasing the power simply makes the signal more broadband, not necessarily easier to copy. There's no better way to earn the wrath of your fellow PSK31 operators than to crash onto the frequency with a "dirty" .5 kHz-wide signal. The best compliment you can receive is that your digital signal is "clean."

Still, it's possible to run high power and put out a clean digital signal. Many operators from Asia run as much as 500 watts and put out terrific (and clean) digital signals. But, they have to have the sensitive antennas to match their big signal output to avoid being "alligators" – all mouth, no ears.

Just how great is PSK31 as a QRP, poor-

ARRL BAND PLAN FOR DIGITAL MODES

| Band (Meters) | Frequency | Mode, Notes |
|---------------|--------------------|--|
| 160 | 1.800-1.810z | PSK31, RTTY, other digital modes |
| 160 | 1.843-2.000 | SSTV, SSB and other wideband modes |
| 80 | 3.570-3.600 | Domestic RTTY, PSK31 and other digital modes |
| 80 | 3.590 | RTTY and other digital modes DX Operating Frequency |
| 40 | 7.040 | RTTY and other digital modes DX Operating Frequency |
| 40 | 7.080-7.125 | Domestic RTTY, PSK31 and other digital modes |
| 30 | 10.130-10.140 | All RTTY |
| 30 | 10.140-10.150 | Packet |
| 20 | 14.070-14.095 | RTTY (Most PSK31 in centered at 14.070) |
| 20 | 14.095-14.995 | Packet |
| 20 | 14.230 | SSTV Calling Frequency |
| 17 | 18.100-18.105 | PSK31 and RTTY |
| 17 | 18.105-18.110 | Packet |
| 15 | 21.070-21.110 | RTTY, PSK31 |
| 15 | 21.240 | SSTV Calling Frequency |
| 12 | 24.920-24.925 | RTTY, PSK31 |
| 12 | 24.925-24.930 | Packet |
| 10 | 28.070-28.150 | RTTY, PSK31 (Most PSK31 in centered at 28.120) |
| 10 | 28.680 | SSTV Calling Frequency |
| 6 | 50.620 | Packet Calling Frequency |
| 6 | 51.120-51.180 | Digital Repeater Inputs |
| 6 | 51.620-51.680 | Digital Repeater Outputs |
| 2 | 145.01,03,05,07,09 | are widely used for Packet |
| 2 | 145.800 | International Space Station Packet Repeater Downlink |



The MFJ-1275 (\$110) is a versatile digital interface that comes with a power supply and RS-232 cable. (Courtesy: MFJ Enterprise)

band-conditions mode? My first contact was on a seemingly dead 15 meter band. I had been "reading the mail" on 20 meters to get my feet wet in copying this mode, but was reluctant, due to the crowded conditions on 14.070, to try my hand at a QSO. So, I moved up to 15 meters. On arriving at 21.070 MHz I was disappointed to see that, unlike 20 meters which had 10 or 15 separate QSOs transmitting simultaneously, there were no signals. I tuned up to the SSB portion of the band and heard nothing. There weren't even any signals in the CW basement of 15 meters.

I kept the transceiver tuned to 21.070 and kept working at the desk, glancing now and then at the screen that would indicate the presence of a signal. One time I saw a very small spike on the screen indicating a transmission. It might have been just a random tone. I placed the cursor over the peak of the signal and watched the screen. In a few seconds a CQ from SV8UM, Aegina Island, Greece, magically appeared on the screen. I clicked the transmit button on the HamScope screen and started typing. Minutes later I had completed my first digital QSO on what had been an otherwise "dead" band.

In the last four years, and at the worst possible part of the solar cycle, I've worked a total of 188 countries using digital modes (ARRL DXCC awards don't make any distinction between PSK31 and RTTY modes, both are considered "digital" modes for their awards purposes) and confirmed 155 of those contacts. In fact, if it weren't for digital operating, I would not have worked many countries that I hadn't previously gotten on SSB, including Mongolia, Tajikistan and Antarctica.

❖ Becoming a Savvy Operator

It takes a while to become a proficient operator in the digital modes. Two things seem to be the most difficult for beginners. One is just learning the use of all of the options available on any of the digital programs. Getting used to the various modes, setting the polarity (reverse polarity for bands below 30 meters) and setting the balance from your computer's audio card to avoid overdriving the audio input, and using "macros." A macro is a ready-made stream of information that you prepare yourself and is used to speed up the typical exchange of information in a QSO.

That brings me to the second biggest problem with these modes. Many hams are terrible typists. Some of us are a little older and have trouble seeing what we're doing and so make a lot of typographical errors (referred



QSL from SV8UM on a "dead" 15 meter band. (Courtesy: Author)

to as having "fat fingers"). Others are simply "hunt-and-peck" typists, which really slows down the QSO speed.

By pre-setting your macro buttons you can place your cursor on the proper macro and simply click it. Miraculously, a stream of typing begins to appear on the screen (without errors) that makes it seem like you're a really great typist. Instructions on setting up macros vary from program to program, but once you figure it out, you can tailor your macros to respond to many common on-air questions.

Many hams have complete lists of everything in their shack on these macros and this works well in many QSOs; it's often part of the "first QSO protocol" between stations. But, not with a rare DX station. It's the second way to earn the wrath of your fellow digital mode operators: hitting the macro containing your "brag" file. The minutes drag by while your computer details every little power supply and connector in your shack; every detail about your computer and the interface you're using. For this reason some DX operators, when sending a CQ, finish their call with the words "no brag files, please."

Most digital QSOs are done simplex: the transmitting frequency is the same as the receiving frequency. In the case of a rare DX station, especially a DXpedition station, operating simplex is inviting total chaos on the frequency. Better DX operators choose to operate "split" on digital modes. They will explain their operation in their CQ. For example: "CQ CQ CQ de FRIHA up 2 QRZ?" That means "I'm calling all stations and listening up the band 2 kHz, any station come now." So, if the DX station is transmitting on 14.084 MHz that means that he or she is listening for your call on 14.086 MHz, not 14.084.

Sometimes, particularly during a DXpedition, the station will be even more specific: "CQ CQ CQ de 3Y0X listening up 2-4 NA only." That means, "I'm transmitting here but listening between 2 and 4 kHz up the band for North American stations only." To work a station operating split, you have to set your transceiver to do so, too. Your owner's manual will explain how this is done. A third way to irritate all other digital mode operators is to ignore the DX station's instructions and send your call on the proper frequency when you're not from the area the station is asking for.

Sometimes stations responding to the



Typical RTTY screen shows the distinctive twin peaks of a RTTY signal, in this case, RK6CK, Temyruk, Russia. (Courtesy: Author)

DX station forget to set the split button on their transceiver and mistakenly transmit on the DX station's transmitting frequency. The DX station can't hear that you're transmitting on his frequency, but everyone else can. That usually brings out the "frequency cops" who add to the chaos by sending "up up up up, lid...he's listening up, you idiot... what don't you understand about up?, etc." So, check your transceiver to make sure your settings are correct before you hit the transmit button and save us all a lot of grief.

There are times, particularly during a rare DXpedition, that the DX station takes up a big chunk of a particular band by announcing that they are listening up (and sometimes down!) 10 or 20 kHz. This makes it hard for any other digital operators to function on the band, as every kHz is taken in a 20 kHz segment by hard core digital DXers eager to put this one in the log. Many will trample on anybody's QSO just to log the DX. So, before you transmit, see if there are any other non-participating QSOs happening on the frequency on which you're about to transmit. If there are, move.

And, finally, there are many chances to rack up your DXCC count during the seemingly innumerable digital mode contests. These contests can also create a lot of animosity among non-digital operators by causing the contesters to occupy great amounts of a band that may be typically used by other modes. Try to avoid interfering with the enjoyment of our crowded ham bands, particularly on the weekends when these contests are often held. It's called being a "considerate operator" and, it's the true ham spirit.

Discover Longwave!

BeaconFinder II Directory

- 75+ pages, ready for 3-ring binding
- Covers 0-530 kHz spectrum
- Lists 100's of Beacons
- \$13.95 Postpaid



Sounds of Longwave

- Discover the intrigue of LW
- Hear Natural Radio, Milcom, WWVB, Beacons, Euro-BC, Lowfers, & more!
- \$13.95 Postpaid (Specify CD or Cassette)

Kevin Carey, Box 56, W. Blmfld, NY 14585

Looking for South Africa? Try the Internet!

If you ask shortwave radio enthusiasts for their favorite part of the world to tune in, many would say Africa. But in recent years, the opportunities to tune in stations from this part of the world have been greatly reduced. Thankfully, the Internet continues to provide an option for the world to listen to many of these stations, especially those originating from South Africa.

I started my search of South African radio stations by listening to 702 Talk Radio in Johannesburg, where the topic of the moment was American celebrities who were coming to African countries and adopting children "as a fashion accessory." There was also discussion about global diamond prices and their effect on the local economy.

Next, it was a trip to Cape Town's Bush Radio 89.5 FM. After a few station promos for "the best hip-hop from South Africa," the music began. The station really does offer a good mix of both local hip-hop artists as well as artists from the United States, the United Kingdom, and elsewhere.

Staying in Cape Town, I found some more traditional African sounding music on Tygerberg FM 104. While not in English, the station did have a pretty good mix of music from the region, in the style of Paul Simon's "Graceland" album.

More of a Western music feel could be found on Port Elisabeth's Algoa FM. During my listening session, the mix of a British sounding personality and a mix of current hits and those from the 1980s made it almost feel as if I was listening to a station in Britain or Australia.

Cape Town seems to have more stations with an American sound than do some of the surrounding towns. Examples of these are KFM 94.5, which also features British-sounding imaging and pop music from America; SA FM was playing Peaches and Herb's "Re-united" during my listening session, but the station features South African personalities. While I was listening, local callers were calling in debating ways to fight the AIDS epidemic in South Africa.

Overall, there seems to be a good mix of South African culture to be found from the country's local radio stations, but as one of the more advanced countries in Africa,

there is a large dose of Western culture influencing the programming as well.

In the GlobalNet links below, you will find a site listing all of the stations mentioned here as well as a few others.

Shortwave listeners might be familiar with Channel Africa, but it can be difficult to tune in from the United States. Have no fear, the Internet provides another option for listeners. The station that claims to be "the gateway to Africa" provides a wide variety of programs, each highlighting a different aspect of African culture. A full broadcast schedule can be found on the Channel Africa Web site.



❖ Internet Radio Bucks the Trend

While the terrestrial radio industry is on the verge of collapse or at the very least in a major decline, Internet radio is seeing further growth not only in the amount of advertising revenue it is bringing in, but also in the number of listeners that are jumping on board.

Recent surveys by both Arbitron and Edison Research show the number of Internet radio listeners over the age of 12 in the United States has grown to more than 42 million. That is an increase in share from 13 percent in 2008 to 17 percent in 2009. Also, when you combine projected revenues for Internet radio and podcasting advertising, some surveys see as much as a 28 percent increase in revenue for the industry.

But true trends are hardly ever noticed in the span of a year. So what does the growth curve look like in the past couple of years? In short, explosive.

According to a report published by *Media Daily News*, from 2006 to this year, traditional media saw a 30 percent drop in advertising revenue, while Internet advertising grew in that same period by some 37.5 percent.

What does this mean for the streaming enthusiast? Think of it as something like job security. If the industry continues to grow as it currently is, the impetus for broadcasters

to embrace the Internet market should only increase.

There had been some concern that with the struggling global economy, Internet products would be the first to take a hit in many broadcasters' bottom lines. However, with advertising revenue growing for their online components, many broadcasters might just turn to their Internet product to be the thing that saves them from bankruptcy.

A big part of that increase is also thanks to an increase in users accessing streams from their mobile phones. Leading the charge is Pandora, which claims 45,000 new users a day on their mobile phone service alone. Blackberry and iPhone users are pushing Internet radio into uncharted waters for the industry and should make a push for even further developments in the mobile streaming product world.

❖ One Stream to Rule Them All

The Internet Media Device Alliance (IMDA) has recently announced a certification standard for stand-alone Internet radio players. The standard, called IMDA Profile 1, should streamline competing technologies and make things easier and more efficient for consumers.

Right now, there are many different technologies and codecs for the various streaming profiles, which are expensive to develop. The streamlined profile should cut those costs, and might even lead to a flood of new devices in the market.

The standard dictates that Internet radio players must be able to decode both WMA and mp3 codecs. In addition, they must be able to handle playlist files such as M3U, ASX and PLS. Developers claim that new devices bearing the IMDA certified logo will be hitting stores by Christmas 2009.

Further standardization of streaming video and other products is also said to be on the agenda for the IMDA.

❖ LAUNCHcast wins Appeal

Yahoo's LAUNCHcast service, which has been fighting in court over paying extra licensing fees normally paid by streaming music providers, won a Federal appeal's court ruling recently, saving them from having to pay hundreds of millions in licensing fees.

The court determined that LAUNCHcast



was not “interactive enough” and that the listeners of the service would not use it to replace buying music outright. They said the service provided no more user control over what songs will be played than if a listener picked a radio station in their car that played a certain format.

The move by the court could open the doors for other services to offer music to listeners as long as they don’t allow listeners to select specific songs that they want to hear.

❖ **New WiFi Radios Hit the Market**

It seems like every month there are more and more WiFi radios hitting the streets. Each seems to be an advancement over those that came before. This gives listeners more options with which to pull in their favorite streaming content.

Enter Logitech’s new addition: the Squeezebox Radio. The newest in a line that already includes the highly popular Squeezebox Boom, the Squeezebox Radio adds a few new touches to the basic WiFi radio. For one thing, the Squeezebox Radio adds a color video screen, allowing users to display album artwork and photo slideshows. Secondly, a new feature is the ability to share favorite tracks with Facebook friends, thanks to an included application.

The Squeezebox Radio retails for \$200, boasts a single mono speaker, alarm clock, auto-adjusting contrast on the display and a headphone jack. Coming in November, an optional accessory pack will be released giving users an infrared remote control and a battery pack that will provide up to six hours of portable operation.

In addition to the new Squeezebox Radio, Logitech is also updating their existing Squeezebox model in a version they are calling the Squeezebox Touch. The Touch is a gateway device that requires an existing audio system through which to route audio. It will retail for



\$300 once it is released in the U.S. in December and it will also have wall-mount capability with an optional \$100 mount.



South African radio stations:
www.surfmusic.de/country/south+africa.html

Channel Africa:
www.channelafrica.org/portal/site/ChannelAfrica/
Internet Radio Revs Up:
www.emarketer.com/Article.aspx?R=1007264

Media Daily News:
www.mediapost.com/publications/?fa=Articles.showArticle&art_aid=113045

More users listening to Internet radio on their phones:
www.switched.com/2009/09/13/internet-radio-taking-leap-from-the-desktop-to-the-pocket/
IMDA Announces New Certification:

www.reuters.com/article/pressRelease/idUS112531+07-Sep-2009+BW20090907

LAUNCHcast wins court ruling:
www.newsday.com/online-radio-service-wins-ruling-over-license-fees-1.1385302

Squeezebox Touch, Radio:
www.macworld.com/article/142588/2009/09/squeezeboxtouchradio.html

Revo Ikon on CNET:
http://news.cnet.com/8301-17938_105-10316713-1.html

Pure Siesta Flow:
www.pocket-lint.com/news/26875/pure-siesta-flow-elan-chronos

Pure Company Web site:
www.pure.com/
VTech IS9181:
http://content.zdnet.com/2346-9595_22-337120.html

Another WiFi radio available for streaming enthusiasts is the Revo Ikon. Those with iPods or iPhones will especially enjoy the Ikon’s docking station. The Ikon also includes a color video screen with an icon-based navigation, full support of Internet radio and Digital Audio Broadcasting, DAB+ and terrestrial radio broadcasts with RDS-support.

The Ikon will be available sometime this month, but at a hefty \$450.



Readers in the United Kingdom have a new choice for bedside Internet radio. The Siesta Flow, which will retail for £99.99, offers a different waking tone for each day of the year, USB connectivity to power external devices (mp3 players, etc.), DAB and FM radio reception, and iPod/mp3 inputs.

The Siesta Flow and other new Pure WiFi radio products can be ordered through the company’s Web site, listed in the links table at the end of this article.

Finally, VTech, the popular cordless phone company, has also now jumped on the



WiFi radio bandwagon, with the release of the IS9181 (\$160 retail).

What makes the VTech model an attractive choice? Portability. The IS9181 can be powered with 6 AA batteries, making it one of the few portable table-top WiFi radios on the market. Also, it has a down-firing subwoofer, which should give the audio coming from the speakers plenty of low-end. Curiously, a few features were not included with the IS9181, most notably, a headphone jack, the model also lacks Pandora or podcast support.

GRACE Wi-Fi

Now you can listen to more than 15,000 streaming radio stations from around the world! Famous networks like the BBC and NPR; international shortwave stations; talk show and music broadcasters of every imaginable kind; even scanner traffic like police, fire and EMTs from metropolitan action centers! Simply plug any of these units into your Internet phone line, or invisibly join your wireless network from anywhere in your home or office—no computer needed.

Order ITC-IR1000
\$174^{95*}

Order GDI-IRP600
\$194^{95*}

**plus \$13.95 UPS Ground or Priority Mail shipping*



800-438-8155 order@grove-ent.com
828-837-9200 7540 Highway 64 West
fax: 828-837-2216 Brasstown, NC 28902

www.grove-ent.com

Taming Talkgroups

Trunked radio systems are capable of carrying many conversations simultaneously. Have you ever stopped to consider how those systems keep track of each conversation and make sure that the correct radios participate in the correct conversation? More importantly, do you know how your scanner manages to track those same conversations?

Hi Dan.

I have read both introductory articles you've written on how trunked radios work and found it to be very helpful. However, I have searched the web and still cannot find anybody who can explain to me how do I find out what the talk group IDs are?

I currently own a Bearcat BCD996T Trunk tracking scanner that I sort of know how to use but don't understand how to program it correctly. The system I am trying to track is the local police and I am simply listening to them in the conventional manner between the frequency range 417.320 MHz and 420.440 MHz. I am speaking under correction but there are four control channels (417.780/ 417.920/ 419.720/419.960) or what sounds like control channels (sounds like a motor boat) but I am not sure how to program my scanner to listen to the conversation correctly.

Could you please assist me in setting up the scanner or could you please explain?

Bevil in Cape Town, South Africa

In order to explain how trunked radio systems use talkgroups, we need a bit of background, so let's start with some basics. Trunked radio systems use a set of radio frequencies assigned by a national authority responsible for spectrum allocation. In the United States, this duty falls to the Federal Communications Commission (FCC) for public safety and commercial organizations. For what is generically called "Land Mobile" communications, these frequencies are typically assigned in pairs, where one frequency is designated for mobile-radio-to-base (sometimes referred to as the *Inbound* direction) transmissions and the other for base-to-mobile-radio (*Outbound*) transmissions.

The actual signals carried on these inbound and outbound frequencies are usually classified as either *voice* traffic or *control* traffic. Voice traffic is the actual message content from the radio user, typically the user's voice in analog or digital format. Control traffic consists of digitized commands, requests, and other data used to carry out the moment-by-moment operation of the system. The control traffic is not supposed to be heard or noticed by the user; it is intended

for the digital microprocessors inside trunked radio and base station equipment.

Outbound control traffic is almost always continuous, meaning a base station is transmitting on the assigned control frequency all the time, even if it doesn't have any instructions for any particular radio at the time. Inbound control traffic comes from individual radios out in the field, and occurs only when a radio is requesting service or responding to a previous outbound control command. The inbound control frequency is shared by all active radios within range of the base station.



As you might expect, both outbound and inbound voice frequencies are active only when they are carrying part of a conversation. If no one is using the system at a particular moment, all of the voice frequencies will be idle.

When a user wishes to communicate on the system, pressing the push-to-talk button causes the radio to transmit a request message on the inbound control channel. The system will quickly locate an idle voice frequency pair, if there is one, and assign it to the requesting radio. It informs the radio of the assignment over the outbound control channel.

The requesting radio immediately retunes to the assigned inbound voice frequency and emits the ubiquitous "beep-beep," informing the user that he or she may begin speaking. When user is done and releases the push-to-talk button, the system releases the assigned voice frequency pair back to the "idle pool" and waits for another request to come in. Meanwhile, the requesting radio has retuned to the outbound control channel and listens for subsequent instructions.

❖ Talkgroups

Before a radio can work properly on a trunked radio system, it must be programmed with a few pieces of information. At a minimum it needs to know the radio frequencies of the control channels, so that it can send and receive requests and instructions. It also needs to know which other radios it can communicate with. Technically, any radio can communicate with any other radio on the system, but not every conversation is relevant to every user. Because



all users share the same trunked radio system frequencies, a method is needed to automatically indicate when a conversation is of interest to a user.

In trunked radio systems, a *talkgroup identifier* serves to organize conversations, or, more specifically, identifies the radios that can participate in a shared conversation.

Type II

| Talkgroup ID | Status Bits |
|--------------|-------------|
| 12 | 4 |

❖ Examples

Public safety agencies typically organize their users by function and geography. For example, police patrol officers may have two talkgroups, one for the north side of town and the other for the south side. Detectives may have their own talkgroup, separate from the patrol officers. Our example system may also be shared by the fire department, which will have a completely different set of talkgroups for their operations – dispatch, fireground, arson investigation, training, and so on.

So, we can create a simple talkgroup list for this system:

| Talkgroup Number | Description |
|------------------|-----------------------|
| 10 | Police Patrol (North) |
| 20 | Police Patrol (South) |
| 30 | Detectives |
| 40 | Fire (Dispatch) |
| 50 | Fireground |
| 60 | Investigators |
| 70 | Training |

During a normal day for our fictional system, all the radios are tuned to the outbound control channel, waiting for an instruction. At some point, one of the patrol officers in the south end of town wants to speak with the dispatcher. When the officer presses the push-to-talk button, the radio transmits a request message containing the officer's talkgroup number, 20, on the inbound control channel. The system receives the request, assigns a

voice channel to talkgroup 20, and transmits a "channel assignment" message that includes the talkgroup number on the outbound control channel.

Since all of the town's radios are tuned to the outbound control channel, every radio receives the channel assignment message. Each radio immediately checks to see if the talkgroup number it was programmed with matches the talkgroup number in the message. If so, the radio tunes to the assigned voice channel and unmutes the squelch, allowing the user to hear the voice traffic. If the radio is not programmed for the talkgroup, it simply discards the message and waits to receive the next outbound control channel message. In this way, each radio decides whether to participate in a conversation based on talkgroup numbers that were programmed into it.

❖ Open and Closed Scanners

A scanner monitoring that same outbound channel will receive the same channel assignment messages coming from the system. Depending on the scanner and how it is programmed, one of following actions may take place:

If the scanner is programmed to operate in what is called "open" trunking mode, it will show the talkgroup number on the display and tune to the voice channel so that you can hear the conversation. It will do this for every assignment message it receives. By making note of the talkgroup number on the scanner's display and listening to the content of the voice traffic, you can begin to associate talkgroup numbers with specific departments and activities.

If the scanner is programmed to operate in "closed" mode, the scanner will check if the talkgroup number received in the assignment message is also in a list of previously-programmed talkgroups held in its memory. If it is in the list, the scanner will tune to the voice channel and allow the user to listen. If the received talkgroup number has not been programmed into memory, the scanner will ignore the channel assignment message and continue listening to the control channel.

This suggests a two-step process for monitoring a trunked system. The first step is a data collection stage, where you collect and identify the various talkgroups that appear on the system by running in "open" mode. Once you have the groups you're interested in, you move to the second stage, which is the "closed" mode where you listen only to the talkgroups you're interested in.

❖ Uniden BCD996T

The Bearcat BCD996T is a high-end base/mobile scanner introduced in 2006. Among its many features is a "Talk Group ID Auto Store" that automatically stores every new talkgroup number it monitors. This feature is described in the Owner's Manual beginning on page 99 and might be an easy way for you to quickly accumulate a list of talkgroup numbers. You

will still need to listen to the traffic related to each talkgroup to figure out what departments and/or activities the talkgroup refers to.

The BCD996T uses different terminology for "open" and "closed" trunked system monitoring. On page 48 the manual describes "ID Scan" as the equivalent to our closed mode and "ID Search" as the open mode. You will want to operate in "ID Search" mode, at least in the beginning, in order to capture all of the available talkgroups on the system.

Before doing any of this, though, you will need to determine exactly what type of system you're actually monitoring. The BCD996T is capable of tracking activity on most types of Motorola and EDACS (Enhanced Digital Access Communications) systems, as well as LTR (Logic Trunked Radio) and Project 25-based networks. Until you correctly identify the system, the scanner will not know how to interpret the messages it receives on the outbound control channel.

❖ Status Codes

Sometimes talkgroup numbers carry more information than just an identifier for a conversation. Talkgroups in a Motorola Type II system, for instance, can also carry status information between the radio and the base station. You may have noticed that sequential Motorola talkgroup numbers go up by 16 rather than by 1. This is because of status bits that are part of every talkgroup identifier.

Motorola Type II talkgroup numbers use 16 bits (a bit is a "binary digit" that can be either a 0 or 1), broken up into a 12-bit Identifier field and a 4-bit Status field. The 12 bits represent the actual talkgroup number, which can range from 0 up to 4095. The four status bits give 16 possibilities and represent a code with the following meaning:

Code Meaning

| | |
|----|--|
| 0 | Normal message |
| 1 | Fleet-wide message (to reach all radios) |
| 2 | Emergency |
| 3 | Patch between talkgroups |
| 4 | Emergency and patch |
| 5 | Emergency and multi-group selection |
| 6 | Not assigned |
| 7 | Multi-Group selection |
| 8 | Talkgroup is encrypted |
| 9 | Encrypted, Fleet-wide message |
| 10 | Encrypted, Emergency |
| 11 | Encrypted, Patch |
| 12 | Encrypted, Emergency, Patch |
| 13 | Encrypted, Emergency, Multi-Group |
| 14 | Not assigned |
| 15 | Encrypted, Multi-Group selection |

Most scanners typically display whatever talkgroup number they receive, whether it has a status code set or not. This can lead to some confusion if you're looking at received talkgroup numbers and find ones that aren't even multiples of 16. When you find such a talkgroup, consult the status code table to see what extra information is being transmitted. If you're programming your scanner to operate in the "closed" trunking mode, you may miss some interesting activity if you have only the normal talkgroup number programmed in.

GRE PSR-500

- Frequency Coverage 25.000-1300.000 MHz (less cellular)
- Menu Driven Programming with Context Sensitive Help
- Flexible Free-Form Memory Organization
- GRE's Exclusive V-Scanner Technology
- Multi-System Trunking
- P25 NAC Functionality
- Exclusive ALERT LED
- Spectrum Sweeper
- Real-time Signal Strength Indicator
- SAME and All Hazards Weather Alerting and SKYWARN



Order SCN18

\$ 449^{95*}

* plus \$17.95 UPS Ground shipping in the U.S.

GROVE

800-438-8155
828-837-9200 fax: 828-837-2216
order@grove-ent.com
7540 Highway 64 West
Brasstown, NC 28902

www.grove-ent.com

WWW.SCANCAT.COM

**ORDER TOLL FREE
888-722-6228**

COMBO CD SPECIAL

Reg. \$29.95
ScanCat-Lite-Plus.....\$29.95
Mr. Scanner FCC Public Safety\$29.95
Nat-Com's FCC Scancat Files\$9.95
Bonus Disk Of Frequencies.....\$15.00
NOW \$49.95 \$84.85

PLUS FREE Scanning Magazine(s)
(With Purchase Of Special. While Supplies Last)

**SUPPORT JUST ADDED FOR
RADIOSHACK PRO-106/197/404/405
UNIDEN BCD-346XT/396XT/996XT**

ScanCat-Lite-PLUS
Reg. \$39.95 - Limited Time Special \$29.95

**Now It's Easier Than Ever To
Use Your ScanCat Software.**

**FREE walk-you-through set up
video to get you going fast.**

www.scancat.com **You Tube**
Click on learn as you view.

**Scancat-Gold for Windows
Version 8.50 \$99.95**

**Scancat-Gold for Windows-SE -
\$159.95**

Skysweep Decoder Software \$99.95

**COMPUTER AIDED
TECHNOLOGIES**

ORDERS: (318) 687-4444 FAX: (318) 686-0449
Info/Tech Support: (318) 687-2555
(9 a.m. - 3 p.m. Central M-F)

WWW.SCANCAT.COM

❖ Oswego, New York

Oswego, New York fire and police have gone to EF Johnson trunking system and none of my scanners will receive them. I am looking to buy one that will.

Is there any scanner available now that will trunk these frequencies correctly? I purchased a Bearcat 898T but it receives a clocking interference on the control channels. I also have various other scanners but they all do the same thing.

Thanks,
Bob

Oswego is a city of about 18,000 residents located on the shore of Lake Ontario in north central New York. Oswego is also the name of the county, which covers about 1,300 square miles and is home to nearly 120,000 people.



Since 2001 Oswego County has been operating an upgraded Logic Trunked Radio (LTR) system, transmitting from five base stations located in Boylston, Constantia Center, Dexterville, Hastings and Oswego on the following frequencies: 851.1375, 851.4625, 851.6125, 851.6375, 851.6875, 852.0375, 852.0875, 852.4375, 852.5125 and 852.5375 MHz. A sixth site in Redfield transmits on 852.3875 and 852.8875 MHz.

Logic Trunked Radio was developed by the E. F. Johnson company back in the late 1970s. A number of variations have been introduced since then, including the Multi-Net version of LTR used in Oswego County. Multi-Net supports several advanced trunking features, including the ability to queue channel requests when no frequencies are available and the use of unique radio identifiers.

Unlike other trunking systems with a channel dedicated to control messages, LTR systems combine voice and control traffic on the same radio frequency. Voice is transmitted in analog format with the control information carried in a "sub-audible" data stream. Radios listen to this data stream and act on the messages found there.

Radio frequency pairs are assigned a Logical Channel Number (LCN) that can range from 1 to 20. Messages in the data stream use these LCNs rather than sending the actual radio frequency, since LCNs are much shorter and therefore consume less bandwidth.

Radios on an LTR system are assigned a "home channel" and monitor the sub-audible data stream there when idle. If the system is not busy, conversations will take place on that channel. When the home channel for a radio is busy, the system may assign an alternate channel for a conversation. Messages in the data stream of the home channel will inform all



listening radios that a conversation is taking place on a different channel, causing them to retune to that channel. The radios then return to monitoring their home channel when the transmission is finished.

❖ LTR Talkgroups

Talkgroups are called "Group Identifiers" in an LTR system and are made up of three parts. The first part is an "Area Code" which can be either a 0 or 1 and is used to distinguish between

LTR Talkgroup Format

| | | |
|-----------|---------------|---------|
| Area Code | Home Repeater | User ID |
|-----------|---------------|---------|

Area Code: 0 or 1
Home Repeater: 01 to 20
User ID: 000 to 254

two nearby LTR systems. All of the talkgroups from a system will have the same Area Code. If there is another LTR system nearby, all of its talkgroups will use the other Area Code and thus keep the two systems from carrying each other's traffic.

The second part of a Group Identifier is a two-digit number from 1 to 20 that identifies the "home repeater" channel that a radio will monitor when it is idle. This corresponds to the LCN assigned to that radio frequency channel.

The third number is called a "User ID" or "Group Value" and ranges from 0 to 254. Each radio programmed with this code will be part of the talkgroup.

❖ Monitoring Multi-Net

Although there are several scanner models on the market that are able to track standard LTR systems by monitoring the sub-audible data stream, no scanner currently on the market is able to understand the Multi-Net messages and therefore cannot track conversations if subsequent transmissions use an alternate channel. However, since the voice traffic is in analog format, a scanner will be able to hear individual transmissions and you can monitor the system in conventional (non-trunked) mode.

Since you have more than one scanner, here's a technique that might help you to follow the action in Oswego.

1. Program the first scanner with the two most active frequencies on the system, which are 851.4625 and 852.5125 MHz. You will probably hear most activity on 852.5125, but keep 851.4625 as a Priority scan to be sure not to miss any "overflow" traffic.
2. Program a second scanner with all of the remaining frequencies, being sure not to include the two frequencies in the first scanner.

❖ Computer-based LTR Monitoring

If you have a computer and are adventurous, there are a couple of software programs that might help you follow the action on LTR and LTR Multi-Net systems.

At <http://home.ica.net/~phoenix/wap/> LTR you will find a ZIP archive containing a

program called **LTR-Analyzer**. This program runs under the Microsoft Windows operating system (from Windows 98 up through Vista) and requires a sound card and a scanner with a discriminator output. Once everything is configured and running, the program will display the control messages on the outbound channel the scanner is tuned to. The program can also produce detailed reports containing lists of channel numbers and talkgroups observed. For Multi-Net systems, the program can identify channel numbers that are in use.

A pair of programs, called **LTRTrunk** and **LTRDump**, were under active development a few years ago that analyze and track activity on LTR systems, including Multi-Net. Unfortunately, they don't appear to be readily available today despite an apparent need for such tools.

I would be interested in hearing from readers who are using computer programs to help them monitor LTR systems. Send me an email with the details of your set up, including web site links, and I will put the results on my web site at www.signalharbor.com.

You may also find activity in Oswego County on the following frequencies, if they are still in use:

| Frequency | Description |
|-----------|---|
| 45.72 | Highway Department |
| 153.995 | County Fire and Emergency Medical Services (Dispatch) |
| 154.115 | State University of New York at Oswego Police |
| 155.130 | Oswego City Police |
| 155.160 | School Buses |
| 155.250 | Sheriff (Dispatch) |
| 155.730 | Oswego City Police |
| 155.955 | State University of New York at Oswego Police |

That's all for this month. You can read more about trunking, talkgroups, and LTR on my website at www.signalharbor.com. In the meantime, have a Happy Thanksgiving, take a moment to consider everything you have to be thankful for, and if you're looking for a chance to get away from the in-laws for a while, listening to a scanner can be a great escape!

MTXTRA: AIR REFUELING LISTENERS GUIDE

Subscribers to MT Express not only get Monitoring Times in color, with active links to web pages and email addresses, they now get access to additional material.

In NOVEMBER ONLY, your MT Express password will give you access to the complete listener's guide to Air Refueling Tracks and Anchors, with maps, designators, frequencies, call signs, responsible military units, and more. See the Milcom column on page 52 for a taste of what is available.

Every month MTXtra's Shortwave Listener's Guide is updated and available for download. The guide lists schedules for all languages, sorted by time.

A subscription is \$19.95 per year, or only \$11.95 if added to an existing print subscription. Call 1-800-438-8155 or email order@grove-ent.com for more information.

Monitoring Times

7540 Hwy 64 West, Brasstown, NC 28902

Q. *I have been given an atomic clock which monitors the 60 kHz frequency standard station in Colorado. At those low frequencies, how can it send enough data to set my clock? Isn't there a time delay for the signal to be accurate over distances? (MB, Indiana)*

A. WWVB continuously broadcasts time and frequency signals at 60 kHz at a data rate of 1 bit per second using pulse width modulation. The code contains the year, day of year, hour, minute, second, Daylight Saving Time, leap years, and leap seconds.

VLF signals travel by ground wave; the delay of arrival at your location would only be 0.006 seconds. I doubt that your clock can display time that accurately!

Q. *I am thinking of replacing my outdoor loop antenna with an active whip like the LF Engineering H-800 or H-900, then reduce the electrical noise interference with an MFJ 1025 noise canceller. What should I use for the noise antenna? (Fred Edwards, email)*

A. The key here is the separation of the desired-signal antenna from the noise antenna so that you don't cancel both the signal and the noise. That's the reason to put the noise antenna near the noise; with that canceled, the only thing left is the desired signal from the receive antenna.

If I were doing the installation, I'd first mount the serious antenna as high and away from power lines and household noise as possible. It would be great if you could carry a portable shortwave radio with you as listen for the minimal noise spot to install the antenna.

For the noise antenna, simply run a random wire around the edge of your room (ceiling or floor) for some 10-20 feet; that should be enough to pick up enough ambient noise to cancel the lesser noise heard on the rooftop active whip.

The H-800 and H-900 are omnidirectional, while the loop is bidirectional. You may still wish to leave the loop in place in case you want to favor one direction over another. The H-800 is excellent; we sell a lot of them to very happy listeners. The primary advantage of the 900 is its slightly-greater dynamic range. If you are plagued with local overload, get the 900; if you aren't, get the 800.

Every situation is somewhat different. After mounting the antenna in that quiet spot, try placing that random noise antenna wire around in

different locations while playing with the noise canceller to find the best configuration for noise reduction.

Q. *How often should I replace my 100 foot RG-6/U outdoor coax cable? When I do, should I replace it with LMR-400? (Shon Clark, Concord, CA)*

A. RG-6/U is good, all-around coax for outdoor installations. The general rule of thumb for all coax, however, is to replace it every five years. On the other hand, my cable has been up for some 15 years and I don't detect any worsening loss.

LMR-400 is lower-loss cable, but only by 2-3 dB at 900 MHz, and it's considerably more expensive. You would only see very minor improvement on the weakest signals at that frequency, and even less at lower frequencies.

Q. *Years ago I remember a gadget that you plugged into an electrical outlet to use the household wiring as a substitute for an outdoor TV antenna. Did these things actually work? (MB, email)*

A. I actually have one of those in my quackery/fraud collection. They didn't work worth a hoot or they'd still be on the market and there wouldn't be rooftop antennas. Some of the deficiencies include:

1. Household wiring isn't resonant on any particular TV frequency for proper impedance matching;
2. Wiring is electrically long in terms of TV wavelengths, rejecting signals broadside to the wires;
3. Incoming signals were blocked by household aluminum siding and metalized Mylar insulation;
4. Since they were connected to appliances all over the house, they were rife with electrical interference;
5. Because wiring is routed near conductive wiring, ducting, and metalized insulation, it was lossy.

Q. *The Slinky® toy is periodically resurrected as a portable dipole for ham and SWL use. Can it be assumed that its performance is really the same as a conventional wire dipole of the same length? (email)*

A. Because the Slinky is, in fact, a coil, it has a Q (selectivity) which varies with frequency depending on how compressed or stretched it is. Thus, its bandwidth/impedance characteristics vary differently than a straight wire of the same length.

If we aren't concerned about the Q (as in the case where it's being used as a random-length receiving antenna), then yes, its performance (aperture to intercept signal voltage) would be roughly equal to a straight wire antenna of the same length.

Q. *When we saw fire trucks going by our house today, we got out a very old scanner that we picked up at an auction years ago, but didn't hear anything. Have emergency communications all gone digital? (Wendy Kedzierski, Berryville, VA)*

A. While digital has definitely taken hold of the public safety agencies, it's been in steps that were bad for scanner listeners for a while until the consumer electronics industry caught up. Here's a simplified chronology:

1. Years ago, everything was analog (like AM/FM radio);
2. For security purposes, agencies started using analog scramblers until the consumer market started making analog descramblers;
3. The FCC and Congress banned descramblers that were intended to decode privacy communications, but these devices were still easy to come by or even make yourself;
4. Scanner manufacturers introduced digital scramblers that couldn't be duplicated in the workshop, and manufacturers kept the algorithms (codes) confidential;
5. Along came trunking so that a given series of transmissions could keep changing channels and analog scanners couldn't follow them;
6. The scanner industry then made trunk-tracking scanners, so we got back to at least step 4;
7. Following communications failures after 9/11, a reliable digital standard was called for by the government for interagency communications; APCO P-25, an open (public) algorithm, not developed for security, was adopted and has been widely implemented;
8. Scanner manufacturers now make P-25 compatible scanners.

Of course, there's still the possibility that your fire department has simply changed frequencies! One easy way to check local frequencies for your area is to go to www.radioreference.com and look up Clarke County.

Questions or tips sent to Ask Bob, c/o MT are printed in this column as space permits. Mail your questions along with a self-addressed stamped envelope in care of MT, or e-mail to bobgrove@monitoringtimes.com. (Please include your name and address.)

Around the Bands: Odds and Ends

Let's start with some old business from last month, namely the Green Angels radio network in Mexico. You might remember how this civilian service helps motorists in trouble on the nation's major toll highways.

I was all set to go wall to wall with everything I've learned about its use of high-frequency radio (HF). Once again, though, Mike Chace-Ortiz beat me to it, with some great information from a knowledgeable Los Angeles listener. Readers are advised to grab the September *MT*, and read his excellent *Digital Digest* column that runs right after *Utility World*. About the only thing left for me to do is to note that extensive monitoring of 7790 kilohertz (kHz) upper sideband (USB) can back up everything that was said there.

The big news is that the Green Angels' radio network is not limited to the states around Mexico City. Along with Mike's source, I have monitored daily traffic from Baja California. One base station, identifying "Ensenada," is extremely loud in the morning. The woman has a distinctive voice, and she pronounces it as "En-sen-a-DAAAH." A few mobiles are also audible. They frequently mention such border areas as Tijuana.

Mike's source backs up my observation that signals from the mobile units show distinct characteristics of NVIS propagation. NVIS (Near Vertical Incidence Skywave) is a technique commonly used for military tactical nets.

Most of the time, NVIS is accomplished by tilting the typical vehicle whip antenna at an extreme angle from the vertical, sometimes almost horizontal, for a very high angle of radiation. The resulting skip is very strong in a local area, and there are no dead spots. Of course, this compromises the long paths, making it harder for us to hear.

I figured that all frequencies except 7790 were for Automatic Link Establishment (ALE). However, I heard a station follow a typical ALE burst on 7815 kHz with two-way voice communication. Is voice allowed elsewhere as well, or was this just a mistake?

Other ALE frequencies confirmed by monitoring here are 7563, 7640, 7802, 7815, 7828, 7920, 8115, 8175, 10364, and 10369 kHz. These are all USB. ALE nets typically use a much wider frequency range, but then, the ones we hear don't usually use NVIS. Maybe this has something to do with it.

Mention the Green Angels, and the essential service they render, next time someone tells you that "Nobody uses short wave any more."

❖ Two-Year-Old Scholars?

Many thanks go to the alert readers who did the arithmetic on the Walter Kendall Myers "Cuban spy" case mentioned in the September *Utility World*. It would have been very nice if I had done the same. Then, I would not have written that Myers, age 72, was a noted political writer at the start of World War II - when he was two years old!

The confusion is due to late hours doing "research" on the Internet. I read the many Google hits properly when they said he wrote A Rationale for Appeasement. The part that I rather woosily missed was that it was the title of his Ph.D. dissertation in 1972.

And so, yes, Myers is accused of spying for Cuba. But no, he was not giving foreign policy advice when he was two.

I hope that everyone can see my bright red face right through the paper or screen. I apologize for a BIG oops on THAT one.

❖ Kyodo News Lives!

I don't know if the problem was lousy band conditions, or something else, but no one had reported the Kyodo News FAX for months. Now, however, the radiofacsimile transmission from this respected Japanese news agency is alive and well. I have it printing just fine on 16971.0 kHz. As winter comes, these long paths should improve in the United States.



Technically, shortwave fax is analog frequency modulation (international designator F3C), with a center frequency of 1.9 kHz. Deviation is plus or minus 400 hertz, with tone frequency corresponding to brightness. Black is therefore 1500 hertz, and white is 2300.



Fax is tuned in USB mode, and is centered properly when your dial reads around 1.9 kHz lower than the published frequencies. Most multi-mode digital programs do fax, though it's usually fussy to get it absolutely straight.

Other published Kyodo frequencies are 4316.0, 8467.5, 12745.5, 17069.5, and 22542.5. These come from JJC, Tokyo Radio, in Japan.

There is also a transmitter in Singapore, call sign 9VF, using 16035 and 17430.

Kyodo spends most of its daily schedule sending a Japanese newspaper. This runs at 60 lines per minute (LPM), half normal speed. Their web site claims about 1600 subscribers on ships, remote islands, or in communities abroad.

A small English newspaper is sent daily at 120 LPM. This is intended for foreign crew members on Japanese ships. Fishery charts are also broadcast.

Since these broadcasts are for subscribers, we should treat anything we receive as someone else's property. Kyodo used to scramble a lot of their products, and we'd hate to see that happen again.

❖ HBG Going Off-Air

As we discussed in August, long-wave time stations are very popular for the automatic setting of consumer and commercial "atomic clocks." Well, in two years there will be one less such signal.

This news comes in a press release from the Swiss Federal Office of Metrology (METAS), which operates the HBG standard time station on 75 kilohertz (kHz). This station will leave the air at the end of 2011.

As always, the reason is money. Inspection has revealed significant age-related weakening of the 300-foot antenna towers in Prangins. Some good photos of this majestic site are at www.emetteurs.ch/gallery/Prangin/Antennes_HBG_1

METAS cannot afford the necessary repairs, and an independent study found few or no other options. One suggestion was to find a commercial user for a multiplex signal on HBG's carrier. Another was to pass the operation to a different agency. Neither proved feasible.

The long notice is so Swiss institutional users can reconfigure master clock systems. There are, according to the release, 3600 of these in schools and churches.

METAS claims that nearly all industrial, laboratory, and consumer devices used in Switzerland will also work with Germany's mighty DCF77 on 77.5 kHz. Many are probably using it already. The DCF77 signal uses compatible, though not identical, encoding. Reception is said to be about the same.

METAS will continue to distribute the Swiss time standard by Internet. Network Time Protocol users can go to ntp.metas.ch. The METAS web site, in four languages, is at www.metas.ch.

ABBREVIATIONS USED IN THIS COLUMN

| | |
|----------------|---|
| AFB..... | Air Force Base |
| ALE..... | Automatic Link Establishment |
| AM..... | Amplitude Modulation |
| CAMSLANT..... | Communications Area Master Station, Atlantic |
| CAMSPAC..... | Communications Area Master Station, Pacific |
| COTHEN..... | Customs Over-The-Horizon Enforcement Network |
| CW..... | On-off keyed "Continuous Wave" Morse telegraphy |
| DHFCS..... | UK Defence High-Frequency Communications Service |
| DSC..... | Digital Selective Calling |
| EAM..... | Emergency Action Message |
| E10..... | Israeli phonetic station, with or without message |
| FAX..... | Radiofacsimile |
| FEMA..... | US Federal Emergency Management Agency |
| FSK..... | Frequency-Shift Keying |
| HFDL..... | High-Frequency Data Link |
| HF-GCS..... | High-Frequency Global Communication System |
| LDOC..... | Long Distance Operational Control |
| LSB..... | Lower Sideband |
| MARS..... | US Military Affiliate Radio System |
| MFA..... | Ministry of Foreign Affairs |
| MX..... | All Russian single-letter beacons/markers |
| NASA..... | US National Aeronautics and Space Administration |
| NAT..... | North Atlantic air control, nets A-F |
| NS/EP..... | US National Security/ Emergency Preparedness |
| PACTOR-I..... | Packet Teleprinting Over Radio, mode 1 |
| PR..... | Puerto Rico |
| RTTY..... | Radio Teletype |
| Selcal..... | Selective Calling |
| SITOR-A/B..... | Simplex Telex Over Radio, mode A or B |
| STANAG..... | Standardization Agreement |
| STS..... | Space Transportation System ("Space Shuttle") |
| UK..... | United Kingdom |
| Unid..... | Unidentified |
| US..... | United States |
| USAF..... | US Air Force |
| USCG..... | US Coast Guard |
| VOLMET..... | Formatted voice aviation weather |

All transmissions are USB (upper sideband) unless otherwise indicated. All frequencies are in kHz (kilohertz) and all times are UTC (Coordinated Universal Time). "Numbers" stations have their ENIGMA (European Numbers Information Gathering and Monitoring Association) designators in ().

| | |
|--------|---|
| 501.5 | EIOCF-Amateur with 500 kHz experimental license, Ireland, working GW3UEP, UK, CW at 2050 (MPJ-UK). |
| 502.8 | EIOCF, working GM3BST, Scotland, CW at 2210 (MPJ-UK). |
| 1797.0 | SDJ-Stockholm Radio, Sweden, maritime information in English and Swedish, at 2203 (MPJ-UK). |
| 2097.3 | "A"-CW pirate beacon, AZ, at 0925 and 1034 (Jim-GA). |
| 2187.5 | Keriolet-Irish fishing boat, arranging voice comm on 3425 with Fishing Vessel Boy Jason (EI7397), DSC at 1908 (MPJ-UK). |
| 2216.0 | XSS-UK DHFCS, Forest Moor, ALE sounding, also on 3226, 3236.5, 4166.3, 4239.5, 8167, 8182, 9019, 9020, 10344.5, 11208, and 12230, at 1010 (MPJ-UK). |
| 2311.0 | Arklow Radio-Arklow Shipping Company, Ireland, duplex with unheard vessel, at 1925 (Michel Lacroix-France). |
| 2971.0 | Shanwick-NAT-D oceanic air route control, position from Scandinavian Airlines 926, at 0235 (Prez-MD). |
| 3016.0 | Shanwick-NAT-A air control, selcal and position check with Lufthansa Cargo 827, at 0220 (Prez-MD). |
| 3053.0 | CBE-USCG Cutter <i>Tahoma</i> , ALE sounding, also on 4730 and 6709, at 1316 (Mark Cleary-SC). |
| 3181.0 | RMP-Russian Baltic Fleet, Kaliningrad, CW storm warning to group call sign REO, parallel 3264, at 1959 (MPJ-UK). |
| 3246.5 | Unid-Russian Air Defense, time-stamped CW idle strings, parallel 5221.5, at 2013 (MPJ-UK). |
| 3341.0 | FR4FEM001 (FEMA Region 4, GA), ALE sounding, also on 9462, at 1030 (MDMonitor-MD). |
| 3425.0 | EI7397-Fishing Vessel <i>Boy Jason</i> , working <i>Keriolet</i> in clear voice and secure Fishone, came from 2187.5, at 1912 (MPJ-UK). |
| 3449.8 | "OK"-CW pirate beacon, possibly OK, at 0931 (Jim-GA). |
| 3476.0 | Gander-NAT-F air control, Canada, working aircraft with Shanwick, Ireland/Scotland, at 0200. (MDMonitor-MD). |
| 3802.7 | Unid-German Red Cross, calling DEKA2710 (Hanover mobile), PACTOR-I at 1025 (ALF-Germany). |

| | |
|--------|---|
| 4026.9 | AAA4CH-US Army MARS, net with AAA4SC and AAA4WR, at 1137 (Cleary-SC). |
| 4031.0 | "P"-Russian Navy, Kaliningrad, FSK Morse broadcast in 5-figure groups, then back to single-letter marker, at 2233 (MPJ-UK). |
| 4077.4 | "MO"-CW pirate beacon, OK, at 0933 (Jim-GA). |
| 4088.8 | Unid-CW pirate dasher beacon, CA, at 1030 (Jim-GA). |
| 4096.2 | "Hexie"-CW pirate dasher beacon, CA, in and out at 0937 (Jim-GA). |
| 4096.6 | "Kelsie"-CW pirate dasher beacon, CA, in and out at 0939 (Jim-GA). |
| 4102.3 | "W"-Pirate CW wind beacon, CA, ID and wind speed pips, at 1016 (Jim-GA). |
| 4483.0 | DHJ67-German Air Force, Köln, working DHO78 in German, at 2104 (Lacroix-France). |
| 4703.0 | OWE-Danish Air Force, Karup, working unknown station in Danish, at 2105 (Lacroix-France). |
| 4744.5 | JWT-Norway Navy, Stavanger, voice and STANAG 4285 at 1957 (Lacroix-France). |
| 5097.0 | CFH-Canadian Forces, Halifax, NS, RTTY markers at 2125 (PPA-Netherlands). |
| 5118.0 | VMKI-Russian military, 5-letter CW message to Z09K, at 1756 (PPA-Netherlands). |
| 5138.5 | Russian Navy, weather for group call RKN (Caspian Sea Flotilla), CW at 0335 (ALF-Germany). |
| 5153.7 | "D"-Russian Navy CW single-letter beacon (MX), Sevastopol, Ukraine, also on 10871.7 and 13527.7, at 2034 (MPJ-UK). |
| 5153.9 | "S"-Russian MX, Severomorsk, CW beacon at 2111 (Lacroix-France). |
| 5157.6 | "Blinky"-CW pirate dasher beacon, possibly FL, at 1450 (Jim-GA). |
| 5166.0 | RIW-Russian Navy, Moscow, calling RIF80 and RIC83, CW at 0501 (PPA-Netherlands). |
| 5215.0 | RCV-Russian Navy, Sevastopol, working RJD83, CW at 0342 (ALF-Germany). |
| 5270.5 | DELTA03RS1006-Uzbek Military, working ASKAR17RS1006, ALE at 0115 (ALF-Germany). |
| 5334.0 | 035-Hungarian military, working 082, ALE at 2045 (PPA-Netherlands). |
| 5343.0 | RIT-Russian Navy, Severomorsk, calling RIR96, CW at 2108 (PPA-Netherlands). |
| 5598.0 | N552UA-United Airlines Boeing 757, checking selcal BS-LQ with Shanwick, at 1912 (Lacroix-France). |
| 5616.0 | Reach 188-USAF Air Mobility Command, working Shanwick at 0718 (Lacroix-France). |
| 5713.5 | FAV22-French military Morse code practice, Favières, CW drill messages at 2015 (MPJ-UK). |
| 6312.0 | J8B2638-St. Vincent and Grenadines vessel <i>Lona</i> , DSC safety test with Aarhus/Bremen, at 1927 (MPJ-UK). |
| 6330.5 | HBY4256-Swiss registry yacht <i>Citadel</i> , calling OSY (SailMail, Belgium), PACTOR-I at 1511 (ALF-Germany). |
| 6464.0 | 567-Unknown, raised 673 in ALE, then voice in French, at 0246 (ALF-Germany). |
| 6507.0 | VMC-Australia Weather East, Charleville, marine weather at 1800 (Jim-GA). |
| 6532.0 | FedEx 008-Federal Express freighter, HFDL position for Shannon, Ireland, at 2018 (Lacroix-France). |
| 6604.0 | Gander Radio-Canadian Volmet, aviation weather at 2127 (MPJ-UK). |
| 6617.0 | St. Petersburg Volmet, weather in Russian at 2106 (PPA-Netherlands). |
| 6676.0 | HSD-Bangkok Volmet, Thailand, weather at 1940 (PPA-Netherlands). |
| 6693.0 | Tyumen Volmet, weather in Russian at 1753 (PPA-Netherlands). |
| 6712.0 | CO0056-Continental Airlines, HFDL position for Reykjavik at 0524 (Lacroix-France). |
| 6729.0 | JWT-Danish Navy, duplex with unheard vessel, at 0724 (Lacroix-France). |
| 6733.0 | Ascot 5104-UK Royal Air Force C-130M, getting cricket scores from TASCComm (Tactical Air-Sea Comm), at 1155 (ALF-Germany). |
| 6751.0 | BRD-NASA Booster Recovery Director, Kennedy Space Center, FL, radio checks with STS-128 Booster Recovery Vessels <i>Freedom Star</i> and <i>Liberty Star</i> , at 0330 and 0403, then announcing weather scrub at 0526 (Hugh Stegman-CA). |
| 6800.0 | America 9-Unknown vessel, Spanish chatter with Medico 5, Barcelona 5, Denmark 1, and several others, at 1940 (ALF-Germany). |
| 6803.1 | ATTPRLCH101B249-AT&T NS/EP station, Pearl City, HI, working WNDRF252, probably in FL, ALE at 2139 (Jack Metcalfe-KY). |
| 6834.0 | GYA-UK Royal Navy, Northwood, FAX Middle East weather chart at 1837 (PPA-Netherlands). |

6840.0 EZI2-Israeli intelligence phonetic station (E10), callup only at 2001 (PPA-Netherlands).

6877.0 RIT-Russian Navy, Severomorsk, CW weather for group call RLO, at 0305 (ALF-Germany).

6897.8 S3D005E2-Moroccan weather net, calling 1S3D005E2, PACTOR-I at 0134 (ALF-Germany).

6945.0 Turkmenbashi Aero, Turkmenistan, working AMBA (Samara Aero, Russia), in Russian at 0306 (ALF-Germany).

7122.0 Unid-Russian military, messages for RDL in FSK Morse, at 0946 (ALF-Germany).

7480.1 ATTPHNXAZ01P255- AT&T NS/EP, Phoenix, AZ, working ATTCHPNSC01P148, AT&T Chapin, SC, ALE at 2236 (Metcalfe-KY).

7527.0 Foxtrot 35-USCG HU-25, securing guard with CAMSLANT at 1155 (Cleary-SC).

7530.0 CAMSLANT-USCG, VA, radio checks with District 7 and Sector Upper Mississippi, at 1308 (Cleary-SC).

7646.0 DDH7-German Weather Office, Pinneberg, RTTY observations for Europe, at 1740 (PPA-Netherlands).

7664.0 RIW-Russian Navy, Moscow, calling RFH77, CW at 1722 (PPA-Netherlands).

7675.0 RIT-Russian Northern Fleet, Severomorsk, working RMPV, CW at 1955 (MPJ-UK).

7697.1 CHLTNC116-Unknown NS/EP, Charlotte, NC, working BDMN-NJ112P, Bedminster, NJ, and WNDRF252, ALE at 1926. ATLAGA104-Unknown NS/EP, Atlanta, GA, working KEYWFL168, Key West, FL, ALE at 1709 (Metcalfe-KY).

7791.5 VES-USCG Cutter *Venturous*, ALE message "USCG NVIS Antenna Testing ALE Net," at 0225 (ALF-Germany). [NVIS = Near-Vertical Incidence Skip. -Hugh]

7841.5 DTNTAM-Algerian Direction des Transmissions Nationales (DTN), Tamansrasset, calling INGUES (In Guezam), PACTOR-I at 1905 (ALF-Germany).

7880.0 DDK3-Pinneberg weather, FAX surface chart at 1817 (PPA-Netherlands).

7903.0 XVS-Ho Chi Minh Radio, Viet Nam, fishery information in Vietnamese, at 1803 (PPA-Netherlands).

7918.0 YHF-Israeli E10, callup and message at 1938 (PPA-Netherlands).

8000.8 "S"-Pirate CW beacon, sometimes sending "H," at 1008 (Jim-GA).

8023.7 Unid-Egyptian Embassy, Rabat, Morocco, SITOR-A at 2025 (Lacroix-France).

8035.1 WQDT278-XNet Yacht Association, PACTOR idler and CW "XNET," also 8045.1, at 0005 (ALF-Germany).

8040.0 GYA-UK Royal Navy, Northwood, FAX chart at 0739 (PPA-Netherlands).

8047.0 MDANG-Texas Army National Guard, ALE sounding at 1200 (MDMonitor-MD).

8050.0 FC8FEM-FEMA Region 8, CO, calling unknown PASFEM, ALE, also on 14776, at 0100. PMHUNG-Unknown FEMA, calling PISTON, at 0400 (MDMonitor-MD).

8066.7 SSE-Egyptian MFA, Cairo, SITOR-B Arabic call to Rome, then SITOR-A, at 1829 (ALF-Germany).

8113.0 VMW-Australia Weather West, Wiluna, marine weather at 0903 (Jim-GA).

8114.0 Unid-Two probable fishermen, in Spanish, also on 8160, at 1039 (Jim-GA).

8211.9 "OR"-Pirate CW beacon, unknown location, at 1012 (Jim-GA).

8283.7 ARL4-Pakistani Navy, Karachi, calling vessel KCGO, PACTOR-I at 0120 (ALF-Germany).

8285.0 F213-Venezuelan Navy Frigate *Mariscal Sucre*, calling CGA3 (Headquarters), LSB ALE at 0028 (ALF-Germany).

8292.5 Unid-Algerian Provincial Net, calling several stations beginning in BOSTAN, PACTOR-I at 1555 (ALF-Germany).

8301.6 Sector San Juan-USCG, PR, setting aircraft guard at 2348 (Cleary-SC).

8340.0 F21-Venezuelan Navy, Frigate *Mariscal Sucre*, calling CGA3 (Headquarters), LSB ALE at 0300 (MDMonitor-MD).

8345.0 RIR96-Russian Navy vessel, calling RIT with message for RJH45, CW at 0559 (PPA-Netherlands).

8376.6 VFF-Canadian Coast Guard, Iqaluit, SITOR-B Arctic weather, at 2030 (MPJ-UK).

8393.0 RFH77-Russian Navy vessel, working RIR96, CW at 0030 (ALF-Germany).

8414.5 MGLJ9-UK registry container ship *Dirhami*, DSC safety test with Lyngby Radio, Denmark, at 1131 (Lacroix-France).

8550.5 CTP-Portuguese Navy, Oeiras, RTTY marker at 1100 (MPJ-UK).

8879.0 G-YMMC-British Airways Boeing 777, selcal BJ-KL with Gander, Canada, at (Lacroix-France).

8885.0 B-6080-Air China A330, flight CA0965, HFDL log-on with Mu-harraq, at 2003 (MPJ-UK).

8912.0 Foxtrot 33-USCG HU-25, working CAMSLANT at 1301 (Cleary-SC). TSC-US Customs, FL, calling F12, USCG Falcon Jet #2112, ALE at 1920 (MDMonitor-MD).

8918.0 N921AN-American Airlines B737, selcal BJ-CM with New York, at 2057 (Lacroix-France).

8930.0 N851EL-Gulfstream IV bizjet, selcal MR-AJ, working Stockholm LDOC at 2004 (Lacroix-France).

8971.0 Fiddle-US Navy, working P-3C Goldfinch 711, at 1623 (Cleary-SC).

8992.0 Jeep 23-US Air Force Reserve tanker, working Lajes HF-GCS at 2327 (Cleary-SC).

9000.0 Unid-Chinese Firedrake jammer, deliberately over-modulated AM oriental music, also on 11300, at 2024 (Mike T-West Sussex, UK).

9025.0 OFF-USAF, Offutt AFB, NE, calling 538029, USAF Reserve tanker #63-8029, at 1450 (MDMonitor-MD). Foxtrot 33-USCG HU-25, ALE-initiated patch to Cape Air, MA, at 2333 (Cleary-SC).

9034.0 NOJ-USCG, AK, calling J07 (an MH-60J), ALE at 0346 (Cleary-SC).

9110.7 RIW-Russian Navy, Moscow, working RFH77, went to 13469, CW at 1316 (MPJ-UK).

9145.0 RIW, working RFH77 in CW, at 1858 (MPJ-UK).

9180.0 RIW, working RGK39, CW at 1537 (MPJ-UK).

9201.0 FAV22-French military CW code practice, drill message at 1407 (MPJ-UK).

9228.0 LCR154-Polish Army, Janki, working SOG933, at 1356 (MPJ-UK).

9380.0 1Z8C-Venezuelan Navy, calling 1EW1 (Vessel *Goijaira*), LSB ALE at 0430 (MDMonitor-MD).

9462.0 PASFEM-Unknown FEMA, calling PASTOR2, ALE at 0130 (MDMonitor-MD).

9996.0 RWM-Russian standard time station, Moscow, CW pips at 1246 (Lacroix-France).

10024.0 Cenamer-Central American air control, position from Lancia 05 in Spanish, at 0120 (MDMonitor-MD).

10051.0 Gander Volmet, Canada, formatted aviation weather at 0125 (MDMonitor-MD).

10540.0 RCV-Russian Navy, Sevastopol, Ukraine, working RMK39 in CW, at 1759 (MPJ-UK).

10872.0 "C"-Russian MX, Moscow, also 13528, CW at 2017 (Mike-UK).

10872.1 "A"-Russian MX, possibly Astrakhan, also 13528.1, CW at 2018 (Mike-UK).

11003.1 "CO"-Pirate CW beacon, CO, at 1448 (Jim-GA).

11175.0 Red Alder-US military, patch via Puerto Rico HF-GCS to Geometric (Offutt AFB, NE), at 1635 (Allan Stern-FL).

11184.0 XA-MXP-Mexicana Airlines A330, flight MX1587, HFDL log-on with Reykjavik at 1517 (MPJ-UK).

11226.0 210193-USAF C-17, working HAW, Ascension Island, ALE at 2004 (Lacroix-France).

11232.0 Akela 96-USAF MC-130, patch via Trenton Military to Kirtland AFB, NM, at 1557 (Cleary-SC). Halifax Military-Canadian Forces, NS, patching aircraft Rescue 338 to Rescue Coordination Centre, went to 15010, at 1839 (Stern-FL).

11282.0 San Francisco-Pacific oceanic air control, selcal and position check with Hawaiian Airlines 407, at 0155 (Prez-MD).

11436.0 CAMSLANT-USCG, radio checks with District 7 stations at 1316 (Cleary-SC).

11494.0 PAC-USCG, CA, raised 716 in ALE, then voice as CAMSPAC working C-130 Coast Guard 1716, on COTHEN at 2050 (Stegman-CA).

12577.0 SWAK-Greek registry tanker *Minerva Eleonora*, DSC safety test with ECA6, Madrid, at 1357 (MPJ-UK).

12613.0 XSQ-Guangzhou Radio, China, service bulletin and back to SITOR-A idler, at 1450 (MPJ-UK).

12916.5 HLF-Seoul Radio, Korea, weak CW marker at 1442 (MPJ-UK).

13200.0 Red Alder, came from 11175 for Andrews (Andrews AFB, MD), both stations calling but not hearing other, at 1719 (Stern-FL).

13215.0 HAW-USAF, Ascension Island, ALE sound at 2103 (Lacroix-France).

13303.0 OD-MEB-Middle East Airlines A330, HFDL log-on with Canarias, Canary Islands, at 1524 (MPJ-UK).

13342.0 CS-TEJ-White Airways A310, selcal BM-CR with Stockholm LDOC at 1332 (Lacroix-France).

13469.0 RIW-Russian Navy, Moscow, working RJF77, came from 9179.5, CW at 1329 (MPJ-UK).

13527.9 "S"-Russian MX, Severomorsk, CW at 1449 (MPJ-UK).

13927.0 Batt 71-USAF B-2A, morale patch via USAF MARS station AFA5RS, IN, at 1905 (Stern-FL).

14389.0 AFA5AD-USAF MARS, patching MN Air National Guard Gofer ?? to Scott AFB for weather; came from 13927, at 1840 (Stern-FL).

14522.0 RMIB-Russian Navy warship, CW 5-figure group message, at 1452 (MPJ-UK).

15010.0 Halifax Military, radio check with Rescue 338, came from 11232, at 1842 (Stern-FL).

15867.0 I21-US Customs Cessna 550, registration N26621, COTHEN ALE sounding at 1945 (MDMonitor-MD).

16050.0 FUE-French Navy, Brest, working FAKB in STANAG 4285, at 0430 (Eddy Waters-Australia).

16557.0 FUE-French Navy, Brest, working unknown station in STANAG 4285, at 0530 (Waters-Australia).

21955.0 AAF279-Aigle Azur flight, HFDL position for Las Palmas, Canary Islands, at 1637 (Lacroix-France).

Maritime Listening with SITOR-B

This month we focus on activity from the some of the world's maritime stations. Though these sections of the HF shortwave bands have also seen a number of changes over the past decade and reflect the general shift away from simple modes like CW and SITOR, there are still many stations that can be picked up as long as you are patient.

First, let's look in a little more detail at SITOR, the system most favored by these stations.

SITOR in Focus

Simplex Telegraph Over Radio, SITOR for short, comprises two related digital systems. Both use two tones (FSK) at 100bd with a 170Hz shift as standard, though some organizations are peculiar or distinctive in their use of slightly different speeds and/or tone shift. Check UMC's Decoder Pages by Mike Agner (www.chace-ortiz.org/umc/software.html) for software that can read SITOR-A and B signals.

SITOR-A uses an ARQ format, or Automatic Repeat ReQuest to ensure that data arrives relatively error-free at the receiving station, whereas SITOR-B uses FEC or Forward Error Correction to accomplish the same function.

In SITOR-A, the information sending station (or ISS) sends a burst of characters, then waits for the acknowledgment from the receiving station (or IRS). If this is not received in the prescribed time interval, or the IRS was not able to copy the characters, it requests a repeat. All of this happens very quickly, in less than half a second, and is the reason for the familiar, rhythmic chirp-chirp-chirp of ARQ-type signals. ARQ thus works well for two stations and a one-to-one link.

FEC is better suited to a broadcast environment where there are multiple listeners. Without a "reply" signal from the receiving stations, the SITOR-B sending station ensures that its data gets copied well (again, not 100% guaranteed error-free) by sending the same characters one or more times interleaved or spread out in time. In the case of SITOR-B, it is spread by slightly less than half a second, or 350ms, with the characters being coded in a way that allows errors to be spotted. NAVTEX also uses SITOR-B.

Organizations using the standard SITOR-B signal include many coastal radio stations, many coast guard stations, US Forces MARS, Argentine Navy, Algerian Navy, Brazilian Navy, Portuguese Police, and the Diplomatic Services of both Egypt and Morocco.

The Ecuadorian Navy (see February 2006's *Digital Digest*) use the combination of 109bd and 400Hz tone shift.

Coastal Station SITOR-B

Despite the downturn in coastal radio station activity over the past years and their switch to more complex transmission systems, there are plenty of examples still on-air today.

Here is a list of recently monitored stations that provide easy listening opportunities in both the US and Europe:

VFF Canadian Coast Guard, Iqaluit

This station can be heard most evenings on 8376.6 kHz

NMC US Coast Guard, Point Reyes CA

Can be heard nightly on 6323.5 and 8416.5 kHz

SVO Olympia Radio, Greece

Transmits every day using SITOR-B on 4123, 8424, 12603, 16830.5 and 22388 kHz. You can see a Google Earth picture of the antenna farm at 37.604211N, 21.488196E.



SVO Olympia Greece (credit: Google Earth)

These stations send a variety of ship navigation warnings and other information in addition to weather and sea condition reports and forecasts.

Here are some examples of what can be received.

Example 1: The sign-off information for station VFF

```
mcts iqaluit / vff and nordreg canada
63 43 42 n 068 33 00 w
mmsi : 00 316 0023
mailing address : fisheries and oceans canada canadian
coast guard
officer - in - charge iqaluit mcts centre / nordreg canada
p . o . box 1 89 iqaluit , nu x 0 ~ 0 0
telephone numbers : 867-979-5 260 officer --8, -
charge 867-979-5269
mcts operations 867-979-
5724 nordreg operations
facsimile : 867-979-
4264 mcts / nor dreg
operations
telex number (telex) : 063-
15529 nordreg cda
electr-nic mail : iqanordreg
& innav . gc . ca
mcts iqaluit / vff , out
```

Note the "~" character in a few places

that is used by the Hoka decoder to denote that a character was received in error.

Example 2: Message from SVO in Greek with latest currency exchange rates

```
deltio timwn synallagmatos
dolario hpa : 1,4031
lira agglas : 0,86517
korwna danias : 7,5036
korwna soyhdias : 11,0537
gien iapwnias : 134,64
fragko elbetias : 1,5133
korwna norbhgias : 8,9536
dolario kanada : 1,5884
dolario aystralias : 1,7668
sdr dolario : 1,54179
sdr euro : 1,10761
stop
de svo svo velos kala taxidia
nnnn
```

STANAG4285 Independent Sideband Transmission

It is quite common practice to use the lower and upper sidebands of a transmitter to send independent signals on each. This is often heard with NATO Naval Link-11 signals (see October 2008's *Digital Digest*) and is sometimes heard in conjunction with the Russian Navy MS5 12 tone modems.

Not so often is an ISB STANAG4285 transmission heard. However, one has been heard using the frequencies of 8701 and 12704.5 kHz for the past few weeks.

The arrangement sends a regular KG84 encrypted stream of data on the upper sideband but the lower sends what appears to be a type of CARB (Channel Availability Radio Broadcast) as follows:
2315z//cta02i/cta04i/cta06i/cta08i/cta14i/cta16i// 2316z//cta02i/cta04i/cta06i/cta08i/cta14i/cta16i//

The (presumed) callsign of this station, CTA, has not been logged before and would indicate Portugal as the origin if it conforms to international standards. Consulting the ITU files suggests that this station is indeed located close to Lisbon judging by past STANAG4285 signals using the frequency.

DIGITAL BANDSCAN (8200 TO 8300 KHZ)

| | |
|---------|---|
| 8200.0U | Mexican PEMEX Oil & Gas Operations with DSC selcals on 8201.9 kHz |
| 8201.8 | UNID Codan 8580 controlled net with "2011", "2012", etc. |
| 8204.0 | Russian Forces 75bd/200 FSK secure |
| 8221.5U | Australian Forces MIL-188-110A HF modem continuous tfc |
| 8230.0U | Mexican Navy MIL-188-110A HF modem ASCII tfc |
| 8234.0U | Israeli Air Force USB Voice and MIL-188-141A ALE "AAA", "M64", etc. |
| 8243.0U | Mexican PEMEX MIL-188-141A ALE "REBOM1", etc. |
| 8258.0L | Moroccan Forces MIL-188-110A 39 tone modem, off-line crypto |
| 8270.0U | Venezuelan Navy MIL-188-141A ALE "CGA", "PR3", etc. |
| 8276.0U | French Navy MIL-188-141A ALE "1TLOFF", "1TA6FF", etc. |
| 8283.7 | Pakistani Navy PacTOR-II "ARL4", etc. |
| 8292.1U | Mexican PEMEX MIL-188-141A ALE "REBOM1", etc. |

PROGRAMMING SPOTLIGHT

WHAT'S ON WHEN AND WHERE?

Fred Waterer

fredwaterer@monitoringtimes.com

www.doghousecharlie.com/radio

Everything Old is New Again

The other day I was reading about a program that had been on the air since the 1950s. It got me to thinking about international broadcasters and the programs that have endured, in some cases for decades. I put on my thinking cap and came up with a list of such programs. Perhaps there is one I missed. If there is, please let me know! We'll also shine the *Programming Spotlight* on a long time favorite that has been revived.

❖ British Longevity

As one might expect, you will find a number of these programs at the BBC. Two of my favorites, are **Just a Minute** and **Brain of Britain**. Both are examples of light entertainment programming, which has been dropped, for the most part, from the World Service in favor of a concentration on news and current events – which is a pity. But that's a rant for another day.

Just a Minute is one of my all time favorite BBC programs. I'm not alone in this opinion, as the program is going as strong today as it did when it debuted in December 1967. Nicholas Parsons has hosted the program continuously for 42 years. The rules of the game are simple. A panelist must speak on a topic for sixty seconds without repetition, deviation or hesitation. It sounds fairly easy, but it's trickier than one might think. Especially with three other panelists primed to jump in and steal the topic at the first sign of an infraction.



The key to the success of this program is the fabulous cast of panelists over the years. When I first heard the program on the World Service in 1978, it was worth it just to hear the verbal sparring between the outrageous Kenneth Williams, the erudite Clement Freud, Peter Jones, and Derek Nimmo. Sadly all the original panelists have left us, but the game continues, thanks to a stellar cast of players, anchored by Paul Merton.

Today, **Just a Minute** can be heard via the BBC Radio 4 website. It usually runs for twelve or so weeks, twice a year. You can access the **Just a Minute** home page at: www.bbc.co.uk/programmes/b006s5dp In addition, BBC 7 frequently runs old episodes of **Just a Minute**, offering the listener a chance to once again hear Kenneth Williams steal the show, or Clement Freud steal the topic. www.bbc.co.uk/radio7/

Brain of Britain is another program I was introduced to by the World Service. It's a general knowledge quiz, hosted for many

years by Robert Robinson. "**Brain of Britain**, the longest-running of all the broadcast quiz shows open to the public in Britain, started life as part of the series **What Do You Know?** hosted by Franklin Engelmann on the BBC Light Programme in 1953." (BBC website)

The program has similarities to TV's *Jeopardy*. Contestants have 10 seconds to answer a question, and if they cannot, their turn passes to another contestant. Those who get five straight answers correct get a bonus point. I've always enjoyed "playing along at home," and Mr. Robinson has a very dignified, charming style. Winners of **Brain of Britain** often go on to compete in a series of **Brain of Brains** programs.

Like **Just A Minute**, **Brain of Britain** can be heard on BBC Radio 4. You can hear it at: www.bbc.co.uk/programmes/b00813s0

From Our Own Correspondent has been one of BBC's flagship programs for over 50 years. Each week the BBC uses its vast network of correspondents around the world to bring the listeners the stories behind the headlines, often with a personal perspective. It can be heard a number of ways. Radio 4: Saturdays, 1130. Second weekly edition on Thursdays, 1100 (some weeks only) Listeners can also download the podcast or read story by story at the programme website

http://news.bbc.co.uk/2/hi/programmes/from_our_own_correspondent/default.stm

❖ Canadian Mix

Next we turn to some Canadian programs that have been with us for decades.

Quirks and Quarks – In September, **Quirks and Quarks** began its 35th season as the flagship science program in the CBC Radio One line-up. The program's first host was renowned environmentalist Dr. David Suzuki. He was succeeded by Jay Ingram (who has gone on to host a similar show on Discovery Canada), and then by current host Bob McDonald. Both Ingram and Bob McDonald share the ability to explain scientific concepts in understandable language.

As the program website suggests, you don't need a PhD to enjoy it! This is evidenced by a reported weekly audience in Canada of half a million listeners, making it one of the most popular programs on CBC Radio One.

The program has won over 70 awards over its 35-year run. It can be heard at noon local time on Saturdays, 3pm Wednesdays and 11pm Mondays across the CBC Radio One network, via a podcast (available from www.cbc.ca/podcasting/), and on shortwave via the CBC Northern Quebec Shortwave Service at 1700 UTC Saturdays and 0400 UTC Mondays on 9625 kHz.

Cross Country Checkup has been Canada's

national kitchen table discussion since 1965, without a lot of the bombast usually associated with talk radio. The program has been hosted by a number of people over the years, most recently by Rex Murphy. Previous hosts included Dennis Trudeau, Harry Elton, Dale Goldhawk, Elizabeth Gray and Moses Znaimer. On occasion it has hooked up with NPR in the United States, or Radio Canada International to become an international talk show.

The program provides a lively and balanced discussion of the issues of the day and reportedly attracts as many as 5-10,000 callers. The program can be heard on the CBC Radio Network live across the country at 4pm Eastern Time. It can also be heard via shortwave at 2100 UTC on 9625 kHz. Finally, you can subscribe to the podcast (see *Quirks and Quarks* above).

As It Happens is perhaps the best current affairs program from CBC Radio. It's very simple. Using a telephone they talk to people all over the world. "As It Happens" gets its stories from 'the horse's mouth' – securing interviews with world leaders, rabble-rousers, bingo callers and deposed dictators. The show has a soft-spot for 'characters' and never turns its nose up at something wild, weird or wacky. And, on the complex and troubling stories of the day, **As It Happens** searches for greater understanding in the story behind the story." (AIH website)

A program like this doesn't last for forty years without being good. **As It Happens** has been hosted by some of the giants in Canadian radio, including Barbara Frum, Alan Maitland, and Barbara Budd. Michael Enright, during his time at the program, in effect alerted the world to the genocide in Rwanda through his calls to General Romeo Dallaire, who pleaded for reinforcements for his tiny UN Peacekeeping contingent, which was, instead, reduced. Carol Off's interviews with Benazir Bhutto were compelling radio, in light of Ms. Bhutto's subsequent assassination.

There is also a lighter side to the program. Barbara Budd has a keen wit, which shows through in some of the "wackier" interviews that are aired from time to time.

As it Happens can be heard weeknights at 630pm local (7pm in Newfoundland) across the full CBC network. Also listen on shortwave via the Northern Quebec service at 2330UTC on 9625 kHz. **As It Happens** also has a podcast available via the CBC podcasting page listed above. I'm told **As It Happens** can also be heard in the United States via some NPR outlets.

❖ Old Friends from Russia

Folk Box is another program that dates back many, many years. It hasn't changed a lot since Soviet times. Each week, Svetlana Ye-

kimenko presents a 30-minute showcase of folk music from Russia's many diverse cultural groups. You might hear the bells of one of Russia's many cathedrals, intriguing throat singers from the far north, stunning vocal ensembles and distinctive Russian musical instruments. It is one of the few programs which haven't changed all that much since the end of the Soviet Union. The only real difference is that they no longer discuss the former Soviet Republics which are no longer part of Russia.

Moscow Mailbag is one of the longest running programs on first, Radio Moscow, then the Voice of Russia. For over 50 years, it has answered listener's letters and questions about Russia and the Soviet Union.



Svetlana Yakimenko

For many of those years, Joe Adamov, a very effective apologist for the Soviet Union, hosted the program. He was known for his engaging nature, his wit and, of course, his corny jokes, which featured in most editions of the program. **Moscow Mailbag** always ended with the catch phrase "You couldn't do better than write us that letter!"

I recall my excitement the first time Joe answered one of my questions on the program. My Radio Moscow files indicate it was read on August 12, 1979. I was an 18 year old and terribly excited about shortwave radio.

It was with some sadness I read a posting on the Voice of Russia website which noted the passing of Yuri Reshetnikov. "We report with sorrow the loss of our dear and cherished friend and colleague Yuri Reshetnikov. He succumbed after struggling with a grave disease on August 19th. From the bottom of our hearts we thank Voice of Russia listeners for sending in their condolences on Yuri Reshetnikov's death." (Moscow Mailbag web page) Reshetnikov was heard in a number of Voice of Russia programs and was a worthy successor to Joe Adamov. As one listener in Phoenix stated "We will miss Yuri as the friendly, consistent, far-away friend brought into our living rooms via RUVR."



The program, now approaching its 60th year, continues to be heard via the Voice of Russia website and on shortwave on Monday at 01.00, 05.00, 11.00 and 17.00, on Tuesday at 04.00, 13.00, 16.00 and 23.00, Thursday at 06.00, 10.00 and 17.00, Friday at 04.00, 13.00, 21.00 and 23.00 and Sunday at 01.00, 06.00 and 10.00 and 15.00 UTC.

When I listened most recently (in early September), Voice of Russia veteran Carl Watts was in the host's chair. I also noted they have changed the catchy theme tune which went back decades.

❖ And the Winner is...

Unshackled is a program which has been discussed before in these pages. It is a throw-back to the "golden age" of radio drama. **Unshackled** has been on the air since 1950, which may very well make it the longest running radio drama in history. It has been heard


on many shortwave stations such as HCJB and Trans World Radio over the years, as well as a vast network of domestic outlets. Today one can hear it via WWCR at 1230 UTC Tuesdays 15820, and at 2330 UTC Saturdays on 7465 kHz.

"Today 'UNSHACKLED!' is broadcast around the world over 7,000 times each week on over 1,800 radio outlets. In addition to the English broadcast, it is translated and re-dramatized in Spanish, Arabic, Russian, Romanian Polish, Korean and Japanese." (www.unshackled.org)

❖ Modern Echo of a Happy Past

In 2008, the **Happy Station** program "returned" to the airwaves. Sort of. In its original form, the **Happy Station** program was the world's longest running shortwave radio program, airing from 1927 until its cancellation in 1995. It was a production of Radio Netherlands and its predecessor PCJJ. For over 40 years it was hosted by Eddie Startz. Upon his retirement, Tom Meijer hosted well into the 1990s, followed briefly by Pete Myers and Jonathan Groubert.

I'm too young to remember Eddie Startz, but you could say I "grew up" with Tom Meijer. Tom was a regular Sunday night guest in my home for many years, bringing with him his delightful program full of "smiles across the miles." The late seventies and early eighties were an era in which I thought of Radio Netherlands itself as "the Happy Station." At one time, I don't think Radio Netherlands minded that name, either. Still, times change.



TOM MEIJER

After Tom retired, the program seemed to lose some of its appeal. Pete Myers was a nice guy, I liked him, but I guess he just wasn't Tom. Interest in the program dwindled on my part and evidently also at Radio Netherlands, as it was gone not long after.



A few years ago, someone started a **Happy Station** group on yahoo. It gave a lot of "us" listeners of a certain vintage a chance to reminisce about the program.

Then, earlier this year came the announcement that a new version of the **Happy Station** program was returning to the airwaves. However, this one is not affiliated with Radio Netherlands. Keith Perron, who has worked at a number of international broadcasters, including Radio Canada International, Radio Habana Cuba, and China Radio International, hosts this

newer version. Tom Meijer is involved in a consulting role.

This new program can be heard via WRMI on UTC Thursdays on 9955 kHz at 0100-0155, and repeated at 1500-1555 UTC.

Special New Years broadcasts

"Starting September 10th, 2009 we are launching a New Years contest with the winners to be announced at 1230am (local HK TIME) that's 1730UTC on January 1st, 2010.

"Times reflect the November time shift. Meaning 0100UTC now will be 0200UTC after that.

"Let me fill you in the loop, as they say. On December 31, 2009 both editions of Happy Station will be 2 hours each.

"The transmission at 0200UTC will be a special program for South America and the Caribbean and will run for 2 hours. Details are still being worked on at this moment. I will fill you in when they become available. This program will be recorded.

"The transmission at 1600UTC will be LIVE from Hong Kong. My friends at RTHK (Radio Television Hong Kong) are giving us a studio over looking Victoria Harbor where at 1659UTC we will do the countdown to 2010. They are also letting us patch into the audio feeds for RTHK, so you will be able to hear the countdown live as it happens in Hong Kong. After the countdown, plus a small concert of the Hong Kong Symphony Orchestra, I will announce the winner of the contest." (*The Happy Station Show Facebook page*)

NASB

National Association of Shortwave Broadcasters

Representing the privately-owned shortwave stations in the USA

- Find links to all of our members at www.shortwave.org
- Subscribe to our free Newsletter: nasbmem@rocketmail.com
- Listen to "The Voice of the NASB" on the third Saturday of each month on HCJB's DX Party Line: 12 midnight Eastern Time on 9955 kHz
- Next annual meeting May 21, 2010 in Hamilton, ON, Canada
- More info at www.shortwave.org/meeting.htm

NASB is a member of the HFCC (High Frequency Coordination Conference) and the DRM (Digital Radio Mondiale) Consortium

THE QSL REPORT

VERIFICATIONS RECEIVED BY OUR READERS

Gayle Van Horn, W4GVH

gaylevanhorn@monitoringtimes.com

Radio Saint Helena ready for annual Party-on-the-Air

The broadcast team from Radio Saint Helena have announced their annual broadcast will be on Saturday, November 14, 2009 on 11092.5 USB. Broadcast times in UTC include:

2000-2100 targeted to India and Southeast Asia
2100-2200 targeted to Japan and Asia
2200-2330 targeted to Europe
2330-0100 targeted to North America, Central America and the Caribbean.

This year's newly designed QSL card is being sponsored by the *Japan Shortwave Club*. Reception reports via airmail must contain verifiable details and recordings will not be returned. In European countries, please enclose a 5-Euro banknote. Otherwise, please enclose three or more U.S. dollars to cover the required postage. Email reports will not be verified. Thanks to Irving Ambler for sharing his 2008 QSL card photo with our *MT* readers.



Send your report to: Radio St. Helena, P.O. Box 93, Jamestown, St. Helena, STHL 1ZZ, South Atlantic Ocean, via Airmail, via United Kingdom & Ascension

Amateur Radio Expedition to Easter Island

CE0Y-XR0YA calls have been issued to the expedition to Easter Island (SA-001) which will be active October 31-November 15, 2009. The six team members (Marco-CE6TBN, Leszek-NI1L, Art-PA3C, Zbig-SP7HOV, Stan-SQ8X and Victoria-SV2KBS) are operating on all bands, with a focus on 160, 80, 40 and 30 meters (CW only, as digital modes on 30 meters are not allowed).

Working Europe on 30 meters will be their priority during the first week on the island. XR0YA will have three stations with two amplifiers and several antennas. Morse code will be the main operating mode, with some RTTY being planned. For QSLing and additional information, go to: <http://rapanui2009.org/>

AMATEUR RADIO

Guinea Bissau, J5UAP (ITU: 46/CQ: 35) 14335 SSB/RTTY 14089.0. Full data color scenery card signed by Peter Brucker. Received in two months for \$2.00US to: QSL Manager, Peter Brucker HA3AU1, P.O. Box 15 Zamardi, H-8621 Hungary. Operator's email: j5uap@cqafrica.net (Larry Van Horn, NC)

UN Headquarters Amateur Radio Station, 4U1UN (ITU: 8/WAZ 5) 40 meters/RTTY. Full data color UN/satellite dish card signed by Herb. Received in 82 days for \$2.00US to: QSL Manager, Herbert Aebly, Rte. Du Moulin 1, CH-1782 Belfaux, Switzerland (Van Horn)

BOSNIA

International Radio of Serbia and Montenegro, 6190 kHz. Full data *Listener's Club* card, unsigned. Received in 135 days for an English report and mint stamps (not used). Station address: P.O. Box 200, Hilendarska 2, 11000 Beograd, Serbia (Bill Wilkins, Springfield, MO)

CLANDESTINE

Cheetah Radio, 11885 kHz. Email response in three days to: radio@cheetahlearning.com (Sam Wright, Biloxi, MS) Brokered by Media Broadcast, Cheetah Radio broadcast in English on 11730 kHz, 1600-1700 on Saturday, via Wertachtal, Germany. Reception reports may be sent to QSL-Shortwave@media-broadcast.com or michelle@cheetahpower.net Postal address: Michael Puetz, Media Broadcast GmbH, Order Management & Backoffice, Josef-Lammering-Allee 8-10, D-50933 Cologne, Germany.

Radio Dabanga, 11500 kHz. Full data handwritten verification letter, unsigned. Received for report sent to: Press Now, Witte Kruislaan 55, 1217 AM Hilversum, The Netherlands. (Artur Fernández Llorella, Catalonia, Spain/HCDX). Brokered by Media Broadcast, broadcasting to Darfur with the support of the Dutch NGO Press Now. Complete Arabic and vernacular schedules may be found in *MTExtra SW Guide*. Email: radiodabanga@yahoo.com Website: www.radiodabanga.org

Radio República, 9545 kHz. Handwritten statement on verification letter, unsigned. Received in 26 days for an English report and \$1.00 US. Station address: P.O. Box 110235, Hialeah, FL 33011 USA (Harold Woering N1FTP, East Hampton, MA).

^ www.radiorepublica.org

COLOMBIA

Radio Marfil Estereo, 5910 kHz. Full data local scenes QSL card, unsigned. Also received religious tracts and a CD-R. Received in 115 days for an English report and mint stamps (used for reply). Station address: La Voz de Conciencia, Colombia para Cristo, c/o Raphael Rodriguez R., Ap # 67751, SF de Bogotá, Colombia (or) Calle 44° No. 13-67, Local 1, Barrio Palamemo, SF de Bogotá, Colombia (Wilkins). Email: rafaelcoldx@yahoo.com

EQUATORIAL GUINEA

Radio Africa 15190 kHz. Verification letter on Pan American Broadcasting letterhead, plus current broadcasting schedule and a full data color studio card unsigned. Received in 21 days for an English report, SAE, address label (used for reply), \$1.00US, souvenir postcard and MT business card. QSL address: Pan American Broadcasting, 7011 Koll Center Pkwy, Pleasanton, CA 94566-3253 USA (Gayle Van Horn, NC). Received in 148 days. (Woering)

PIRATE RADIO

Euro: Sonnet Radio, 6309 kHz. Full data QSL from Mike West. Received in 24 hours for an email to: studio@sonnetradio.com (Roberto Pavanello/playdx via Dario Monferini, Italy)

U.S.: Radio Casablanca, 6940 USB kHz. Full data QSL featuring *Casablanca* movie poster. Received in two days for an email report to: radiocasablanca@gmail.com (Joe Wood, Greenback, TN).

THAILAND

Radio Thailand World Service, 15275

kHz. Full data color scenery QSL card of Bangkok's Grand Palace, signed by Mitver Patanajag-Broadcasting Operation Supervisor. Received in 25 days for an English report and one IRC (returned). Station address: IBB Thailand Transmitting Station, P.O. Box 99, Ampur Muang, Udorn Thani 41000, Thailand. Received via: Thailand Transmitting Station, U.S. Embassy, Box UD, APO AP 96546-0001 Thailand (Richard W. Parker, Pennsburg, PA).

UTILITY

Australia: Townsville Radio VZG420, 6324 kHz (120 watts). Full data prepared card, signed by Paul Weldon-Service Manager/Director. Received in 44 days for report, prepared QSL card and mp3 file. Station address: Seabourne Electronics Pty Ltd., P.O. Box 1726, Townsville, Australia (Martin Foltz, CA/UDXF via LVH). Station is part of the Global Link Network. www.globalinknetwork.com/

New Zealand: ZLM-Taupo Maritime Radio, 6224 kHz. Email verification and attached station information from Peter Baird-Radio Operator. Received in 30 minutes for an email follow-up with an mp3 file to: maritime@korida.co.nz (Foltz) Schedule of news bulletins and coastal warnings on 2207, 4146, 6224 kHz at 0133, 0555, 1333, 1733 UTC.

US: Pirate Beacons CW (Colorado) CO 11.002.7 MHz, UFO 8.432.91 MHz, Pike 8.003.6 MHz. Full data UFO and sunset card. Verified from email report to: hiferbeacon@yahoo.com Reports may be posted at: www.hfunderground/board/index.php/board.9.0.html Site is dedicated to documenting longwave, mediumwave, utility/military stations, spy numbers and pirate radio (James McCalahan, Bowdon Junction, GA).

Additional QSLs, tips, photos and information excluded for space constraints are posted at the *Shortwave Central Blog* at <http://mt-shortwave.blogspot.com/>



HOW TO USE THE SHORTWAVE GUIDE

0000-0100 twhfa USA, Voice of America 5995am 6130ca 7405am 9455af
 ① ② ⑤ ③ ④ ⑥ ⑦

Convert your time to UTC.

Broadcast time on ① and time off ② are expressed in Coordinated Universal Time (UTC) – the time at the 0 meridian near Greenwich, England. To translate your local time into UTC, first convert your local time to 24-hour format, then add (during Daylight Time) 4, 5, 6 or 7 hours for Eastern, Central, Mountain or Pacific Times, respectively. Eastern, Central, and Pacific Times are already converted to UTC for you at the top of each hour.

Note that all dates, as well as times, are in UTC; for example, a show which might air at 0030 UTC Sunday will be heard on Saturday evening in America (in other words, 8:30 pm Eastern, 7:30 pm Central, etc.).

Find the station you want to hear.

Look at the page which corresponds to the time you will be listening. English broadcasts are listed by UTC time on ①, then alphabetically by country ③, followed by the station name ④. (If the station name is the same as the country, we don't repeat it, e.g., "Vanuatu, Radio" [Vanuatu].)

If a broadcast is not daily, the days of broadcast ⑤ will appear in the column following the time of broadcast, using the following codes:

| | |
|--------------|------------------------|
| Codes | |
| s/Sun | Sunday |
| m/Mon | Monday |
| t | Tuesday |
| w | Wednesday |
| h | Thursday |
| f | Friday |
| a/Sat | Saturday |
| occ: | occasional |
| DRM: | Digital Radio Mondiale |
| irreg | Irregular broadcasts |
| vl | Various languages |
| USB: | Upper Sideband |

Choose the most promising frequencies for the time, location and conditions.

The frequencies ⑥ follow to the right of the station listing; all frequencies are listed in kilohertz (kHz). Not all listed stations will be heard from your location and virtually none of them will be heard all the time on all frequencies.

Shortwave broadcast stations change some of their frequencies at least twice a year, in April and October, to adapt to seasonal conditions. But they can also change in response to short-term conditions, interference, equipment problems, etc. Our frequency manager coordinates published station schedules with confirmations and reports from her monitoring team and MT readers to make the Shortwave Guide up-to-date as of one week before

print deadline.

To help you find the most promising signal for your location, immediately following each frequency we've included information on the target area ⑦ of the broadcast. Signals beamed toward your area will generally be easier to hear than those beamed elsewhere, even though the latter will often still be audible.

Target Areas

- af: Africa
- al: alternate frequency (occasional use only)
- am: The Americas
- as: Asia
- ca: Central America
- do: domestic broadcast
- eu: Europe
- me: Middle East
- na: North America
- pa: Pacific
- sa: South America
- va: various

Mode used by all stations in this guide is AM unless otherwise indicated.

Shortwave Broadcast Bands

| kHz | Meters |
|-------------|--|
| 2300-2495 | 120 meters (Note 1) |
| 3200-3400 | 90 meters (Note 1) |
| 3900-3950 | 75 meters (Regional band, used for broadcasting in Asia only) |
| 3950-4000 | 75 meters (Regional band, used for broadcasting in Asia and Europe) |
| 4750-4995 | 60 meters (Note 1) |
| 5005-5060 | 60 meters (Note 1) |
| 5730-5900 | 49 meter NIB (Note 2) |
| 5900-5950 | 49 meter WARC-92 band (Note 3) |
| 5950-6200 | 49 meters |
| 6200-6295 | 49 meter NIB (Note 2) |
| 6890-6990 | 41 meter NIB (Note 2) |
| 7100-7300 | 41 meters (Regional band, not allocated for broadcasting in the western hemisphere) (Note 4) |
| 7300-7350 | 41 meter WARC-92 band (Note 3) |
| 7350-7600 | 41 meter NIB (Note 2) |
| 9250-9400 | 31 meter NIB (Note 2) |
| 9400-9500 | 31 meter WARC-92 band (Note 3) |
| 9500-9900 | 31 meters |
| 11500-11600 | 25 meter NIB (Note 2) |
| 11600-11650 | 25 meter WARC-92 band (Note 3) |
| 11650-12050 | 25 meters |
| 12050-12100 | 25 meter WARC-92 band (Note 3) |
| 12100-12600 | 25 meter NIB (Note 2) |
| 13570-13600 | 22 meter WARC-92 band (Note 3) |
| 13600-13800 | 22 meters |
| 13800-13870 | 22 meter WARC-92 band (Note 3) |
| 15030-15100 | 19 meter NIB (Note 2) |
| 15100-15600 | 19 meters |
| 15600-15800 | 19 meter WARC-92 band (Note 3) |
| 17480-17550 | 17 meter WARC-92 band (Note 3) |
| 17550-17900 | 17 meters |
| 18900-19020 | 15 meter WARC-92 band (Note 3) |
| 21450-21850 | 13 meters |
| 25670-26100 | 11 meters |

Notes

- Note 1 Tropical bands, 120/90/60 meters are for broadcast use only in designated tropical areas of the world.
- Note 2 Broadcasters can use this frequency range on a (NIB) non-interference basis only.
- Note 3 WARC-92 bands are allocated officially for use by HF broadcasting stations in 2007
- Note 4 WRC-03 update. After March 29, 2009, the spectrum from 7100-7200 kHz will no longer be available for broadcast purposes and will be turned over to amateur radio operations worldwide

MT MONITORING TEAM

Gayle Van Horn
 Frequency Manager
 gaylevanhorn@monitoringtimes.com

Larry Van Horn, MT Asst. Editor
 larryvanhorn@monitoringtimes.com

Additional Contributors to This Month's Shortwave Guide:

Thank You to ...

AOKI; BCL News; Ardic DX Club; DX Asia; British DX Club; Cumbre DX; EIBI; HFCC; Hard-Core DX; Radio Bulgaria DX Mix News; Play DX 2003; WRTH; WWDXC- BC DX, Top News; World DX Club/Contact.

Alokesh Gupta, New Delhi, India; Evelyn Marcy/WYFR; Ivo Ivanov; Bulgaria; Jeff White/WRMI; Jaisakthivel, Chennai, India; José Miguel Romero, Spain; Mike Barraclough, UK; Noel Green, UK; Rachel Baughn/MT; Rich D'Angelo/NASWA Flash Sheet, NASWA Journal; Tom Taylor, UK; Wolfgang Büeschel, Germany

"MISSING" LANGUAGES?

A **FREE** download to MTXpress subscribers, the online MTXtra Shortwave Guide is 115+ pages of combined language schedules, sorted by time. Print subscribers: add a full year to your subscription for only \$11.95. Call **1-800-438-8155** or visit www.monitoringtimes.com to learn how.

0000 UTC - 7PM EST / 6PM CST / 4PM PST

| | | | | |
|------|------|--|----------|----------|
| 0000 | 0000 | UK, BBC World Service | 5970as | 6195as |
| | | 7395as | 9410as | 9740as |
| | | 13725as | 15335as | 15360as |
| 0000 | 0005 | Canada, Radio Canada International | | 6100am |
| 0000 | 0005 | Greece, Voice of Greece | 7475va | 9420va |
| 0000 | 0020 | Japan, NHK World/ Radio Japan | | 5960eu |
| | | 6145 na | 13650as | 17810as |
| 0000 | 0027 | Czech Republic, Radio Prague | 7345na | 9440na |
| 0000 | 0030 | Egypt, Radio Cairo | 11590na | |
| 0000 | 0030 | Thailand, Radio Thailand World Service | | 15275na |
| 0000 | 0030 | USA, Voice of America | 7555va | |
| 0000 | 0045 | India, All India Radio | 9705as | 9950as |
| | | 11620as | 11645as | |
| 0000 | 0045 | USA, WYFR/Family Radio Worldwide | | 6085na |
| | | 11720sa | | |
| 0000 | 0056 | Romania, Radio Romania International | | 6135na |
| | | 7535na | 9580na | |
| 0000 | 0100 | Anguilla, Worldwide Univ Network | | 6090am |
| 0000 | 0100 | Australia, ABC NT Alice Springs | | 4835do |
| 0000 | 0100 | Australia, ABC NT Katherine | 5025do | |
| 0000 | 0100 | Australia, ABC NT Tennant Creek | | 4910do |
| 0000 | 0100 | Australia, Radio Australia | 9660as | 12080as |
| | | 13690as | 15240pa | 17665as |
| | | 17750va | 17775va | 17795va |
| 0000 | 0100 | Bahrain, Radio Bahrain | 6010me | 9745al |
| 0000 | 0100 | Canada, CFRX Toronto ON | 6070na | |
| 0000 | 0100 | Canada, CFVP Calgary AB | 6030na | |
| 0000 | 0100 | Canada, CKZN St John's NF | 6160na | |
| 0000 | 0100 | Canada, CKZU Vancouver BC | 6160na | |
| 0000 | 0100 | Canada, Radio Canada International | | 11700as |
| 0000 | 0100 | China, China Radio International | | 6020na |
| | | 6075as | 6180as | 7415as |
| | | 11790as | 11885as | 13750as |
| 0000 | 0100 | Germany, Deutsche Welle | 9885as | 15595as |
| | | 17525as | | |
| 0000 | 0100 | Malaysia, RTM/Traxx FM | 7295do | |
| 0000 | 0100 | DRM New Zealand, Radio NZ International | | 13730pa |
| 0000 | 0100 | DRM New Zealand, Radio NZ International | | 15720pa |
| 0000 | 0100 | Russia, Voice of Russia | 9480sa | 9665sa |
| 0000 | 0100 | Spain, Radio Exterior de Espana | | 6055na |
| 0000 | 0100 | Ukraine, Radio Ukraine International | | 7440na |
| 0000 | 0100 | USA, American Forces Network | | 4319usb |
| | | 5446usb | 5765usb | 6350usb |
| | | 10320usb | 12133usb | 12759usb |
| 0000 | 0100 | USA, EVTN Vandiver AL | 11520af | |
| 0000 | 0100 | USA, WBCQ Monticello ME | 5110am | 7415am |
| 0000 | 0100 | USA, WBOH Newport NC | 5920am | |
| 0000 | 0100 | USA, WHRA Greenbush ME | 7385eu | |
| 0000 | 0100 | USA, WHRI Cypress Creek SC | 5875na | 7315va |
| 0000 | 0100 | USA, WINB Red Lion PA | 9265am | |
| 0000 | 0100 | vi USA, WRMI Miami FL | 9955va | |
| 0000 | 0100 | USA, WTJC Newport NC | 9370na | |
| 0000 | 0100 | USA, WWCN Nashville TN | 5070na | 5935na |
| | | 7465na | 9980na | |
| 0000 | 0100 | USA, WWRB Manchester TN | 3185va | 5050va |
| | | 5745va | 6890va | |
| 0000 | 0100 | USA, WYFR/Family Radio Worldwide | | 5950na |
| | | 9595na | 15440na | |
| 0000 | 0100 | Zambia CVC Intl/ The Voice Africa | | 4965af |
| 0005 | 0100 | Canada, Radio Canada International | | 6100am |
| 0005 | 0100 | Greece, Voice of Greece | 7475va | 9420va |
| 0013 | 0017 | twhfa Austria, ORF/Radio Austria Intl | 9820am | |
| 0025 | 0100 | Sri Lanka, SLBC | 6005as | 15745as |
| 0030 | 0045 | twhfas Albania, Radio Tirana | 9345na | |
| 0030 | 0045 | Sun Germany, Pan American Broadcasting | | 9640as |
| 0030 | 0058 | mtwhfa Serbia, International Radio of Serbia | | 9675na |
| 0030 | 0100 | Australia, Radio Australia | 15415as | 17665as |
| 0030 | 0100 | China, China Radio International | | 11730as |
| 0030 | 0100 | Thailand, Radio Thailand World Service | | 15275na |
| 0030 | 0100 | fas UK, Bible Voice Broadcasting | 9490as | |
| 0030 | 0100 | USA, Voice of America/Special English | | 7430as |
| | | 9715as | 9780as | 11725as |
| | | 15560as | 17820as | 15205as |
| 0030 | 0100 | Uzbekistan, CVC Intl/ The Voice Asia | | 11800as |
| 0043 | 0047 | twhfa Austria, ORF/Radio Austria Intl | 9820am | |

0100 UTC - 8PM EST / 7PM CST / 5PM PST

| | | | | |
|------|------|--|---------|--------|
| 0100 | 0105 | Canada, Radio Canada International | | 6100am |
| 0100 | 0105 | m Greece, Voice of Greece | 7475va | 9420va |
| | | | 15630va | |
| 0100 | 0125 | Vietnam, Voice of Vietnam | 6175na | |
| 0100 | 0127 | Czech Republic, Radio Prague | 6200na | 7345na |
| 0100 | 0127 | Slovakia, Radio Slovakia International | | 5930am |

| | | | | |
|------|------|---|----------|----------|
| | | | | 9440am |
| 0100 | 0128 | Serbia, International Radio of Serbia | | 9675na |
| 0100 | 0130 | Australia, Radio Australia | 9660as | 12080as |
| | | 13690as | 15240pa | 17665as |
| | | 17750va | 17775va | 17795va |
| 0100 | 0157 | North Korea, Voice of Korea | 7140as | 9345as |
| | | 9730as | 11735sa | 13760sa |
| 0100 | 0200 | Anguilla, Worldwide Univ Network | | 6090am |
| 0100 | 0200 | Australia, ABC NT Alice Springs | | 4835do |
| 0100 | 0200 | Australia, ABC NT Katherine | 5025do | |
| 0100 | 0200 | Australia, ABC NT Tennant Creek | | 4910do |
| 0100 | 0200 | Bahrain, Radio Bahrain | 6010me | 9745al |
| 0100 | 0200 | Canada, CFRX Toronto ON | 6070na | |
| 0100 | 0200 | Canada, CFVP Calgary AB | 6030na | |
| 0100 | 0200 | Canada, CKZN St John's NF | 6160na | |
| 0100 | 0200 | Canada, CKZU Vancouver BC | 6160na | |
| 0100 | 0200 | Canada, Radio Canada International | | 9620as |
| 0100 | 0200 | China, China Radio International | | 6175as |
| | | 9410eu | 9470eu | 9535as |
| | | 9790na | 11870as | 15125as |
| 0100 | 0200 | DRM China, China Radio International | | 6080na |
| 0100 | 0200 | DRM Cuba, Radio Havana Cuba | 6000na | 6140na |
| 0100 | 0200 | DRM Malaysia, RTM/Traxx FM | 7295do | |
| 0100 | 0200 | DRM New Zealand, Radio NZ International | | 13730pa |
| 0100 | 0200 | DRM New Zealand, Radio NZ International | | 15720pa |
| 0100 | 0200 | Palau, T8WH/World Harvest | 15710as | |
| 0100 | 0200 | Russia, Voice of Russia | 9480sa | 9665sa |
| 0100 | 0200 | Sri Lanka, SLBC | 6005as | 15745as |
| 0100 | 0200 | Taiwan, Radio Taiwan International | | 11875as |
| 0100 | 0200 | UK, BBC World Service | 7395as | 9410as |
| | | 9740as | 11750as | 11955as |
| | | 15335as | 15360as | 17615as |
| 0100 | 0200 | USA, American Forces Network | | 4319usb |
| | | 5446usb | 5765usb | 6350usb |
| | | 10320usb | 12133usb | 12759usb |
| 0100 | 0200 | USA, EWTN Vandiver AL | 11520af | |
| 0100 | 0200 | USA, KJES Vado NM | 7555na | |
| 0100 | 0200 | USA, Voice of America | 7430va | 9780va |
| | | 11705va | | |
| 0100 | 0200 | mtwhfa USA, WBCQ Monticello ME | 5110am | 7415am |
| 0100 | 0200 | USA, WBOH Newport NC | 5920am | |
| 0100 | 0200 | USA, WHRA Greenbush ME | 7385eu | |
| 0100 | 0200 | USA, WHRI Cypress Creek SC | 5875na | 7315va |
| 0100 | 0200 | mtwhf USA, WHRI Cypress Creek SC | 5850na | |
| 0100 | 0200 | Sat/Sun USA, WHRI Cypress Creek SC | 7315na | |
| 0100 | 0200 | USA, WINB Red Lion PA | 9265am | |
| 0100 | 0200 | vi USA, WRMI Miami FL | 9955va | |
| 0100 | 0200 | USA, WRNO New Orleans LA | 7505am | |
| 0100 | 0200 | USA, WTJC Newport NC | 9370na | |
| 0100 | 0200 | USA, WWCN Nashville TN | 5070na | 5935na |
| | | 7465na | 9980na | |
| 0100 | 0200 | USA, WWRB Manchester TN | 3185va | 5050va |
| | | 5745va | 6890va | |
| 0100 | 0200 | USA, WYFR/Family Radio Worldwide | | 7455na |
| | | 9505na | 15440na | |
| 0100 | 0200 | Uzbekistan, CVC Intl/ The Voice Asia | | 11790as |
| | | 11880as | | |
| 0100 | 0200 | Zambia CVC Intl/ The Voice Africa | | 4965af |
| 0113 | 0117 | twhfa Austria, ORF/Radio Austria Intl | 9820am | |
| 0130 | 0200 | Australia, Radio Australia | 9660as | 12080as |
| | | 13690as | 15240pa | 15415as |
| | | 17715va | 17750va | 17795va |
| 0130 | 0200 | Iran, Voice of Islamic Rep. of Iran | | 7235na |
| | | 9495na | | |
| 0130 | 0200 | Sweden, Radio Sweden | 6010na | |
| 0130 | 0200 | twhfa USA, Voice of America/Special English | | 6040ca |
| | | 9820ca | | |
| 0140 | 0200 | Vatican City State, Vatican Radio | | 5915as |
| | | 7335as | | |
| 0145 | 0200 | twhfes Albania, Radio Tirana | 7425na | |

0200 UTC - 9PM EST / 8PM CST / 6PM PST

| | | | | |
|------|------|--|---------|---------|
| 0200 | 0227 | Iran, Voice of Islamic Rep. of Iran | | 7235na |
| | | 9495na | | |
| 0200 | 0230 | Thailand, Radio Thailand World Service | | 15275na |
| 0200 | 0230 | USA, KJES Vado NM | 7555na | |
| 0200 | 0257 | North Korea, Voice of Korea | 13650as | 15100as |
| 0200 | 0258 | Sun Lithuania, Mighty KBC Radio | 6110na | |
| 0200 | 0300 | Anguilla, Worldwide Univ Network | | 6090am |
| 0200 | 0300 | Argentina, Radio Nacional RAE | | 11710am |
| 0200 | 0300 | Australia, ABC NT Alice Springs | | 4835do |
| 0200 | 0300 | Australia, ABC NT Katherine | 5025do | |
| 0200 | 0300 | Australia, ABC NT Tennant Creek | | 4910do |
| 0200 | 0300 | Australia, Radio Australia | 9660as | 12080as |
| | | 13690as | 15240pa | 15415as |
| | | 17750va | 21725va | 15515as |

| | | | | | | | | |
|-----------|--------|---------------------------------------|----------|----------|-----------|----------------------------------|---------------------------------------|----------|
| 0200 0300 | | Bahrain, Radio Bahrain | 6010me | 9745al | 0300 0400 | Canada, CKZN St John's NF | 6160na | |
| 0200 0300 | DRM | Bulgaria, Radio Bulgaria | 9500na | | 0300 0400 | Canada, CKZU Vancouver BC | 6160na | |
| 0200 0300 | | Bulgaria, Radio Bulgaria | 9700na | 11700na | 0300 0400 | China, China Radio International | 9690na | |
| 0200 0300 | | Canada, CFRX Toronto ON | 6070na | | | 9790na | 11770as | 13750as |
| 0200 0300 | | Canada, CFVP Calgary AB | 6030na | | | 15120as | 15785as | 15110as |
| 0200 0300 | | Canada, CKZN St John's NF | 6160na | | 0300 0400 | Cuba, Radio Havana Cuba | 6000na | 6140na |
| 0200 0300 | | Canada, CKZU Vancouver BC | 6160na | | 0300 0400 | Germany, Deutsche Welle | 11975as | 13770as |
| 0200 0300 | | China, China Radio International | 11770as | | | 15595as | | |
| | | 13640as | | | 0300 0400 | Malaysia, RTM/Traxx FM | 7295do | |
| 0200 0300 | | Cuba, Radio Havana Cuba | 6000na | 6140na | 0300 0400 | Malaysia, RTM/Voice of Malaysia | 9750as | 15295as |
| 0200 0300 | | Egypt, Radio Cairo | 7540na | | | 9750as | 15295as | 6175as |
| 0200 0300 | | Indonesia, Voice of Indonesia | 9525va | 11785al | 0300 0400 | DRM | New Zealand, Radio NZ International | 13730pa |
| | | 15150al | | | 0300 0400 | DRM | New Zealand, Radio NZ International | 15720pa |
| 0200 0300 | | Malaysia, RTM/Traxx FM | 7295do | | 0300 0400 | | Oman, Radio Oman | 15355af |
| 0200 0300 | DRM | New Zealand, Radio NZ International | 13730pa | | 0300 0400 | | Palau, T8WH/World Harvest | 15700as |
| 0200 0300 | | New Zealand, Radio NZ International | 15720pa | | 0300 0400 | DRM | Russia, Voice of Russia | 15735as |
| 0200 0300 | | Palau, T8WH/World Harvest | 15710as | | 0300 0400 | | Russia, Voice of Russia | 9665sa |
| 0200 0300 | | Philippines, PBS/ Radyo Pilipinas | 11880me | | | | 15585as | 15755as |
| | | 15285me | 15510me | | 0300 0400 | | South Africa, Channell Africa | 3345af |
| 0200 0300 | | Russia, Voice of Russia | 9480sa | 9665sa | 0300 0400 | | Sri Lanka, SLBC | 6005as |
| | | 15425na | | | 0300 0400 | | Sweden, Radio Sweden | 6010na |
| 0200 0300 | | South Korea, KBS World Radio | 9580sa | | 0300 0400 | | Taiwan, Radio Taiwan International | 5950na |
| 0200 0300 | | Sri Lanka, SLBC | 6005as | 9770as | | | 15320as | |
| 0200 0300 | | Taiwan, Radio Taiwan International | 9680na | 5950na | 0300 0400 | | Uganda, UBC Radio | 4976do |
| | | | | | 0300 0400 | | UK, BBC World Service | 3255af |
| 0200 0300 | | Uganda, UBC Radio | 4976do | | | | 6145af | 6190af |
| 0200 0300 | | UK, BBC World Service | 6005af | 6195me | | | 6195as | 7255af |
| | | 9410eu | 11955as | 15310as | | | 9410eu | 9750af |
| | | | | | | | 15310as | 12035af |
| | | | | | | | | 12095as |
| 0200 0300 | | USA, American Forces Network | 4319usb | | 0300 0400 | | Ukraine, Radio Ukraine International | 7440na |
| | | 5446usb | 5765usb | 6350usb | 0300 0400 | | USA, American Forces Network | 4319usb |
| | | 10320usb | 12133usb | 12759usb | | | 5446usb | 5765usb |
| | | | | | | | 6350usb | 7812usb |
| | | | | | | | 10320usb | 12133usb |
| | | | | | | | 12759usb | 13362usb |
| 0200 0300 | | USA, EWTN Vandiver AL | 11520af | | 0300 0400 | | USA, EWTN Vandiver AL | 11520af |
| 0200 0300 | mtwhfa | USA, WBCQ Monticello ME | 5110am | 7415am | 0300 0400 | | USA, Voice of America | 4930af |
| 0200 0300 | | USA, WBOH Newport NC | 5920am | | 0300 0400 | | 9885af | 15580af |
| 0200 0300 | | USA, WHRA Greenbush ME | 7385eu | | 0300 0400 | twhfa | USA, WBCQ Monticello ME | 7415am |
| 0200 0300 | | USA, WHRI Cypress Creek SC | 5875na | 7315va | 0300 0400 | | USA, WBOH Newport NC | 5920am |
| 0200 0300 | | USA, WINB Red Lion PA | 9265am | | 0300 0400 | | USA, WHRA Greenbush ME | 7385eu |
| 0200 0300 | vl | USA, WRMI Miami FL | 9955va | | 0300 0400 | | USA, WHRI Cypress Creek SC | 5875na |
| 0200 0300 | | USA, WRNO New Orleans LA | 7505am | | 0300 0400 | vl | USA, WRMI Miami FL | 9955va |
| 0200 0300 | | USA, WTJC Newport NC | 9370na | | 0300 0400 | | USA, WRNO New Orleans LA | 7505am |
| 0200 0300 | | USA, WWCR Nashville TN | 3215na | 5070na | 0300 0400 | | USA, WTJC Newport NC | 9370na |
| | | 589na | 5935na | | 0300 0400 | | USA, WWCR Nashville TN | 3215na |
| 0200 0300 | | USA, WWRB Manchester TN | 3185va | 5050va | | | 589na | 5935na |
| | | 5745va | 6890va | | 0300 0400 | | USA, WWRB Manchester TN | 3185va |
| 0200 0300 | | USA, WYFR/Family Radio Worldwide | 4985na | | 0300 0400 | | 5745va | 6890va |
| | | 6890na | 7455na | 9505na | | | 9505na | |
| 0200 0300 | | Uzbekistan, CVC Intl/ The Voice Asia | 11790as | | 0300 0400 | | USA, WYFR/Family Radio Worldwide | 9930af |
| | | 11880as | | | | | 9985eu | 9985eu |
| 0200 0300 | | Zambia CVC Intl/ The Voice Africa | 4965af | | 0300 0400 | | Uzbekistan, CVC Intl/ The Voice Asia | 13680as |
| 0215 0230 | | Nepal, Radio Nepal | 5005as | | 0300 0400 | | Zambia CVC Intl/ The Voice Africa | 4965af |
| 0230 0300 | twhf | Albania, Radio Tirana | 7425na | | 0300 0400 | | Zambia, Zambia Natl Broadcasting Corp | 6165do |
| 0230 0300 | | China, China Radio International | 15435as | | 0330 0357 | | Czech Republic, Radio Prague | 9445na |
| 0230 0300 | | Sweden, Radio Sweden | 6010na | 11550as | 0330 0400 | twhf | Albania, Radio Tirana | 7425na |
| 0245 0300 | | Australia, HCJB Global | 15400as | | 0330 0400 | | UK, BBC World Service | 11945af |
| 0245 0300 | | Zambia, Zambia Natl Broadcasting Corp | 6165do | | 0330 0400 | | Uzbekistan, CVC Intl/ The Voice Asia | 15555as |
| 0250 0300 | | Vatican City State, Vatican Radio | 7305am | 6040am | 0345 0400 | vl/Sat/Sun | Uganda, UBC Radio | 4976do |

0300 UTC - 10PM EST / 9PM CST / 7PM PST

| | | | | | | | | |
|-----------|------|--------------------------------------|---------|---------|--|--|--|--|
| 0300 0320 | | Vatican City State, Vatican Radio | 7305am | 6040am | | | | |
| 0300 0327 | | Czech Republic, Radio Prague | 7345na | 9870na | | | | |
| 0300 0330 | | Egypt, Radio Cairo | 7540na | | | | | |
| 0300 0330 | | Philippines, PBS/ Radyo Pilipinas | 11880me | | | | | |
| | | 15285me | 15510me | | | | | |
| 0300 0330 | | Uzbekistan, CVC Intl/ The Voice Asia | 11880as | | | | | |
| 0300 0330 | | Vatican City State, Vatican Radio | 9310as | 9660af | | | | |
| 0300 0355 | | Turkey, Voice of Turkey | 5975va | 7325na | | | | |
| 0300 0356 | | Romania, Radio Romania International | 9645na | 9735as | | | | |
| | | 11895as | | | | | | |
| 0300 0357 | | North Korea, Voice of Korea | 7140as | 9345as | | | | |
| | | 9730as | | | | | | |
| 0300 0400 | | Anguilla, Worldwide Univ Network | 6090am | | | | | |
| 0300 0400 | | Australia, ABC NT Alice Springs | 4835do | | | | | |
| 0300 0400 | | Australia, ABC NT Katherine | 5025do | | | | | |
| 0300 0400 | | Australia, ABC NT Tennant Creek | 4910do | | | | | |
| 0300 0400 | | Australia, Radio Australia | 9660as | 12080as | | | | |
| | | 13690as | 15240pa | 15415as | | | | |
| | | 17750va | 21725va | | | | | |
| 0300 0400 | | Bahrain, Radio Bahrain | 6010me | 9745al | | | | |
| 0300 0400 | twhf | Canada, CBC NQ SW Service | 9625na | | | | | |
| 0300 0400 | | Canada, CFRX Toronto ON | 6070na | | | | | |
| 0300 0400 | | Canada, CFVP Calgary AB | 6030na | | | | | |

0400 UTC - 11PM EST / 10PM CST / 8PM PST

| | | | | | | | | |
|-----------|-------|-------------------------------------|---------|---------|--|--|--|--|
| 0400 0430 | | Australia, Radio Australia | 9660as | 12080as | | | | |
| | | 13690as | 15160as | 15240pa | | | | |
| | | 17750va | 21725va | | | | | |
| 0400 0430 | mtwhf | France, Radio France International | 11995af | | | | | |
| 0400 0445 | | USA, WYFR/Family Radio Worldwide | 9505na | | | | | |
| 0400 0458 | DRM | New Zealand, Radio NZ International | | 13730pa | | | | |
| 0400 0458 | | New Zealand, Radio NZ International | | 15720pa | | | | |
| 0400 0500 | | Anguilla, Worldwide Univ Network | 6090am | | | | | |
| 0400 0500 | | Australia, ABC NT Alice Springs | 4835do | | | | | |
| 0400 0500 | | Australia, ABC NT Katherine | 5025do | | | | | |
| 0400 0500 | | Australia, ABC NT Tennant Creek | 4910do | | | | | |
| 0400 0500 | | Bahrain, Radio Bahrain | 6010me | 9745al | | | | |
| 0400 0500 | twhf | Canada, CBC NQ SW Service | 9625na | | | | | |
| 0400 0500 | | Canada, CFRX Toronto ON | 6070na | | | | | |
| 0400 0500 | | Canada, CKZN St John's NF | 6160na | | | | | |
| 0400 0500 | | Canada, CKZU Vancouver BC | 6160na | | | | | |
| 0400 0500 | | China, China Radio International | 6020na | | | | | |
| | | 6080na | 6190na | 13750as | | | | |
| | | 15785as | 17730as | 17855as | | | | |
| 0400 0500 | | Cuba, Radio Havana Cuba | 6000na | 6140na | | | | |
| 0400 0500 | | Germany, Deutsche Welle | 6180af | 7245af | | | | |
| | | 12045af | 15445af | | | | | |
| 0400 0500 | | Malaysia, RTM/Traxx FM | 7295do | | | | | |
| 0400 0500 | | Malaysia, RTM/Voice of Malaysia | 9750as | 15295as | | | | |
| 0400 0500 | | Palau, T8WH/World Harvest | 15700as | | | | | |

| | | | | | |
|------|------|--------|---------------------------------------|----------|----------|
| 0400 | 0500 | DRM | Russia, Voice of Russia | 15735as | |
| 0400 | 0500 | | Russia, Voice of Russia | 13755na | 15585as |
| | | | 15755as | | |
| 0400 | 0500 | | South Africa, Channel Africa | 3345af | |
| 0400 | 0500 | | Sri Lanka, SLBC | 6005as | 15745as |
| 0400 | 0500 | | Uganda, UBC Radio | 4976do | |
| 0400 | 0500 | DRM | UK, BBC World Service | 3995eu | |
| 0400 | 0500 | | UK, BBC World Service | 3255af | 6005af |
| | | | 6190af | 7255af | 7310af |
| | | | 11945af | 12035af | 12095as |
| | | | 15310as | 15360as | 17790as |
| 0400 | 0500 | | USA, American Forces Network | | 4319usb |
| | | | 5446usb | 5765usb | 6350usb |
| | | | 10320usb | 12133usb | 12759usb |
| 0400 | 0500 | | USA, EWTN Vandiver AL | | 11520af |
| 0400 | 0500 | | USA, Voice of America | 4930af | 4960af |
| | | | 6080af | 9885af | 15580af |
| 0400 | 0500 | | USA, WBOH Newport NC | | 5920am |
| 0400 | 0500 | | USA, WHRA Greenbush ME | | 7385eu |
| 0400 | 0500 | | USA, WHRI Cypress Creek SC | 5875na | 7315va |
| 0400 | 0500 | smtwhf | USA, WHRI Cypress Creek SC | 5850na | |
| 0400 | 0500 | Sat | USA, WHRI Cypress Creek SC | 9825na | |
| 0400 | 0500 | vl | USA, WRMI Miami FL | 9955va | |
| 0400 | 0500 | | USA, WTJC Newport NC | 9370na | |
| 0400 | 0500 | | USA, WWCR Nashville TN | 3215na | 5070na |
| | | | 5890na | 5935na | |
| 0400 | 0500 | | USA, WWRB Manchester TN | 3185va | 5745va |
| 0400 | 0500 | | USA, WYFR/Family Radio Worldwide | | 6915na |
| | | | 9680na | | |
| 0400 | 0500 | | Uzbekistan, CVC Intl/ The Voice Asia | | 13680as |
| | | | 15555as | | |
| 0400 | 0500 | | Zambia CVC Intl/ The Voice Africa | | 4965af |
| | | | 9430af | | |
| 0400 | 0500 | | Zambia, Zambia Natl Broadcasting Corp | 6165do | |
| 0430 | 0500 | | Australia, Radio Australia | 9660as | 12080as |
| | | | 13690as | 15240pa | 15415as |
| | | | 17750va | 21725va | |
| 0430 | 0500 | mtwh | Italy, IRRS-Shortwave | 5990va | |
| 0430 | 0500 | mtwhf | Swaziland, TWR Swaziland | 3200af | |
| 0459 | 0500 | DRM | New Zealand, Radio NZ International | | 11675pa |
| 0459 | 0500 | | New Zealand, Radio NZ International | | 11725pa |

| | | | | | |
|------|------|-----|--|----------|----------|
| 0500 | 0600 | DRM | UK, BBC World Service | 3995af | |
| 0500 | 0600 | | UK, BBC World Service | 3255af | 3995eu |
| | | | 6005af | 6190af | 7255af |
| | | | 9410eu | 11945af | 12095as |
| | | | 15360as | 15420af | 15565eu |
| | | | 17790as | | 17640af |
| 0500 | 0600 | | Ukraine, Radio Ukraine International | | 7440na |
| 0500 | 0600 | | USA, American Forces Network | | 4319usb |
| | | | 5446usb | 5765usb | 6350usb |
| | | | 10320usb | 12133usb | 12759usb |
| 0500 | 0600 | | USA, EWTN Vandiver AL | | 11520af |
| 0500 | 0600 | | USA, Voice of America | 4930af | 6080af |
| | | | 12080af | 15580af | |
| 0500 | 0600 | | USA, WBOH Newport NC | | 5920am |
| 0500 | 0600 | | USA, WHRA Greenbush ME | | 7390af |
| 0500 | 0600 | | USA, WHRI Cypress Creek SC | 5875na | 11565na |
| 0500 | 0600 | Sun | USA, WHRI Cypress Creek SC | 7365na | |
| 0500 | 0600 | vl | USA, WRMI Miami FL | 9955va | |
| 0500 | 0600 | | USA, WTJC Newport NC | 9370na | |
| 0500 | 0600 | | USA, WWCR Nashville TN | 3215na | 5070na |
| | | | 5890na | 5935na | |
| 0500 | 0600 | | USA, WWRB Manchester TN | 3185va | |
| 0500 | 0600 | | USA, WYFR/Family Radio Worldwide | | 6915na |
| | | | 9680na | | |
| 0500 | 0600 | | Uzbekistan, CVC Intl/ The Voice Asia | | 13680as |
| | | | 15555as | | |
| 0500 | 0600 | | Zambia CVC Intl/ The Voice Africa | | 4965af |
| | | | 9430af | | |
| 0500 | 0600 | | Zambia, Zambia Natl Broadcasting Corp | 6165do | |
| 0515 | 0530 | | Rwanda, Radio Rwanda | 6055do | |
| 0530 | 0556 | | Romania, Radio Romania International | | 7305eu |
| | | | 9655eu | 15345pa | 17760pa |
| 0530 | 0600 | | Australia, Radio Australia | 9660as | 12080as |
| | | | 13690as | 15160as | 15240pa |
| | | | 15515as | 17750va | 15415as |
| 0530 | 0600 | | Clandestine, Sudan Radio Service | | 13720af |
| 0530 | 0600 | | Thailand, Radio Thailand World Service | | 17655va |

0600 UTC - 1AM EST / 12AM CST / 10PM PST

0500 UTC - 12AM EST / 11PM CST / 9PM PST

| | | | | | |
|------|------|-------|--|---------|---------|
| 0500 | 0507 | twhf | Canada, CBC NQ SW Service | 9625na | |
| 0500 | 0530 | | Australia, Radio Australia | 9660as | 12080as |
| | | | 13690as | 15160as | 15240pa |
| | | | 17750va | | 15515as |
| 0500 | 0530 | mtwhf | France, Radio France International | | 11995af |
| | | | 13680af | 15160as | |
| 0500 | 0530 | | Germany, Deutsche Welle | 6180af | 7430af |
| | | | 9700af | 9825af | |
| 0500 | 0530 | mtwh | Italy, IRRS-Shortwave | 5990va | |
| 0500 | 0530 | | Japan, NHK World/ Radio Japan | | 5975eu |
| | | | 6110na | 11970af | 15325as |
| 0500 | 0530 | | Vatican City State, Vatican Radio | | 4005eu |
| | | | 5965eu | 7250eu | 9660af |
| | | | 13765af | | 11625af |
| 0500 | 0600 | | Anguilla, Worldwide Univ Network | | 6090am |
| 0500 | 0600 | | Australia, ABC NT Alice Springs | | 4835do |
| 0500 | 0600 | | Australia, ABC NT Katherine | 5025do | |
| 0500 | 0600 | | Australia, ABC NT Tennant Creek | | 4910do |
| 0500 | 0600 | | Bahrain, Radio Bahrain | 6010me | 9745af |
| 0500 | 0600 | | Bhutan, Bhutan Broadcasting Service | | 6035as |
| 0500 | 0600 | | Canada, CFRX Toronto ON | 6070na | |
| 0500 | 0600 | | Canada, CKZN St John's NF | 6160na | |
| 0500 | 0600 | | Canada, CKZU Vancouver BC | 6160na | |
| 0500 | 0600 | | China, China Radio International | | 6020na |
| | | | 11710af | 11880as | 11895as |
| | | | 15465as | 17505va | 17540as |
| | | | 17855as | | 17730as |
| 0500 | 0600 | | Cuba, Radio Havana Cuba | 6000na | 6010na |
| | | | 6140na | 11760na | |
| 0500 | 0600 | | Germany, Deutsche Welle | 17525as | |
| 0500 | 0600 | | Kuwait, Radio Kuwait | 15110as | |
| 0500 | 0600 | | Malaysia, RTM/Traxx FM | 7295do | |
| 0500 | 0600 | | Malaysia, RTM/Voice of Malaysia | | 6175as |
| | | | 9750as | 15295as | |
| 0500 | 0600 | DRM | New Zealand, Radio NZ International | | 11675pa |
| 0500 | 0600 | | New Zealand, Radio NZ International | | 11725pa |
| 0500 | 0600 | | Nigeria, Voice of Nigeria/External Service | | 15120af |
| 0500 | 0600 | | Palau, T8WH/World Harvest | 15700as | |
| 0500 | 0600 | | Russia, Voice of Russia | 13755na | |
| 0500 | 0600 | | South Africa, Channel Africa | 7230af | |
| 0500 | 0600 | | Swaziland, TWR Swaziland | 3200af | |
| 0500 | 0600 | | Taiwan, Radio Taiwan International | | 5950na |
| 0500 | 0600 | | Uganda, UBC Radio | 4976do | |

| | | | | | |
|------|------|---------|--|----------|----------|
| 0600 | 0603 | | Croatia, Voice of Croatia | 7355eu | |
| 0600 | 0615 | Sat/Sun | South Africa, Trans World Radio | | 11640af |
| 0600 | 0630 | Sat/Sun | Australia, Radio Australia | 15180as | 15290as |
| 0600 | 0630 | | Australia, Radio Australia | 9660as | 11650as |
| | | | 12080as | 13690as | 15160as |
| | | | 15515as | 17750va | 15240pa |
| 0600 | 0630 | mtwhf | France, Radio France International | | 9765af |
| | | | 11610af | 15160af | 17800af |
| 0600 | 0630 | | Germany, Deutsche Welle | 7310af | 15275af |
| 0600 | 0630 | | Laos, Lao National Radio | 7145as | |
| 0600 | 0645 | mtwhf | South Africa, Trans World Radio | | 11640af |
| 0600 | 0658 | DRM | New Zealand, Radio NZ International | | 11675pa |
| 0600 | 0658 | | New Zealand, Radio NZ International | | 11725pa |
| 0600 | 0700 | | Anguilla, Worldwide Univ Network | | 6090am |
| 0600 | 0700 | | Australia, ABC NT Alice Springs | | 4835do |
| 0600 | 0700 | | Australia, ABC NT Katherine | 5025do | |
| 0600 | 0700 | | Australia, ABC NT Tennant Creek | | 4910do |
| 0600 | 0700 | | Bahrain, Radio Bahrain | 6010me | 9745af |
| 0600 | 0700 | | Canada, CFRX Toronto ON | 6070na | |
| 0600 | 0700 | | Canada, CFVP Calgary AB | 6030na | |
| 0600 | 0700 | | Canada, CKZN St John's NF | 6160na | |
| 0600 | 0700 | | Canada, CKZU Vancouver BC | 6160na | |
| 0600 | 0700 | | China, China Radio International | | 11710af |
| | | | 11870as | 11880as | 11895as |
| | | | 15140as | 15350as | 15465as |
| | | | 17540as | 17710as | 17505va |
| 0600 | 0700 | | Cuba, Radio Havana Cuba | 6000na | 6010na |
| | | | 6140na | 11760na | |
| 0600 | 0700 | | Greece, Voice of Greece | 11645eu | |
| 0600 | 0700 | | Kuwait, Radio Kuwait | 15110as | |
| 0600 | 0700 | | Malaysia, RTM/Traxx FM | 7295do | |
| 0600 | 0700 | | Malaysia, RTM/Voice of Malaysia | | 6175as |
| | | | 9750as | 15295as | |
| 0600 | 0700 | | Nigeria, Voice of Nigeria/External Service | | 15120af |
| 0600 | 0700 | | Palau, T8WH/World Harvest | 15700as | |
| 0600 | 0700 | | Russia, Voice of Russia | 17635pa | |
| 0600 | 0700 | | South Africa, Channel Africa | 7230af | 15255af |
| 0600 | 0700 | | UK, BBC World Service | 3995eu | 6005af |
| | | | 6190af | 9410af | 9860af |
| | | | 12015af | 12095as | 15310as |
| | | | 17790as | | 17640af |
| 0600 | 0700 | Sat/Sun | UK, BBC World Service | 15420af | |
| 0600 | 0700 | | USA, American Forces Network | | 4319usb |
| | | | 5446usb | 5765usb | 6350usb |
| | | | 10320usb | 12133usb | 12759usb |
| 0600 | 0700 | | USA, EWTN Vandiver AL | | 11520af |
| 0600 | 0700 | | USA, Voice of America | 6080af | 12080af |

| | | | | | |
|------|------|--------|---------------------------------------|---------|---------|
| 0600 | 0700 | | 15580af | | |
| 0600 | 0700 | | USA, WBOH Newport NC | 5920am | |
| 0600 | 0700 | | USA, WHRA Greenbush ME | 7390af | |
| 0600 | 0700 | | USA, WHRI Cypress Creek SC | 5875va | 7365na |
| | | | 11565na | | |
| 0600 | 0700 | vl | USA, WRMI Miami FL | 9955va | |
| 0600 | 0700 | | USA, WTJC Newport NC | 9370na | |
| 0600 | 0700 | | USA, WWCR Nashville TN | 3215na | 5070na |
| | | | 5890na | 5935na | |
| 0600 | 0700 | | USA, WWRB Manchester TN | 3185va | |
| 0600 | 0700 | | USA, WYFR/Family Radio Worldwide | 5745sa | |
| | | | 6000ca | 9680na | 9985eu |
| 0600 | 0700 | | Uzbekistan, CVC Intl/ The Voice Asia | 15555as | |
| 0600 | 0700 | | Zambia CVC Intl/ The Voice Africa | 6065af | |
| | | | 13590af | | |
| 0600 | 0700 | | Zambia, Zambia Natl Broadcasting Corp | 6165do | |
| 0609 | 0613 | mtwhf | Austria, ORF/Radio Austria Intl | 6155eu | 13730eu |
| 0630 | 0645 | mtwhfa | Vatican City State, Vatican Radio | 4005eu | |
| | | | 5965eu | 7250eu | 9645eu |
| | | | 15595va | | 11740eu |
| 0630 | 0700 | | Australia, Radio Australia | 9660as | 11650as |
| | | | 12080as | 13690as | 15160as |
| | | | 15415as | 15515as | 17750va |
| 0630 | 0700 | | Bulgaria, Radio Bulgaria | 9600eu | 11600eu |
| 0630 | 0700 | | Swaziland, TWR Swaziland | 6120af | |
| 0630 | 0700 | | Vatican City State, Vatican Radio | 11625va | |
| | | | 13765af | 15570af | |
| 0645 | 0700 | Sun | Germany, TWR Europe | 6105eu | 9800eu |
| 0645 | 0700 | Sun | Monaco, TWR Europe | 9800eu | |
| 0659 | 0700 | DRM | New Zealand, Radio NZ International | 7285pa | |
| 0659 | 0700 | | New Zealand, Radio NZ International | 6170pa | |

0700 UTC - 2AM EST / 1AM CST / 11PM PST

| | | | | | |
|------|------|---------|--|----------|----------|
| 0700 | 0727 | | Czech Republic, Radio Prague | 9880eu | 11600na |
| 0700 | 0727 | | Slovakia, Radio Slovakia International | 11650va | 9440va |
| 0700 | 0730 | mtwhf | France, Radio France International | | 13675af |
| 0700 | 0730 | Sun | UK, Bible Voice Broadcasting | 5945eu | |
| 0700 | 0745 | | USA, WYFR/Family Radio Worldwide | 5745sa | |
| | | | 5950na | | |
| 0700 | 0750 | smtwhf | Germany, TWR Europe | 6105eu | 9800eu |
| 0700 | 0750 | smtwhf | Monaco, TWR Europe | 9800eu | |
| 0700 | 0800 | | Anguilla, Worldwide Univ Network | 6090am | |
| 0700 | 0800 | | Australia, ABC NT Alice Springs | 4835do | |
| 0700 | 0800 | | Australia, ABC NT Katherine | 5025do | |
| 0700 | 0800 | | Australia, ABC NT Tennant Creek | 4910do | |
| 0700 | 0800 | | Australia, Radio Australia | 9475as | 9660as |
| | | | 9710as | 11650as | 11945as |
| | | | 13630pa | 15160va | 15240pa |
| | | | 17750va | | 17750va |
| 0700 | 0800 | | Bahrain, Radio Bahrain | 6010me | 9745al |
| 0700 | 0800 | DRM | Belgium, TDP Radio | 17755as | |
| 0700 | 0800 | | Canada, CFRX Toronto ON | 6070na | |
| 0700 | 0800 | | Canada, CFVP Calgary AB | 6030na | |
| 0700 | 0800 | | Canada, CKZN St John's NF | 6160na | |
| 0700 | 0800 | | Canada, CKZU Vancouver BC | 6160na | |
| 0700 | 0800 | | China, China Radio International | 11880as | |
| | | | 11895as | 13660as | 13710eu |
| | | | 15350as | 15465as | 17490eu |
| | | | 17710as | | 17540as |
| 0700 | 0800 | mtwhf | Equatorial Guinea, Radio Africa # 2 | | 15190af |
| 0700 | 0800 | Sat/Sun | Equatorial Guinea, Radio East Africa | | 15190af |
| 0700 | 0800 | | Kuwait, Radio Kuwait | 15110as | |
| 0700 | 0800 | Sat | Latvia, Radio SWH 9290eu | | |
| 0700 | 0800 | | Malaysia, RTM/Traxx FM | 7295do | |
| 0700 | 0800 | | Malaysia, RTM/Voice of Malaysia | 6175as | |
| | | | 9750as | 15295as | |
| 0700 | 0800 | | Myanmar, Myanma Radio | 9730do | |
| 0700 | 0800 | DRM | New Zealand, Radio NZ International | 7285pa | |
| 0700 | 0800 | | New Zealand, Radio NZ International | 6170pa | |
| 0700 | 0800 | | Palau, T8WH/World Harvest | 9930as | 15700as |
| 0700 | 0800 | | Russia, Voice of Russia | 17635as | 21790as |
| 0700 | 0800 | | South Africa, Channel Africa | 7230af | |
| 0700 | 0800 | | Swaziland, TWR Swaziland | 6120af | |
| 0700 | 0800 | Sat/Sun | UK, BBC World Service | 15420af | |
| 0700 | 0800 | | UK, BBC World Service | 5790eu | 6190af |
| | | | 9860af | 11760me | 11765af |
| | | | 15310af | 15400af | 15575as |
| | | | 17830af | | 17790as |
| 0700 | 0800 | Sat | UK, Bible Voice Broadcasting | 5945eu | |
| 0700 | 0800 | | USA, American Forces Network | 4319usb | |
| | | | 5446usb | 5765usb | 6350usb |
| | | | 10320usb | 12133usb | 12759usb |
| 0700 | 0800 | | USA, EWTN Vandiver AL | 11520af | |
| 0700 | 0800 | | USA, WBOH Newport NC | 5920am | |
| 0700 | 0800 | | USA, WHRA Greenbush ME | 11565pa | |
| 0700 | 0800 | | USA, WHRI Cypress Creek SC | 7385va | 7390na |

| | | | | | |
|------|------|-----|---------------------------------------|---------|---------|
| 0700 | 0800 | vl | 11565na | | |
| 0700 | 0800 | | USA, WRMI Miami FL | 9955va | |
| 0700 | 0800 | | USA, WTJC Newport NC | 9370na | |
| 0700 | 0800 | | USA, WWCR Nashville TN | 3215na | 5070na |
| | | | 5890na | 5935na | |
| 0700 | 0800 | | USA, WWRB Manchester TN | 3185va | |
| 0700 | 0800 | | USA, WYFR/Family Radio Worldwide | 6915na | |
| | | | 7455na | 9495ca | 11580va |
| 0700 | 0800 | | Uzbekistan, CVC Intl/ The Voice Asia | 15555as | |
| 0700 | 0800 | | Zambia CVC Intl/ The Voice Africa | 6065af | |
| | | | 13590af | | |
| 0700 | 0800 | | Zambia, Zambia Natl Broadcasting Corp | 6165do | |
| 0715 | 0750 | Sat | Germany, TWR Europe | 6105eu | 9800eu |
| 0715 | 0750 | Sat | Monaco, TWR Europe | 9800eu | |
| 0730 | 0800 | | Australia, HCJB Global | 11750pa | |
| 0730 | 0800 | | Clandestine, Cotton Tree News | | 15220af |
| 0745 | 0800 | f | UK, Bible Voice Broadcasting | 5945eu | |

0800 UTC - 3AM EST / 2AM CST / 12AM PST

| | | | | | |
|------|------|---------|--|----------|----------|
| 0800 | 0815 | Sat | UK, Bible Voice Broadcasting | 5945eu | |
| 0800 | 0825 | | Malaysia, RTM/Voice of Malaysia | 6175as | |
| | | | 9750as | 15295as | |
| 0800 | 0830 | | Australia, ABC NT Alice Springs | 4835do | |
| 0800 | 0830 | | Australia, ABC NT Katherine | 5025do | |
| 0800 | 0830 | | Australia, ABC NT Tennant Creek | 4910do | |
| 0800 | 0830 | | Myanmar, Myanma Radio | 9730do | |
| 0800 | 0845 | | USA, WYFR/Family Radio Worldwide | 11580va | |
| 0800 | 0900 | | Anguilla, Worldwide Univ Network | 6090am | |
| 0800 | 0900 | | Australia, HCJB Global | 11750pa | |
| 0800 | 0900 | | Australia, Radio Australia | 5995as | 9475as |
| | | | 9580va | 9590as | 9710as |
| | | | 12080as | 13630pa | 11945pa |
| 0800 | 0900 | | Bahrain, Radio Bahrain | 6010me | 9745al |
| 0800 | 0900 | m/DRM | Belgium, TDP Radio | 6015eu | |
| 0800 | 0900 | | Canada, CFRX Toronto ON | 6070na | |
| 0800 | 0900 | | Canada, CFVP Calgary AB | 6030na | |
| 0800 | 0900 | | Canada, CKZN St John's NF | 6160na | |
| 0800 | 0900 | | Canada, CKZU Vancouver BC | 6160na | |
| 0800 | 0900 | | China, China Radio International | 11620as | |
| | | | 11880as | 11895as | 13710eu |
| | | | 15350as | 15465as | 15625as |
| | | | 17540as | | 17490eu |
| 0800 | 0900 | | China, Guangxi FBS/Beibu Bay Radio | 5050as | |
| | | | 9820as | | |
| 0800 | 0900 | mtwhf | Equatorial Guinea, Radio Africa # 2 | 15190af | |
| 0800 | 0900 | Sat/Sun | Equatorial Guinea, Radio East Africa | 15190af | |
| 0800 | 0900 | DRM | Germany, Deutsche Welle | 9545eu | 12095as |
| | | | 13810eu | | |
| 0800 | 0900 | Sat | Italy, IRRS-Shortwave | 9510va | |
| 0800 | 0900 | | Malaysia, RTM/Traxx FM | 7295do | |
| 0800 | 0900 | DRM | New Zealand, Radio NZ International | 7285pa | |
| 0800 | 0900 | | New Zealand, Radio NZ International | 6170pa | |
| 0800 | 0900 | | Nigeria, Voice of Nigeria/External Service | 9690af | |
| 0800 | 0900 | | Palau, T8WH/World Harvest | 9930as | 15700as |
| 0800 | 0900 | DRM | Russia, Voice of Russia | 12060eu | |
| 0800 | 0900 | | Russia, Voice of Russia | 17635as | 21790as |
| 0800 | 0900 | | South Africa, Channel Africa | 9625af | |
| 0800 | 0900 | Sun | South Africa, SA Radio League | 7205af | 17570af |
| 0800 | 0900 | | South Korea, KBS World Radio | | 9570as |
| 0800 | 0900 | | Swaziland, TWR Swaziland | 6120af | |
| 0800 | 0900 | | UK, BBC World Service | 6190af | 9860af |
| | | | 11760me | 15310as | 15400af |
| | | | 17640af | 17790as | 17830af |
| 0800 | 0900 | | USA, American Forces Network | 4319usb | |
| | | | 5446usb | 5765usb | 6350usb |
| | | | 10320usb | 12133usb | 12759usb |
| 0800 | 0900 | | USA, EWTN Vandiver AL | 11520af | |
| 0800 | 0900 | | USA, KNLS Anchor Point AK | 7355as | |
| 0800 | 0900 | | USA, WBOH Newport NC | 5920am | |
| 0800 | 0900 | | USA, WHRA Greenbush ME | 11565pa | |
| 0800 | 0900 | | USA, WHRI Cypress Creek SC | 7385va | |
| 0800 | 0900 | vl | USA, WRMI Miami FL | 9955va | |
| 0800 | 0900 | | USA, WTJC Newport NC | 9370na | |
| 0800 | 0900 | | USA, WWCR Nashville TN | 3215na | 5070na |
| | | | 5890na | 5935na | |
| 0800 | 0900 | | USA, WWRB Manchester TN | 3185va | |
| 0800 | 0900 | | USA, WYFR/Family Radio Worldwide | 5950na | |
| | | | 6915na | 7455na | |
| 0800 | 0900 | | Uzbekistan, CVC Intl/ The Voice Asia | 15555as | |
| 0800 | 0900 | | Zambia CVC Intl/ The Voice Africa | 6065af | |
| | | | 13590af | | |
| 0800 | 0900 | | Zambia, Zambia Natl Broadcasting Corp | 6165do | |
| 0805 | 0900 | thf | Guam, KTWR/TWR | 15190as | |
| 0820 | 0900 | w | Guam, KTWR/TWR | 15170as | |
| 0830 | 0900 | | Australia, ABC NT Alice Springs | | 2310do |
| 0830 | 0900 | | Australia, ABC NT Katherine | 2485do | |

| | | | |
|------|------|---------------------------------|---------|
| 0830 | 0900 | Australia, ABC NT Tennant Creek | 2325do |
| 0830 | 0900 | Australia, CVC International | 15555as |
| 0835 | 0900 | m Guam, KTWR/TWR | 15170as |
| 0855 | 0900 | mtwhf Guam, KTWR/TWR | 11840pa |

0900 UTC - 4AM EST / 3AM CST / 1AM PST

| | | | | |
|------|------|--|----------|----------|
| 0900 | 0927 | Czech Republic, Radio Prague | 9880am | 9955na |
| | | 21745af | | |
| 0900 | 0930 | Australia, HCJB Global | 11750pa | |
| 0900 | 0930 | mtwhf Guam, KTWR/TWR | 11840pa | |
| 0900 | 0930 | Japan, NHK World/ Radio Japan | 9625pa | |
| | | 9825pa | 11815as | 15590as |
| 0900 | 0930 | Uzbekistan, CVC Intl/ The Voice Asia | 15555as | |
| 0900 | 1000 | Anguilla, Worldwide Univ Network | 6090am | |
| 0900 | 1000 | Australia, ABC NT Alice Springs | 2310do | |
| 0900 | 1000 | Australia, ABC NT Katherine | 2485do | |
| 0900 | 1000 | Australia, ABC NT Tennant Creek | 2325do | |
| 0900 | 1000 | Australia, Radio Australia | 9475va | 9580va |
| | | 9590va | 11945as | 12080as |
| 0900 | 1000 | Bahrain, Radio Bahrain | 6010me | 9745al |
| 0900 | 1000 | t/DRM Belgium, TDP Radio | 6015eu | |
| 0900 | 1000 | Bhutan, Bhutan Broadcasting Service | 6035as | |
| 0900 | 1000 | Canada, CFRX Toronto ON | 6070na | |
| 0900 | 1000 | Canada, CFVP Calgary AB | 6030na | |
| 0900 | 1000 | Canada, CKZN St John's NF | 6160na | |
| 0900 | 1000 | Canada, CKZU Vancouver BC | 6160na | |
| 0900 | 1000 | China, China Radio International | 11620as | |
| | | 15210va | 15270eu | 15350as |
| | | 17490eu | 17570eu | 17690va |
| 0900 | 1000 | China, Guangxi FBS/Beibu Bay Radio | 5050as | |
| | | 9820as | | |
| 0900 | 1000 | mtwhf Equatorial Guinea, Radio Africa # 2 | 15190af | |
| 0900 | 1000 | Sat/Sun Equatorial Guinea, Radio East Africa | 15190af | |
| 0900 | 1000 | 2nd Sun Germany, Blue Star Radio | 6140eu | |
| 0900 | 1000 | DRM Germany, Deutsche Welle | 9545eu | 13810eu |
| 0900 | 1000 | Germany, Deutsche Welle | 15340as | 17705as |
| 0900 | 1000 | 3rd Sun Germany, European Music Radio | 6140eu | |
| 0900 | 1000 | 4th Sun Germany, Radio Gloria International | 6140eu | |
| 0900 | 1000 | Malaysia, RTM/Traxx FM | 7295do | |
| 0900 | 1000 | DRM New Zealand, Radio NZ International | 7285pa | |
| 0900 | 1000 | New Zealand, Radio NZ International | 6170pa | |
| 0900 | 1000 | Nigeria, Voice of Nigeria/External Service | 9690af | |
| 0900 | 1000 | Palau, T8WH/World Harvest | 9930as | 15700as |
| 0900 | 1000 | DRM Russia, Voice of Russia | 12060eu | |
| 0900 | 1000 | Russia, Voice of Russia | 15470as | 15610as |
| | | 21790as | | |
| 0900 | 1000 | South Africa, Channel Africa | 9625af | |
| 0900 | 1000 | Tajikistan, Voice of Tajik | 7245as | |
| 0900 | 1000 | UK, BBC World Service | 6190af | 6195as |
| | | 9740as | 9860af | 11760me |
| | | 15400af | 15575as | 17640af |
| | | 17790as | 17830af | 21470af |
| | | | | 21660as |
| 0900 | 1000 | Ukraine, Radio Ukraine International | 9950eu | |
| 0900 | 1000 | USA, American Forces Network | 4319usb | |
| | | 5446usb | 5765usb | 6350usb |
| | | 10320usb | 12133usb | 12759usb |
| | | | | 13362usb |
| 0900 | 1000 | USA, EWTN Vandiver AL | 11640as | |
| 0900 | 1000 | USA, WBOH Newport NC | 5920am | |
| 0900 | 1000 | USA, WHRA Greenbush ME | 11565pa | |
| 0900 | 1000 | USA, WHRI Cypress Creek SC | 7385va | |
| 0900 | 1000 | smtwhf USA, WHRI Cypress Creek SC | 9425na | |
| 0900 | 1000 | Sat USA, WHRI Cypress Creek SC | 7465na | |
| 0900 | 1000 | vl USA, WRMI Miami FL | 9955va | |
| 0900 | 1000 | USA, WTJC Newport NC | 9370na | |
| 0900 | 1000 | USA, WWCR Nashville TN | 5070na | 5890na |
| | | 5935na | 9985na | |
| 0900 | 1000 | USA, WWRB Manchester TN | 3185va | |
| 0900 | 1000 | USA, WYFR/Family Radio Worldwide | 5950na | |
| | | 6915na | 7455na | |
| 0900 | 1000 | Zambia CVC Intl/ The Voice Africa | 6065af | |
| | | 13590af | | |
| 0900 | 1000 | Zambia, Zambia Natl Broadcasting Corp | 6165do | |
| 0915 | 0930 | Sat Guam, KTWR/TWR | 11840pa | |
| 0930 | 1000 | Australia, CVC International | 15555as | |
| 0930 | 1000 | Sat/Sun Italy, IRRS-Shortwave | 9510va | |

1000 UTC - 5AM EST / 4AM CST / 2AM PST

| | | | | |
|------|------|--------------------------------------|---------|---------|
| 1000 | 1004 | Pakistan, Radio Pakistan | 15100as | 17835as |
| 1000 | 1030 | Vietnam, Voice of Vietnam | 9840as | 12020as |
| 1000 | 1057 | Netherlands, R Netherlands Worldwide | 11895as | |
| | | 12065as | 15110as | |
| 1000 | 1057 | North Korea, Voice of Korea | 11710sa | 11735as |
| | | 13650as | 15180sa | |
| 1000 | 1058 | New Zealand, Radio NZ International | 6170pa | |

| | | | | |
|------|------|--|----------|----------|
| 1000 | 1058 | DRM New Zealand, Radio NZ International | 7285pa | |
| 1000 | 1100 | Anguilla, Worldwide Univ Network | 11775am | |
| 1000 | 1100 | Australia, ABC NT Alice Springs | 2310do | |
| 1000 | 1100 | Australia, ABC NT Katherine | 2485do | |
| 1000 | 1100 | Australia, ABC NT Tennant Creek | 2325do | |
| 1000 | 1100 | Australia, CVC International | 15555as | |
| 1000 | 1100 | Australia, Radio Australia | 9475va | 9580va |
| | | 9590va | 11945as | 12080as |
| 1000 | 1100 | Bahrain, Radio Bahrain | 6010me | 9745al |
| 1000 | 1100 | w/DRM Belgium, TDP Radio | 6015eu | |
| 1000 | 1100 | Canada, CFRX Toronto ON | 6070na | |
| 1000 | 1100 | Canada, CFVP Calgary AB | 6030na | |
| 1000 | 1100 | Canada, CKZN St John's NF | 6160na | |
| 1000 | 1100 | Canada, CKZU Vancouver BC | 6160na | |
| 1000 | 1100 | China, China Radio International | 6040na | |
| | | 6090as | 11610as | 11635as |
| | | 13590as | 13620as | 13720as |
| | | 15350as | 17490eu | 15190as |
| 1000 | 1100 | mtwhf Equatorial Guinea, Radio Africa # 2 | 15190af | |
| 1000 | 1100 | Sat/Sun Equatorial Guinea, Radio East Africa | 15190af | |
| 1000 | 1100 | DRM Germany, Deutsche Welle | 9545eu | 13810eu |
| 1000 | 1100 | India, All India Radio | 7270as | 13695va |
| | | 15070as | 15260as | 15410pa |
| | | 17800pa | 17895pa | 17510pa |
| 1000 | 1100 | Indonesia, Voice of Indonesia | 9525va | 11785al |
| 1000 | 1100 | Sat/Sun Italy, IRRS-Shortwave | 9510va | |
| 1000 | 1100 | Malaysia, RTM/Traxx FM | 7295do | |
| 1000 | 1100 | Nigeria, Voice of Nigeria/External Service | 9690af | |
| 1000 | 1100 | Palau, T8WH/World Harvest | 9930as | 15700as |
| 1000 | 1100 | Russia, Voice of Russia | 15470as | 15610as |
| 1000 | 1100 | Saudi Arabia, BSKSA/External Service | 15250af | |
| 1000 | 1100 | South Africa, Channel Africa | 9625af | |
| 1000 | 1100 | UK, BBC World Service | 15400af | 17830af |
| 1000 | 1100 | Sat/Sun UK, BBC World Service | 6190af | 6195as |
| | | 9545eu | 9740as | 9860af |
| | | 15310af | 15575as | 17640af |
| | | 17790as | 21470af | 21660as |
| 1000 | 1100 | USA, American Forces Network | 4319usb | |
| | | 5446usb | 5765usb | 6350usb |
| | | 10320usb | 12133usb | 12759usb |
| | | | | 13362usb |
| 1000 | 1100 | USA, EWTN Vandiver AL | 11640as | |
| 1000 | 1100 | USA, KNLS Anchor Point AK | 6890as | |
| 1000 | 1100 | USA, WBOH Newport NC | 5920am | |
| 1000 | 1100 | USA, WHRA Greenbush ME | 11565pa | |
| 1000 | 1100 | USA, WHRI Cypress Creek SC | 7385va | |
| 1000 | 1100 | USA, WINB Red Lion PA | 9265am | |
| 1000 | 1100 | vl USA, WRMI Miami FL | 9955va | |
| 1000 | 1100 | USA, WTJC Newport NC | 9370na | |
| 1000 | 1100 | USA, WWCR Nashville TN | 5070na | 5890na |
| | | 5935na | 9985na | |
| 1000 | 1100 | USA, WWRB Manchester TN | 3185va | |
| 1000 | 1100 | USA, WYFR/Family Radio Worldwide | 5950na | |
| | | 6890na | 6915na | |
| 1000 | 1100 | Zambia CVC Intl/ The Voice Africa | 6065af | |
| | | 13590af | | |
| 1000 | 1100 | Zambia, Zambia Natl Broadcasting Corp | 6165do | |
| 1015 | 1045 | Sun UK, Bible Voice Broadcasting | 5910as | |
| 1030 | 1057 | Czech Republic, Radio Prague | 9880eu | 11665eu |
| 1030 | 1100 | Iran, Voice of Islamic Rep. of Iran | 15600as | |
| | | 17660as | | |
| 1030 | 1100 | Mongolia, Voice of Mongolia | 12085as | |
| 1059 | 1100 | New Zealand, Radio NZ International | 6170pa | 9655pa |

1100 UTC - 6AM EST / 5AM CST / 3AM PST

| | | | | |
|------|------|---|---------|---------|
| 1100 | 1103 | mtwhf Croatia, Voice of Croatia | 6165eu | |
| 1100 | 1112 | Venezuela, Radio Nacional de Venezuela | 6060ca | |
| 1100 | 1127 | Iran, Voice of Islamic Rep. of Iran | 15600as | |
| | | 17660as | | |
| 1100 | 1130 | Australia, CVC International | 15555as | |
| 1100 | 1130 | China, China Radio International | 6060as | |
| 1100 | 1130 | f/ DRM Japan, NHK World/ Radio Japan | 9760eu | |
| 1100 | 1130 | Vietnam, Voice of Vietnam | 7285as | |
| 1100 | 1145 | USA, WYFR/Family Radio Worldwide | 5950na | |
| | | 6000ca | | |
| 1100 | 1156 | Romania, Radio Romania International | 11775af | |
| | | 15210af | 15430af | 17730af |
| 1100 | 1158 | DRM New Zealand, Radio NZ International | 7285pa | |
| 1100 | 1200 | Anguilla, Worldwide Univ Network | 11775am | |
| 1100 | 1200 | Australia, ABC NT Alice Springs | 2310do | |
| 1100 | 1200 | Australia, ABC NT Katherine | 2485do | |
| 1100 | 1200 | Australia, ABC NT Tennant Creek | 2325do | |
| 1100 | 1200 | DRM Australia, Radio Australia | 12080pa | |
| 1100 | 1200 | Australia, Radio Australia | 6020va | 9475as |
| | | 9560as | 9580va | 9590va |
| 1100 | 1200 | Bahrain, Radio Bahrain | 6010me | 9745al |
| 1100 | 1200 | h/DRM Belgium, TDP Radio | 6015eu | |

| | | | | | |
|------|------|---------|--|----------|----------|
| 1100 | 1200 | Sat/Sun | Canada, CBC NQ SW Service | 9625na | |
| 1100 | 1200 | | Canada, CFRX Toronto ON | 6070na | |
| 1100 | 1200 | | Canada, CFVP Calgary AB | 6030na | |
| 1100 | 1200 | | Canada, CKZN St John's NF | 6160na | |
| 1100 | 1200 | | Canada, CKZU Vancouver BC | 6160na | |
| 1100 | 1200 | | China, China Radio International | 5955as | |
| | | | 6040na | 11650as | 11660as |
| | | | 13645as | 13650eu | 13790eu |
| 1100 | 1200 | mtwhf | Equatorial Guinea, Radio Africa # 2 | 15190af | |
| 1100 | 1200 | Sat/Sun | Equatorial Guinea, Radio East Africa | 15190af | |
| 1100 | 1200 | DRM | Germany, Deutsche Welle | 9545eu | 13810eu |
| 1100 | 1200 | Sat/Sun | Italy, IRRS-Shortwave | 9510va | |
| 1100 | 1200 | | Malaysia, RTM/Traxx FM | 7295do | |
| 1100 | 1200 | | New Zealand, Radio NZ International | 9655pa | |
| 1100 | 1200 | | Nigeria, Voice of Nigeria/External Service | 9690af | |
| 1100 | 1200 | | Palau, T8WH/World Harvest | 9930as | 15700as |
| 1100 | 1200 | | Russia, Voice of Russia | 12065as | 15470as |
| 1100 | 1200 | | Saudi Arabia, BSKSA/External Service | 15250af | |
| 1100 | 1200 | | South Africa, Channel Africa | 9625af | |
| 1100 | 1200 | | Taiwan, Radio Taiwan International | 7445as | |
| | | | 11715as | | |
| 1100 | 1200 | | UK, BBC World Service | 6190af | 6195as |
| | | | 9740as | 9860af | 9545eu |
| | | | 15310as | 15340as | 15400af |
| | | | 17640af | 17760as | 17790as |
| | | | 21470af | | |
| 1100 | 1200 | | Ukraine, Radio Ukraine International | 9950eu | |
| 1100 | 1200 | | USA, American Forces Network | 4319usb | |
| | | | 5446usb | 5765usb | 6350usb |
| | | | 10320usb | 12133usb | 12759usb |
| 1100 | 1200 | | USA, EWTN Vandiver AL | 11640as | |
| 1100 | 1200 | | USA, WBOH Newport NC | 5920am | |
| 1100 | 1200 | | USA, WHRI Cypress Creek SC | 7315va | 7385va |
| 1100 | 1200 | | USA, WINB Red Lion PA | 9265am | |
| 1100 | 1200 | vl | USA, WRMI Miami FL | 9955va | |
| 1100 | 1200 | | USA, WTJC Newport NC | 9370na | |
| 1100 | 1200 | | USA, WWCR Nashville TN | 5890na | 5935na |
| | | | 7490na | 15830na | |
| 1100 | 1200 | | USA, WWRB Manchester TN | 3185va | |
| 1100 | 1200 | | USA, WYFR/Family Radio Worldwide | 7455na | 6890na |
| | | | 7455na | 11725ca | 11830sa |
| 1100 | 1200 | | Zambia CVC Intl/ The Voice Africa | 6065af | |
| | | | 13590af | | |
| 1100 | 1200 | | Zambia, Zambia Natl Broadcasting Corp | 6165do | |
| 1115 | 1130 | mtwhfa | UK, Bible Voice Broadcasting | 5945as | |
| 1115 | 1145 | Sun | UK, Bible Voice Broadcasting | 5945as | |
| 1130 | 1145 | f | USA, Eternal Good News | 15525as | |
| 1130 | 1200 | | Australia, CVC International | 13635as | |
| 1130 | 1200 | | Bulgaria, Radio Bulgaria | 11700eu | 15700eu |
| 1130 | 1200 | f | Vatican City State, Vatican Radio | 17765me | 15595me |
| 1130 | 1200 | | Vietnam, Voice of Vietnam | 9840as | 12020as |

1200 UTC - 7AM EST / 6AM CST / 4AM PST

| | | | | | |
|------|------|---------|--------------------------------------|---------|---------|
| 1200 | 1225 | | Saudi Arabia, BSKSA/External Service | 15250af | |
| 1200 | 1230 | | China, China Radio International | 11780as | |
| 1200 | 1230 | mtwhf | France, Radio France International | 13640af | |
| | | | 17800af | 21620af | |
| 1200 | 1230 | | Japan, NHK World/ Radio Japan | 6120na | |
| | | | 9625pa | 9695as | 9790eu |
| 1200 | 1245 | | Australia, HCJB Global | 15400as | |
| 1200 | 1245 | | USA, WYFR/Family Radio Worldwide | 6890na | |
| 1200 | 1258 | | New Zealand, Radio NZ International | 9655pa | |
| 1200 | 1300 | | Anguilla, Worldwide Univ Network | 11775am | |
| 1200 | 1300 | | Australia, ABC NT Alice Springs | 2310do | |
| 1200 | 1300 | | Australia, ABC NT Katherine | 2485do | |
| 1200 | 1300 | | Australia, ABC NT Tennant Creek | 2325do | |
| 1200 | 1300 | | Australia, CVC International | 13635as | |
| 1200 | 1300 | DRM | Australia, Radio Australia | 5995pa | 12080pa |
| 1200 | 1300 | | Australia, Radio Australia | 6020va | 9475as |
| | | | 9560pa | 9580va | 9590va |
| | | | 11945as | | 9745al |
| 1200 | 1300 | | Bahrain, Radio Bahrain | 6010me | |
| 1200 | 1300 | f/DRM | Belgium, TDP Radio | 6015eu | |
| 1200 | 1300 | Sat/Sun | Canada, CBC NQ SW Service | 9625na | |
| 1200 | 1300 | | Canada, CFRX Toronto ON | 6070na | |
| 1200 | 1300 | | Canada, CFVP Calgary AB | 6030na | |
| 1200 | 1300 | | Canada, CKZN St John's NF | 6160na | |
| 1200 | 1300 | | Canada, CKZU Vancouver BC | 6160na | |
| 1200 | 1300 | | China, China Radio International | 5955as | |
| | | | 9460as | 9600as | 9645as |
| | | | 9760va | 11650as | 11660as |
| | | | 11760va | 11980as | 13645as |
| | | | 17490eu | | 13650eu |
| 1200 | 1300 | Sat/Sun | Equatorial Guinea, Radio East Africa | 15190af | |
| 1200 | 1300 | DRM | Germany, Deutsche Welle | 9545eu | 13810eu |
| 1200 | 1300 | Sun | Latvia, Radio SWH | 9290eu | |

| | | | | | |
|------|------|--------|--|----------|----------|
| 1200 | 1300 | vl | Libya, LJB/Voice of Africa | 17725af | 21695af |
| 1200 | 1300 | | Malaysia, RTM/Traxx FM | 7295do | |
| 1200 | 1300 | | Nigeria, Voice of Nigeria/External Service | 9690af | |
| 1200 | 1300 | | Palau, T8WH/World Harvest | 9930as | 12130as |
| 1200 | 1300 | | Poland, Polish Radio | 7330eu | 9525eu |
| 1200 | 1300 | | Russia, Voice of Russia | 7330as | 12065as |
| | | | 15470as | | |
| 1200 | 1300 | | South Korea, KBS World Radio | 9650na | |
| 1200 | 1300 | DRM | Taiwan, Radio Taiwan International | 9850va | |
| 1200 | 1300 | | UK, BBC World Service | 5875as | 6190af |
| | | | 6195as | 9545eu | 9740as |
| | | | 11750as | 11760me | 15310as |
| | | | 17640af | 17790as | 17830af |
| 1200 | 1300 | | USA, American Forces Network | 4319usb | |
| | | | 5446usb | 5765usb | 6350usb |
| | | | 10320usb | 12133usb | 12759usb |
| 1200 | 1300 | | USA, EWTN Vandiver AL | 12160as | |
| 1200 | 1300 | | USA, KNLS Anchor Point AK | 7355as | 9780as |
| 1200 | 1300 | | USA, Voice of America | 6140va | 7575va |
| | | | 9510va | 9760va | 12075va |
| 1200 | 1300 | | USA, WBOH Newport NC | 5920am | |
| 1200 | 1300 | | USA, WHRI Cypress Creek SC | 7315va | 7385va |
| 1200 | 1300 | | USA, WINB Red Lion PA | 9265am | |
| 1200 | 1300 | vl | USA, WRMI Miami FL | 9955va | |
| 1200 | 1300 | | USA, WTJC Newport NC | 9370na | |
| 1200 | 1300 | | USA, WWCR Nashville TN | 7490na | 9980na |
| | | | 13845na | 15830na | |
| 1200 | 1300 | | USA, WWRB Manchester TN | 9385va | |
| 1200 | 1300 | | USA, WYFR/Family Radio Worldwide | 7455na | |
| | | | 11530sa | 11970am | |
| 1200 | 1300 | | Zambia CVC Intl/ The Voice Africa | 6065af | |
| | | | 13590af | | |
| 1200 | 1300 | | Zambia, Zambia Natl Broadcasting Corp | 6165do | |
| 1209 | 1213 | mtwhf | Austria, ORF/Radio Austria Intl | 17715va | |
| 1230 | 1300 | | Bangladesh, Bangladesh Betar | 7250as | |
| 1230 | 1300 | mtwhf | Ethiopia, Radio Ethiopia/National Service | 5990do | |
| | | | 7110do | 9704do | |
| 1230 | 1300 | | India, All India Radio | 4920as | 4970as |
| | | | 5040as | 5050as | |
| 1230 | 1300 | | Thailand, Radio Thailand World Service | 9890va | |
| 1230 | 1300 | | Turkey, Voice of Turkey | 15420eu | 15520as |
| 1230 | 1300 | | Vietnam, Voice of Vietnam | 9840as | 12020as |
| 1245 | 1300 | smtwhf | Australia, HCJB Global | 15400as | |

1300 UTC - 8AM EST / 7AM CST / 5AM PST

| | | | | | |
|------|------|---------|--|---------|---------|
| 1300 | 1325 | | Turkey, Voice of Turkey | 15450eu | 15520as |
| 1300 | 1327 | | Czech Republic, Radio Prague | 13580af | 17540af |
| 1300 | 1330 | | Egypt, Radio Cairo | 17835as | |
| 1300 | 1345 | | USA, WYFR/Family Radio Worldwide | 7455na | |
| | | | 11970na | | |
| 1300 | 1357 | | North Korea, Voice of Korea | 9335na | 11710na |
| | | | 13760eu | 15245eu | |
| 1300 | 1400 | | Anguilla, Worldwide Univ Network | 11775am | |
| 1300 | 1400 | | Australia, ABC NT Alice Springs | 2310do | |
| 1300 | 1400 | | Australia, ABC NT Katherine | 2485do | |
| 1300 | 1400 | | Australia, CVC International | 13635as | |
| 1300 | 1400 | DRM | Australia, Radio Australia | 5995pa | 12080pa |
| 1300 | 1400 | | Australia, Radio Australia | 6020va | 9560as |
| | | | 9580va | 9590va | |
| 1300 | 1400 | | Bahrain, Radio Bahrain | 6010me | 9745al |
| 1300 | 1400 | a/DRM | Belgium, TDP Radio | 6015eu | |
| 1300 | 1400 | Sat/Sun | Canada, CBC NQ SW Service | 9625na | |
| 1300 | 1400 | | Canada, CFRX Toronto ON | 6070na | |
| 1300 | 1400 | | Canada, CFVP Calgary AB | 6030na | |
| 1300 | 1400 | | Canada, CKZN St John's NF | 6160na | |
| 1300 | 1400 | | Canada, CKZU Vancouver BC | 6160na | |
| 1300 | 1400 | | China, China Radio International | 5995as | |
| | | | 9570na | 9650na | 9730as |
| | | | 9870as | 11660as | 11980as |
| | | | 13755as | 13790eu | 15260na |
| 1300 | 1400 | Sat/Sun | Equatorial Guinea, Radio East Africa | 15190af | |
| 1300 | 1400 | DRM | Germany, Deutsche Welle | 9545eu | |
| 1300 | 1400 | | Indonesia, Voice of Indonesia | 9525va | 11785al |
| 1300 | 1400 | vl | Libya, LJB/Voice of Africa | 17725af | 21695af |
| 1300 | 1400 | | Malaysia, RTM/Traxx FM | 7295do | |
| 1300 | 1400 | | New Zealand, Radio NZ International | 9655pa | 6170pa |
| 1300 | 1400 | | Nigeria, Voice of Nigeria/External Service | 9690af | |
| 1300 | 1400 | | Palau, T8WH/World Harvest | 9930as | |
| 1300 | 1400 | | Russia, Voice of Russia | 7330as | 12065as |
| 1300 | 1400 | | South Korea, KBS World Radio | 9570na | |
| | | | 9770as | | |
| 1300 | 1400 | | Uganda, UBC Radio | 4976do | |
| 1300 | 1400 | DRM | UK, BBC World Service | 9545eu | 13810eu |
| 1300 | 1400 | | UK, BBC World Service | 5875as | 6190af |
| | | | 6195as | 9545eu | 9740as |
| | | | 11760me | 15310as | 15420af |
| | | | | | 15575as |

| | | | | | | | |
|------|------|---------|---------------------------------------|----------|----------|----------|--|
| 1300 | 1400 | | 17640af | 17790as | 17830af | 21470af | |
| | | | USA, American Forces Network | | | 4319usb | |
| | | | 5446usb | 5765usb | 6350usb | 7812usb | |
| | | | 10320usb | 12133usb | 12759usb | 13362usb | |
| 1300 | 1400 | | USA, EWTN Vandiver AL | | 12160as | | |
| 1300 | 1400 | | USA, KJES Vado NM | | 11715na | | |
| 1300 | 1400 | | USA, Voice of America | | 7575va | 9340va | |
| | | | 9510va | 9760va | | | |
| 1300 | 1400 | | USA, WBOH Newport NC | | 5920am | | |
| 1300 | 1400 | Sat/Sun | USA, WHRA Greenbush ME | | 15195va | | |
| 1300 | 1400 | | USA, WHRI Cypress Creek SC | | 7315va | | |
| 1300 | 1400 | Sat/Sun | USA, WHRI Cypress Creek SC | | 9840va | | |
| 1300 | 1400 | | USA, WINB Red Lion PA | | 9265am | | |
| 1300 | 1400 | vl | USA, WRMI Miami FL | | 9955va | | |
| 1300 | 1400 | | USA, WTJC Newport NC | | 9370na | | |
| 1300 | 1400 | | USA, WWCR Nashville TN | | 7490na | 9980na | |
| | | | 13845na | 15830na | | | |
| 1300 | 1400 | | USA, WWRB Manchester TN | | 9385va | | |
| 1300 | 1400 | | USA, WYFR/Family Radio Worldwide | | | 11830na | |
| | | | 11855as | | | | |
| 1300 | 1400 | | Zambia CVC Intl/ The Voice Africa | | | 6065af | |
| | | | 13590af | | | | |
| 1300 | 1400 | | Zambia, Zambia Natl Broadcasting Corp | | 6165do | | |
| 1305 | 1400 | Sun | Greece, Voice of Greece | | 9420va | 15630va | |
| 1310 | 1340 | | Japan, NHK World/ Radio Japan | | | 11985as | |
| 1330 | 1357 | fa/ DRM | Czech Republic, Radio Prague | | 9850eu | | |
| 1330 | 1400 | mtwhf | Guam, KSDA/ AWR | | 15275as | | |
| 1330 | 1400 | ha | Guam, KSDA/ AWR | | 11880as | | |
| 1330 | 1400 | | India, All India Radio | | 9690as | 11620as | |
| | | | 13710as | | | | |
| 1330 | 1400 | | Laos, Lao National Radio | | 7145as | | |
| 1330 | 1400 | | Sweden, Radio Sweden | | 15735va | | |
| 1330 | 1400 | | Vietnam, Voice of Vietnam | | 9840as | 12020as | |

1400 UTC - 9AM EST / 8AM CST / 6AM PST

| | | | | | | | |
|------|------|---------|--|---------|---------|---------|---------|
| 1400 | 1427 | | Czech Republic, Radio Prague | | 9955na | | |
| 1400 | 1430 | | Australia, Radio Australia | | 5995va | 6080va | |
| | | | 7240va | 9590va | | | |
| 1400 | 1430 | | China, China Radio International | | | 7325as | |
| 1400 | 1430 | f | Clandestine, Shiokaze/Sea Breeze | | | 6120as | |
| 1400 | 1430 | Sun | Germany, Pan American Broadcasting | | | 15205as | |
| 1400 | 1430 | | Japan, NHK World/ Radio Japan | | | 11705as | |
| | | | 11985as | 13630eu | 21560af | | |
| 1400 | 1430 | | Laos, Lao National Radio | | 6130as | | |
| 1400 | 1430 | | Thailand, Radio Thailand World Service | | | 9455va | |
| 1400 | 1430 | Sun | United Arab Emirates, FEBA Radio | | | 12025as | |
| 1400 | 1457 | | Netherlands, R Netherlands Worldwide | | | 5825as | |
| | | | 7530as | 9345as | 11835as | 15815as | |
| 1400 | 1500 | | Anguilla, Worldwide Univ Network | | | 11775am | |
| 1400 | 1500 | | Australia, ABC NT Alice Springs | | | 2310do | |
| 1400 | 1500 | | Australia, ABC NT Katherine | | | 2485do | |
| 1400 | 1500 | | Australia, ABC NT Tennant Creek | | | 2325do | |
| 1400 | 1500 | | Australia, CVC International | | | 13635as | |
| 1400 | 1500 | | Australia, HCJB Global | | | 15425as | |
| 1400 | 1500 | | Bahrain, Radio Bahrain | | | 6010me | 9745al |
| 1400 | 1500 | s/DRM | Belgium, TDP Radio | | | 6015eu | |
| 1400 | 1500 | | Bhutan, Bhutan Broadcasting Service | | | | 6035as |
| 1400 | 1500 | Sat/Sun | Canada, CBC NQ SW Service | | | 9625na | |
| 1400 | 1500 | | Canada, CFRX Toronto ON | | | 6070na | |
| 1400 | 1500 | | Canada, CFVP Calgary AB | | | 6030na | |
| 1400 | 1500 | | Canada, CKZN St John's NF | | | 6160na | |
| 1400 | 1500 | | Canada, CKZU Vancouver BC | | | 6160na | |
| 1400 | 1500 | | China, China Radio International | | | 5955as | |
| | | | 9870as | 11675as | 11765as | 13740na | |
| | | | 13710eu | 13790eu | | | |
| 1400 | 1500 | Sat/Sun | Equatorial Guinea, Radio East Africa | | | 15190af | |
| 1400 | 1500 | | Germany, CVC Intl-Christian Vision | | | 17770af | |
| 1400 | 1500 | | Germany, Overcomer Ministries | | | 6110eu | |
| | | | 13810as | | | | |
| 1400 | 1500 | | India, All India Radio | | | 9690as | 11620as |
| | | | 13710as | | | | |
| 1400 | 1500 | vl | Libya, LJB/Voice of Africa | | | 17725af | 21695af |
| 1400 | 1500 | | Malaysia, RTM/Traxx FM | | | 7295do | |
| 1400 | 1500 | | New Zealand, Radio NZ International | | | 6170pa | |
| 1400 | 1500 | | Nigeria, Voice of Nigeria/External Service | | | 9690af | |
| 1400 | 1500 | | Oman, Radio Oman | | | 15140va | |
| 1400 | 1500 | | Palau, T8WH/World Harvest | | | 9930as | 9965as |
| 1400 | 1500 | DRM | Russia, Voice of Russia | | | 9445as | 9750eu |
| 1400 | 1500 | | Russia, Voice of Russia | | | 6045as | 7330as |
| | | | 9850as | 15605as | | | |
| 1400 | 1500 | | South Africa, Channel Africa | | | 9625af | |
| 1400 | 1500 | | Uganda, UBC Radio | | | 4976do | |
| 1400 | 1500 | DRM | UK, BBC World Service | | | 9545eu | 15780eu |
| 1400 | 1500 | | UK, BBC World Service | | | 5875as | 6190af |
| | | | 6195as | 7230af | 9545eu | 9740as | |
| | | | 11920as | 12095as | 15310as | 17640af | |

| | | | | | | | |
|------|------|---------|---------------------------------------|----------|----------|----------|--------|
| 1400 | 1500 | Sat/Sun | 17830af | 21470af | | | |
| 1400 | 1500 | | UK, Bible Voice Broadcasting | | | 17805as | |
| | | | USA, American Forces Network | | | 4319usb | |
| | | | 5446usb | 5765usb | 6350usb | 7812usb | |
| | | | 10320usb | 12133usb | 12759usb | 13362usb | |
| 1400 | 1500 | | USA, EWTN Vandiver AL | | 12160as | | |
| 1400 | 1500 | | USA, KJES Vado NM | | 11715na | | |
| 1400 | 1500 | | USA, KNLS Anchor Point AK | | 7355as | | |
| 1400 | 1500 | | USA, Voice of America | | 4930af | 6080af | |
| | | | 7575va | 9760va | 11715va | 13750af | |
| | | | 15580af | 17585af | | | |
| 1400 | 1500 | | USA, WBOH Newport NC | | 5920am | | |
| 1400 | 1500 | Sat/Sun | USA, WHRA Greenbush ME | | 15195va | | |
| 1400 | 1500 | Sat/Sun | USA, WHRI Cypress Creek SC | | 9840va | | |
| 1400 | 1500 | | USA, WINB Red Lion PA | | | 13570am | |
| 1400 | 1500 | vl | USA, WRMI Miami FL | | 9955va | | |
| 1400 | 1500 | | USA, WTJC Newport NC | | 9370na | | |
| 1400 | 1500 | | USA, WWCR Nashville TN | | 7490na | 9980na | |
| | | | 13845na | 15830na | | | |
| 1400 | 1500 | | USA, WWRB Manchester TN | | 9385va | | |
| 1400 | 1500 | | USA, WYFR/Family Radio Worldwide | | | 11565na | |
| | | | 11855as | 13695na | 17760na | | |
| 1400 | 1500 | | Zambia CVC Intl/ The Voice Africa | | | 6065af | |
| | | | 13590af | | | | |
| 1400 | 1500 | | Zambia, Zambia Natl Broadcasting Corp | | 6165do | | |
| 1415 | 1430 | | Nepal, Radio Nepal | | | 5005as | |
| 1415 | 1439 | mtwhfa | Germany, Pan American Broadcasting | | | 15205as | |
| 1415 | 1450 | | Guam, KTWB/TWR | | | 9975as | |
| 1430 | 1445 | Sun | Germany, Pan American Broadcasting | | | 15205as | |
| 1430 | 1500 | mtwhfa | Albania, Radio Tirana | | | 13625na | |
| 1430 | 1500 | | Australia, Radio Australia | | | 5995va | 6080va |
| | | | 7240va | 9475as | 9590va | 11660pa | |
| 1430 | 1500 | | China, CPBS/CNR Business Radio | | | 6010do | |
| | | | 7245do | | | | |
| 1430 | 1500 | f/ DRM | New Zealand, Radio NZ International | | | 9660eu | |
| 1430 | 1500 | f/ DRM | South Korea, KBS World Radio | | | 9660eu | |
| 1430 | 1500 | | Sweden, Radio Sweden | | | 13820va | |

1500 UTC - 10AM EST / 9AM CST / 7AM PST

| | | | | | | | |
|------|------|---------|--------------------------------------|---------|--------|---------|---------|
| 1500 | 1510 | mtwhfa | Turkmenistan, Turkmen Radiosi | | | 5015eu | |
| 1500 | 1515 | Sun | UK, Bible Voice Broadcasting | | | 15680as | |
| 1500 | 1525 | Sun | China, Voice of the Strait | | | 9505as | |
| 1500 | 1530 | | Australia, HCJB Global | | | 15425as | |
| 1500 | 1530 | | China, China Radio International | | | 9600as | |
| 1500 | 1530 | Sat/Sun | Clandestine, Sudan Radio Service | | | 17745af | |
| 1500 | 1530 | | Guam, KSDA/ AWR | | | 11720as | |
| 1500 | 1530 | | UK, BBC World Service | | | 7385af | 11860af |
| | | | 15420af | | | | |
| 1500 | 1530 | Sat | UK, Bible Voice Broadcasting | | | 15295as | |
| 1500 | 1530 | | UK, Sudan Radio Service | | | 17745af | |
| 1500 | 1530 | | Vietnam, Voice of Vietnam | | | 7285va | 9840va |
| | | | 12020va | | | | |
| 1500 | 1545 | | USA, WYFR/Family Radio Worldwide | | | 15210sa | |
| 1500 | 1550 | | New Zealand, Radio NZ International | | | 6170pa | |
| 1500 | 1557 | | North Korea, Voice of Korea | | | 9335na | 11710na |
| | | | 13760eu | 15245eu | | | |
| 1500 | 1600 | | Anguilla, Worldwide Univ Network | | | 11775am | |
| 1500 | 1600 | | Australia, ABC NT Alice Springs | | | 2310do | |
| 1500 | 1600 | | Australia, ABC NT Katherine | | | 2485do | |
| 1500 | 1600 | | Australia, CVC International | | | 11730as | |
| 1500 | 1600 | | Australia, Radio Australia | | | 5995va | 6080va |
| | | | 7240va | 9475as | 9590va | 11660pa | |
| 1500 | 1600 | | Bahrain, Radio Bahrain | | | 6010me | 9745al |
| 1500 | 1600 | DRM | Belgium, TDP Radio | | | 6015eu | |
| 1500 | 1600 | Sat/Sun | Canada, CBC NQ SW Service | | | 9625na | |
| 1500 | 1600 | | Canada, CFRX Toronto ON | | | 6070na | |
| 1500 | 1600 | | Canada, CFVP Calgary AB | | | 6030na | |
| 1500 | 1600 | | Canada, CKZN St John's NF | | | 6160na | |
| 1500 | 1600 | | Canada, CKZU Vancouver BC | | | 6160na | |
| 1500 | 1600 | | Canada, Radio Canada International | | | 11675va | |
| | | | 17720va | | | | |
| 1500 | 1600 | | China, China Radio International | | | 5955as | |
| | | | 6095as | 7160as | 7325as | 7405as | |
| | | | 9720as | 9800as | 9870as | 11965eu | |
| | | | 13640as | 13740na | | | |
| 1500 | 1600 | Sat/Sun | Equatorial Guinea, Radio East Africa | | | 15190af | |
| 1500 | 1600 | | Germany, CVC Intl-Christian Vision | | | 17770af | |
| 1500 | 1600 | | Germany, Overcomer Ministries | | | 6110eu | |
| | | | 13810as | 17485af | | | |
| 1500 | 1600 | vl | Libya, LJB/Voice of Africa | | | 17725af | 21695af |
| 1500 | 1600 | | Malaysia, RTM/Traxx FM | | | 7295do | |
| 1500 | 1600 | | Myanmar, Myanmar Radio | | | 5985as | |
| 1500 | 1600 | | Palau, T8WH/World Harvest | | | 9965as | |
| 1500 | 1600 | | Russia, Voice of Russia | | | 4975me | 9625as |
| | | | 9660as | 9735me | 9850as | 11985me | |
| | | | 12040eu | 15605as | | | |

| | | | | | |
|------|------|---------|---------------------------------------|----------|----------|
| 1500 | 1600 | | South Africa, Channel Africa | 9625af | |
| 1500 | 1600 | | Uganda, Dunamis Shortwave | 4750af | |
| 1500 | 1600 | | Uganda, UBC Radio | 4976do | |
| 1500 | 1600 | DRM | UK, BBC World Service | 5790eu | 15780eu |
| 1500 | 1600 | | UK, BBC World Service | 5875as | 5975as |
| | | | 6190af | 6195as | 7230af |
| | | | 7385af | 9740as | 11920as |
| | | | 12095eu | 15310af | 15400af |
| | | | 17830af | 21470af | |
| 1500 | 1600 | | USA, American Forces Network | 4319usb | |
| | | | 5446usb | 5765usb | 6350usb |
| | | | 7812usb | 10320usb | 12133usb |
| | | | 12759usb | 13362usb | |
| 1500 | 1600 | | USA, EWTN Vandiver AL | 15610eu | |
| 1500 | 1600 | | USA, Voice of America | 4930af | 6080af |
| | | | 7545va | 7575va | 9700va |
| | | | 12005va | 12150va | 13750va |
| | | | 15530va | 15580af | 17740va |
| | | | 17895af | | |
| 1500 | 1600 | | USA, Voice of America/Special English | 6160va | |
| | | | 7520va | 9485va | 9760va |
| | | | 15550va | | |
| 1500 | 1600 | | USA, WBOH Newport NC | 5920am | |
| 1500 | 1600 | Sat/Sun | USA, WHRA Greenbush ME | 15195va | |
| 1500 | 1600 | Sat/Sun | USA, WHRI Cypress Creek SC | 9840va | 11785va |
| 1500 | 1600 | | USA, WINB Red Lion PA | 13570am | |
| 1500 | 1600 | vl | USA, WRMI Miami FL | 9955na | |
| 1500 | 1600 | | USA, WTJC Newport NC | 9370na | |
| 1500 | 1600 | | USA, WWCN Nashville TN | 7490na | 9980na |
| | | | 13845na | 15830na | |
| | | | USA, WWRB Manchester TN | 9385va | |
| 1500 | 1600 | | USA, WYFR/Family Radio Worldwide | 11855as | 11760na |
| | | | 11855as | 17760na | |
| 1500 | 1600 | | Zambia CVC Intl/ The Voice Africa | 6065af | |
| | | | 13590af | | |
| 1500 | 1600 | | Zambia, Zambia Natl Broadcasting Corp | 6165do | |
| 1505 | 1600 | DRM | Canada, Radio Canada International | 9800na | |
| 1505 | 1600 | | Canada, Radio Canada International | 9515na | |
| 1530 | 1545 | | India, All India Radio | 7255as | 9820as |
| | | | 9910as | | |
| 1530 | 1550 | smtwhf | Vatican City State, Vatican Radio | 13765as | |
| | | | 15235as | | |
| 1530 | 1600 | | Germany, AWR-Europe | 15335as | |
| 1530 | 1600 | | Iran, Voice of Islamic Rep. of Iran | 7305as | |
| | | | 9600as | 9635as | |
| 1530 | 1600 | | Mongolia, Voice of Mongolia | 9665as | |
| 1530 | 1600 | | Sweden, Radio Sweden | 13600va | |
| 1530 | 1600 | Sat | UK, BBC World Service | 7385af | 15420af |
| 1530 | 1600 | Sun | UK, Bible Voice Broadcasting | 13590me | |
| 1530 | 1600 | ha | UK, Bible Voice Broadcasting | 15680as | |
| 1530 | 1600 | | Vatican City State, Vatican Radio | 11850as | |
| 1530 | 1600 | Sat | Vatican City State, Vatican Radio | 13765as | |
| | | | 15235as | | |
| 1545 | 1600 | mw | UK, Bible Voice Broadcasting | 13590me | |
| 1545 | 1600 | thf | UK, Bible Voice Broadcasting | 13590me | |
| 1551 | 1600 | DRM | New Zealand, Radio NZ International | 6170pa | |
| 1551 | 1600 | | New Zealand, Radio NZ International | 7285pa | |

1600 UTC - 11AM EST / 10AM CST / 8AM PST

| | | | | | |
|------|------|--------|---|---------|---------|
| 1600 | 1605 | Sun | Croatia, Voice of Croatia | 6165eu | |
| 1600 | 1615 | mtwhfa | Croatia, Voice of Croatia | 6165eu | |
| 1600 | 1615 | | Pakistan, Radio Pakistan | 9385va | 11565va |
| | | | 15100as | | |
| 1600 | 1615 | | UK, Bible Voice Broadcasting | 13590me | |
| 1600 | 1627 | | Czech Republic, Radio Prague | 5930eu | 17845na |
| 1600 | 1627 | | Iran, Voice of Islamic Rep. of Iran | 7305as | |
| | | | 9600as | | |
| 1600 | 1630 | Sun | Germany, Pan American Broadcasting | 13830as | |
| 1600 | 1630 | | Guam, KSDA/ AWR | 11720as | 11805as |
| 1600 | 1630 | | Myanmar, Myanma Radio | 9730do | |
| 1600 | 1630 | | Vietnam, Voice of Vietnam | 7220va | 7280va |
| | | | 9550va | 9730va | |
| 1600 | 1630 | | Yemen, Rep of Yemen Radio/ Radio Sana'a | 9780me | |
| 1600 | 1645 | h | UK, Bible Voice Broadcasting | 13590me | |
| 1600 | 1645 | | USA, WYFR/Family Radio Worldwide | 11830na | 17760na |
| | | | 11830na | | |
| 1600 | 1657 | | North Korea, Voice of Korea | 9990va | 11545va |
| 1600 | 1700 | | Anguilla, Worldwide Univ Network | 11775am | |
| 1600 | 1700 | | Australia, ABC NT Alice Springs | 2310do | |
| 1600 | 1700 | | Australia, ABC NT Katherine | 2485do | |
| 1600 | 1700 | | Australia, CVC International | 9680as | |
| 1600 | 1700 | | Australia, Radio Australia | 5995va | 6080va |
| | | | 7240as | 9475va | 9580va |
| | | | 9710as | 11660pa | |
| 1600 | 1700 | | Bahrain, Radio Bahrain | 6010me | 9745al |
| 1600 | 1700 | Sat | Canada, CBC NQ SW Service | 9625na | |
| 1600 | 1700 | | Canada, CFRX Toronto ON | 6070na | |
| 1600 | 1700 | | Canada, CFVP Calgary AB | 6030na | |
| 1600 | 1700 | | Canada, CKZN St John's NF | 6160na | |

| | | | | | |
|------|------|--------|---|----------|----------|
| 1600 | 1700 | | Canada, CKZU Vancouver BC | 6160na | |
| 1600 | 1700 | DRM | Canada, Radio Canada International | 9800na | |
| 1600 | 1700 | | Canada, Radio Canada International | 9515na | |
| 1600 | 1700 | | China, China Radio International | 6095af | |
| | | | 6180as | 7235as | 7420af |
| | | | 9570af | 9720af | 9760as |
| | | | 11650eu | 11940eu | 11965eu |
| | | | 13760eu | | |
| 1600 | 1700 | Sat | Clandestine, Cheetah Radio | 11730as | |
| 1600 | 1700 | | Egypt, Radio Cairo | 12170af | |
| 1600 | 1700 | | Ethiopia, Radio Ethiopia/External Service | 7165af | |
| | | | 9560af | | |
| 1600 | 1700 | mtwhf | France, Radio France International | 15605af | |
| | | | 17605af | | |
| 1600 | 1700 | | Germany, CVC Intl-Christian Vision | 17770af | |
| 1600 | 1700 | | Germany, Deutsche Welle | 6170as | 9485as |
| | | | 9540as | 15640as | |
| 1600 | 1700 | | Malaysia, RTM/Traxx FM | 7295do | |
| 1600 | 1700 | DRM | New Zealand, Radio NZ International | 6170pa | |
| 1600 | 1700 | | New Zealand, Radio NZ International | 7285pa | |
| 1600 | 1700 | | Palau, T8WH/World Harvest | 9965as | |
| 1600 | 1700 | | Russia, Voice of Russia | 4975me | 11985va |
| | | | 12040af | 13855af | |
| 1600 | 1700 | | South Korea, KBS World Radio | 9515eu | |
| 1600 | 1700 | | Taiwan, Radio Taiwan International | 11550as | |
| | | | 13840as | | |
| 1600 | 1700 | | Uganda, Dunamis Shortwave | 4750af | |
| 1600 | 1700 | | Uganda, UBC Radio | 4976do | |
| 1600 | 1700 | DRM | UK, BBC World Service | 5790eu | 11810eu |
| 1600 | 1700 | | UK, BBC World Service | 3255af | 5790eu |
| 1600 | 1700 | | 5975as | 6190af | 7385af |
| | | | 9625as | 11920as | 12095eu |
| | | | 17640af | 17795af | 17830af |
| | | | 21470af | | |
| 1600 | 1700 | Sat | UK, BBC World Service | 7385af | 15420af |
| 1600 | 1700 | t | UK, Bible Voice Broadcasting | 13590me | |
| 1600 | 1700 | Sun | UK, Bible Voice Broadcasting | 13590me | |
| 1600 | 1700 | | USA, American Forces Network | 4319usb | |
| | | | 5446usb | 5765usb | 6350usb |
| | | | 7812usb | 10320usb | 12133usb |
| | | | 12759usb | 13362usb | |
| 1600 | 1700 | | USA, EWTN Vandiver AL | 15610eu | |
| 1600 | 1700 | | USA, Voice of America | 4930af | 6080af |
| | | | 9885af | 15580af | 17715af |
| 1600 | 1700 | | USA, Voice of America/Special English | 12080va | |
| | | | 13570va | 17895va | |
| 1600 | 1700 | | USA, WBOH Newport NC | 5920am | |
| 1600 | 1700 | | USA, WHRA Greenbush ME | 17520af | |
| 1600 | 1700 | | USA, WHRI Cypress Creek SC | 9840va | 11785va |
| 1600 | 1700 | | USA, WINB Red Lion PA | 13570am | |
| 1600 | 1700 | vl | USA, WRMI Miami FL | 9955na | |
| 1600 | 1700 | | USA, WTJC Newport NC | 9370na | |
| 1600 | 1700 | | USA, WWCN Nashville TN | 9980na | 12160na |
| | | | 13845na | 15830na | |
| 1600 | 1700 | | USA, WWRB Manchester TN | 9385va | |
| 1600 | 1700 | | USA, WYFR/Family Radio Worldwide | 13695na | 17690af |
| | | | 18980eu | 21455eu | |
| 1600 | 1700 | | Zambia CVC Intl/ The Voice Africa | 6065af | |
| | | | 13590af | | |
| 1600 | 1700 | | Zambia, Zambia Natl Broadcasting Corp | 6165do | |
| 1615 | 1630 | | Vatican City State, Vatican Radio | 4005eu | |
| | | | 5885eu | 7250eu | 9645eu |
| | | | 15595va | | |
| 1615 | 1700 | Sun | UK, BBC World Service | 7385af | 11860af |
| | | | 15420af | | |
| 1630 | 1657 | | Slovakia, Radio Slovakia International | 5920eu | |
| | | | 6055eu | | |
| 1630 | 1700 | | Guam, KSDA/ AWR | 6190as | |
| 1630 | 1700 | mtwhf | UK, BBC World Service | 15420af | |
| 1630 | 1700 | Sat | UK, BBC World Service | 11860af | |
| 1640 | 1650 | mtwhfa | Turkmenistan, Turkmen Radiosi | 4930eu | |
| 1645 | 1700 | | Tajikistan, Voice of Tajik | 7245as | |

1700 UTC - 12PM EST / 11AM CST / 9AM PST

| | | | | | |
|------|------|-----|--------------------------------------|---------|---------|
| 1700 | 1705 | DRM | Canada, Radio Canada International | 9800na | |
| 1700 | 1725 | | Vietnam, Voice of Vietnam | 9725eu | |
| 1700 | 1727 | | Czech Republic, Radio Prague | 5930eu | 17485eu |
| 1700 | 1730 | | Australia, CVC International | 9680as | |
| 1700 | 1730 | DRM | Romania, Radio Romania International | 7460eu | |
| 1700 | 1730 | | USA, Voice of America | 6080af | 9885af |
| | | | 11835af | 15580af | |
| 1700 | 1745 | | USA, WYFR/Family Radio Worldwide | 18980eu | |
| 1700 | 1746 | | UK, BBC World Service | 6005af | 9410af |
| 1700 | 1750 | DRM | New Zealand, Radio NZ International | 6170pa | |
| 1700 | 1750 | | New Zealand, Radio NZ International | 7285pa | |
| 1700 | 1756 | | Romania, Radio Romania International | 9535eu | |
| | | | 11735eu | | |
| 1700 | 1759 | | Poland, Polish Radio | 9790eu | |
| 1700 | 1800 | | Anguilla, Worldwide Univ Network | 11775am | |
| 1700 | 1800 | | Australia, ABC NT Alice Springs | 2310do | |

| | | | | | |
|------|------|---------|--|----------|----------|
| 1700 | 1800 | | Australia, ABC NT Katherine | 2485do | |
| 1700 | 1800 | | Australia, Radio Australia | 5995va | 6080va |
| | | | 9475as | 9580va | 11880as |
| 1700 | 1800 | | Bahrain, Radio Bahrain | 6010me | 9745al |
| 1700 | 1800 | Sat | Canada, CBC NQ SW Service | 9625na | |
| 1700 | 1800 | | Canada, CFRX Toronto ON | 6070na | |
| 1700 | 1800 | | Canada, CFVP Calgary AB | 6030na | |
| 1700 | 1800 | | Canada, CKZN St John's NF | 6160na | |
| 1700 | 1800 | | Canada, CKZU Vancouver BC | 6160na | |
| 1700 | 1800 | | Canada, Radio Canada International | 9515va | |
| 1700 | 1800 | Sat/Sun | Canada, Radio Canada International | 5850va | |
| 1700 | 1800 | | China, China Radio International | 6060as | |
| | | | 6090as | 6140as | 6145eu |
| | | | 7235as | 7265as | 7315va |
| | | | 7410as | 7420as | 9570af |
| | | | 11900af | 11940eu | 13760eu |
| 1700 | 1800 | | Egypt, Radio Cairo | 12170af | |
| 1700 | 1800 | | Equatorial Guinea, Radio Africa | 15190af | 7190af |
| 1700 | 1800 | | Germany, CVC Intl-Christian Vision | 17770af | |
| 1700 | 1800 | | Malaysia, RTM/Traxx FM | 7295do | |
| 1700 | 1800 | | Nigeria, Voice of Nigeria/External Service | 15120af | |
| 1700 | 1800 | | Palau, T8WH/World Harvest | 9965as | |
| 1700 | 1800 | DRM | Poland, Polish Radio | 7265eu | |
| 1700 | 1800 | DRM | Romania, Radio Romania International | 9535eu | |
| 1700 | 1800 | | Russia, Voice of Russia | 4975me | 11610me |
| | | | 11985af | 12040af | 12070af |
| 1700 | 1800 | | South Africa, Channel Africa | 15235af | |
| 1700 | 1800 | | Swaziland, TWR Swaziland | 3200af | |
| 1700 | 1800 | | Taiwan, Radio Taiwan International | 15690af | |
| 1700 | 1800 | | Tajikistan, Voice of Tajik | 7245as | |
| 1700 | 1800 | | Uganda, Dunamis Shortwave | 4750af | |
| 1700 | 1800 | | Uganda, UBC Radio | 4976do | |
| 1700 | 1800 | | UK, BBC World Service | 3255af | 5790eu |
| | | | 5875eu | 5975as | 6190af |
| | | | 7405af | 9625as | 9960eu |
| | | | 13675eu | 15400af | 17795af |
| 1700 | 1800 | Sat | UK, Bible Voice Broadcasting | 9430me | |
| 1700 | 1800 | Sun | UK, Bible Voice Broadcasting | 13590me | |
| 1700 | 1800 | | USA, American Forces Network | 4319usb | |
| | | | 5446usb | 5765usb | 6350usb |
| | | | 10320usb | 12133usb | 12759usb |
| 1700 | 1800 | | USA, EWTN Vandiver AL | 15610na | |
| 1700 | 1800 | Sat/Sun | USA, Voice of America | 15675af | |
| 1700 | 1800 | | USA, WBCQ Monticello ME | 15420am | |
| 1700 | 1800 | | USA, WBOH Newport NC | 5920am | |
| 1700 | 1800 | | USA, WHRA Greenbush ME | 17520af | |
| 1700 | 1800 | | USA, WHRI Cypress Creek SC | 11785va | |
| 1700 | 1800 | smtwhf | USA, WHRI Cypress Creek SC | 9840va | |
| 1700 | 1800 | Sat | USA, WHRI Cypress Creek SC | 9495va | |
| 1700 | 1800 | | USA, WINB Red Lion PA | 13570am | |
| 1700 | 1800 | vl | USA, WRMI Miami FL | 9955va | |
| 1700 | 1800 | | USA, WTJC Newport NC | 9370na | |
| 1700 | 1800 | | USA, WWCR Nashville TN | 9980na | 12160na |
| | | | 13845na | 15830na | |
| 1700 | 1800 | | USA, WWRB Manchester TN | 9385va | |
| 1700 | 1800 | | USA, WYFR/Family Radio Worldwide | 13695na | |
| | | | 17555na | 21455eu | |
| 1700 | 1800 | | Zambia CVC Intl/ The Voice Africa | 4965af | |
| | | | 13590af | | |
| 1700 | 1800 | | Zambia, Zambia Natl Broadcasting Corp | 6165do | |
| 1720 | 1740 | fas | USA, Voice of America | 4930va | 11605va |
| | | | 15775va | | |
| 1730 | 1800 | DRM | Bulgaria, Radio Bulgaria | 9400eu | |
| 1730 | 1800 | | Bulgaria, Radio Bulgaria | 5900eu | 7400eu |
| 1730 | 1800 | | Clandestine, Sudan Radio Service | 9590af | |
| 1730 | 1800 | fa | UK, Bible Voice Broadcasting | 13590me | |
| 1730 | 1800 | mtwhf | UK, Sudan Radio Service | 9840af | |
| 1730 | 1800 | | USA, Voice of America | 6080af | 9885af |
| | | | 15580af | 17895af | |
| 1730 | 1800 | mtwh | USA, Voice of America | 4930va | 11605va |
| | | | 15775va | | |
| 1730 | 1800 | | Vatican City State, Vatican Radio | 11625af | |
| | | | 13765af | 15570af | |
| 1745 | 1800 | | Bangladesh, Bangladesh Betar | 7250as | |
| 1745 | 1800 | DRM | India, All India Radio | 9950eu | |
| 1745 | 1800 | | India, All India Radio | 7410eu | 9445af |
| | | | 11620eu | 11935af | 13605as |
| | | | 17670af | | 15155af |
| 1750 | 1800 | | New Zealand, Radio NZ International | 6170pa | |
| 1751 | 1800 | DRM | New Zealand, Radio NZ International | 7285pa | |

| | | | | | |
|------|------|---------|--|----------|----------|
| 1800 | 1830 | | South Africa, AWR Africa | 3215af | 3345af |
| | | | 9610af | | |
| 1800 | 1830 | | UK, BBC World Service | 5975as | 6015as |
| | | | 9625as | | |
| 1800 | 1830 | Sat | UK, Bible Voice Broadcasting | 13590as | |
| 1800 | 1830 | | USA, Voice of America | 6080af | 9885af |
| | | | 15580af | | |
| 1800 | 1830 | Sat/Sun | USA, Voice of America | 4930af | |
| 1800 | 1845 | smtwhf | Swaziland, TWR Swaziland | 9500af | |
| 1800 | 1845 | Sat | UK, Bible Voice Broadcasting | 6130eu | |
| 1800 | 1850 | DRM | New Zealand, Radio NZ International | 7285pa | |
| 1800 | 1850 | | New Zealand, Radio NZ International | 6170pa | |
| 1800 | 1857 | | Netherlands, R Netherlands Worldwide | 6020af | |
| | | | 15535af | | |
| 1800 | 1857 | | North Korea, Voice of Korea | 13760eu | 15245eu |
| 1800 | 1900 | | Anguilla, Worldwide Univ Network | 11775am | |
| 1800 | 1900 | mtwhf | Argentina, Radio Nacional RAE | 9690eu | |
| | | | 15345eu | | |
| 1800 | 1900 | | Australia, ABC NT Alice Springs | 2310do | |
| 1800 | 1900 | | Australia, ABC NT Katherine | 2485do | |
| 1800 | 1900 | | Australia, Radio Australia | 6080va | 7240as |
| | | | 9475va | 9580as | 11880as |
| 1800 | 1900 | | Bahrain, Radio Bahrain | 6010me | 9745al |
| 1800 | 1900 | | Bangladesh, Bangladesh Betar | 7250eu | |
| 1800 | 1900 | | Canada, CFRX Toronto ON | 6070na | |
| 1800 | 1900 | | Canada, CFVP Calgary AB | 6030na | |
| 1800 | 1900 | | Canada, CKZN St John's NF | 6160na | |
| 1800 | 1900 | | Canada, CKZU Vancouver BC | 6160na | |
| 1800 | 1900 | | Canada, Radio Canada International | 9530af | |
| | | | 11765af | 17735af | 17810af |
| 1800 | 1900 | | China, China Radio International | 6030eu | |
| | | | 9600eu | 13760eu | |
| 1800 | 1900 | | Equatorial Guinea, Radio Africa | 7190af | |
| | | | 15190af | | |
| 1800 | 1900 | | Germany, CVC Intl-Christian Vision | 17770af | |
| 1800 | 1900 | DRM | India, All India Radio | 9950eu | |
| 1800 | 1900 | | India, All India Radio | 7410eu | 9445af |
| 1800 | 1900 | | India, All India Radio | 11620eu | 11935af |
| | | | 17670af | 13605as | 15155af |
| 1800 | 1900 | fas | Italy, IRRS-Shortwave | 7290va | |
| 1800 | 1900 | | Kuwait, Radio Kuwait | 11990va | |
| 1800 | 1900 | | Malaysia, RTM/Traxx FM | 7295do | |
| 1800 | 1900 | | Nigeria, Voice of Nigeria/External Service | 15120af | |
| 1800 | 1900 | | Palau, T8WH/World Harvest | 9965as | |
| 1800 | 1900 | | Russia, Voice of Russia | 4975me | 12040af |
| | | | 12070af | | |
| 1800 | 1900 | | South Korea, KBS World Radio | 7275eu | |
| 1800 | 1900 | | Swaziland, TWR Swaziland | 3200af | |
| 1800 | 1900 | Sat | Swaziland, TWR Swaziland | 9500af | |
| 1800 | 1900 | | Taiwan, Radio Taiwan International | 6155eu | |
| 1800 | 1900 | | Uganda, Dunamis Shortwave | 4750af | |
| 1800 | 1900 | | Uganda, UBC Radio | 4976do | |
| 1800 | 1900 | | UK, BBC World Service | 3255af | 5790eu |
| | | | 5875eu | 5995as | 6190af |
| | | | 9485as | 9660eu | 11810af |
| | | | 13675eu | 15400af | 17795af |
| 1800 | 1900 | | USA, American Forces Network | 4319usb | |
| | | | 5446usb | 5765usb | 6350usb |
| | | | 10320usb | 12133usb | 12759usb |
| 1800 | 1900 | | USA, EWTN Vandiver AL | 15610na | |
| 1800 | 1900 | | USA, Voice of America | 17895af | |
| 1800 | 1900 | | USA, WBCQ Monticello ME | 15420am | |
| 1800 | 1900 | | USA, WBOH Newport NC | 5920am | |
| 1800 | 1900 | | USA, WHRA Greenbush ME | 17520af | |
| 1800 | 1900 | | USA, WHRI Cypress Creek SC | 9840va | 11785va |
| 1800 | 1900 | | USA, WINB Red Lion PA | 13570am | |
| 1800 | 1900 | vl | USA, WRMI Miami FL | 9955ca | |
| 1800 | 1900 | | USA, WTJC Newport NC | 9370na | |
| 1800 | 1900 | | USA, WWCR Nashville TN | 9980na | 12160na |
| | | | 13845na | 15830na | |
| 1800 | 1900 | | USA, WWRB Manchester TN | 9385va | |
| 1800 | 1900 | | USA, WYFR/Family Radio Worldwide | 6915na | |
| | | | 13695na | 15115af | 17535na |
| 1800 | 1900 | | Yemen, Rep of Yemen Radio/ Radio Sana'a | 9780me | |
| 1800 | 1900 | | Zambia CVC Intl/ The Voice Africa | 4965af | |
| | | | 13590af | | |
| 1800 | 1900 | | Zambia, Zambia Natl Broadcasting Corp | 6165do | |
| 1805 | 1810 | Sat | Croatia, Voice of Croatia | 6165eu | |
| 1805 | 1815 | mtwhf | Croatia, Voice of Croatia | 6165eu | |
| 1810 | 1820 | f | USA, Voice of America | 4930va | 11605va |
| | | | 15775va | | |
| 1815 | 1845 | Sun | UK, Bible Voice Broadcasting | 9430me | |
| 1830 | 1845 | | Rwanda, Radio Rwanda | 6055do | |
| 1830 | 1857 | | Slovakia, Radio Slovakia International | 5920eu | |
| | | | 6055eu | | |
| 1830 | 1858 | | Serbia, International Radio of Serbia | 6100eu | |
| 1830 | 1900 | | Turkey, Voice of Turkey | 9785eu | |

1800 UTC - 1PM EST / 12PM CST / 10AM PST

| | | | | | |
|------|------|-----|----------------------------------|---------|--|
| 1800 | 1815 | Sun | UK, Bible Voice Broadcasting | 13590me | |
| 1800 | 1830 | | China, China Radio International | 6020eu | |
| | | | 7265eu | | |

| | | | | |
|------|-------------|-------------------------------------|---------|---------|
| 1830 | 1900 | UK, BBC World Service | 6005af | 9410af |
| 1830 | 1900 f | UK, Bible Voice Broadcasting | 9430me | |
| 1830 | 1900 | USA, Voice of America | 4930af | 6080af |
| | | 9885af | 15580af | 17895af |
| 1845 | 1900 mtwhfa | Albania, Radio Tirana | 7435eu | 13640na |
| 1845 | 1900 Sun | UK, Bible Voice Broadcasting | 11830af | |
| 1851 | 1900 DRM | New Zealand, Radio NZ International | | 9890pa |

1900 UTC - 2PM EST / 1PM CST / 11AM PST

| | | | | |
|------|--------------|--|----------|----------|
| 1900 | 1905 | Canada, Radio Canada International | 9515va | |
| 1900 | 1925 | Turkey, Voice of Turkey | 9785eu | |
| 1900 | 1930 | Germany, Deutsche Welle | 6150af | 11795af |
| | | 13650af | 17860af | |
| 1900 | 1930 | Vietnam, Voice of Vietnam | 7280va | 9730va |
| 1900 | 1935 DRM | New Zealand, Radio NZ International | | 9890pa |
| 1900 | 1945 DRM | India, All India Radio | 9950eu | |
| 1900 | 1945 | India, All India Radio | 7410eu | 9445af |
| | | 11620eu | 11935af | 13605as |
| | | 17670af | | |
| 1900 | 1945 | USA, WYFR/Family Radio Worldwide | 6085na | |
| | | 15565as | | |
| 1900 | 1950 | New Zealand, Radio NZ International | 9615pa | |
| 1900 | 1955 | Netherlands, R Netherlands Worldwide | 9480af | |
| | | 11660af | 15335af | |
| 1900 | 1957 | North Korea, Voice of Korea | 7100af | 9975va |
| | | 11910af | 11535va | |
| 1900 | 2000 | Anguilla, Worldwide Univ Network | 11775am | |
| 1900 | 2000 | Australia, ABC NT Alice Springs | 2310do | |
| 1900 | 2000 | Australia, ABC NT Katherine | 2485do | |
| 1900 | 2000 | Australia, Radio Australia | 6080va | 7240as |
| | | 9500va | 9580va | 9710as |
| | | | | 11880as |
| 1900 | 2000 | Bahrain, Radio Bahrain | 6010me | 9745al |
| 1900 | 2000 | Canada, CFRX Toronto ON | 6070na | |
| 1900 | 2000 | Canada, CFVP Calgary AB | 6030na | |
| 1900 | 2000 | Canada, CKZN St John's NF | 6160na | |
| 1900 | 2000 | Canada, CKZU Vancouver BC | 6160na | |
| 1900 | 2000 | China, China Radio International | 7285eu | |
| | | 7295va | 9435va | 9440va |
| 1900 | 2000 | Egypt, Radio Cairo | 11510af | |
| 1900 | 2000 | Equatorial Guinea, Radio Africa | 7190af | |
| | | 15190af | | |
| 1900 | 2000 | Germany, CVC Intl-Christian Vision | 17770af | |
| 1900 | 2000 | Germany, Overcomer Ministries | 6175eu | |
| 1900 | 2000 fas | Italy, IRRS-Shortwave | 7290va | |
| 1900 | 2000 | Kuwait, Radio Kuwait | 11990va | |
| 1900 | 2000 | Malaysia, RTM/Traxx FM | 7295do | |
| 1900 | 2000 | Nigeria, Voice of Nigeria/External Service | 15120af | |
| 1900 | 2000 | Palau, T8WH/World Harvest | 9965as | |
| 1900 | 2000 | Russia, Voice of Russia | 12040af | 12070af |
| 1900 | 2000 mtwhf | Spain, Radio Exterior de Espana | 9665eu | |
| | | 11620af | | |
| 1900 | 2000 | Swaziland, TWR Swaziland | 3200af | |
| 1900 | 2000 | Thailand, Radio Thailand World Service | 7570eu | |
| 1900 | 2000 | Uganda, UBC Radio | 4976do | |
| 1900 | 2000 | UK, BBC World Service | 3255af | 3995eu |
| | | 5875eu | 5995as | 6005af |
| | | 6190af | 9410af | 11810af |
| | | 15400af | 17795af | 12095af |
| 1900 | 2000 Sun | UK, Bible Voice Broadcasting | 11830af | |
| 1900 | 2000 | Ukraine, Radio Ukraine International | 7490eu | |
| 1900 | 2000 | USA, American Forces Network | 4319usb | |
| | | 5446usb | 5765usb | 6350usb |
| | | 10320usb | 12133usb | 12759usb |
| 1900 | 2000 | USA, EWTN Vandiver AL | 15610na | |
| 1900 | 2000 | USA, Voice of America | 4930af | 4940af |
| | | 6120af | 9885af | 15580af |
| 1900 | 2000 | USA, Voice of America/Special English | 7480va | |
| | | 9780va | | |
| 1900 | 2000 smtwhf | USA, WBCQ Monticello ME | 7415am | |
| 1900 | 2000 | USA, WBOH Newport NC | 5920am | |
| 1900 | 2000 twhf | USA, WHRA Greenbush ME | 9840af | |
| 1900 | 2000 | USA, WHRI Cypress Creek SC | 11785va | |
| 1900 | 2000 | USA, WINB Red Lion PA | 13570am | |
| 1900 | 2000 vl | USA, WRMI Miami FL | 9955ca | |
| 1900 | 2000 | USA, WTJC Newport NC | 9370na | |
| 1900 | 2000 | USA, WWCR Nashville TN | 9980na | 12160na |
| | | 13845na | 15830na | |
| 1900 | 2000 | USA, WWRB Manchester TN | 9385va | |
| 1900 | 2000 | USA, WYFR/Family Radio Worldwide | 6915na | |
| | | 13695na | 15115af | 17535na |
| | | | | 17555na |
| 1900 | 2000 | Zambia CVC Intl/ The Voice Africa | 4965af | |
| | | 5940af | | |
| 1900 | 2000 | Zambia, Zambia Natl Broadcasting Corp | 6165do | |
| 1905 | 1920 Sat | Mali, RDTV Du Mali | 5995do | |
| 1905 | 2000 Mon | South Africa, SA Radio League | 3215af | |
| 1930 | 2000 Sat/Sun | Germany, Pan American Broadcasting | 9515af | |

| | | | | |
|------|------------|-------------------------------------|---------|---------|
| 1930 | 2000 | Iran, Voice of Islamic Rep. of Iran | 5940eu | |
| | | 6205eu | 7205eu | 9800af |
| 1930 | 2000 | South Africa, RTE Radio One | 6225af | |
| 1936 | 1950 DRM | New Zealand, Radio NZ International | | 9890pa |
| 1945 | 2000 mtwhf | UK, Bible Voice Broadcasting | 11830af | |
| 1945 | 2000 DRM | Vatican City State, Vatican Radio | | 9800na |
| 1950 | 2000 | New Zealand, Radio NZ International | | 11725pa |
| 1950 | 2000 | Vatican City State, Vatican Radio | 4005eu | |
| | | 5885eu | 7250eu | 9645eu |
| 1951 | 2000 DRM | New Zealand, Radio NZ International | | 9890pa |

2000 UTC - 3PM EST / 2PM CST / 12PM PST

| | | | | |
|------|--------------|--|----------|----------|
| 2000 | 2005 Mon | South Africa, SA Radio League | 3215af | |
| 2000 | 2015 Sat/Sun | Germany, Pan American Broadcasting | 9515af | |
| 2000 | 2015 mtwhf | UK, Bible Voice Broadcasting | 11830af | |
| 2000 | 2020 | Vatican City State, Vatican Radio | 4005eu | |
| | | 5885eu | 7250eu | 9645eu |
| 2000 | 2027 | Czech Republic, Radio Prague | 5930eu | 11600na |
| 2000 | 2028 | Iran, Voice of Islamic Rep. of Iran | 5940eu | |
| | | 6205eu | 7205eu | 9800af |
| | | | | 9925af |
| 2000 | 2030 mtwhfa | Albania, Radio Tirana | 7465eu | 13640na |
| 2000 | 2030 | Egypt, Radio Cairo | 11510af | |
| 2000 | 2030 Sat | Germany, Pan American Broadcasting | 9515af | |
| 2000 | 2030 | South Africa, RTE Radio One | 6225af | |
| 2000 | 2030 | Swaziland, TWR Swaziland | 3200af | |
| 2000 | 2030 | USA, Voice of America | 4930af | 4940af |
| | | 6080af | 9885af | 15580af |
| | | | | 17895af |
| 2000 | 2030 DRM | Vatican City State, Vatican Radio | 9800na | |
| 2000 | 2030 | Vatican City State, Vatican Radio | 7365af | |
| | | 9755af | 11625af | |
| 2000 | 2045 | USA, WYFR/Family Radio Worldwide | 5745eu | |
| 2000 | 2050 DRM | New Zealand, Radio NZ International | 9890pa | |
| 2000 | 2050 | New Zealand, Radio NZ International | 11725pa | |
| 2000 | 2057 | Netherlands, R Netherlands Worldwide | 5905af | |
| | | 7425af | 11610af | |
| 2000 | 2100 | Anguilla, Worldwide Univ Network | 11775am | |
| 2000 | 2100 | Australia, ABC NT Alice Springs | 2310do | |
| 2000 | 2100 | Australia, ABC NT Katherine | 2485do | |
| 2000 | 2100 | Australia, ABC NT Tennant Creek | 2325do | |
| 2000 | 2100 Sat/Sun | Australia, Radio Australia | 6080va | 7240va |
| | | 12080as | | |
| 2000 | 2100 | Australia, Radio Australia | 9500va | 11650as |
| | | 11660pa | 11880as | |
| 2000 | 2100 | Bahrain, Radio Bahrain | 6010me | 9745al |
| 2000 | 2100 | Belarus, Radio Belarus | 7210eu | 7255as |
| | | 7390eu | | |
| 2000 | 2100 | Canada, CFRX Toronto ON | 6070na | |
| 2000 | 2100 | Canada, CFVP Calgary AB | 6030na | |
| 2000 | 2100 | Canada, CKZN St John's NF | 6160na | |
| 2000 | 2100 | Canada, CKZU Vancouver BC | 6160na | |
| 2000 | 2100 | Canada, Radio Canada International | 15235va | |
| | | 17735va | | |
| 2000 | 2100 | China, China Radio International | 5960eu | |
| | | 5985af | 7275va | 7285eu |
| | | 9600eu | 11640af | 13630af |
| 2000 | 2100 | Equatorial Guinea, Radio Africa | 7190af | |
| | | 15190af | | |
| 2000 | 2100 | Germany, CVC Intl-Christian Vision | 17770af | |
| 2000 | 2100 | Germany, Deutsche Welle | 6150af | 11795af |
| | | 11865af | 13650af | |
| 2000 | 2100 | Indonesia, Voice of Indonesia | 9525va | 11785al |
| 2000 | 2100 | Kuwait, Radio Kuwait | 11990va | |
| 2000 | 2100 | Malaysia, RTM/Traxx FM | 7295do | |
| 2000 | 2100 | Nigeria, Voice of Nigeria/External Service | 15120af | |
| 2000 | 2100 | Palau, T8WH/World Harvest | 9965as | |
| 2000 | 2100 | Russia, Voice of Russia | 12040af | 12070af |
| 2000 | 2100 | Uganda, UBC Radio | 4976do | |
| 2000 | 2100 DRM | UK, BBC World Service | 3995eu | 5875eu |
| 2000 | 2100 | UK, BBC World Service | 3255af | 3995eu |
| | | 5875eu | 6005af | 6190af |
| | | 11810af | 12095af | 13820af |
| | | | | 15400af |
| 2000 | 2100 | USA, American Forces Network | 4319usb | |
| | | 5446usb | 5765usb | 6350usb |
| | | 10320usb | 12133usb | 12759usb |
| | | | | 13362usb |
| 2000 | 2100 | USA, EWTN Vandiver AL | 15610me | |
| 2000 | 2100 | USA, WBCQ Monticello ME | 7415am | |
| 2000 | 2100 | USA, WBOH Newport NC | 5920am | |
| 2000 | 2100 | USA, WHRA Greenbush ME | 15665af | |
| 2000 | 2100 mtwhf | USA, WHRI Cypress Creek SC | 7520va | |
| 2000 | 2100 Sun | USA, WHRI Cypress Creek SC | 9495va | |
| 2000 | 2100 | USA, WHRI Cypress Creek SC | 11785va | 15665na |
| 2000 | 2100 | USA, WINB Red Lion PA | 13570am | |
| 2000 | 2100 vl | USA, WRMI Miami FL | 9955ca | |
| 2000 | 2100 | USA, WTJC Newport NC | 9370na | |
| 2000 | 2100 | USA, WWCR Nashville TN | 9980na | 12160na |
| | | 13845na | 15830na | |

| | | | | |
|------|------|---|---------|---------|
| 2000 | 2100 | USA, WWRB Manchester TN | 9385va | |
| 2000 | 2100 | USA, WYFR/Family Radio Worldwide | 6915na | |
| | | 15115af | 17535na | 17555na |
| 2000 | 2100 | Zambia CVC Intl/ The Voice Africa | 4965af | |
| | | 5940af | | |
| 2000 | 2100 | Zambia, Zambia Natl Broadcasting Corp | 6165do | |
| 2000 | 2105 | Uganda, UBC Radio | 4976do | |
| 2030 | 2045 | Thailand, Radio Thailand World Service | 9680eu | |
| 2030 | 2056 | Romania, Radio Romania International | 9690na | |
| | | 9765eu | 11810eu | 11940af |
| 2030 | 2100 | Cuba, Radio Havana Cuba | 11760va | 17660va |
| 2030 | 2100 | Sweden, Radio Sweden | 7395va | |
| 2030 | 2100 | Turkey, Voice of Turkey | 7205va | |
| 2030 | 2100 | USA, Voice of America | 4930af | 6080af |
| | | 7555va | 9885af | 15580af |
| | | | | 17895af |
| 2030 | 2100 | Vietnam, Voice of Vietnam | 7220va | 7280va |
| | | 9550va | 9730va | |
| 2045 | 2100 | India, All India Radio | 7410eu | 9445eu |
| | | 9910pa | 9950eu | 11620va |
| | | | | 11715pa |
| 2051 | 2100 | New Zealand, Radio NZ International | 13730pa | |
| 2051 | 2200 | DRM New Zealand, Radio NZ International | 15720pa | |

2100 UTC - 4PM EST / 3PM CST / 1PM PST

| | | | | |
|------|------|---|----------|----------|
| 2100 | 2125 | Turkey, Voice of Turkey | 7205va | |
| 2100 | 2128 | Serbia, International Radio of Serbia | 6100eu | |
| 2100 | 2130 | Australia, ABC NT Alice Springs | 2310do | |
| 2100 | 2130 | Australia, ABC NT Alice Springs | 2310do | |
| 2100 | 2130 | Australia, ABC NT Katherine | 2485do | |
| 2100 | 2130 | Australia, ABC NT Tennant Creek | 2325do | |
| 2100 | 2130 | Sat Canada, CBC NQ SW Service | 9625na | |
| 2100 | 2130 | China, China Radio International | 6135eu | |
| | | 7225eu | 7415eu | 9490eu |
| | | 11640af | 13630af | |
| 2100 | 2130 | Cuba, Radio Havana Cuba | 17600va | 17660va |
| 2100 | 2130 | Germany, TWR Europe | 11955af | |
| 2100 | 2130 | South Korea, KBS World Radio | 3955eu | |
| 2100 | 2145 | USA, WYFR/Family Radio Worldwide | 6915na | |
| | | 15115af | 17535na | 17555na |
| 2100 | 2157 | North Korea, Voice of Korea | 13760eu | 15245eu |
| 2100 | 2200 | Angola, Radio Nacional de Angola | 7217do | |
| 2100 | 2200 | Anguilla, Worldwide Univ Network | 11775am | |
| 2100 | 2200 | Australia, Radio Australia | 9500as | 9660as |
| | | 11650pa | 11660pa | 11695as |
| | | | | 12080as |
| | | | | 15515as |
| 2100 | 2200 | Bahrain, Radio Bahrain | 6010me | 9745al |
| 2100 | 2200 | Belarus, Radio Belarus | 7210eu | 7255as |
| | | 7390eu | | |
| 2100 | 2200 | Bulgaria, Radio Bulgaria | 5900eu | 7400eu |
| 2100 | 2200 | Canada, CFRX Toronto ON | 6070na | |
| 2100 | 2200 | Canada, CFVP Calgary AB | 6030na | |
| 2100 | 2200 | Canada, CKZN St John's NF | 6160na | |
| 2100 | 2200 | Canada, CKZU Vancouver BC | 6160na | |
| 2100 | 2200 | DRM Canada, Radio Canada International | 9800na | |
| 2100 | 2200 | China, China Radio International | 5990eu | |
| | | 7205af | 7285eu | 7325af |
| 2100 | 2200 | Equatorial Guinea, Radio Africa | 7190af | |
| | | 15190af | | |
| 2100 | 2200 | Germany, Deutsche Welle | 9735af | 11865af |
| | | 15205af | | |
| 2100 | 2200 | Germany, Overcomer Ministries | 6175eu | |
| 2100 | 2200 | India, All India Radio | 7410eu | 9445eu |
| | | 9910pa | 9950eu | 11620va |
| | | | | 11715pa |
| 2100 | 2200 | Malaysia, RTM/Traxx FM | 7295do | |
| 2100 | 2200 | New Zealand, Radio NZ International | 13730pa | |
| 2100 | 2200 | Palau, T8WH/World Harvest | 9965as | |
| 2100 | 2200 | Russia, Voice of Russia | 12040af | 12070af |
| 2100 | 2200 | Sat/Sun Spain, Radio Exterior de Espana | 9650eu | |
| 2100 | 2200 | Syria, Radio Damascus | 9330eu | 12085as |
| 2100 | 2200 | DRM UK, BBC World Service | 3995eu | 5790eu |
| 2100 | 2200 | UK, BBC World Service | 3255af | 3915as |
| | | 5790eu | 5905as | 5965as |
| | | 6190af | 6195as | 7410af |
| | | | | 9915af |
| | | | | 12095af |
| 2100 | 2200 | Ukraine, Radio Ukraine International | 5840eu | |
| 2100 | 2200 | USA, American Forces Network | 4319usb | |
| | | 5446usb | 5765usb | 6350usb |
| | | 10320usb | 12133usb | 12759usb |
| | | | | 13362usb |
| 2100 | 2200 | USA, EWTN Vandiver AL | 15610me | |
| 2100 | 2200 | USA, Voice of America | 6080af | 7555va |
| | | 15580af | | |
| 2100 | 2200 | USA, WBCQ Monticello ME | 7415am | |
| 2100 | 2200 | USA, WBOH Newport NC | 5920am | |
| 2100 | 2200 | USA, WHRA Greenbush ME | 15665af | |
| 2100 | 2200 | USA, WHRI Cypress Creek SC | 11785va | 11885na |
| 2100 | 2200 | mtwhfa USA, WHRI Cypress Creek SC | 15665na | |
| 2100 | 2200 | Sun USA, WHRI Cypress Creek SC | 9690na | |

| | | | | |
|------|------|---------------------------------------|---------|---------|
| 2100 | 2200 | USA, WINB Red Lion PA | 9265am | |
| 2100 | 2200 | USA, WRMI Miami FL | 9955ca | |
| 2100 | 2200 | USA, WTJC Newport NC | 9370na | |
| 2100 | 2200 | USA, WWCN Nashville TN | 7465na | 9980na |
| | | 12160na | 15830na | |
| 2100 | 2200 | USA, WWRB Manchester TN | 9385va | |
| 2100 | 2200 | USA, WYFR/Family Radio Worldwide | 5950na | |
| 2100 | 2200 | Zambia CVC Intl/ The Voice Africa | 4965af | |
| | | 5940af | | |
| 2100 | 2200 | Zambia, Zambia Natl Broadcasting Corp | 6165do | |
| 2115 | 2200 | Egypt, Radio Cairo | 6255eu | |
| 2130 | 2157 | Czech Republic, Radio Prague | 9410na | 11600na |
| 2130 | 2200 | Australia, ABC NT Alice Springs | 4835do | |
| 2130 | 2200 | Australia, ABC NT Katherine | 5025do | |
| 2130 | 2200 | mtwhfa Canada, CBC NQ SW Service | 9625na | |
| 2130 | 2200 | China, China Radio International | 6135eu | |
| | | 7225eu | 7325eu | 7365eu |
| | | | | 7415eu |
| | | | | 9600eu |
| 2130 | 2200 | Guam, KSDA/ AWR | 11850as | |
| 2130 | 2200 | Sweden, Radio Sweden | 7395va | |
| 2130 | 2228 | Lithuania, Mighty KBC Radio | 6055eu | |

2200 UTC - 5PM EST / 4PM CST / 2PM PST

| | | | | |
|------|------|---|----------|----------|
| 2200 | 2205 | Zambia, Zambia Natl Broadcasting Corp | 6165do | |
| 2200 | 2220 | Japan, NHK World/ Radio Japan | 13640pa | |
| 2200 | 2230 | Australia, HCJB Global | 15525as | |
| 2200 | 2230 | India, All India Radio | 7410eu | 9445eu |
| | | 9910pa | 9950eu | 11620va |
| | | | | 11715pa |
| 2200 | 2235 | DRM New Zealand, Radio NZ International | 15720pa | |
| 2200 | 2235 | New Zealand, Radio NZ International | 13730pa | |
| 2200 | 2245 | Egypt, Radio Cairo | 6255eu | |
| 2200 | 2245 | USA, WYFR/Family Radio Worldwide | 17690af | |
| 2200 | 2255 | Turkey, Voice of Turkey | 9830va | |
| 2200 | 2256 | Romania, Radio Romania International | 7440eu | |
| | | 9675eu | 9790af | 11940af |
| 2200 | 2300 | Anguilla, Worldwide Univ Network | 6090am | |
| 2200 | 2300 | Australia, ABC NT Alice Springs | 4835do | |
| 2200 | 2300 | Australia, ABC NT Katherine | 5025do | |
| 2200 | 2300 | Australia, Radio Australia | 12010va | 13630pa |
| | | 15230va | 15240pa | 15515as |
| | | | | 15560pa |
| | | | | 17795va |
| 2200 | 2300 | Bahrain, Radio Bahrain | 6010me | 9745al |
| 2200 | 2300 | smtwhf Canada, CBC NQ SW Service | 9625na | |
| 2200 | 2300 | Canada, CFRX Toronto ON | 6070na | |
| 2200 | 2300 | Canada, CFVP Calgary AB | 6030na | |
| 2200 | 2300 | Canada, CKZN St John's NF | 6160na | |
| 2200 | 2300 | Canada, CKZU Vancouver BC | 6160na | |
| 2200 | 2300 | China, China Radio International | 7240as | |
| | | 7350eu | 7360eu | 9590as |
| 2200 | 2300 | Equatorial Guinea, Radio Africa | 7190af | |
| | | 15190af | | |
| 2200 | 2300 | Malaysia, RTM/Traxx FM | 7295do | |
| 2200 | 2300 | Palau, T8WH/World Harvest | 9965as | |
| 2200 | 2300 | Russia, Voice of Russia | 9890na | 12040af |
| | | 12070af | | |
| 2200 | 2300 | UK, BBC World Service | 3915as | 5905as |
| | | 5965as | 6005af | 6195as |
| | | 9740as | 9915af | 12095af |
| 2200 | 2300 | USA, American Forces Network | 4319usb | |
| | | 5446usb | 5765usb | 6350usb |
| | | 10320usb | 12133usb | 12759usb |
| | | | | 13362usb |
| 2200 | 2300 | USA, EWTN Vandiver AL | 15610me | |
| 2200 | 2300 | USA, Voice of America | 5895va | 5915va |
| | | 7480va | 7555va | 9415va |
| | | | | 11955va |
| 2200 | 2300 | USA, WBCQ Monticello ME | 5110am | 7415am |
| 2200 | 2300 | USA, WBOH Newport NC | 5920am | |
| 2200 | 2300 | USA, WHRA Greenbush ME | 11885af | |
| 2200 | 2300 | USA, WHRI Cypress Creek SC | 11785va | 11885na |
| 2200 | 2300 | USA, WINB Red Lion PA | 9265am | |
| 2200 | 2300 | USA, WRMI Miami FL | 9955ca | |
| 2200 | 2300 | USA, WTJC Newport NC | 9370na | |
| 2200 | 2300 | USA, WWCN Nashville TN | 7465na | 9980na |
| | | 12160na | 13845na | |
| 2200 | 2300 | USA, WWRB Manchester TN | 5050va | 6890va |
| | | 9385va | | |
| 2200 | 2300 | USA, WYFR/Family Radio Worldwide | 5950na | |
| | | 11740na | 15440na | |
| 2200 | 2300 | Zambia CVC Intl/ The Voice Africa | 4965af | |
| 2215 | 2230 | mtwhs Moldova, (Transnistria) Radio PMR | 9665na | |
| 2230 | 2257 | Czech Republic, Radio Prague | 7345na | 9415na |
| 2230 | 2300 | Guam, KSDA/ AWR | 15320as | |
| 2230 | 2300 | USA, Voice of America/Special English | 9570va | |
| | | 11705va | 15145va | |
| 2236 | 2300 | DRM New Zealand, Radio NZ International | 13730pa | |
| 2245 | 2300 | India, All India Radio | 9705eu | 9950as |
| | | 11620as | 11645as | 13605as |

2300 UTC - 6PM EST / 5PM CST / 3PM PST

| | | | |
|-----------|-------------------------------------|---------|---------|
| 2300 0000 | Anguilla, Worldwide Univ Network | 6090am | |
| 2300 0000 | Australia, ABC NT Alice Springs | 4835do | |
| 2300 0000 | Australia, ABC NT Katherine | 5025do | |
| 2300 0000 | Bahrain, Radio Bahrain | 6010me | 9745al |
| 2300 0000 | Belgium, TDP Radio | 9790na | |
| 2300 0000 | Bulgaria, Radio Bulgaria | 9700na | 11700na |
| 2300 0000 | Canada, CBC NQ SW Service | 9625na | |
| 2300 0000 | Canada, CFRX Toronto ON | 6070na | |
| 2300 0000 | Canada, CFVP Calgary AB | 6030na | |
| 2300 0000 | Canada, CKZN St John's NF | 6160na | |
| 2300 0000 | Canada, CKZU Vancouver BC | 6160na | |
| 2300 0000 | China, China Radio International | 5915as | |
| | 5990na | 6145na | 7410na |
| | 11690as | 11790as | 11840na |
| 2300 0000 | Cuba, Radio Havana Cuba | 13790sa | |
| 2300 0000 | Egypt, Radio Cairo | 11590na | |
| 2300 0000 | India, All India Radio | 9705eu | 9950as |
| | 11620as | 11645as | 13605as |
| 2300 0000 | Malaysia, RTM/Traxx FM | 7295do | |
| 2300 0000 | New Zealand, Radio NZ International | 13730pa | |
| 2300 0000 | New Zealand, Radio NZ International | 15720pa | |
| 2300 0000 | Russia, Voice of Russia | 9665sa | 9890na |
| 2300 0000 | UK, BBC World Service | 3915as | 5965as |
| | 6195as | 9580as | 9740as |
| | 11850as | 12010as | |
| 2300 0000 | USA, American Forces Network | 4319usb | |
| | 5446va | 5765va | 6350va |
| | 10320va | 12133va | 12759va |
| | | | 13362va |
| 2300 0000 | USA, EWTN Vandiver AL | 15610me | |
| 2300 0000 | USA, Voice of America | 5895va | 5915va |
| | 7480va | 9415va | 11955va |
| 2300 0000 | USA, WBCQ Monticello ME | 5110am | 7415am |

| | | | |
|-----------|--|---------|---------|
| 2300 0000 | USA, WBOH Newport NC | 5920am | |
| 2300 0000 | USA, WHRA Greenbush ME | 9615eu | |
| 2300 0000 | USA, WHRI Cypress Creek SC | 5875na | 7315va |
| | 11785va | | |
| 2300 0000 | USA, WINB Red Lion PA | 9265am | |
| 2300 0000 | USA, WRMI Miami FL | 9955ca | |
| 2300 0000 | USA, WTJC Newport NC | 9370na | |
| 2300 0000 | USA, WWCR Nashville TN | 5070na | 7465na |
| | 9980na | 13845na | |
| 2300 0000 | USA, WWRB Manchester TN | 5050va | 6890va |
| | 9385va | | |
| 2300 0000 | USA, WYFR/Family Radio Worldwide | 9430sa | |
| | 15400sa | 15440na | |
| 2300 0000 | Zambia CVC Intl/ The Voice Africa | 4965af | |
| 2300 2330 | Australia, Radio Australia | 9660as | 12010pa |
| | 12080pa | 13690pa | 15230va |
| | 15560va | 17795va | 15240pa |
| 2300 2330 | Palau, T8WH/World Harvest | 15550as | |
| 2300 2330 | USA, Voice of America/Special English | 9570va | |
| | 13755va | 15145va | |
| 2300 2330 | Venezuela, Radio Nacional de Venezuela | 13680ca | |
| | 15250ca | | |
| 2300 2345 | USA, WYFR/Family Radio Worldwide | 11740na | |
| 2300 2345 | Vatican City State, Vatican Radio | 9755na | |
| 2305 0000 | Canada, Radio Canada International | 6100am | |
| 2305 0000 | Greece, Voice of Greece | 7475va | 9420va |
| 2315 2330 | Croatia, Voice of Croatia | 3985eu | 7375sa |
| 2330 0000 | Australia, Radio Australia | 9660as | 12010as |
| | 12080as | 13690as | 15230va |
| | 15560va | 17750va | 17795va |
| 2330 0000 | USA, Voice of America/Special English | 7460va | |
| | 9570va | 13755va | 15145va |
| 2330 2358 | Vietnam, Voice of Vietnam | 9840as | 12020as |

MT SHORTWAVE STATION RESOURCE GUIDE

| | |
|---|--|
| Albania, Radio Tirana | http://rtsh.sil.at/ |
| Angola, Radio Nacional de Angola | www.rna.ao/ |
| Anguilla, Worldwide Univ Network | www.worldwideuniversitynetwork.com/ |
| Argentina, Radio Nacional RAE | www.radionacional.com.ar/ |
| Australia, ABC NT Alice Springs | www.abc.net.au/radio/ |
| Australia, ABC NT Katherine | www.abc.net.au/radio/ |
| Australia, ABC NT Tennant Creek | www.abc.net.au/radio/ |
| Australia, CVC International | www.christianvision.com/ |
| Australia, HCJB Global | www.hcjb.org/ |
| Australia, Radio Australia | www.abc.net.au/ra/ |
| Austria, ORF/Radio Austria Intl | http://oe1.orf.at/service/international |
| Bahrain, Radio Bahrain | www.radiobahrain.net |
| Bangladesh, Bangladesh Betar | www.betar.org.bd/ |
| Belarus, Radio Belarus | www.radiobelarus.tvr.by/eng/ |
| Belgium, TDP Radio | www.airtime.be/schedule.html |
| Bhutan, Bhutan Broadcasting Service | www.bbs.com.bt/ |
| Bulgaria, Radio Bulgaria | www.bnr.bg/ |
| Canada, CBC NQ SW Service | www.cbc.ca/north/ |
| Canada, CFRX Toronto ON | www.cfrb.com |
| Canada, CFVP Calgary AB | www.classiccountriam1060.com |
| Canada, CKZN St John's NF | www.cbc.ca/listen/index.html |
| Canada, CKZU Vancouver BC | www.cbc.ca/bc |
| Canada, Radio Canada International | www.rcinet.ca/ |
| China, China Radio International | www.cri.cn/ |
| China, CPBS/CNR Business Radio | www.rcinet.ca/ |
| China, Guangxi FBS/Beibu Bay Radio | www.gxradio.com/index/index.asp |
| China, Voice of the Strait | www.vos.com.cn |
| Clandestine, Cotton Tree News | www.cottontreenews.org/ |
| Clandestine, Shiokeze/Sea Breeze | www.chosa-kai.jp |
| Clandestine, Sudan Radio Service | www.sudanradio.org |
| Croatia, Voice of Croatia | www.hrt.hr/ |
| Cuba, Radio Havana Cuba | www.radiohc.cu/ |
| Czech Republic, Radio Prague | www.radio.cz/ |
| Egypt, Radio Cairo | www.sis.gov.eg/ |
| Ethiopia, Radio Ethiopia/External Service | www.angelfire.com/biz/radioethiopia/ |
| France, Radio France International | http://rfienglish.com |
| Germany, AWR-Europe | www.awr2.org/ |
| Germany, CVC Intl-Christian Vision | www.christianvision.com/ |
| Germany, Deutsche Welle | www.dw-world.de/ |
| Germany, European Music Radio | www.emr.org.uk/ |
| Germany, Overcomer Ministries | www.overcomerministry.org/ |
| Germany, Pan American Broadcasting | www.radiopanam.com/ |
| Germany, TWR Europe | www.twr.org |
| Greece, Voice of Greece | www.voiceofgreece.gr/ |
| Guam, KSDA/ AWR | www.awr2.org/ |
| Guam, KTWR/TWR | www.twr.org/ |
| India, All India Radio | www.allindiaradio.org/ |
| Indonesia, Voice of Indonesia | www.voi.co.id |
| Iran, Voice of Islamic Rep. of Iran | www.irib.ir/English/ |
| Italy, IRRS-Shortwave | www.nexus.org |
| Japan, NHK World/ Radio Japan | www.nhk.or.jp/english/ |
| Kuwait, Radio Kuwait | www.media.gov.kw/ |
| Laos, Lao National Radio | www.lnr.org.la |
| Latvia, Radio SWH | www.radioswh.lv/index.php |
| Libya, LJB/Voice of Africa | www.voiceofafrica.com.ly |
| Lithuania, Mighty KBC Radio | www.kbcradio.eu |
| Malaysia, RTM/Traxx FM | www.traxx.net/index.php |
| Malaysia, RTM/Voice of Malaysia | www.rtm.gov.my |

| | |
|--|--|
| Mali, RDTV Du Mali | www.ortm.ml |
| Monaco, TWR Europe | www.twr.org/ |
| Nepal, Radio Nepal | www.radionepal.org/ |
| Netherlands, R Netherlands Worldwide | www.radionetherlands.nl/ |
| New Zealand, Radio NZ International | www.rnzi.com |
| Nigeria, Voice of Nigeria/External Service | www.voiceofnigeria.org |
| Oman, Radio Oman | www.oman-tv.gov.om |
| Pakistan, Radio Pakistan | www.radio.gov.pk |
| Palau, T8WH/World Harvest | www.whr.org/ |
| Philippines, PBS/ Radyo Pilipinas | www.pbs.gov.ph/ |
| Poland, Polish Radio | www.polskieradio.pl |
| Romania, Radio Romania International | www.rri.ro/ |
| Russia, Voice of Russia | www.ruvr.ru/ |
| Rwanda, Radio Rwanda | www.orinfor.gov.rw/ |
| Saudi Arabia, BSKSA/External Service | www.saudiaradio.net/ |
| Slovakia, Radio Slovakia International | www.rsi.sk |
| South Africa, RTE Radio One | www.rte.ie/radio1/ |
| South Africa, AWR Africa | www.awr2.org/ |
| South Africa, Channel Africa | www.channelafrica.org |
| South Africa, SA Radio League | www.channelafrica.org |
| South Africa, Trans World Radio | www.twr.org/ |
| South Korea, KBS World Radio | http://rki.kbs.co.kr/english/ |
| Spain, Radio Exterior de Espana | www.ree.rne.es/ |
| Sri Lanka, SLBC | www.slbc.lk |
| Swaziland, TWR Swaziland | www.twr.org.za |
| Sweden, Radio Sweden | www.sr.se/rs/english/ |
| Syria, Radio Damascus | www.rtv.gov.sy/ |
| Taiwan, Radio Taiwan International | http://english.riti.org.tw/ |
| Thailand, Radio Thailand World Service | www.hsk9.com/ |
| Turkey, Voice of Turkey | www.trt.net.tr |
| Uganda, Dunamis Shortwave | www.biblevoice.org/stations/east-africa |
| UK, BBC World Service | www.bbc.co.uk/worldservice/ |
| UK, Bible Voice Broadcasting | www.biblevoice.org/ |
| UK, Sudan Radio Service | www.sudanradio.org/ |
| Ukraine, Radio Ukraine International | www.nrcu.gov.ua/ |
| United Arab Emirates, FEBA Radio | www.febanad.info |
| USA, American Forces Network | http://myafn.dodmedia.osd.mil/ |
| USA, Eternal Good News | www.oldpaths.net/ |
| USA, EWTN Vandiver AL | www.ewtn.com |
| USA, KNLS Anchor Point AK | www.knls.org/ |
| USA, Voice of America | www.voanews.com/ |
| USA, Voice of America/Special English | www.voanews.com/ |
| USA, WBCQ Monticello ME | www.wbcq.com/ |
| USA, WBOH Newport NC | www.fbnradio.com/ |
| USA, WHRA Greenbush ME | www.whr.org/ |
| USA, WHRI Cypress Creek SC | www.whr.org/ |
| USA, WINB Red Lion PA | www.winb.com/ |
| USA, WRMI Miami FL | www.wrmi.net/ |
| USA, WRNO New Orleans LA | www.wrnworldwide.org/ |
| USA, WTJC Newport NC | www.fbnradio.com/ |
| USA, WWCR Nashville TN | www.wwcr.com |
| USA, WWRB Manchester TN | www.wwrb.org/ |
| USA, WYFR/Family Radio Worldwide | www.worldwide.familyradio.org |
| Uzbekistan, CVC Intl/ The Voice Asia | www.christianvision.com/ |
| Vatican City State, Vatican Radio | www.vaticanradio.org |
| Vietnam, Voice of Vietnam | www.vov.org.vn |
| Yemen, Rep of Yemen Radio/ Radio Sana'a | |
| Zambia CVC Intl/ The Voice Africa | www.christianvision.com/ |
| Zambia, Zambia Natl Broadcasting Corp | www.znbc.co.zm |

SHORTWAVE GUIDE



MTXTRA

Shortwave Broadcast Guide

SPANISH

The following language schedule is extracted from our new MTXtra Shortwave Broadcast Guide pdf which is a free download to all MTXpress subscribers. The online SW Guide combines more than 9,100 entries including all languages, sorted by time and updated monthly.

0000 UTC - 7PM EST / 6PM CST / 4PM PST

| | | | | | |
|------|------|-------|--------------------------------------|---------|---------|
| 0000 | 0005 | | Austria, ORF/Radio Austria Intl | 9820ca | |
| 0000 | 0010 | mtwhf | Spain, Radio Exterior de Espana | | 17595sa |
| 0000 | 0027 | | Czech Republic, Radio Prague | 7275sa | |
| 0000 | 0100 | | Bolivia, Radio Eco | 4409do | |
| 0000 | 0100 | | Bolivia, Radio Estambul | 4498do | |
| 0000 | 0100 | | Bolivia, Radio Nacional de Huanuni | | 5967do |
| 0000 | 0100 | | Bolivia, Radio San Jose | 5580do | |
| 0000 | 0100 | | Bolivia, Radio San Miguel | 4699do | |
| 0000 | 0100 | | Bolivia, Radio Tacana | 4781do | |
| 0000 | 0100 | | Bolivia, Radio Virgen de Remedios | | 4834do |
| 0000 | 0100 | | Bolivia, Radio Yura | 4716do | |
| 0000 | 0100 | | Canada, Radio Canada International | | 11990sa |
| | | | 13725ca | | |
| 0000 | 0100 | | Chile, La Voz Crista | 9745sa | 11665sa |
| 0000 | 0100 | | China, China Radio International | | 5990ca |
| | | | 15120sa | | |
| 0000 | 0100 | | Clandestine, Radio Republica | 9545ca | |
| 0000 | 0100 | | Colombia, La Voz de tu Conciencia | | 6010do |
| | | | 5910al | | |
| 0000 | 0100 | | Colombia, La Voz del Guaviare | | 6035do |
| 0000 | 0100 | | Colombia, Radio Marfil Estereo | | 5910do |
| | | | 6010al | | |
| 0000 | 0100 | | Cuba, Radio Havana Cuba | 5965ca | 6000na |
| | | | 6060na | 6120na | 6140na |
| | | | 11690sa | 13760eu | 9600sa |
| 0000 | 0100 | | Cuba, Radio Rebelde | | 5025na |
| 0000 | 0100 | | Ecuador, HCJB Global | | 11625am |
| 0000 | 0100 | | Ecuador, Radio Quito | | 4919do |
| 0000 | 0100 | | Guatemala, Radio Verdad | | 4052do |
| 0000 | 0100 | | Honduras, HRMI/ Radio Misiones Intl | | 3340do |
| 0000 | 0100 | | Honduras, Radio Luz y Vida | | 3250do |
| 0000 | 0100 | | Mexico, XEOI/Radio Mil | | 6010do |
| 0000 | 0100 | | Mexico, XERTA/Radio Transcontinental | | 4800do |
| 0000 | 0100 | | Mexico, XEXQ/Radio Universidad | | 6045do |
| 0000 | 0100 | | North Korea, Voice of Korea | 11735am | 13760am |
| | | | 15180am | | |
| 0000 | 0100 | | Peru, Radio Bethel | 5949do | |
| 0000 | 0100 | | Peru, Radio Bolivar | | 5460do |
| 0000 | 0100 | Sun | Peru, Radio Cusco | 6195do | |
| 0000 | 0100 | | Peru, Radio La Voz De Bolivar | 5460do | 4755al |
| 0000 | 0100 | | Peru, Radio La Voz de la Selva | 4824do | |
| 0000 | 0100 | | Peru, Radio La Voz de las Huarinjas | | 5059do |
| 0000 | 0100 | | Peru, Radio Libertad de Junin | 5039do | |
| 0000 | 0100 | | Peru, Radio Maranon | 4835do | |
| 0000 | 0100 | | Peru, Radio Melodia | 5940do | |
| 0000 | 0100 | | Peru, Radio Rasuwilca | 4805do | |
| 0000 | 0100 | | Peru, Radio San Antonio | 4940do | |
| 0000 | 0100 | | Peru, Radio San Nicolas | 5470do | |
| 0000 | 0100 | | Peru, Radio Santa Monica | 4965do | |
| 0000 | 0100 | | Peru, Radio Santa Rosa | 6047do | |
| 0000 | 0100 | | Peru, Radio Super Sensacion | 6536do | |
| 0000 | 0100 | twhf | Peru, Radio Tarma | 4775do | |
| 0000 | 0100 | | Peru, Radio Union | 6114do | |
| 0000 | 0100 | | Peru, Radio Vision | 4790do | |
| 0000 | 0100 | | Russia, Voice of Russia | | 7300sa |
| | | | 11510sa | | 9810sa |
| 0000 | 0100 | | Spain, Radio Exterior de Espana | | 6020sa |
| | | | 9535am | 9620sa | 11680sa |
| | | | 15160sa | | |
| 0000 | 0100 | mtwhf | Spain, Radio Exterior de Espana | | 5970sa |
| 0000 | 0100 | Sat | Spain, Radio Exterior de Espana | | 11815sa |
| 0000 | 0100 | | USA, EWTN Vandiver AL | 5810ca | 17510sa |
| 0000 | 0100 | | USA, KVOH Rancho Simi CA | 17775ca | |
| 0000 | 0100 | | USA, Radio Marti | 6030ca | 7365ca |
| | | | 11775ca | | 11775ca |
| 0000 | 0100 | | USA, WYFR/Family Radio Worldwide | | 5985ca |

| | | | | | |
|------|------|-------------------------------------|---------|---------|---------|
| | | 9760sa | 11835ca | 11855ca | 15215sa |
| | | 17895sa | | | |
| 0000 | 0100 | Venezuela, Radio Amazonas | 4940do | | mt0909 |
| 0030 | 0035 | Austria, ORF/Radio Austria Intl | 9820eu | | |
| 0030 | 0057 | Czech Republic, Radio Prague | 7345am | | 9440am |
| 0030 | 0100 | Iran, Voice of Islamic Rep. of Iran | | | 9655sa |
| | | 9905sa | | | |
| 0045 | 0100 | Egypt, Radio Cairo | 7540na | 9360ca | 9915sa |

0100 UTC - 8PM EST / 7PM CST / 5PM PST

| | | | | | |
|------|------|------|--------------------------------------|--------|---------|
| 0100 | 0105 | | Austria, ORF/Radio Austria Intl | 9820sa | |
| 0100 | 0130 | | France, Radio France International | | 5995sa |
| | | | 9750sa | | |
| 0100 | 0130 | | Peru, Radio San Nicolas | | 5470do |
| 0100 | 0145 | | USA, WYFR/Family Radio Worldwide | | 17725sa |
| 0100 | 0157 | | Netherlands, R Netherlands Worldwide | | 6165am |
| | | | 7325ca | 9450ca | |
| 0100 | 0200 | | Bolivia, Radio Eco | 4409do | |
| 0100 | 0200 | | Bolivia, Radio Estambul | | 4498do |
| 0100 | 0200 | | Bolivia, Radio Nacional de Huanuni | | 5967do |
| 0100 | 0200 | | Bolivia, Radio San Jose | 5580do | |
| 0100 | 0200 | | Bolivia, Radio San Miguel | 4699do | |
| 0100 | 0200 | | Bolivia, Radio Tacana | 4781do | |
| 0100 | 0200 | | Bolivia, Radio Yura | 4716do | |
| 0100 | 0200 | | Bulgaria, Radio Bulgaria | 7400sa | 9400va |
| 0100 | 0200 | | Chile, La Voz Crista | 9745sa | 11665sa |
| 0100 | 0200 | | China, China Radio International | | 9595sa |
| | | | 9665sa | 9710sa | |
| 0100 | 0200 | | Clandestine, Radio Republica | 9545ca | |
| 0100 | 0200 | | Colombia, La Voz de tu Conciencia | | 6010do |
| | | | 5910al | | |
| 0100 | 0200 | | Colombia, La Voz del Guaviare | | 6035do |
| 0100 | 0200 | | Colombia, Radio Marfil Estereo | | 5910do |
| | | | 6010al | | |
| 0100 | 0200 | | Cuba, Radio Havana Cuba | 5965ca | 6060na |
| | | | 6120na | 9600sa | 11690sa |
| | | | 13790eu | | 13760eu |
| 0100 | 0200 | | Cuba, Radio Rebelde | | 5025na |
| 0100 | 0200 | | Ecuador, HCJB Global | | 11625am |
| 0100 | 0200 | | Ecuador, Radio Quito | | 4919do |
| 0100 | 0200 | | Egypt, Radio Cairo | 7540na | 9360ca |
| 0100 | 0200 | | Guatemala, Radio Verdad | 4052do | |
| 0100 | 0200 | | Honduras, HRMI/ Radio Misiones Intl | | 3340do |
| 0100 | 0200 | | Honduras, Radio Luz y Vida | | 3250do |
| 0100 | 0200 | | Mexico, XEOI/Radio Mil | | 6010do |
| 0100 | 0200 | | Mexico, XERTA/Radio Transcontinental | | 4800do |
| 0100 | 0200 | | Mexico, XEXQ/Radio Universidad | | 6045do |
| 0100 | 0200 | | Peru, Radio Bethel | 5949do | |
| 0100 | 0200 | | Peru, Radio Bolivar | | 5460do |
| 0100 | 0200 | Sun | Peru, Radio Cusco | 6195do | |
| 0100 | 0200 | | Peru, Radio La Voz De Bolivar | 5460do | 4755al |
| 0100 | 0200 | | Peru, Radio La Voz de la Selva | 4824do | |
| 0100 | 0200 | | Peru, Radio La Voz de las Huarinjas | | 5059do |
| 0100 | 0200 | | Peru, Radio Libertad de Junin | 5039do | |
| 0100 | 0200 | | Peru, Radio Maranon | 4835do | |
| 0100 | 0200 | | Peru, Radio Melodia | 5940do | |
| 0100 | 0200 | | Peru, Radio San Antonio | 4940do | |
| 0100 | 0200 | | Peru, Radio Santa Monica | 4965do | |
| 0100 | 0200 | | Peru, Radio Santa Rosa | 6047do | |
| 0100 | 0200 | twhf | Peru, Radio Tarma | 4775do | |
| 0100 | 0200 | | Peru, Radio Union | 6114do | |
| 0100 | 0200 | | Peru, Radio Vision | 4790do | |
| 0100 | 0200 | | Peru, Radio Vision | 4790do | |
| 0100 | 0200 | | Russia, Voice of Russia | | 7300sa |
| | | | 9810sa | 9880ca | 9945sa |
| | | | 11510sa | | 11510sa |
| 0100 | 0200 | | South Korea, KBS World Radio | | 9580sa |

WANT MORE?

Access to the MTXtra Shortwave Broadcast Guide is free to MTXpress subscribers. If you are a subscriber to the printed magazine, you may add a full year of MTXpress/MTXtra to your subscription for only \$11.95. Call 1-800-438-8155 or visit www.monitoringtimes.com to learn how.

| | | | |
|------|------|--|-------------------|
| 0100 | 0200 | Spain, Radio Exterior de Espana 6055na 9535am 9620sa 11680sa 15160sa | 6020sa 11680sa |
| 0100 | 0200 | mtwhf Spain, Radio Exterior de Espana 17595sa | 5970sa |
| 0100 | 0200 | Sat Spain, Radio Exterior de Espana | 11815sa |
| 0100 | 0200 | Turkey, Voice of Turkey | 9770va 9870va |
| 0100 | 0200 | USA, EWTN Vandiver AL | 5810ca 11870sa |
| 0100 | 0200 | USA, KVOH Rancho Simi CA | 9975ca |
| 0100 | 0200 | USA, KVOH Rancho Simi CA | 9975ca |
| 0100 | 0200 | USA, Radio Marti 6030ca | 7365ca 11775ca |
| 0100 | 0200 | USA, WYFR/Family Radio Worldwide | 5985ca |
| | | 11835ca 11855ca 15215sa | 15255sa |
| | | 17750sa | |
| 0100 | 0200 | Vatican City State, Vatican Radio | 7305sa |
| | | 9610ca 11910sa | |
| 0100 | 0200 | Venezuela, Radio Amazonas | 4940do mt0909 |

0200 UTC - 9PM EST / 8PM CST / 6PM PST

| | | | |
|------|------|---------------------------------------|-----------------|
| 0200 | 0227 | Czech Republic, Radio Prague | 6200am 7345am |
| 0200 | 0227 | Iran, Voice of Islamic Rep. of Iran | 9905sa 9655sa |
| | | 9905sa | |
| 0200 | 0230 | Bolivia, Radio San Jose | 5580do |
| 0200 | 0230 | South Korea, KBS World Radio | 9560na |
| 0200 | 0230 | Vatican City State, Vatican Radio | 7305sa |
| | | 9610ca 11910sa | |
| 0200 | 0245 | USA, WYFR/Family Radio Worldwide | 17750sa |
| | | 17845sa | |
| 0200 | 0257 | Netherlands, R Netherlands Worldwide | 6165ca |
| 0200 | 0300 | Bolivia, Radio Estambul | 4498do |
| 0200 | 0300 | Bolivia, Radio San Miguel | 4699do |
| 0200 | 0300 | Bolivia, Radio Tacana | 4781do |
| 0200 | 0300 | Canada, Radio Canada International | 9755na |
| | | 13710ca | |
| 0200 | 0300 | China, China Radio International | 9595sa |
| | | 9710sa | |
| 0200 | 0300 | Clandestine, Radio Republica | 9545ca |
| 0200 | 0300 | Colombia, La Voz de tu Conciencia | 5910al 6010do |
| 0200 | 0300 | Colombia, La Voz del Guaviare | 6035do |
| 0200 | 0300 | Colombia, Radio Marfil Estereo | 5910do |
| | | 6010al | |
| 0200 | 0300 | Cuba, Radio Havana Cuba | 5965ca 6060na |
| | | 6120na 9600sa 11690sa | 13760eu |
| | | 13790eu | |
| 0200 | 0300 | Cuba, Radio Rebelde | 5025na |
| 0200 | 0300 | Ecuador, HCJB Global | 6050sa 9745ca |
| 0200 | 0300 | Ecuador, Radio Quito | 4919do |
| 0200 | 0300 | Guatemala, Radio Verdad | 4052do |
| 0200 | 0300 | Honduras, HRMI/ Radio Misiones Intl | 3340do |
| 0200 | 0300 | Honduras, Radio Luz y Vida | 3250do |
| 0200 | 0300 | Mexico, XEOI/Radio Mil | 6010do |
| 0200 | 0300 | Mexico, XERTA/Radio Transcontinental | 4800do |
| 0200 | 0300 | Mexico, XEXQ/Radio Universidad | 6045do |
| 0200 | 0300 | North Korea, Voice of Korea | 11735am 13760am |
| | | 15180am | |
| 0200 | 0300 | Peru, Radio Bethel | 5949do |
| 0200 | 0300 | Peru, Radio Bolivar | 5460do |
| 0200 | 0300 | Peru, Radio Cusco 6195do | 4755al |
| 0200 | 0300 | Peru, Radio La Voz De Bolivar | 5460do |
| 0200 | 0300 | Peru, Radio La Voz de la Selva | 4824do |
| 0200 | 0300 | Peru, Radio Maranon | 4835do |
| 0200 | 0300 | Peru, Radio Melodia | 5940do |
| 0200 | 0300 | Peru, Radio Santa Monica | 4965do |
| 0200 | 0300 | Peru, Radio Santa Rosa | 6047do |
| 0200 | 0300 | twhf Per, Radio Tarma 4775do | |
| 0200 | 0300 | Peru, Radio Union 6114do | |
| 0200 | 0300 | Peru, Radio Vision 4790do | |
| 0200 | 0300 | Russia, Voice of Russia | 7300sa 9735ca |
| | | 9880ca 9945sa | |
| 0200 | 0300 | Spain, Radio Exterior de Espana | 3350sa |
| | | 6020sa 6055na 6125sa | 9535am |
| | | 9620sa 9630na | |
| 0200 | 0300 | mtwhf Spain, Radio Exterior de Espana | 5970sa |
| | | 17595sa | |
| 0200 | 0300 | Sat Spain, Radio Exterior de Espana | 11815sa |
| 0200 | 0300 | Taiwan, Radio Taiwan International | 7570sa |
| | | 9840sa | |
| 0200 | 0300 | USA, EWTN Vandiver AL | 5810ca 11870sa |
| 0200 | 0300 | USA, KVOH Rancho Simi CA | 9975ca |
| 0200 | 0300 | USA, Radio Marti 6030ca | 7365ca 11775ca |
| 0200 | 0300 | USA, WYFR/Family Radio Worldwide | 9760sa |
| | | 11740ca 15255sa | |
| 0200 | 0300 | Venezuela, Radio Amazonas | 4940do mt0909 |
| 0205 | 0300 | Canada, Radio Canada International | 6100am |
| 0230 | 0300 | Iran, Voice of Islamic Rep. of Iran | 9905sa |

| | | | |
|------|------|--|--------|
| 0230 | 0300 | Slovakia, Radio Slovakia International | 5930sa |
| | | 9440sa | |

0300 UTC - 10PM EST / 9PM CST / 7PM PST

| | | | |
|------|------|---------------------------------------|----------------|
| 0300 | 0305 | Canada, Radio Canada International | 6100am |
| 0300 | 0327 | Iran, Voice of Islamic Rep. of Iran | 9905sa |
| 0300 | 0330 | Peru, Radio La Voz De Bolivar | 5460do 4755al |
| 0300 | 0345 | USA, WYFR/Family Radio Worldwide | 11580sa |
| | | 15215sa | |
| 0300 | 0357 | Netherlands, R Netherlands Worldwide | 6165ca |
| 0300 | 0400 | Bolivia, Radio Estambul | 4498do |
| 0300 | 0400 | China, China Radio International | 9560sa |
| | | 9665ca | |
| 0300 | 0400 | Clandestine, Radio Republica | 9545ca |
| 0300 | 0400 | Colombia, La Voz de tu Conciencia | 5910al 6010do |
| 0300 | 0400 | Colombia, Radio Marfil Estereo | 5910do |
| | | 6010al | |
| 0300 | 0400 | Cuba, Radio Havana Cuba | 5965ca 6060na |
| | | 6120na 9600sa 11690sa | 13760eu |
| | | 13790eu | |
| 0300 | 0400 | Cuba, Radio Rebelde | 5025na |
| 0300 | 0400 | Ecuador, HCJB Global | 6050sa 9745ca |
| 0300 | 0400 | Ecuador, Radio Quito | 4919do |
| 0300 | 0400 | Guatemala, Radio Verdad | 4052do |
| 0300 | 0400 | Honduras, HRMI/ Radio Misiones Intl | 3340do |
| 0300 | 0400 | Honduras, Radio Luz y Vida | 3250do |
| 0300 | 0400 | Mexico, XEOI/Radio Mil | 6010do |
| 0300 | 0400 | Mexico, XERTA/Radio Transcontinental | 4800do |
| 0300 | 0400 | Mexico, XEXQ/Radio Universidad | 6045do |
| 0300 | 0400 | Peru, Radio Cusco 6195do | |
| 0300 | 0400 | Peru, Radio Melodia | 5940do |
| 0300 | 0400 | Peru, Radio Santa Monica | 4965do |
| 0300 | 0400 | Peru, Radio Santa Rosa | 6047do |
| 0300 | 0400 | twhf Per, Radio Tarma 4775do | |
| 0300 | 0400 | Peru, Radio Union 6114do | |
| 0300 | 0400 | Peru, Radio Vision 4790do | |
| 0300 | 0400 | Russia, Voice of Russia | 7300sa 9665ca |
| | | 9735ca 9880ca 9945sa | |
| 0300 | 0400 | Spain, Radio Exterior de Espana | 3350sa |
| | | 5935ca 6020sa 6055na | 6125sa |
| | | 9535na 9620sa 9630na | |
| 0300 | 0400 | mtwhf Spain, Radio Exterior de Espana | 5970sa |
| | | 17595sa | |
| 0300 | 0400 | Sat Spain, Radio Exterior de Espana | 11815sa |
| 0300 | 0400 | USA, EWTN Vandiver AL | 5810ca 11870sa |
| 0300 | 0400 | USA, KVOH Rancho Simi CA | 9975ca |
| 0300 | 0400 | USA, Radio Marti 6030ca | 7365ca |
| 0300 | 0400 | USA, WYFR/Family Radio Worldwide | 5985ca |
| | | 9680na 9715ca 11855ca | |
| 0304 | 0400 | USA, WYFR/Family Radio Worldwide | 6915sa |
| 0320 | 0400 | Vatican City State, Vatican Radio | 7305ca 6040am |

0400 UTC - 11PM EST / 10PM CST / 8PM PST

| | | | |
|------|------|---------------------------------------|---------------|
| 0400 | 0430 | Japan, NHK World Radio Japan | 6195sa |
| 0400 | 0445 | USA, WYFR/Family Radio Worldwide | 5985ca |
| | | 7730sa 9985sa 11740ca | 15255sa |
| 0400 | 0500 | Colombia, La Voz de tu Conciencia | 6010do |
| | | 5910al | |
| 0400 | 0500 | Sat/Sun Colombia, La Voz del Guaviare | 6035do |
| 0400 | 0500 | Colombia, Radio Marfil Estereo | 5910do |
| | | 6010al | |
| 0400 | 0500 | Cuba, Radio Havana Cuba | 5965ca 6060na |
| | | 6120na 9600sa 11690sa | 13760eu |
| | | 13790eu | |
| 0400 | 0500 | Cuba, Radio Rebelde | 5025na |
| 0400 | 0500 | Ecuador, HCJB Global | 6050sa 9745ca |
| 0400 | 0500 | Ecuador, Radio Quito | 4919do |
| 0400 | 0500 | Guatemala, Radio Verdad | 4052do |
| 0400 | 0500 | Honduras, HRMI/ Radio Misiones Intl | 3340do |
| 0400 | 0500 | Mexico, XEOI/Radio Mil | 6010do |
| 0400 | 0500 | Mexico, XERTA/Radio Transcontinental | 4800do |
| 0400 | 0500 | Mexico, XEXQ/Radio Universidad | 6045do |
| 0400 | 0500 | Peru, Radio Melodia | 5940do |
| 0400 | 0500 | Peru, Radio Santa Monica | 4965do |
| 0400 | 0500 | Peru, Radio Santa Rosa | 6047do |
| 0400 | 0500 | Peru, Radio Union 6114do | |
| 0400 | 0500 | Peru, Radio Vision 4790do | |
| 0400 | 0500 | Russia, Voice of Russia | 9735ca 9880ca |
| | | 9945sa | |
| 0400 | 0500 | Spain, Radio Exterior de Espana | 3350sa |
| | | 5965sa 6055na 6125sa | 9535am |
| | | 9620sa 9630na | |

| | | | | |
|------|------|-------|--|----------------|
| 0400 | 0500 | mtwhf | Spain, Radio Exterior de Espana 12035eu 17595sa | 5970sa |
| 0400 | 0500 | Sat | Spain, Radio Exterior de Espana | 11815sa |
| 0400 | 0500 | | Taiwan, Radio Taiwan International | 17725ca |
| 0400 | 0500 | | USA, EWTN Vandiver AL | 5810ca 11870sa |
| 0400 | 0500 | | USA, KVOH Rancho Simi CA | 9975ca |
| 0400 | 0500 | | USA, Radio Marti 6030ca | 7405ca |
| 0400 | 0500 | | USA, WYFR/Family Radio Worldwide | 9715ca |
| 0430 | 0457 | | Czech Republic, Radio Prague | 9955am |

0500 UTC - 12AM EST / 11PM CST / 9PM PST

| | | | | |
|------|------|---------|---|----------------|
| 0500 | 0530 | | Japan, NHK World Radio Japan | 6195ca |
| 0500 | 0545 | | USA, WYFR/Family Radio Worldwide | 7520ca |
| 0500 | 0600 | | Colombia, La Voz de tu Conciencia 5910al | 6010do |
| 0500 | 0600 | Sat/Sun | Colombia, La Voz del Guaviare | 6035do |
| 0500 | 0600 | | Colombia, Radio Marfil Estereo 6010al | 5910do |
| 0500 | 0600 | | Cuba, Radio Rebelde | 5025na |
| 0500 | 0600 | | Ecuador, Radio Quito | 4919do |
| 0500 | 0600 | | Honduras, HRMI/ Radio Misiones Intl | 3340do |
| 0500 | 0600 | | Mexico, XEOI/Radio Mil | 6010do |
| 0500 | 0600 | | Mexico, XERTA/Radio Transcontinental | 4800do |
| 0500 | 0600 | | Peru, Radio Melodia | 5940do |
| 0500 | 0600 | | Peru, Radio Santa Monica | 4965do |
| 0500 | 0600 | | Peru, Radio Santa Rosa | 6047do |
| 0500 | 0600 | | Peru, Radio Union 6114do | |
| 0500 | 0600 | | Peru, Radio Vision 4790do | |
| 0500 | 0600 | | Spain, Radio Exterior de Espana 5965sa 6055na 9630na | 3350sa 11895me |
| 0500 | 0600 | mtwhf | Spain, Radio Exterior de Espana 17595sa | 5970sa |
| 0500 | 0600 | Sat | Spain, Radio Exterior de Espana | 11815sa |
| 0500 | 0600 | DRM | Spain, Radio Exterior de Espana | 9780eu |
| 0500 | 0600 | | USA, EWTN Vandiver AL | 7555ca 11870sa |
| 0500 | 0600 | | USA, KVOH Rancho Simi CA | 9975ca |
| 0500 | 0600 | | USA, Radio Marti 6030ca | 7405ca |
| 0500 | 0600 | | USA, WYFR/Family Radio Worldwide 9715ca 9985sa | 5850ca |
| 0504 | 0600 | | USA, WYFR/Family Radio Worldwide | 9505ca |
| 0530 | 0600 | | Iran, Voice of Islamic Rep. of Iran 17785va | 15530va |

0600 UTC - 1AM EST / 12AM CST / 10PM PST

| | | | | |
|------|------|---------|--|-----------------|
| 0600 | 0627 | | Iran, Voice of Islamic Rep. of Iran 17785va | 15530va |
| 0600 | 0630 | | Bulgaria, Radio Bulgaria | 11800eu 15800eu |
| 0600 | 0700 | | China, China Radio International | 17680eu |
| 0600 | 0700 | | Colombia, La Voz de tu Conciencia 5910al | 6010do |
| 0600 | 0700 | Sat/Sun | Colombia, La Voz del Guaviare | 6035do |
| 0600 | 0700 | | Colombia, Radio Marfil Estereo 6010al | 5910do |
| 0600 | 0700 | | Cuba, Radio Rebelde | 5025na |
| 0600 | 0700 | | Ecuador, Radio Quito | 4919do |
| 0600 | 0700 | | Honduras, HRMI/ Radio Misiones Intl | 3340do |
| 0600 | 0700 | | Mexico, XEOI/Radio Mil | 6010do |
| 0600 | 0700 | | Mexico, XERTA/Radio Transcontinental | 4800do |
| 0600 | 0700 | | Peru, Radio Melodia | 5940do |
| 0600 | 0700 | | Peru, Radio Santa Monica | 4965do |
| 0600 | 0700 | | Peru, Radio Santa Rosa | 6047do |
| 0600 | 0700 | | Peru, Radio Union 6114do | |
| 0600 | 0700 | | Peru, Radio Vision 4790do | |
| 0600 | 0700 | | South Korea, KBS World Radio | 6045eu |
| 0600 | 0700 | | Spain, Radio Exterior de Espana 11895me 12035eu | 5965sa |
| 0600 | 0700 | DRM | Spain, Radio Exterior de Espana | 9780eu |
| 0600 | 0700 | mtwhf | Spain, Radio Exterior de Espana 17595sa | 5970sa |
| 0600 | 0700 | Sat | Spain, Radio Exterior de Espana | 11815sa |
| 0600 | 0700 | | Taiwan, Radio Taiwan International | 5950ca |
| 0600 | 0700 | | USA, EWTN Vandiver AL | 7555ca 11870sa |
| 0600 | 0700 | | USA, KVOH Rancho Simi CA | 9975ca |
| 0600 | 0700 | | USA, Radio Marti 6030ca | 7405ca |
| 0600 | 0700 | | USA, WYFR/Family Radio Worldwide 9505ca 9715ca | 6915sa |

0700 UTC - 2AM EST / 1AM CST / 11PM PST

| | | | | |
|------|------|--|--|---------|
| 0700 | 0745 | | USA, WYFR/Family Radio Worldwide 9680na | 9355eu |
| 0700 | 0800 | | China, China Radio International | 17680eu |

| | | | | |
|------|------|-------|--|----------------|
| 0700 | 0800 | | Colombia, La Voz de tu Conciencia 5910al | 6010do |
| 0700 | 0800 | | Colombia, Radio Marfil Estereo 6010al | 5910do |
| 0700 | 0800 | | Cuba, Radio Rebelde | 5025na |
| 0700 | 0800 | | Ecuador, Radio Quito | 4919do |
| 0700 | 0800 | | Honduras, HRMI/ Radio Misiones Intl | 3340do |
| 0700 | 0800 | | Mexico, XEOI/Radio Mil | 6010do |
| 0700 | 0800 | | Mexico, XERTA/Radio Transcontinental | 4800do |
| 0700 | 0800 | | Peru, Radio Melodia | 5940do |
| 0700 | 0800 | | Peru, Radio Santa Monica | 4965do |
| 0700 | 0800 | | Peru, Radio Santa Rosa | 6047do |
| 0700 | 0800 | | Peru, Radio Union 6114do | |
| 0700 | 0800 | | Peru, Radio Vision 4790do | |
| 0700 | 0800 | | Spain, Radio Exterior de Espana 12035eu 13720eu 17770pa | 5965sa |
| 0700 | 0800 | DRM | Spain, Radio Exterior de Espana | 9780eu |
| 0700 | 0800 | mtwhf | Spain, Radio Exterior de Espana 17595sa | 5970sa |
| 0700 | 0800 | Sat | Spain, Radio Exterior de Espana | 11815sa |
| 0700 | 0800 | | USA, EWTN Vandiver AL | 7555ca 11870sa |
| 0700 | 0800 | | USA, KVOH Rancho Simi CA | 9975ca |
| 0700 | 0800 | | USA, Radio Marti 5980ca | 6030ca |
| 0700 | 0800 | | USA, WYFR/Family Radio Worldwide 9715ca | 5850ca |

0800 UTC - 3AM EST / 2AM CST / 12AM PST

| | | | | |
|------|------|-------|--|-----------------|
| 0800 | 0827 | | Czech Republic, Radio Prague | 11600am 15710va |
| 0800 | 0900 | | Colombia, La Voz de tu Conciencia 5910al | 6010do |
| 0800 | 0900 | | Colombia, La Voz del Guaviare | 6035do |
| 0800 | 0900 | | Colombia, Radio Marfil Estereo 6010al | 5910do |
| 0800 | 0900 | | Cuba, Radio Rebelde | 5025na |
| 0800 | 0900 | | Ecuador, Radio Quito | 4919do |
| 0800 | 0900 | | Greece, Voice of Greece | 11645eu |
| 0800 | 0900 | | Honduras, HRMI/ Radio Misiones Intl | 3340do |
| 0800 | 0900 | | Mexico, XEOI/Radio Mil | 6010do |
| 0800 | 0900 | | Mexico, XERTA/Radio Transcontinental | 4800do |
| 0800 | 0900 | | Peru, Radio Melodia | 5940do |
| 0800 | 0900 | | Peru, Radio Santa Monica | 4965do |
| 0800 | 0900 | | Peru, Radio Santa Rosa | 6047do |
| 0800 | 0900 | | Peru, Radio Union 6114do | |
| 0800 | 0900 | | Peru, Radio Vision 4790do | |
| 0800 | 0900 | | Spain, Radio Exterior de Espana 13720eu 17770pa | 12035eu |
| 0800 | 0900 | DRM | Spain, Radio Exterior de Espana | 9780eu |
| 0800 | 0900 | mtwhf | Spain, Radio Exterior de Espana 17595sa | 5970sa |
| 0800 | 0900 | Sat | Spain, Radio Exterior de Espana | 11815sa |
| 0800 | 0900 | | USA, EWTN Vandiver AL | 7555ca 11870sa |
| 0800 | 0900 | | USA, Radio Marti 5980ca | 6030ca |
| 0800 | 0900 | | USA, WYFR/Family Radio Worldwide 9505ca 9550sa 9715ca | 5850ca 11855ca |
| 0830 | 0900 | DRM | Ecuador, HCJB Global | 11625eu |

0900 UTC - 4AM EST / 3AM CST / 1AM PST

| | | | | |
|------|------|---------|--|----------------|
| 0900 | 0930 | DRM | Ecuador, HCJB Global | 11625eu |
| 0900 | 0945 | | USA, WYFR/Family Radio Worldwide 9505ca | 5850ca |
| 0900 | 1000 | | Argentina, Radio Nacional RAE | 6060am |
| 0900 | 1000 | | Colombia, La Voz de tu Conciencia 5910al | 6010do |
| 0900 | 1000 | | Colombia, La Voz del Guaviare | 6035do |
| 0900 | 1000 | | Colombia, Radio Marfil Estereo 6010al | 5910do |
| 0900 | 1000 | | Cuba, Radio Rebelde | 5025na |
| 0900 | 1000 | | Ecuador, Radio Quito | 4919do |
| 0900 | 1000 | | Honduras, HRMI/ Radio Misiones Intl | 3340do |
| 0900 | 1000 | | Mexico, XEOI/Radio Mil | 6010do |
| 0900 | 1000 | | Mexico, XERTA/Radio Transcontinental | 4800do |
| 0900 | 1000 | | Peru, Radio La Voz de la Selva | 4824do |
| 0900 | 1000 | | Peru, Radio Libertad de Junin | 5039do |
| 0900 | 1000 | | Peru, Radio Maranon | 4835do |
| 0900 | 1000 | | Peru, Radio Melodia | 5940do |
| 0900 | 1000 | | Peru, Radio Union 6114do | |
| 0900 | 1000 | | Peru, Radio Vision 4790do | |
| 0900 | 1000 | | Spain, Radio Exterior de Espana | 21610me |
| 0900 | 1000 | mtwhf | Spain, Radio Exterior de Espana 13720eu 15585eu 17595sa | 5970sa 21540af |
| 0900 | 1000 | Sat | Spain, Radio Exterior de Espana | 11815sa |
| 0900 | 1000 | Sat/Sun | Spain, Radio Exterior de Espana | 21540af |
| 0900 | 1000 | | USA, EWTN Vandiver AL | 7555ca 11870sa |

| | | | | | |
|------|------|--|--------|--------|-----------------|
| 0900 | 1000 | USA, Radio Marti | 5980ca | 6030ca | |
| 0900 | 1000 | USA, WYFR/Family Radio Worldwide | 9550sa | 9715ca | 11855ca 11970ca |
| 0930 | 0957 | Czech Republic, Radio Prague | 9955am | | |
| 0930 | 1000 | Bolivia, Radio Illimani/Radio Patria Nueva | 6025do | | |
| 0930 | 1000 | Peru, Radio Cusco | 6195do | | |
| 0930 | 1000 | Peru, Radio Tarma | 4775do | | |

| | | | | | |
|------|------|--|---------|---------|---------|
| 1100 | 1200 | Colombia, La Voz del Guaviare | | | 6035do |
| 1100 | 1200 | Colombia, Radio Marfil Estereo | | | 5910do |
| | | 6010al | | | |
| 1100 | 1200 | Cuba, Radio Havana Cuba | 6000na | 6180na | |
| | | 9600na | 11760am | 12000va | 13760eu |
| | | 15120va | 15360sa | | |
| 1100 | 1200 | Cuba, Radio Rebelde | 5025na | | |
| 1100 | 1200 | Ecuador, HCJB Global | 6050sa | 11690sa | |
| 1100 | 1200 | Ecuador, Radio Quito | 4919do | | |
| 1100 | 1200 | Honduras, HRMI/ Radio Misiones Intl | | 3340do | |
| 1100 | 1200 | Honduras, Radio Luz y Vida | 3250do | | |
| 1100 | 1200 | Mexico, XEOI/Radio Mil | 6010do | | |
| 1100 | 1200 | Mexico, XERTA/Radio Transcontinental | | 4800do | |
| 1100 | 1200 | Peru, Radio Bethel | 5949do | | |
| 1100 | 1200 | Peru, Radio Bolivar | 5460do | | |
| 1100 | 1200 | Peru, Radio Cusco | 6195do | | |
| 1100 | 1200 | Peru, Radio La Reyna de la Selva | | 5486do | |
| 1100 | 1200 | Peru, Radio La Voz De Bolivar | 5460do | | |
| 1100 | 1200 | Peru, Radio La Voz de la Selva | 4824do | | |
| 1100 | 1200 | Peru, Radio La Voz de las Huarinjas | | 5059do | |
| 1100 | 1200 | Peru, Radio Libertad de Junin | 5039do | | |
| 1100 | 1200 | Peru, Radio Madre de Dios | 4950do | | |
| 1100 | 1200 | Peru, Radio Melodia | 5940do | | |
| 1100 | 1200 | Peru, Radio San Antonio | 4940do | | |
| 1100 | 1200 | Peru, Radio San Nicolas | 5470do | | |
| 1100 | 1200 | Peru, Radio Santa Rosa | 6047do | | |
| 1100 | 1200 | Peru, Radio Tarma | 4775do | | |
| 1100 | 1200 | Peru, Radio Union | 6114do | | |
| 1100 | 1200 | Peru, Radio Vision | 4790do | | |
| 1100 | 1200 | South Korea, KBS World Radio | | 11795sa | |
| 1100 | 1200 | Spain, Radio Exterior de Espana | | 21610me | |
| 1100 | 1200 | Spain, Radio Exterior de Espana | 13720eu | 15585eu | 17595sa |
| 1100 | 1200 | Spain, Radio Exterior de Espana | | 5970sa | 21540af |
| 1100 | 1200 | Sat | | | |
| 1100 | 1200 | Sat/Sun | | | |
| 1100 | 1200 | Spain, Radio Exterior de Espana | | 21540af | |
| 1100 | 1200 | USA, EWTN Vandiver AL | 7555ca | 12050sa | |
| 1100 | 1200 | USA, Radio Marti | 5980ca | 9805ca | |
| 1100 | 1200 | USA, WYFR/Family Radio Worldwide | 9605ca | 11970ca | 6085ca |
| 1100 | 1200 | Venezuela, Radio Amazonas | 4940do | mt0909 | |
| 1100 | 1200 | Venezuela, Radio Nacional de Venezuela | | 6060ca | |
| 1129 | 1157 | Netherlands, R Netherlands Worldwide | | 6165am | |
| 1130 | 1200 | Guatemala, Radio Verdad | 4052do | | |
| 1130 | 1200 | mtwhf | | | |
| | | USA, Voice of America | 9885ca | 13715sa | |
| | | 15590ca | | | |
| 1130 | 1200 | mtwhfa | | | |
| | | Vatican City State, Vatican Radio | | 21680sa | |

1000 UTC - 5AM EST / 4AM CST / 2AM PST

| | | | | | |
|------|------|--|---------|---------|---------|
| 1000 | 1030 | Japan, NHK World Radio Japan | | 6120sa | |
| | | 6195sa | | | |
| 1000 | 1030 | France, Radio France International | | 5970sa | |
| | | 9875sa | | | |
| 1000 | 1030 | Sun | | | |
| 1000 | 1100 | Peru, Radio Madre de Dios | 4950do | | |
| 1000 | 1100 | Bolivia, Radio Estambul | 4498do | | |
| 1000 | 1100 | Bolivia, Radio Illimani/Radio Patria Nueva | 6025do | | |
| 1000 | 1100 | Bolivia, Radio Nacional de Huanuni | | 5967do | |
| 1000 | 1100 | Bolivia, Radio San Jose | 5580do | | |
| 1000 | 1100 | Bolivia, Radio San Miguel | 4699do | | |
| 1000 | 1100 | Bolivia, Radio Santa Ana | 4451do | | |
| 1000 | 1100 | Bolivia, Radio Tacana | 4781do | | |
| 1000 | 1100 | Bolivia, Radio Virgen de Remedios | | 4834do | |
| 1000 | 1100 | Colombia, La Voz de tu Conciencia | | 6010do | |
| | | 5910al | | | |
| 1000 | 1100 | Colombia, La Voz del Guaviare | | 6035do | |
| 1000 | 1100 | Colombia, Radio Marfil Estereo | | 5910do | |
| | | 6010al | | | |
| 1000 | 1100 | Cuba, Radio Rebelde | 5025na | | |
| 1000 | 1100 | Ecuador, Radio Quito | 4919do | | |
| 1000 | 1100 | Honduras, HRMI/ Radio Misiones Intl | | 3340do | |
| 1000 | 1100 | Iran, Voice of Islamic Rep. of Iran | 9905sa | 9655sa | |
| 1000 | 1100 | Mexico, XEOI/Radio Mil | 6010do | | |
| 1000 | 1100 | Mexico, XERTA/Radio Transcontinental | | 4800do | |
| 1000 | 1100 | Peru, Radio Bethel | 5949do | | |
| 1000 | 1100 | Peru, Radio Bolivar | 5460do | | |
| 1000 | 1100 | Peru, Radio Cusco | 6195do | | |
| 1000 | 1100 | Peru, Radio La Reyna de la Selva | | 5486do | |
| 1000 | 1100 | Peru, Radio La Voz De Bolivar | 5460do | 4755al | |
| 1000 | 1100 | Peru, Radio Libertad de Junin | 5039do | | |
| 1000 | 1100 | Peru, Radio Madre de Dios | 4950do | | |
| 1000 | 1100 | Peru, Radio Maranon | 4835do | | |
| 1000 | 1100 | Peru, Radio Melodia | 5940do | | |
| 1000 | 1100 | Peru, Radio Rasuwilca | 4805do | | |
| 1000 | 1100 | Peru, Radio San Antonio | 4940do | | |
| 1000 | 1100 | Peru, Radio Santa Rosa | 6047do | | |
| 1000 | 1100 | Peru, Radio Tarma | 4775do | | |
| 1000 | 1100 | Peru, Radio Union | 6114do | | |
| 1000 | 1100 | Peru, Radio Vision | 4790do | | |
| 1000 | 1100 | Spain, Radio Exterior de Espana | | 21610me | |
| 1000 | 1100 | Spain, Radio Exterior de Espana | 13720eu | 15585eu | 17595sa |
| 1000 | 1100 | mtwhf | | | |
| 1000 | 1100 | Sat | | | |
| 1000 | 1100 | Sat/Sun | | | |
| 1000 | 1100 | Spain, Radio Exterior de Espana | | 11815sa | |
| 1000 | 1100 | Spain, Radio Exterior de Espana | | 21540af | |
| 1000 | 1100 | USA, EWTN Vandiver AL | 7555ca | 11870sa | |
| 1000 | 1100 | USA, Radio Marti | 5980ca | 9805ca | |
| 1000 | 1100 | USA, WYFR/Family Radio Worldwide | 9550sa | 9715ca | 11855ca |
| 1000 | 1100 | Venezuela, Radio Amazonas | 4940do | mt0909 | |
| 1045 | 1100 | Peru, Radio La Voz de las Huarinjas | | 5059do | |

1100 UTC - 6AM EST / 5AM CST / 3AM PST

| | | | | | |
|------|------|--|---------|---------|---------|
| 1100 | 1127 | Netherlands, R Netherlands Worldwide | | 6165ca | |
| 1100 | 1130 | Bulgaria, Radio Bulgaria | 11800eu | 15800eu | |
| 1100 | 1130 | Peru, Radio Rasuwilca | 4805do | | |
| 1100 | 1145 | USA, WYFR/Family Radio Worldwide | 9355eu | 9715ca | 11855ca |
| 1100 | 1200 | Bolivia, Radio Estambul | 4498do | | |
| 1100 | 1200 | Bolivia, Radio Illimani/Radio Patria Nueva | 6025do | | |
| 1100 | 1200 | Bolivia, Radio Nacional de Huanuni | | 5967do | |
| 1100 | 1200 | Bolivia, Radio San Jose | 5580do | | |
| 1100 | 1200 | Bolivia, Radio San Miguel | 4699do | | |
| 1100 | 1200 | Bolivia, Radio Santa Ana | 4451do | | |
| 1100 | 1200 | Bolivia, Radio Tacana | 4781do | | |
| 1100 | 1200 | Colombia, La Voz de tu Conciencia | | 6010do | |
| | | 5910al | | | |

1200 UTC - 7AM EST / 6AM CST / 4AM PST

| | | | | | |
|------|------|--|---------|---------|---------|
| 1200 | 1227 | Netherlands, R Netherlands Worldwide | | 9715ca | |
| | | 9895ca | | | |
| 1200 | 1230 | France, Radio France International | | 13640sa | |
| 1200 | 1230 | Peru, Radio San Nicolas | 5470do | | |
| 1200 | 1230 | USA, Voice of America | 9885ca | 13715sa | |
| | | 15590ca | | | |
| 1200 | 1300 | mtwhf | | | |
| 1200 | 1300 | Argentina, Radio Nacional RAE | | 11710am | |
| 1200 | 1300 | Bolivia, Radio Estambul | 4498do | | |
| 1200 | 1300 | Bolivia, Radio Illimani/Radio Patria Nueva | 6025do | | |
| 1200 | 1300 | Bolivia, Radio Nacional de Huanuni | | 5967do | |
| 1200 | 1300 | Bolivia, Radio San Jose | 5580do | | |
| 1200 | 1300 | Bolivia, Radio San Miguel | 4699do | | |
| 1200 | 1300 | Bolivia, Radio Santa Ana | 4451do | | |
| 1200 | 1300 | Bolivia, Radio Tacana | 4781do | | |
| 1200 | 1300 | Chile, La Voz Crista | 9635sa | 17680sa | |
| 1200 | 1300 | Colombia, La Voz de tu Conciencia | | 6010do | |
| | | 5910al | | | |
| 1200 | 1300 | Colombia, La Voz del Guaviare | | 6035do | |
| 1200 | 1300 | Colombia, Radio Marfil Estereo | | 5910do | |
| | | 6010al | | | |
| 1200 | 1300 | Cuba, Radio Havana Cuba | 6000na | 6180na | |
| | | 9600na | 11760am | 12000va | 13760eu |
| | | 15120va | 15360sa | | |
| 1200 | 1300 | Cuba, Radio Rebelde | 5025na | | |
| 1200 | 1300 | Ecuador, HCJB Global | 6050sa | 11960sa | |
| 1200 | 1300 | Ecuador, Radio Quito | 4919do | | |
| 1200 | 1300 | Guatemala, Radio Verdad | 4052do | | |
| 1200 | 1300 | Honduras, HRMI/ Radio Misiones Intl | | 3340do | |
| 1200 | 1300 | Honduras, Radio Luz y Vida | 3250do | | |
| 1200 | 1300 | Mexico, XEOI/Radio Mil | 6010do | | |

continued next month

WANT MORE?

Access to the **MTXra Shortwave Broadcast Guide** is free to MTXpress subscribers. If you are a subscriber to the printed magazine, you may add a full year of **MTXpress/MTXtra** to your subscription for only \$11.95. Call 1-800-438-8155 or visit www.monitoringtimes.com to learn how.


North American Aerial Refueling Frequencies

Over the past few years I have documented in this column and on my internet blog (<http://mt-milcom.blogspot.com>) the major changes being made to the 225-400 MHz milair bandplan here in the Continental United States (CONUS). Part of the massive change in frequencies is due to the conversion of most of the 380-400 MHz frequencies from 25 kHz spaced aero frequencies to 12.5 kHz spaced Aero/LMR assignments. Other changes appear to involve new subbands devoted to wideband communications, air traffic control frequency blocks, new nationwide command and control frequencies, and other changes scattered throughout this portion of the UHF spectrum.

In the October 2007 column, I wrote about changes to primary/secondary boom frequencies used on various aerial refueling (AR) routes in CONUS. The biggest change I noted in that column was that some of the 319.500 and 319.700 assignments were being replaced by 256.650 and 343.250 MHz respectively.

Not all of the 319.5/319.7 aerial refueling frequency assignments have changed, but a significant number have. If your local AR route uses 319.500 or 319.700 MHz, you need to program those new frequencies into your scanner, since the old frequencies may go silent at some point.

For the first time since 2003, we present



our latest complete AR frequency list for North America in Table 1.

One of the tips I recommend to Milcom monitors (if they have free memories in their scanners) is to program all of the CONUS aerial refueling boom frequencies into a bank/group, even if a particular route is not within radio range. Monitors have observed that these frequencies are sometimes used off the aerial route as an air-to-air channel by receivers and tankers alike. You might hear some interesting communications that would otherwise be missed if you didn't have all the AR frequencies programmed in.

To aid you in that effort, I have broken out a complete list of all the frequencies noted in MT's AR list into a single list in Table 1. Please note that all the frequencies in both Tables 1 and 2 are in Megahertz (MHz) and the mode is AM.

A few AR boomer frequencies still have not been uncovered. If you have monitored the boomer frequencies for the following routes, please pass them along. Boomer frequencies are unknown for the following aerial refueling routes: AR-115, 208, 214, 221, 222, 223, 224, 657, 658, 44V (Dark Horse East), 45V (Dark Horse West), 46V (Nightstalker East), 47V (Nightstalker West), 48V (Green East), 49V (Green West), 53V (Wardog South), 54V (Wardog North), 55V (Wardog West), 68V, 126V, 127V, 225V, 230V, 231V, 242V, 243V, 304AV/

BV, 305AV/BV, 306AV/BV, and 662V.

❖ Milcom Frequency Changes

We close out this month with a list of the latest frequency changes in the civilian and military aeronautical bands.

- 118.450 Southwest Oregon Regional OR (KOTH) CTAF (ex-122.700)
- 119.100 Tyndall AFB FL (KPAM) North sector below 5000 feet
- 119.775 Tyndall AFB FL (KPAM) South sector below 5000 feet
- 123.600 Fairchild AFB WA (KSKA) Ground control (ex-121.850)
- 127.875 Wallops Flight Facility VA (KWAL) COM GC
- 139.600 Beale AFB CA (KBAB) Supervisory of Flying (ex-138.500)
- 227.400 Lawson AAF/Fort Benning GA Doughboy advisory (ex-244.600)
- 263.150 Tyndall AFB FL (KPAM) Tower
- 269.325 Wallops Flight Facility VA (KWAL) CMSND
- 307.800 Tyndall AFB FL (KPAM) South sector above 5000 feet
- 371.250 Niagara Falls International NY (KIAG) Command Post/Base Operations

So until next time, 73 and good hunting.

TABLE 1. AERIAL REFUELING FREQUENCIES USED IN CONUS

| | | | |
|---------|---------|---------|---------|
| 138.250 | 138.500 | 141.300 | 143.250 |
| 228.250 | 229.500 | 230.050 | 233.725 |
| 235.100 | 235.025 | 235.150 | 236.650 |
| 238.500 | 238.900 | 239.725 | 240.350 |
| 242.050 | 243.450 | 249.500 | 249.525 |
| 252.800 | 252.975 | 255.750 | 255.775 |
| 256.650 | 258.200 | 260.200 | 263.900 |
| 264.325 | 264.900 | 265.050 | 270.200 |
| 271.650 | 274.450 | 275.950 | 276.500 |
| 276.700 | 278.400 | 278.750 | 279.800 |
| 280.400 | 282.000 | 282.550 | 282.700 |
| 283.800 | 283.900 | 284.075 | 284.900 |
| 286.300 | 288.800 | 291.650 | 291.900 |
| 292.600 | 295.400 | 295.800 | 296.000 |
| 297.300 | 303.125 | 305.350 | 305.500 |
| 309.950 | 310.425 | 311.500 | 311.575 |
| 312.225 | 315.900 | 318.000 | 319.500 |
| 319.700 | 320.900 | 324.400 | 324.600 |
| 327.600 | 328.450 | 336.100 | 341.400 |
| 341.750 | 342.550 | 343.250 | 343.500 |
| 344.700 | 348.900 | 349.700 | 352.600 |
| 359.100 | 360.900 | 361.700 | 365.775 |
| 366.300 | 373.600 | 377.700 | 384.600 |
| 394.900 | 396.200 | | |



TABLE 2: NORTH AMERICAN AERIAL REFUELING ROUTE BOOMER FREQUENCIES

Refueling Tracks

| | | |
|--------------|---------|---------|
| AR-1 | 343.500 | 256.650 |
| AR-2 | 283.900 | 256.650 |
| AR-3H | 265.050 | 271.650 |
| AR-3L | 235.100 | 256.650 |
| AR-4A | 344.700 | 292.600 |
| AR-4B | 235.100 | 292.600 |
| AR-5H | 283.900 | 342.550 |
| AR-5L | 256.650 | 278.750 |
| AR-6 | 256.650 | 274.450 |
| AR-7A | 276.500 | 256.650 |
| AR-7B | 236.650 | 256.650 |
| AR-8A | 240.350 | 256.650 |
| AR-8B | 305.500 | 256.650 |
| AR-9 | 238.900 | 292.600 |
| AR-9A | 238.900 | 292.600 |
| AR-10 | 278.750 | 292.600 |
| AR-11 | 235.100 | 320.900 |
| AR-12H | 352.600 | 320.900 |
| AR-12L | 344.700 | 292.600 |
| AR-13 | 238.900 | 260.200 |
| AR-14 | 336.100 | 359.100 |
| AR-16 | 343.500 | 319.700 |
| AR-17 | 276.500 | 320.900 |
| AR-19 | 295.400 | 320.900 |
| AR-20 | 341.750 | 349.700 |
| AR-24 | 295.400 | 320.900 |
| AR-62 Canada | 242.050 | 243.450 |
| AR-80 | 373.600 | 343.500 |
| AR-81 | 373.600 | 343.500 |
| AR-101 | 324.600 | 260.200 |
| AR-102A | 276.500 | 260.200 |
| AR-102B | 276.500 | 260.200 |
| AR-103 | 327.600 | 260.200 |
| AR-104 | 344.700 | 260.200 |
| AR-104M | 344.700 | 260.200 |
| AR-105 | 238.900 | 320.900 |
| AR-106H | 295.800 | 320.900 |
| AR-106L | 305.500 | 320.900 |
| AR-107 | 324.600 | 282.700 |
| AR-108 | 348.900 | 260.200 |
| AR-109H | 343.500 | 320.900 |
| AR-109L | 327.600 | 320.900 |
| AR-110 | 327.600 | 319.700 |
| AR-111 | 348.900 | 319.700 |
| AR-112H | 235.100 | 260.200 |
| AR-112L | 295.800 | 260.200 |
| AR-113 | 283.900 | 260.300 |
| AR-114 | 366.300 | 260.200 |
| AR-116 | 366.300 | 260.200 |
| AR-121 | 229.500 | 258.200 |
| AR-167 | 235.100 | 260.200 |
| AR-200 | 235.100 | 319.700 |
| AR-201 | 336.100 | 319.500 |
| AR-202 | 327.600 | 343.250 |
| AR-203 | 238.900 | 319.700 |
| AR-204 | 324.600 | 282.700 |
| AR-205 | 327.600 | 282.700 |
| AR-206H | 348.900 | 282.700 |
| AR-206L | 235.100 | 282.700 |
| AR-207 | 324.600 | 343.250 |
| AR-209 | 238.900 | 256.650 |

| | | |
|-------------|---------|---------|
| AR-212 | 238.900 | 282.700 |
| AR-216 | 276.500 | 343.250 |
| AR-217 | 283.900 | 282.700 |
| AR-218 | 274.450 | 282.700 |
| AR-219 | 305.500 | 282.700 |
| AR-220 | 274.450 | 282.700 |
| AR-233 | 265.050 | 271.650 |
| AR-255H | 283.900 | 365.775 |
| AR-255L | 327.600 | 365.775 |
| AR-302 | 278.750 | 260.200 |
| AR-307A/B/C | 264.900 | 238.900 |
| AR-309 | 283.900 | 260.200 |
| AR-310 | 352.600 | 319.500 |
| AR-312H | 284.075 | 312.225 |
| AR-212L | 291.900 | 260.200 |
| AR-313/313A | 352.600 | 260.200 |
| AR-314 | 295.800 | 319.500 |
| AR-315 | 343.250 | 236.650 |
| AR-318 | 240.350 | 260.200 |
| AR-321 | 276.500 | 282.700 |
| AR-324 PR | 327.600 | 343.250 |
| AR-328 | 235.150 | 343.250 |
| AR-330 | 305.500 | 260.200 |
| AR-332 PR | 235.100 | 343.250 |
| AR-337/338 | 282.000 | 305.350 |
| AR-355/356 | 320.900 | 238.900 |
| AR-400 | 228.250 | 264.325 |
| AR-406H | 396.200 | 297.300 |
| AR-406L | 297.300 | 396.200 |
| AR-452 | 361.700 | 384.600 |
| AR-453 | 291.900 | 320.900 |
| AR-455 | 336.100 | 291.900 |
| AR-462 | 318.000 | 384.600 |
| AR-505 AK | 315.900 | 263.900 |
| AR-506 AK | 288.800 | 263.900 |
| AR-507 AK | 270.200 | 263.900 |
| AR-508 AL | 288.800 | 263.900 |

Refueling Anchors

| | | |
|------------|---------|---------|
| AR-600 | 348.900 | 319.700 |
| AR-601 | 284.900 | 319.700 |
| AR-602 | 295.400 | 319.500 |
| AR-603 | 238.900 | 319.500 |
| AR-604 | 276.500 | 292.600 |
| AR-606 | 366.300 | 320.900 |
| AR-607 | 235.100 | 320.900 |
| AR-608 | 343.500 | 282.700 |
| AR-609 | 276.500 | 282.700 |
| AR-610A/B | 295.400 | 292.600 |
| AR-611A/B | 255.750 | 275.950 |
| AR-613 | 282.550 | 319.500 |
| AR-614 | 352.600 | 260.200 |
| AR-615 | 295.400 | 260.200 |
| AR-616A/B | 283.900 | 282.700 |
| AR-617 | 324.600 | 343.250 |
| AR-618 | 348.900 | 343.250 |
| AR-619 | 238.900 | 320.900 |
| AR-620 | 238.900 | 343.250 |
| AR-621 | 344.700 | 319.500 |
| AR-623 | 359.100 | 319.500 |
| AR-624 | 366.300 | 319.500 |
| AR-625H | 295.800 | 319.500 |
| AR-625L | 291.900 | 319.500 |
| AR-626 | 235.100 | 292.600 |
| AR-627 | 352.600 | 319.700 |
| AR-628 | 343.500 | 292.600 |
| AR-629 | 296.000 | 360.900 |
| AR-630 | 238.900 | 292.600 |
| AR-631 | 295.800 | 282.700 |
| AR-632 | 238.900 | 282.700 |
| AR-633A/B | 240.350 | 343.250 |
| AR-634 | 235.100 | 319.500 |
| AR-635 | 352.600 | 319.500 |
| AR-636 | 238.900 | 319.700 |
| AR-637 | 291.900 | 319.700 |
| AR-638 | 324.600 | 343.250 |
| AR-639 & A | 291.900 | 319.500 |
| AR-640A | 305.500 | 320.900 |
| AR-640B | 291.900 | 320.900 |
| AR-641A | 295.400 | 319.500 |
| AR-642 | 291.650 | 319.500 |
| AR-643 | 279.800 | 260.200 |
| AR-644 | 324.400 | 319.500 |
| AR-645 | 324.400 | 292.600 |
| AR-646 | 238.900 | 260.200 |
| AR-647 & A | 283.900 | 319.500 |
| AR-648A/B | 238.900 | 256.650 |



| | | |
|-----------|---------|---------|
| AR-649 | 286.300 | 319.500 |
| AR-650 | 295.800 | 260.200 |
| AR-651 | 276.500 | 319.500 |
| AR-652A/B | 249.525 | 255.775 |
| AR-653 | 324.600 | 260.200 |
| AR-654 | 341.400 | 260.200 |
| AR-655 | 276.500 | 343.250 |
| AR-659 | 305.500 | 319.500 |
| AR-667 | 318.000 | 264.900 |
| AR-669 | 394.900 | 384.600 |
| AR-672 | 249.500 | 310.425 |
| AR-674 | 341.400 | 260.200 |
| AR-687 | 280.400 | 377.700 |
| AR-685 | 282.000 | 305.350 |
| AR-716 | 283.900 | 342.550 |
| AR-717AB | 283.900 | 292.600 |
| AR-719 AK | 270.200 | 263.900 |
| AR-720 AK | 276.700 | 263.900 |
| AR-721 AK | 270.200 | 263.900 |
| AR-722 AK | 276.700 | 263.900 |
| AR-723 AK | 278.400 | 263.900 |
| AR-724 AK | 278.400 | 263.900 |
| AR-725 AK | 283.800 | 263.900 |
| AR-727 AK | 270.200 | 263.900 |

VFR Helicopter Refueling Tracks

| | | |
|---------|---------|---------|
| AR-15V | 363.900 | 252.800 |
| AR-18V | 311.575 | 303.125 |
| AR-41V | 230.050 | 260.200 |
| AR-42V | 239.725 | 309.950 |
| AR-117V | 138.500 | 235.025 |
| AR-125V | 138.250 | 252.975 |
| AR-131V | 143.250 | 318.000 |
| AR-132V | 143.250 | 318.000 |
| AR-133V | 141.300 | 311.500 |
| AR-134V | 141.300 | 328.450 |
| AR-135V | 238.500 | 233.725 |
| AR-136V | 233.725 | 238.500 |
| AR-137V | 233.725 | 238.500 |

MTXTRA: AIR REFUELING LISTENERS GUIDE

In NOVEMBER ONLY, MT Express subscribers may download a much more comprehensive Air Refueling Listeners Guide, compiled by Larry Van Horn. The pdf will include refueling tracks/anchors maps, route designators, boomer freqs primary/secondary and Air Refueling Control Point (ARCP)/Exit frequencies of Air Route Traffic Control Centers assigned to each track/anchor. Also included are the call sign and frequencies of the military unit responsible for radar control of refueling operations within the anchor area when known. These are normally an ADCF (Air Defense Control Facility) or CRC/CRP (Control and Reporting Center/Post).

To subscribe, call 1-800-438-8155 or email order@grove-ent.com for more information.

2009 Fed Files Wrap-Up

It's hard to believe that this year has gone by so quickly! And we still have some *Fed Files* topics to put some finishing touches on, so let's go!

❖ More on the Great White Whale

I have to say that no other topic I've covered in this column has generated as much interest as the subject of the September *Fed Files*, the mobile trunked radio system in a motor home that I dubbed The Great White Whale. I have received all sorts of emails about this vehicle and what its true purpose might be. And much like the fictional Moby Dick, this whale is being spotted in various places over and over again.

Shortly after the September issue came out, I heard from a source in Texas that the White Whale was spotted in the Dallas area back in November of 2007. Rumors were that it has something to do with the FAA, and local sources had no knowledge of any visits from the President or any White House officials at the time. It remained in a fenced in lot for several weeks, then disappeared. No one seems to have found the trunked system frequencies while it was there, so it may not have been in continuous operation at the time, or maybe no one was searching.

Some readers have questioned what the purpose of this vehicle is besides the transportable trunked system. Technology now permits the trunked radio system to travel in a much smaller

package than this motor home, so why continue to use such a rig? It does appear that the motor home possibly contains not only the radio equipment and power generator, but also a mobile command post or operations control room within the vehicle. This would provide the agency using this system a base to work out of without much trouble.

So keep an eye out for the White Whale motor home in your area. And in a future *Fed Files* column we'll look into the smaller cousin of the whale that accompanies the President in his motorcades.

❖ Department of Agriculture Frequencies On-Line

Many scanner listeners seek some "official" source for frequencies on the Internet these days. Some local government web sites actually do feature communications frequencies as part of their efforts to keep an open relationship with citizens. But since federal frequencies are not part of the FCC license database, federal monitors have to search elsewhere.



The NTIA Government Master File, the database for all federal agency allocations, is not available to anyone without an official need for the information, and federal agencies rarely, if ever, publish radio communications on their public web sites. There are some exceptions, most notably some of the US Forest Service and their regional fire plans that, with a little digging, can be found on the web.

Over the last few years, many of these plans have had all the radio channels and frequencies deleted. Officially, frequencies such as these are considered "For Official Use Only" and are not supposed to be made available to the general public. However, some do occasionally show up with the frequencies intact. Recently one such plan for the Coleville National Forest in Washington State was found on line. You can check here and see if

it's still available:

www.fs.fed.us/r6/colville/newicc/documents/Colville2009_Radio_UserGuide.pdf

Besides these regional plans, some documents from federal agencies (as they submit their communications budgets or requests for proposals for new radio equipment purchases) will sometimes contain specific frequencies or channel lists. In this case, the US Department of Agriculture has submitted their Strategic Spectrum Plan to the NTIA and it was found available for download here: www.ntia.doc.gov/osmhome/spectrumreform/Spectrum_Plans_2007/Agriculture_strategic_spectrum_plan_Nov2007.pdf

This document has some interesting background on the Department of Agriculture and its use of the radio spectrum. Because of the vast areas over which the Department of Agriculture has responsibility, it has a long history with radio. It started experimenting with wireless communications as far back as the early 1900s, with an early network covering eastern Arizona and western New Mexico. It wasn't until 1931 that the Forest Service officially adopted an HF radio system for communications. That system used the frequencies of 3114 kHz, 3172 kHz, 3250 and 3286 kHz.

Since the early days, the USDA has expanded its use of the federal spectrum to many frequencies in the 30 to 50 MHz, 162 to 174 MHz, and 406.1 to 420 MHz bands.

Probably one the most monitored agencies of the Department of Agriculture is the US Forest Service. They maintain responsibility for national forests and for fighting forest fires in many areas, not only on federal property, but also assisting state and local agencies to fight fires that threaten large areas. We covered some of the Forest Service allocations that can be used during forest fire fighting events back in the May 2006 edition of *Fed Files*.

One specific department of the USDA that has some frequency allocations listed in this document is the Office of the Inspector General. The OIG is responsible for many law enforcement and internal investigation of the USDA and has some specific allocations for these operations. Here are some of the frequencies used by the OIG:

| | | |
|----------|----------|----------|
| 164.1375 | 166.1250 | 167.3500 |
| 167.3375 | 167.3625 | 167.3750 |
| 167.9750 | 168.0250 | 168.1000 |
| 168.1250 | 168.1500 | 168.1750 |
| 168.4125 | 168.6000 | 168.6750 |
| 168.7000 | 168.7250 | 168.7750 |
| 168.9750 | 169.1750 | 169.9500 |
| 170.4750 | 170.6000 | 170.7000 |
| 170.9750 | 172.2500 | 172.3250 |
| 173.2500 | | |

All of these frequencies can be used in analog or APCO P-25 digital modes. Encryption is



certainly available for use by the OIG operations.

An interesting item of note in the above list: the original list in the USDA document had three unusual frequencies listed. They listed 167.3450, 167.3575 and 167.3600 MHz in the table containing the OIG allocated frequencies. These listed frequencies are most likely a typographical error and not the actual frequencies.

Also noted in this document was the official confirmation that the USDA OIG is a subscriber to the DHS Customs nationwide VHF radio network. The USDA agents probably use a unique call sign when communicating with the CBP dispatch center in Orlando, so keep an ear on 165.2375 MHz as well. Also mentioned is the possibility of the USDA OIG being a user of the federal Integrated Wireless Network (IWN) at some future date.

In addition to the frequencies for the OIG, there were references to some other USDA frequencies as well. The National Resources Conservation Service (NRCS) uses some UHF frequencies for engineering support for remote operations:

411.2500 411.3000 411.3250
411.4250 415.0000 415.5000

NRCS land-mobile operations can utilize 163.7125 and 168.6125 MHz. The Soil Climate Analysis Network (SCAN) and the Snow pack Telemetry Network (SNOTEL) both utilize these VHF low-band VHF frequencies for non-voice data:

40.5300 40.6700 41.5300
41.6100 44.2000 45.9000

The SNOTEL network has master control stations located in Boise, ID and at Hill AFB in Ogden, UT. The USDA report noted that the Ogden control station would be relocated to the US Army's Dugway Proving Ground, due to local noise issues. A third SNOTEL master station is located in Anchorage AK and is operated under BLM management.

❖ VHF Mystery Networks

As federal operations continue to move from analog to digital modes of operations, some new frequencies are being heard as well. In some cases, these new frequencies are all running with encrypted traffic, so figuring out who is using them and for what remains a mystery of sorts. Here are some recent examples.

From the Florida panhandle, I have received reports of a "linked" VHF federal radio network. The repeaters all seem to key up with a common input frequency. The voice traffic has all been P-25 digital, but multiple Network Access Codes (NAC) have been noted. Much traffic has been using a NAC of N167, but some traffic is now using a NAC of N330. The frequencies used are:

167.2375 167.3125 167.4125
167.4375 167.4875 167.7125 167.7875
168.8875
168.9250 169.7250 169.7625

From the New York City area, listeners have heard simultaneous repeater outputs on these frequencies:

167.4625 167.5875 171.6125
172.1125 172.2125 172.7625

This linked repeater network has a possible

input of 162.1500 MHz and uses a P-25 NAC of N207. Reports are that these repeaters have been heard around the New York City and Atlantic City/Philadelphia regions. One source has stated that this is a Justice Department network.

Also from the New York City and other areas, these linked P-25 repeaters also carry mostly encrypted traffic:

167.7250 167.7750 171.6875
170.3375 171.7500 171.9875
172.2125

This repeater network has been heard using a P-25 NAC of N95C. One source seems to indicate the Department of Homeland Security possibly operates this network, but that could indicate any number of DHS agencies.

So what is the big mystery about these VHF networks? The biggest mystery is who is using them and for what purpose. In many cases the frequencies used are Justice Department allocations, but some frequencies are new allocations with no previous activity noted. The P-25 NAC codes are new to most monitors and have not been associated with any particular agency.

Another mystery is, why are all these frequencies linked together? Older FBI radio networks often had the ability to key up multiple repeaters from a single input frequency, depending on how the system was set up. The older analog Border Patrol system also had many VHF repeaters that were tied together for wide-area coverage if needed. These new P-25 networks appear to be trying to cover wide areas without the users having to switch channels multiple times as operations move around.

As previously reported in the March 2009 *Fed Files*, the Justice Department is making big changes in its communications networks, and part of that change is a trend towards multiple repeaters serving a wide area. This appears to be a prelude to local VHF trunked systems, and potential new sites as part of the federal Integrated Wireless Network (IWN).

❖ UHF Mystery Networks

Some recent postings on-line from listeners in Colorado and Washington DC have prompted some speculations about some new federal UHF radio systems.

In Gilcrest, Colorado, (north of the Denver area) a listener reported continuous "static" on these frequencies:

407.4250 407.4750 407.5000
416.4250 416.4500 416.5000

The report was that these frequencies carried digital traffic that was not decodable with APCO P-25 scanners. A quick look at the frequencies shows that 407 and 416 frequencies are 9 MHz apart, which should be the standard repeater offset for the federal UHF band. Since signals are being heard on both sets of frequencies, one can't yet assume which are the repeater inputs and which are outputs (I have seen them used both directions). Also, there were no reports of any known format of trunked radio system control channels, so whether or not this is a trunked radio system remains to be seen.

This could be a new system that is being tested and might be carrying a digital "test pattern" on the repeaters to check coverage and signal problems. That would explain the continuous noise

being heard. The frequencies that have been heard have also been used in other UHF trunked systems, mostly at military installations.

Another listener in the Washington, DC area has asked about these frequencies, also carrying un-decodable digital-sounding traffic:

408.2250 408.2750 408.4625
408.5250 408.5375 408.6250
409.0500 417.2750 417.4625
417.5250

Some reports in response to the frequencies posted seemed to indicate this system has been on the air for a while, although I have not heard it when I was in the DC area last. Some speculated that this system has something to do with DARPA (Defense Advanced Research Agency, www.darpa.mil/), but I have no confirmed information on the use of these frequencies.

Anyone who might have any information on these or any other federal mystery networks, please feel free to pass them along to me at the *Fed Files*. All submission sources will be kept confidential, if desired.

That's all for this year in the *Fed Files*. I'll be back next January with more federal monitoring. See you then!

Antenna Designer
New Version 2.1 for Microsoft Windows 95 and 98
Computer program helps you design and build 17 different antennas from common materials. Based on Antenna Handbook by W. Clem Small.

Only \$39.95 Send check or money order to:
\$5 S/H on all orders
CA residents add 8.5%
Shipped on CD ROM

Small Planet Systems
623 Mangels Avenue
San Francisco, CA 94127

www.smallplanetsystems.com 415-337-9394

CC WiFi Internet Radio



**Receive Your Favorite Stations*
Over 14,500 Available Worldwide**

- Excellent, Clear Audio
- Works on Any Broadband Signal
- Real, MP3, WMA Formats
- 99 Presets
- Wireless or Direct Connection via Ethernet Jack, Line-Out, Headphone, Signal Strength Indicator
- No Subscription Fee

* Your favorite station must stream audio. You must have broadband internet service.

\$199⁹⁵

C. CRANE

Free Catalog

800-522-8863 • ccrane.com

“Black Boxes” Cockpit Voice and Flight Data Recorders

When an airliner crashes, we hear on the news about searches for the Cockpit Voice Recorder (CVR) and the Flight Data Recorder (FDR). These are the so-called “black boxes.” The recorders can contain valuable, last-minute information that assists in reconstructing the events leading up to and during a crash.

Airliners, corporate jets, and some others are required to have the two recorders. The CVR records crew conversations, public address announcements, radio transmissions, and sounds heard in the cockpit area. The FDR records up to 88 parameters, some of which are listed below.

Both recorders are usually installed in the aircraft tail section to improve survivability during a crash. As can be expected, traditional CVRs use magnetic tape and newer ones use digital technology with solid state memory.

Guess what? The “black boxes” aren’t black! They are either bright orange or bright yellow. They also have reflective tape on them to facilitate locating them under water. This would also help at ground crash sites at night using spotlights.

Let’s take a closer look at this interesting subject!

❖ The NTSB Component

“The National Transportation Safety Board is an independent Federal agency charged by Congress with investigating every civil aviation accident in the United States and significant accidents in the other modes of transportation – railroad, highway, marine and pipeline – and issuing safety recommendations aimed at preventing future accidents.”

The NTSB seeks to determine “the probable cause of all U.S. civil aviation accidents and certain public-use aircraft accidents.” This is why you always hear them mentioned on news broadcasts whenever there is a U.S. airliner crash. For more, see www.nts.gov/Abt_NTSB/history.htm. (All quotes in this and the next two sections are from NTSB documents.)

Among other things, “The NTSB is responsible for maintaining the government’s database of civil aviation accidents and also conducts special studies of transportation safety issues of national significance.”

The recovered CVRs and FDRs from crash sites are taken to the NTSB Vehicle Recorder Laboratory in Washington, D.C. for data extraction and analysis. The voice transcripts and flight data reports are combined with FAA communications and radar data archives, eye-witness accounts, the weather at the time, maintenance records, crash scene/debris field analysis, time-consuming and

labor-intensive aircraft reconstructions, even microscopic examinations and more, all in an attempt to determine the probable cause of a crash.

The NTSB would like an additional regulation requiring airliners to “Install crash-protected image recorders in cockpits to give investigators more information to solve complex accidents.” “This information is critical in determining whether there had been subtle indications of an approaching emergency, whether the crew followed published procedures, and whether or not any of the crew’s responses to the emergency were effective.”

❖ Brief FDR History

After World War II, the value and importance of crash-survivable flight recorders for airliners became apparent, and efforts began to create workable designs. There were various delays, one being lags in technology to meet the stringent requirements. Things didn’t really get rolling until the late 1950s. The first FDRs were designed to record altitude, airspeed, heading, vertical accelerations, and time.

The next big jump was in late 1972 when additional functions to be recorded were added to FDRs for certain planes with newer recorders.

The FDRs manufactured up to this point employed a single-use metal foil tape onto which the data were imprinted. “Time was determined by foil movement, which typically advanced at a rate of 6 inches per hour. This often resulted in an entire accident sequence being recorded within a 0.1 inch of foil movement. Investigators recovered the recorded information by optically reading the scribed markings through a microscope, and then converting the displacement of the scribed marks from the reference line to engineering units. This process was very time consuming and required a significant amount of reader interpretation.”

The introduction of solid state digital recorders (DFDRs, sometimes called SSFDRs) brought the advantages of little maintenance and much easier access to data.

Requirements remained pretty much the same until rule changes in 1987 and 1988, in which the remaining foil-type FDRs were replaced and yet more parameters were added. These included “pitch and roll attitude; thrust for each engine; flap position; flight control input or control surface position; lateral acceleration; pitch trim; and thrust reverser position for each engine.” Various planes were required to move up to 17 or 28 parameters: Some older planes like the Boeing 707, 727, and 737 continued to operate under the 1957 rules.

In 1997 through 2002, things evolved even



An example of a combination CVR/FDR unit. The cylindrical structure on the end is the Underwater Locator Beacon (ULB) which can send pings once per second for a month down to depths of 14,000 feet when activated by submersion in water. Photo courtesy L3 Communications

more. DFDR parameters were increased to 22, 34, 57, and 88 – depending on the date of manufacture of the plane.

A fairly detailed but interesting history may be found at www.nts.gov/events/journalist/Article_from_JRN0601.pdf

Brief CVR History

The FAA called for installation of Cockpit Voice Recorders in certain airliners by the mid to late 1960s, since Flight Data Recorders alone did not provide enough information.

“The CVR requirements were extended to multiengine turbine-powered aircraft capable of carrying six or more passengers and requiring two pilots” and “Flight crews would be required to use existing CVR hot-microphone systems below 18,000 feet.”

On tape units, 1/4-inch tape holding six or eight tracks were common. One track was recorded at a time, sequentially progressed through the tracks, and then started over – overwriting old data by erasure followed by record.

Eventually, solid state CVRs with even greater memory capacity were developed with advances in solid state memory devices.

❖ CVR Audio Channels

CVRs have four record channels, each recording from different sources simultaneously, and some of which are combined in the Captain’s and First Officer’s audio panels and outputted to the CVR.

The Cockpit Area Microphone in the overhead panel captures voices and other sounds in the cockpit area. Crewmember “hot” headset microphones are used to capture voices and sounds

even when they are not being used for talking on the radio or intercom.

Both sides of radio communications are captured. This includes “company,” ramp control (128.825 - 132.00 MHz), and Air Traffic Control frequencies – Ground, Tower, Departure, Air Route Traffic Control, etc. (118 - 136 MHz).

The CVR also captures data link communications (if installed), public address and aircraft interphone voice, and audio from navigation or approach aids, ATIS, AWOS, etc. when introduced into the headset or speaker. (Data link info: www.answers.com/topic/controller-pilot-data-link-communications)

Recovered CVR Audio

The recovered audio is used to prepare written transcripts, many of which are made available to the public. Reading some of them can draw you in like reading a good novel. In a way, it’s like “hearing” the verbal exchanges between people who may soon die. Reading them can also be disturbing, so read them with caution.

Here is a transcript snippet from Alaska Airlines, Flight 261, January 31, 2000:

16:09:13 CAPT: Let’s do that.
16:09:14 [Sound of click]
16:09:14 CAPT: This’ll click it off.
16:09:16 [Sound of autopilot disengaging] [Sound similar to horizontal stabilizer in motion tone]
16:09:16 CAPT: You got it?
16:09:26 CAPT: It got worse.
16:09:31 CAPT: You’re stalled.
16:09:32 [Sound of air frame vibration]
16:09:33 CAPT: No no you gotta release it ya gotta release it.
16:09:34 [Sound of click]
16:09:52 CAPT: Help me back help me back.
16:09:54 F/O: Ok.
16:09:55 RT CAPT: Center Alaska two sixty one we are uh in a dive here.
16:10:01 RT CAPT: ... and I’ve lost control, vertical pitch.
16:10:01 [Sound of overspeed warning] (continues for 33 seconds)
16:10:05 LA30: Alaska two sixty one uh say again sir.

Many CVR transcript Internet sites and individual transcripts may be found by going to www.google.com and then entering “CVR Recorder Transcripts” but with no quotes. For the NTSB “Accident Database & Synopses,” see www.nts.gov/nts/query.asp.

❖ FDR Data

The regulations covering the number of data parameters to be captured on airliner FDRs are involved and vary with aircraft date of manufacture and other factors. Essentially, all airliners manufactured after August 19, 2002 must be equipped to record 88 parameters. Listed here are the first twenty from such a list to offer an idea of what is recorded: Time, Pressure altitude, Indicated airspeed, Heading, Normal acceleration (Vertical), Pitch attitude, Roll attitude, Manual radio transmitter keying or CVR/DFDR synchronization reference, Thrust/power of each engine, Autopilot engagement status, Longitudinal acceleration, Pitch control input, Lateral control input, Rudder pedal input, Primary pitch control surface position, Primary lateral control surface position, Primary yaw control surface position, Lateral acceleration, Pitch trim surface position, Trailing edge flap or



An example of a Cockpit Voice Recorder (CVR). They record four channels of audio that includes radio transmissions, cockpit voices, and other sounds. Photo courtesy National Transportation Safety Board (NTSB)

cockpit flap control selection ...

A Flight Data Acquisition Unit (FDAU) precedes the FDR by collecting the analog, the discrete (such as engaged / not engaged), and the digital parameter data from numerous aircraft systems and sensors. The FDAU converts the data into digital binary format and passes it on to the FDR.

The binary data is a long series of ones and zeros. Parameter samplings are serially multiplexed, which means one parameter is sampled at a time in a predetermined sequence – one after the other. Some parameters that are typically slow to change are sampled less frequently than others. All this is a very precise, timed operation.

The digital data stream is divided into sequential segments called “frames” and “subframes.” Each frame has four subframes. Subframes are recorded at one per second and each is made up of 32, 64, 128, or 256 “12-bit words” – depending on the FDR model. Each flight data parameter has an assigned “word slot” / location within a subframe.

Each subframe begins with a 12-bit synch word. With no synch words, the data would become meaningless, since no start or end points would be identified.

After an FDR recovery, the extracted data stream is turned back into terms that are more understandable, called “engineering units” and “discrete states.” These are then charted on graphs vs. time in order to be useable by investigators. Here is a good example: www.nts.gov/Dockets/Aviation/DCA-09MA026/418135.pdf

Combination Units

Combination units are manufactured with CVR and FDR functions in one unit. They may eventually replace the separate CVR and FDR units. In such instances, there must be two combination recorders installed, one in the tail section and one near the cockpit, and they must be powered by separate electrical systems. Two combination recorders will provide redundancy and thus maximize recovery of cockpit voice and flight data after a crash.

The two-page description and specifications of this combination unit by L3 Communications can be a lesson in itself:

www.1-3ar.com/PDF_Files/MKT047_FA2100CVDR.pdf

Overwriting Data

As CVRs and FDRs operate, they continuously overwrite the oldest data with new data.

If an aircraft has an “incident,” as opposed to an outright crash and is able to land, important data can be overwritten with useless data while on the ground sitting on the runway, while taxiing, and even while parked if the recorders are not promptly deactivated by a possibly shaken crew with other things on their minds.

Also, if the flight crew recovers after an airborne incident but continues to fly for a time, relevant data can be overwritten.

CVRs using a tape loop with a thirty-minute capacity have greater limitations compared to newer units with a two-hour or greater solid state record time before relevant data is overwritten.

❖ QAR, A Third Black Box?

Well, not really – but almost. Quick Access Recorders are a third recorder, but they are not made to be crash-survivable like the other recorders. However, some do survive and are analyzed by crash investigators. The QAR usually can record many more parameters and at faster sampling rates than can the FDR.

The “Quick Access” means that the stored data can be quickly accessed and downloaded by airliner ground crews. The data is recorded on easily removable optical disks or memory cards which can be read by desktop computers for analysis. This is a regular occurrence rather than one intended for crash investigations. Some systems can send the data, encrypted and compressed, via wireless Internet in fifteen to thirty minutes.

The analysis of QAR recorded data is intended to identify in-flight parameter excursions outside of pre-defined / “normal” ranges. In simple terms, this is used to help identify components or systems needing attention, to help spot potentially problematic trends, and to improve efficiency, flight operations, and safety.

❖ Concluding Thoughts

Some have considered a system to allow in-flight emergency CVR/FDR/QAR data dumps to a satellite system when initiated by the pilot, or following rapid depressurization, explosion, emergency transponder settings, or whatever conditions were set as a triggering event. At this time, it appears to be too expensive in terms of infrastructure development, satellite use costs, and the rare need. That is to say, a poor cost / benefit ratio.

I hope that the next time you hear about “black boxes” in the news, you can draw from the information here to have a better understanding and fuller appreciation of the topic.

Books by Ernest H. Robl:

THE BASIC RAILFAN BOOK

UNDERSTANDING INTERMODAL

THE POWDER RIVER BASIN

Detailed descriptions at

<http://www.robl.w1.com>

LF Receiving Antennas, Part II

We resume our discussion this month on LF receiving antennas. This subject began back in September, and I had originally planned to run this 2nd installment last month. However, there was not enough room to run it as a single piece along with the news, loggings, and mailbag items we had last month so it was saved until now. Thanks for sticking with us, and I apologize for the inconvenience.

Multi-turn Tuned Loops are a time-honored design worth discussing in this two-part series on receiving antennas. These loops usually consist of a box-shaped frame wound with several turns of small diameter wire. The windings are tuned to resonance at LF with a variable capacitor connected across the windings. A separate, one-turn winding is placed in the approximate middle of the tuned winding to provide a low impedance (50-100 ohm) "pickup link." It is this link, and not the multi-turn winding, that connects to the receiver via a coaxial cable.

Multi-turn loops are easy to build, and you can get plans for one by ordering a reprint of the September 1992 *Below 500 kHz* column from *Monitoring Times* – cost \$3, plus an SASE. (An optional preamp for this same antenna was published in the November 1993 column.) Such a loop can be set on a tabletop and rotated to favor (or null) a particular signal. One *MT* reader I spoke with mounted his loop on an old music stand and is achieving excellent results.

One disadvantage of tuned loops is that they must typically be used indoors. Most wire-wound designs are too fragile to mount outside in the elements, and even if you did, there is the problem of tuning it to resonance. Whenever you move your receiver more than 10 kHz or so, the loop should be re-tuned for best performance. It is possible to employ remote tuning schemes, but such arrangements can become complicated and are subject to change with the weather. Some promise has been shown with varactor diode tuning, but getting a wide enough capacity range is usually difficult. The good news is that wire loops seem to perform very well indoors!

Finally, let's discuss **Broadband Shielded Loops**. These antennas have a number of advantages that make them popular with DX-ers. Among the advan-

tages are: Low noise pickup, good sensitivity, tune-free operation, and mechanical stability.

Shielded loops contain only one turn of wire, and, as the name indicates, they are electrically shielded, except for a very small portion (an inch or so) at the top of the loop. Shielding reduces the antenna's susceptibility to electrical field noise, such as static crashes.

Shielded loops are typically made of a rigid or semi-rigid material such as "hardline" coaxial cable or copper pipe, so they can be easily mounted outdoors on a simple mast and turned with a TV rotor.

These loops typically contain a wideband (10-500 kHz) preamplifier, so there's no need for tuning the antenna as you move across the band. In a well-designed system, the preamp begins "rolling off" above 400 kHz and becomes nearly "deaf" above 500 kHz to minimize AM broadcast overload.

Would you like to build a shielded loop? If so, I highly recommend visiting VE7SL's web page at <http://members.shaw.ca/ve7sl/burhans.html>. Here, you'll find specific details for building a high performance loop and its associated preamp/coupler. This project is well within the skill set of most experimenters.

Another excellent reference on loop antennas is the late Joe Carr's *Loop Antenna Handbook*, available from Universal Radio Research, 6830 Americana Parkway, Reynoldsburg, OH 43068 (www.universal-radio.com). It contains over 130 pages of descriptions, plans and theory for many types of loop antennas.

❖ Loggings

As many of you already know, I also serve as editor of the *DX Downstairs* column for the Longwave Club of America's *Lowdown* journal (see www.lwca.org). This has allowed me to give something back to this respected publication, which has done so much to promote the longwave hobby since 1974. The *DX Downstairs* column is mainly devoted to reader loggings. To streamline the process and present the most interesting information, I cross-post many of the logs I receive via *MT* in the *DX Downstairs* column, and vice versa.

This month's loggings are provided courtesy of Richard Palmer (AZ). If you would like to submit loggings, simply send them via e-mail to the address at the top of this column. We have a free Loggings Template that can be obtained by simply requesting it at the same address (or download it at www.monitoringtimes.com/Below_500_kHz-Loggings_Template.pdf). I look forward to hearing from you as we get into the

"DX season" on the longwave band!

| FREQ | ID | ST/PR/ITU* | CITY |
|-------|-----|------------|-------------------|
| 203 | YBL | BC | Campbell River |
| 207 | YNE | MB | Norway House |
| 209 | HGT | CA | Hunter-Liggett MR |
| 212 | OVE | CA | Oroville |
| 214 | CHX | MEX | Choix |
| 218 | PR | BC | Prince Rupert |
| 220 | VI | CA | Visalia |
| 222 | CUW | MEX | Chihuahua |
| 233 | ALJ | AK | Johnstone Point |
| 238 | KT | NZL | Kaitaia |
| 242 | ZT | BC | Port Hardy |
| 260 | NF | NFK | Norfolk Island |
| 270 | FA | SMO | Faleolo |
| 271 | SC | CA | Stockton |
| 280 | IPA | PAQ | Easter Island |
| 282.5 | RT | OCE | Rurutu |
| 283 | DUT | AK | Dutch Harbor |
| 284.5 | MH | OCE | Manihi Atoll |
| 307 | NA | FJI | Nausori |
| 311 | CFS | AUS | Coffs Harbour |
| 332 | POA | HI | Pahoa |
| 332.5 | AA | OCE | Anaa |
| 335 | CC | CA | Concord |
| 338 | LSA | TX | Lamesa |
| 341 | ELF | AK | Cold Bay |
| 347 | LFA | CA | Merrill |
| 349 | TP | OCE | Takapoto |
| 351 | NO | NV | Reno |
| 352 | RG | CKH | Raratonga |
| 353 | LLD | HI | Lanai |
| 368 | GYM | MEX | Guaymas |
| 370 | PAI | CA | Los Angeles |
| 372 | RU | OCE | Raiatea |
| 374 | LV | CA | Livermore |
| 376 | NP | OCE | Napuka |
| 382 | GRN | MEX | Guerrero Negro |
| 388 | JUG | TX | Mesquite |
| 391 | DDP | PR | San Juan |
| 414.5 | RPB | KS | Belleville |
| 415 | CBC | CYM | Cayman Brac |

* For a complete list of ITU codes, see www.wordiq.com/definition/ITU_letter_codes

We have something a little different planned for next month. Ever wonder if you can communicate appreciable distances using the Earth as a transmission medium? Well, according to one experimenter who's been working on this for years, it is indeed possible, and it requires little more than an audio amplifier and some metal rods driven into the Earth.

He has achieved distances up to about a half-mile with this technique, and cites one experimenter who achieved a distance of 10 km (6.2 miles) with a high-powered system. If you want a preview of this subject, try searching online for the terms "Ground Radio" and "Earth Wireless Telegraphy."

See you next month!




Figure 1. Multi-turn tuned loops often surpass the performance of wire antennas, particularly in noisy RF environments.

The Filipino Monkey - Malicious Unlicensed Jamming

The most notorious pirate jammer of all time has for some reason received very little attention in shortwave radio circles. This one is not a hobby pirate, but is instead an intentional jammer who broadcasts malicious interference on naval communications frequencies. It first appeared over a decade ago during the Persian Gulf War. In fact, a recording of the malicious jamming during the Persian Gulf War is posted on U-Tube, so anybody can listen to the dangerous antics of this station. www.youtube.com/watch?v=BYHZjnDyWVI

This sort of interference, with profanity and taunting reminiscent of Monty Python, has by no means been restricted to the Persian Gulf. From time to time it has been noted on various frequencies related to naval communications. The worldwide scope of these broadcasts suggests that this is not one single jammer. Instead, the "Filipino Monkey" has become a generic description for malicious interference to utility station transmitters.

The notorious Filipino Monkey finally got some national attention in the *Wonkette* gossip blog from Washington, DC in early September. It was widely reported in the worldwide press that the Coast Guard had attacked a boat on the Potomac River in Washington. Radio broadcasts of bullets flying were allegedly heard by CNN and other national news organizations. Reports of a Coast Guard boat speeding to catch some sort of intruder vessel on the Potomac got prominent worldwide coverage for one day.

White House Press Secretary Robert Gibbs was forced to comment somewhat sarcastically on these events at a press briefing for White House reporters. Gibbs attributed the action on the river to a "naval exercise," but many news organizations were unable to confirm a scheduled "naval exercise" on the Potomac in Washington, DC. *Wonkette*, hardly a mainstream press source, quickly blamed the malicious broadcasts on "The Filipino Monkey."

Their reporting discovered a similar incident in the Straits of Hormuz on January 14, 2008. Malicious naval broadcasts caused a small military crisis when five small Iranian patrol boats unexpectedly began to maneuver around United States warships in transit through the Straits of Hormuz. Malicious broadcasts on ship communications frequencies said that the small boats were attacking and that they were about to explode.

In the UK, *The Guardian* newspaper blamed the confusion on the Filipino Monkey's aggressive broadcasts on naval communications frequencies. The *Guardian* quoted retired naval captain Rick Hoffman with his analysis. Hoffman said in *The*

Guardian that, "For 25 years, there's been this mythical guy out there who, hour after hour, shouts obscenities and threats. He used to go all night long. The guy is crazy. Could it have been a spurious transmission? Absolutely."

The United States and Iran released two different videos of this incident. The USA version edited in threats from *The Filipino Monkey*, but the Iranian version lacked such information. The US Navy told *The Guardian* that its ships came "within seconds" of firing at the Iranian vessels. United States President George W. Bush filed a formal complaint to the Iranian government, warning Iran of potentially "serious consequences" of such behavior.

Fortunately, neither incident in the Straits of Hormuz or the Potomac caused an actual naval battle, damage, or loss of life. But, it does remind us that it is extremely foolish for any unlicensed broadcaster to operate on military frequencies or to transmit malicious interference on any licensed radio frequency.

There have been occasional pirate radio examples of malicious interference over the years. The most notorious was Lad, the young operator of **The Voice of the Night**. It turned out that despite his intentional jamming of other North American pirates with a series of broadcasts titled the "Kill George Zeller" show, Lad was not actually dangerous on the HF bands. He did, however, receive a sentence of many years in the Kentucky State Prison for probably unrelated physical abuse of his girlfriend in Lexington, KY.

This confluence of events reminds us that even unlicensed pirate broadcasters universally condemn unsound operating practices that include malicious jamming of other radio broadcasters.

❖ **MAC Shortwave QSLs**

Aside from WBNY, the second biggest phenomenon on North American Pirate bands during the past year has been Paul Starr's widely heard **MAC Shortwave**. Sometimes assisted by a young boy called Ultra Man, Starr's well produced replica of top forty radio broadcasters of the 1960s is among the best produced pirate radio stations of all time. But, until recently, QSLs from **MAC Shortwave** have been extremely sparse. As we see here this month, that policy has dramatically changed. Many DXers have been delighted to receive the new **MAC Shortwave QSLs**.

❖ **What We Are Hearing**

Monitoring Times readers heard more than two dozen different pirate radio stations this month. You can hear them too, if you use some

simple techniques. Pirate radio stations never use regularly announced schedules, but shortwave pirate broadcasting increases noticeably on weekends and major holidays. You sometimes have to tune your dial up and down through typically used pirate radio frequencies to find the stations, but more than 95% of all North American shortwave pirate broadcasts are heard on **6925 kHz**, plus or minus 30 or 40 kHz.

Big Dog Radio- This new station features a classic rock music format and barking dogs as sort of an interval signal. (Report to FRW and FRN)

Captain Morgan- The Captain mixes audio from the old Twilight Zone TV show with his rock music broadcasts. (captainmorganshortwave@gmail.com)

Channel Z Radio- Their professionally produced rock music shows are distinctive. (Belfast and channelzradio@gmail.com)

KUSA- Less Whitehouse's rock music podcast is audible on the internet at <http://kusaradio.com/Welcome.html> and also sometimes on the pirate bands. (contact@kusaradio.com)

Liquid Radio- Techno rock dance music is featured on most broadcasts, so **WMPR** is not the only pirate with this format. (wwrbfm@gmail.com)

MAC Shortwave- Paul Starr and Ultra Man still use the old Radio Prague interval signal as a lead-in to their rock and novelty music shows. (macshortwave@yahoo.com)

Mystery Radio- Among the best heard European pirate stations is this one on 6220 kHz. With improving winter propagation, you might hear it around your local sunset on weekends. (radio6220@hotmail.com)

North Sea Radio Ohio- Little is known about this new station that has featured pirate music and an unusual station name. (unknown)

Northwoods Radio- If you hear a loon call interval signal, you probably have Jack Pine Savage's rock music station "from the Great Lakes." He sometimes gives IDs in Morse code. (northwoodsradio@yahoo.com)

Outhouse Radio- Normally they feature a mix of rock and novelty music, but they have been known to relay other pirates. (None, asks for reports to the FRN web site and has QSLed)

Pirates Week Relay- Relays of Ragnar Daneskjold's wonderful weekly pirate news podcast are still appearing on the pirate bands from time to time. If you miss the relays, you can hear the show at www.piratesweek.info/ on the internet. (None)

Radio Casablanca- QSL's have arrived from this 1940s big band music station. (radiocasablanca@gmail.com)

Radio Ga Ga- Uncle Bob's pirate with rock music and SSTV digital pictures has become one of the most active current stations. (popeonthepoint@gmail.com)

Radio Mushroom- Their classic rock format has now been broadcasting for three months. Some DXers have received QSLs. (radiomushroom@gmail.com)

Radio Station XXP- Classic rock music is their normal format. (radiostationxxp@gmail.com)

Scott Joplin Radio- Given the station name, it is no surprise that piano music is their main focus. (unknown)

The Crystal Ship- For decades, the Poet's rock music and leftist political commentary have gone out on the pirate bands. He still normally uses odd frequencies such as 6876 kHz. (Belfast)

Thinking Man Radio- This new rock music station uses a slogan of "never be afraid to sit a while and think." (Thinkingmanradio@gmail.com)

Uncle Deercamp Relay- Some pirate has been relaying this "morning zoo" podcast from Detroit. (unknown)

Undercover Radio- Dr. Benway is back with rock music and tales about his travel adventures. ((Merlin and uses

Continued on page 61

Transversion Conversions and Other Diversions

I am lucky enough to be based in the Northeastern region of the good old US of A. This part of the country is quite a hotbed of amateur radio fun on VHF and above. I live in the signal footprint of the Mount Airy VHF Radio Club, more commonly known as the Pack Rats. I live within a short drive of several hams who have very serious (and very large) Moon Bounce antenna systems in their yards. It's a great part of the world to live in if you have a hankering to work the world using the frequencies from 50 MHz up through Visible Light.

When the Technician Class license superseded the Novice ticket as the entry level path to ham radio fun, I was surprised to find that most folks never strayed beyond the limits of 2 meters or perhaps 432 MHz if they started out with a dual band handi-talkie. Hams have the opportunity to play in the frequency ranges running all the way up through 275 GHz and beyond. Much of this is largely uncharted territory for all but a handful of dedicated experimenters.

If you decide to get into VHF/UHF radio in the upper regions of what is possible, you have probably noticed that it isn't all that easy to find rigs above 1.2 GHz in your handy ham radio catalogs. You can get to just about anywhere in the upper spectrum if you have a good HF or 2 meter transceiver and one or more *transverters*.

Think of a transverter as a black box (actually, in some cases, it *is* a black box) that takes the signal from the transmitter portion of your rig and converts it up to a higher frequency. Likewise, the transverter also takes the higher received frequency and converts it down to something your existing rig can run with. These two functions are managed through a common local oscillator to keep everything coordinated. It is really no more complicated than that.

Transverters are sold (or can be built from a kit or parts) to take a radio with a 28 MHz IF and run it up to 50 MHz, 144 MHz, 222 MHz, or 432 MHz. VHF transceivers operating at 144 MHz can be used with transverters to take your signal up to 902 MHz, 1.2 GHz, 2.3 GHz, 3.4 GHz, 5.7 GHz, and even the 10.3 GHz bands.

The advantage of using transverters is obvious. Usually costing between \$300 and \$500 new, they are still cheaper than buying or building a dedicated transceiver for each of the above mentioned bands. Also, many transceiver designs incorporate filtering and preamplification that maximizes the signal quality of the desired frequency range.

So what are the downsides? As a general rule, transceivers take a minimal signal out of your existing rig and only amplify it marginally

while taking it up the band. That means most practical applications will require you adding a stage of amplification at the higher frequency range. Also, remember, as you go up in frequency, managing feedline and even connector losses becomes an important consideration. So you may find yourself tossing another wad of cash into the mix to get that signal out to the world. Still, in most cases, transverters are still the least costly way to add microwave bands to your shack.

Start out by reading your primary transceiver manual. Does your existing rig have a transverter port? Many newer transceivers do. There are other ways to set up a transverter, but this is usually the easiest. If you don't have a dedicated port, don't worry; many transverters can be made to work against a low power RF signal (usually 5 to 10 watts).

Likewise, get a look at the specifications



The Elecraft XV144 transverter kit is a great way to move your HF transceiver up to VHF.

and manuals for any transverter you are considering. You will find most designs can be made to work in most cases, but there are some lash ups that just won't fly no matter how hard you try. A little prior planning will save you the trouble of testing the transverter company's friendly return policy.

There are a number of transverter manufacturers out there to choose from. Here are a couple of them: Down East Microwave www.downeastmicrowave.com/ and Elecraft www.elecraft.com/ are good places to start your search for transverters and sound advice on setting them up given the nature of your home station.

There is lots of fun to be had up there in the upper limits of the radio spectrum. There is still a lot of experimentation and new challenges to be found.

❖ So What is Up with the Sun...Really?

If you have been a ham for any length of time, you know that a good crop of sunspots is the key to putting a lot of DX into your log-book. If you are any sort of ham today, you are probably well aware that we are going through an unprecedented period of very few (if any)

sunspots. Traditionally, hams and other folks have been able to depend on a fairly regular 11 year cycle of sunspot ups and downs. For reasons that even the best solar scientists can't seem to agree on, things just aren't coming around in the sun spot department. Oh, there are still lots of folks to talk with (and even quite a bit of DX) if you are willing to dig in a bit (CW anyone?), just don't expect to nail the Marshall Islands 59 with 1 watt to a dipole on phone like I did back in 2001, at least not for quite some time to come.

Are we downhearted? Not me, mate! I get on the air most evenings and I find lots of radio fun. The sunspots will come back some day.

But if you want to try to keep track of what the sun is up to and maybe even throw your theories into the mix, let me make a few recommendations to help you along the way.

You can start with the hard data: The daily sunspot report can be found on the NOAA Space Environment Sunspot page at www.swpc.noaa.gov/ftpmenu/forecasts/SRS.html.

Then you might want to get a more detailed perspective by backing out to the more comprehensive information that can be found on the NOAA Space Weather Prediction Center webpage at: www.swpc.noaa.gov/. Here you will find details including near real time satellite imagery.

Another great page that augments the basic NOAA data with more user friendly information and even some interesting history is the Space Weather page: <http://spaceweather.com/>. If you are afraid that the sky might be falling, don't scroll down too far on this page. They also give predictions about the over 1 thousand "Near Earth Objects" listed as "potentially hazardous."

If you use the Firefox Web Browser, there is a great little "plug in" for this browser called Propfire. Developed by Patrick Rundall N0HR, this add-on browser feature puts current HF propagation information right on the browser status bar. Give the info box a click and you get a chart of the last 3 hours of solar activity, as well as a number of links to more comprehensive solar information including the full WWV propagation report. Best of all, this handy little tool is free to Firefox users at: www.n0hr.com/Propfire.htm.

❖ Hey Buddy ... Got The Time

While we were talking about Firefox Web Browser plug ins. I may as well also mention another ham radio favorite. FoxClocks www.stemhaus.com/firefox/foxclocks/. Developed

UNCLE SKIP'S CONTEST CALENDAR

California QSO Party

Oct 3 1600 UTC - Oct 4 2200 UTC

RSGB 21/28 MHz Contest

Oct 4 0700 - 1900 UTC

10-10 International Day Sprint

Oct 10 0100 - 2359 UTC

FISTS Fall Sprint

Oct 10 1700 - 2100 UTC

Pennsylvania QSO Party

Oct 10 1600 UTC - Oct 11 2200 UTC

Illinois QSO Party

Oct 18 1700 UTC - Oct 19 0100 UTC

CQ Worldwide DX Contest SSB

Oct 24 0000 UTC - Oct 25 2400 UTC

10-10 Int. Fall Contest CW and Digital

Oct 24 0001 UTC - Oct 25 2359 UTC

by Andy McDonald, you can set up multiple clocks on your status bar including UTC. Beyond that, you can have it show local times in other parts of the world. FoxClocks is a very comprehensive (and free) tool to make the Web a better place for people who play radio.

❖ November is Sweepstakes Month

It's that time of year again. The harvest is in and hams are gearing up for the ARRL Sweepstakes. This year, the CW weekend will be held on November 7th and 8th and the Phone weekend will be the 21st and 22nd of the month. I think it has something to do with the time of year, but this contest always seems to yield a lot of activity, especially many opportunities for single op stations with low power. You don't have to be a big gun to put together a reasonable score in Sweepstakes. Scan the bands for multipliers, working anything else you hear along the way and you will be surprised how fast the points can add up.

❖ The Alpha Delta DXCC

Every now and then I get asked, "Skip, what kind of antenna would you buy for HF?" Well, without getting into the "build versus buy" debate, the commercial product I have always felt good about is the:

Alpha Delta DXCC Parallel Dipole - \$160
Alpha Delta Communications, Inc.
Order Line 888-302-8777
Info line 606-598-2029
FAX 606-598-4413
Product or order questions e-mail: jfburns@windstream.net
Antenna questions e-mail: tyrrell@cybertrails.com

The Alpha Delta DXCC is a multi-wire, multiband dipole designed to operate on 80, 40, 20, 15 and 10 meters feeding 50 ohm coax, but the antenna can also load the WARC bands with a good tuner. It is rugged and easy to assemble. The DXCC is constructed with 12 gauge insu-

lated solid copper wire that will easily handle the full legal limit in the power department. All hardware is stainless steel and the overall design is severe weather rated.


It can be mounted flat or configured as an Inverted V. It requires only 82 feet spacing and has been tested to work well as low as 35 feet. This makes it the "everyman's" (or every-woman's) basic HF skywire, likely to fit into most back yards.

I have used this antenna in two locations over many years and never found fault with the design or performance. Sure, you can put your own set-up together for less than half the price, but there is a lot to be said for the quality of the Alpha Delta gear and expertise of the Alpha Delta staff.

❖ Ham Radio Book of the Month

But if you want to roll your own antennas, there is only one place to start.

The ARRL Antenna Book 21st Edition
Editor: R. Dean Straw N6BV
ISBN: 9780-87259-987-6
Order Number - 9876
976 pages \$44.95 from
The American Radio Relay
League
225 Main Street
Newington, CT 06111-1494
www.arrl.org/shop
1-888-277-5289



The League's *Antenna Book* has been around in one form or another since 1939. You would think that everything to be said about putting pieces of wire together

Outer Limits continued from page 59

- undercoverradio@gmail.com*)
- Voice of Honor-** There is a clear patriotic theme on this pirate that has been active on various holidays. (*voiceof-honor@gmail.com*)
- Voice of KAOS-** Their rock music protests high levels of chaos in the world. (*voiceofkoas@gmail.com*)
- Voice of the Robots-** Robots such as Dr. Smith's robot on "Lost in Space" play rock music on this pirate. (*voiceoftherobots@gmail.com*)
- WANK-** This new pirate has been programming classic rock music. It is unclear if the North American version is a relay of the Dutch Europirate. (unknown)
- WBNY-** Commander Bunny has announced that he now has a facebook page to supplement his Rodent Revolution broadcasts. (Belfast and *rodentrevolutionhq@yahoo.com*)
- WEAK Radio-** Rock music and comedy are their normal format, but they sometimes switch programming styles. (*weakradio@gmail.com*)
- WMPR-** When you hear "dance party" techno rock music on shortwave, it normally is this veteran station. (None; known to QSL occasionally only at the Kulpville Winter SWL Festival)
- WTCR-** "20th Century Radio" plays music from various decades of the last century, from ancient pop to rock. (Belfast)
- Wolverine Radio-** Some still think that the diction of the announcer's voice on this rock music station sounds like Long Range Radio. (None)

QSLing Pirates

Reception reports to pirate stations require three first class stamps for USA maildrops or \$2 US to foreign locations. The cash defrays postage for mail forwarding and a souvenir QSL to your mailbox. Letters go to these addresses, identified above in parentheses: PO Box 1, Belfast, NY 14711; PO Box 109, Blue Ridge Summit, PA 17214; PO Box 146, Stoneham, MA 02180; PO Box 293, Merlin, Ontario N0P 1W0, Canada, and PO

to pump RF into the sky might have been said by now. Well, this edition of the *Antenna Book* (the 21st) is about twice as thick as the one I first bought back in the 1970s when ham radio entered my life.

Like its sister publication *The ARRL Handbook for Radio Communications*, the *Antenna Book* never disappoints. The new information added (and the old information improved) always gets me out on the roof trying new things. This edition includes something that will allow me to keep my feet on the ground. The 21st handbook includes complete construction information for a mobile "Screwdriver" HF antenna. I have always wanted to give that design a try. This idea is found in among the many wonderful loops, Yagis, verticals and other designs.

And for those cold and rainy months where climbing for antenna work are not particularly safe, you can sit by the fire reading the excellent theory sections of the handbook, also completely revised and expanded. New to this edition is a comprehensive study of Near Vertical Incidence Skywave (NVIS) techniques. Reading this section will make you a believer in "cloud warm-ers."

The handbook includes a CDROM full of antenna utilities. You will find programs for antenna design and modeling as well as transmission line assessment. There are also programs for terrain assessment and even propagation forecasting. (They have included everything but the sunspots!)

This latest edition of the ARRL *Antenna Book* is a winner, just like all its previous iterations. Highly recommended for all hams.

Well, time to hit the key. I'll see you on the bottom end of 40 meters.

Box 9, 8096 ZG, Oldebroek, Netherlands. PO Box 69, Elkhorn, NE 68022 is no longer a valid address, even though a few pirates announce it.

Some pirates prefer e-mail, bulletin logs or internet web site reports instead of snail mail correspondence. The best bulletin for submitting pirate loggings is the e-mailed *Free Radio Weekly* newsletter via *freeradioweekly@gmail.com*. A few pirates will sometimes QSL reports left on the outstanding www.frn.net web site. *The ACE*, a formerly widely read print bulletin, now has a valuable archive of *Free Radio Weekly* issues at www.theaceonline.com/

Thanks

Your loggings and news about unlicensed broadcasting stations are always welcome via 7540 Highway 64 W, Brasstown, NC 28902, or via the e-mail address atop the column. We thank this month's valuable contributors: Brian Alexander, Mechanicsburg, PA; Kirk Allen, Ponca City, OK; Skip Arey, Beverly, NJ; Kirk Baxter, North Canton, OH; Jerry Berg, Lexington, MA; Artie Bigley, Columbus, OH; Richard Cuff, Allentown, PA; Rich D'Angelo, Wyomissing, PA; Ragnar Daneskjold, North America; Gerry Dexter, Lake Geneva, WI; Bill Finn, Philadelphia, PA; Harold Frodge, Midland, MI; William T. Hassig, Mt. Prospect, IL; Don Jensen, Kenosha, WI; Ed Kusalik, Camrose, Alberta; Larry Magne, Penn's Park, PA; Greg Majewski, Oakdale, CT; Gene Patterson, Gibsonia, PA; Paul Starr, QTH unknown; A. J. Michaels, Blue Ridge Summit, PA; Adrian Peterson, Indianapolis, IN; John Poet, Belfast, NY; Mike Rhode, Columbus, OH; Lee Silvi, Mentor, OH; John Wilkins, Wheat Ridge, CO; and Dave Zantow, Janesville, WI.

Build Your Antenna Library And a VHF-UHF Antenna

The most extensive treatment of antenna theory and practical, how-to-do-it information is the *ARRL Antenna Book*. This book deals with antennas for both receiving and transmitting from medium-frequency (HF) through microwave. Design formulas and useful information are given for many of the antennas covered, such that they can be designed for any frequency you wish, not just for ham frequencies.

The broad coverage volume of The Radio Society of Great Britain is *Antennas for All Locations* by Moxon. Although smaller than the *ARRL Antenna Book*, this book is filled with a lot of practical information on a great variety of antennas.

In *Joe Carr's Antenna Handbook*, the late Joe Carr presents an extensive treatment of antenna projects and information. Joe wrote in an informal style and offered a lot of practical information on antenna design and construction.

W. Clem Small's *The Antenna Handbook* presents a wide range of topics from antenna history to projects for building many different practical antennas and antenna accessories.

The late L. B. Cebik, W4RNL, has authored a series of antenna books called *Antennas from the Ground Up*. These books have a great deal of practical information on antenna construction and use. More than any other source I know, Cebik's books not only impart information on how to build various antennas, but also contain extensive discussions of their performance and radiation-reception patterns.

A large, interesting, and useful collection of antenna projects is found in *The Giant Book of Amateur Radio Antennas* published by Blue Ridge Publications. This book is a collection of antenna articles from the old 73 ham-radio magazine.

Bill Orr, W6SAI, often in collaboration with Stuart Cowan, wrote a series of short books, including *Antenna Handbook*, *Beam Antenna Handbook*, *Wire Antennas*, and *Vertical Antennas*. These books contain a lot of practical, how-to-do-it information.

The late Doug Demaw, W1FB, has written a great little antenna book for beginners called *W1FB's Antenna Notebook*, with lots of useful information.

And the late Lew McCoy, W1ICP, has a good discussion of many types of antennas and antenna accessories in his *Lew McCoy On Antennas*.

How to Access Antenna Information:

Radio magazines such as *QST*, *CQ*, and

RADIO RIDDLES

Last month:

I asked: "An antenna is sometimes said to 'capture' the signals it receives from passing radio waves. After the waves are captured, can they ever escape back into space?"

Well, when RF current flows in or on a conductor, radiation of some of that energy occurs. So, yes, some of the energy of the captured (received) waves is radiated back into the space around the antenna, and thus "escapes" from the antenna. In the Yagi-Uda beam antenna, the parasitic elements (reflector

and directors) are not connected to any feed line at all, and so they radiate almost all of the wave energy that they capture. The Yagi-Uda beam's active element (the one connected to the feed line) captures some of this radiation from the reflector and director. The combination of this radiation and the energy captured by the active element itself from the passing waves combine to produce the Yagi-Uda's gain and directivity.

This Month:

Many beam antennas, such as the Yagi-Uda Beam mentioned above, also obtain their gain and directivity from the use of reflectors and directors. Can you name some beam antennas that do not have reflectors or directors in their design?

Monitoring Times routinely contain advertisements for books on antennas. They also publish articles on building and using antennas. Some even have a special, annual issue devoted to antennas.

Libraries near you may have some antenna books, or can get them for you on inter-library loan. Using Google or other search engines, enter the name of the book you want, or enter terms such as "antenna book," "antenna handbook," "antenna information," etc, to bring up the desired results. The same goes for searching Ebay, Half.com, and Amazon.com for antenna books. The National Radio Club also offers papers and booklets on various antenna topics.

Out-of-print publications can often be found by a Google search, or on Ebay, or Half.com. Used book stores are sometimes a useful source. If there's a local ham club near you, check it out: Some clubs have talks on antennas at their meetings, and many have members who are glad to help with antenna questions and can even help in putting antennas up. You can often find a club near you by searching the web with terms like "radio club," "ham club," "amateur radio club," etc, plus the name of your city and state.

Following are some specific sources that are particularly useful.

The American Radio Relay League offers a number of books on antennas: www.arrl.org/catalog/index.php3?category=Antennas,+Transmissions+and+Propagation

Check out *CQ Magazine*: <http://store.cq-amateur-radio.com/Categories/book?category=Books:Antennas>

The National Radio Club site has many pamphlets on antennas: www.nrcdxas.org/catalog/reprints/ Grove Enterprises: www.grove-ent.com/order.html Radioware and Radio Books: www.radiobooks.com/

This Month's Interesting Antenna-Related Web sites:

All materials listed here are free.

The technical section of the *Monitoring Times* website reference library has a number of antenna-related articles, primers, and projects by Bob Grove and myself:

www.monitoringtimes.com/html/reference_library.html

Here's an antenna and propagation book that is used in the U. S. Navy training course for training electronics technicians: <http://libro-ee.blogspot.com/2009/08/210-electronics-technician-volume-7.html>

W1GHZ freely shares his excellent microwave antenna handbook:

www.w1ghz.org/

The Marine's *Field Antenna Handbook* has a lot of practical antenna information, especially on putting up and using antennas outdoors:

www.armymars.net/ArmyMARS/Antennas/Resources/usmc-antenna-hb.pdf

Here's Laport's classic "Radio Antenna Engineering:

www.athm.net/andreas/RadioAntennaEngineering-printer/RadioAntennaEngineering-printer.pdf

Laport has good discussions of antennas for various bands. And a short, antenna book for hams:

www.buxcomm.com/pdfzips/hro-antenna-handbook.pdf

The site "Free Books!" lists quite a number of free antenna and propagation books including Kraus's *Antennas*, 2nd edition, a highly-respected antenna-engineering text:

<http://timeandspacetoday.blogspot.com/2009/01/following-are-links-to-free-antenna.html>

A number of other free antenna books can be downloaded at that same site, *Antenna Systems Guide* is particularly recommended.

LET'S MAKE A QUICK AND EASY VHF OR UHF ANTENNA

Dipole antennas are covered in just about every antenna book. This vertical dipole is portable, but can be used in more permanent installations if protected from the weather.

1. Use the following formula to find the length needed for the elements. Length (in ft) = 234/frequency (in MHz), or Length (in m) = 71.3/frequency (MHz).
For example, a quarter wavelength of wire at 150 MHz is 234/150, or 1.56 ft, which is about 18-3/4 in.
2. Trim the outer insulation from the coax a distance equal to 3 or 4 inches longer than the quarter wavelength found by the formula just given above. Don't use coax that has foil attached to the inner insulation.
3. At the end of the coax just trimmed of insulation, push the wire braid of the outer conductor downward on the coax line. This shield braid should enlarge and slip fairly easily back over itself down the line. Keep working the braid back down the line, eventually folding it back completely over the point where the outer insulation is still on the line (fig. 1B). A few kinds of coax won't push back down like this, so give the coax you intend to use a try to determine if you can use it this way. If not, go to step 5.
4. When you have folded the braid completely back down the coax, it should be a little over a quarter wavelength long. Trim it to the quarter wavelength you got from the formula above, and tape its end in place.
5. If you were unable to fold the coax back down the line, then you will have to make some quarter wavelength wires to take the place of the folded-back coax shield. Cut four bare wires to a quarter





Fig. 1. COAX WITH A PORTION OF OUTER INSULATOR REMOVED (A), WITH BRAID FOLDED BACK OVER THE OUTER INSULATOR (B), THE COMPLETED ANTENNA (C).

6. Remove the inner insulation from the quarter wavelength of inner conductor within about a quarter inch of the rolled back braid (fig. 1C). Make a loop at the end of the bare center conductor such that the length of the center conductor, including the loop, is a quarter wavelength. Solder the loop as it wraps around the wire, and trim any excess wire.
7. If you use this antenna outside where precipitation can reach it, then it must be weatherproofed. One solution is to hang it inside a PVC tube. Cap the top of the tube, but leave the bottom open, or vented.
8. Using the minimum length of coax necessary for comfortable operation with this antenna, put an appropriate coax connector on the far end of the line.

9. Tie the antenna up high and in the clear with a length of nylon fishing line or other line that doesn't absorb water.
10. Connect the antenna to your rig and you're on the air!
11. Don't forget lightning protection if you use this antenna outdoors. The minimum is to never use it or any outdoor antenna during weather likely to produce lightning. And disconnect and ground it when not in use.

❖ Next Month is Goodbye

It has been a genuine pleasure for me to write the *Antenna Topics* monthly column over the many years I've been with *Monitoring Times*. I've enjoyed writing about antennas and related topics with you readers in mind. Now it is time for me to retire from writing this column. I sincerely wish you all, as I have for some 25 years now, Peace, DX, and 73.



**Listening is only half the fun...
POPULAR COMMUNICATIONS
is the other half!**

If you enjoy radio communications in all its variety, you'll love **POPULAR COMMUNICATIONS**. Since 1982 Pop'Comm has delivered thousands of pages of great reading for both the radio enthusiast and the professional communicator. Every month Pop'Comm is crammed with scanner frequencies, shortwave listings, broadcast and utility loggings, radio nostalgia, and technical information. Plus you'll find great features on amateur radio, public service communications, DXing, pirates, clandestines, and much, much more.

YES! Enter my subscription to Popular Communications today!

Name _____
 Address _____
 City _____ State _____ Zip _____
 Check MasterCard VISA AMEX Discover
 Card No. _____ Expires _____
 Signature _____

| | USA | Canada/Mexico | Foreign |
|---------|--------------------------------|---------------------------------|---------------------------------|
| 1 Year | <input type="checkbox"/> 32.95 | <input type="checkbox"/> 42.95 | <input type="checkbox"/> 52.95 |
| 2 Years | <input type="checkbox"/> 58.95 | <input type="checkbox"/> 78.95 | <input type="checkbox"/> 98.95 |
| 3 Years | <input type="checkbox"/> 85.95 | <input type="checkbox"/> 115.95 | <input type="checkbox"/> 145.95 |

Popular Communications, 25 Newbridge Road, Hicksville, NY11801 • Phone: 516-681-2922 • Fax 516-681-2926
 Visit our web site: www.popular-communications.com

An S20-R "S" Meter and Introducing the BC314/BC-344

Here's a P.S. for the Hallicrafters S20-R restoration just completed in the last issue. Located on the rear apron of this receiver are an octal socket and a 5-pin socket. The octal socket is for use in powering the set from an external supply during portable operation. The rarely-used 5-pin socket is for an accessory S-meter. I've done a lot of electronic flea-market shopping in my time, but I've never seen one of these units.

However, if you have an S-20R receiver and wish to add an "S"-meter, here's a way to build your own. The information is from an article by Guy Dexter in a March, 1947 issue of *Radio News*. Reader James Williams, W7MBJ, called the article to my attention and kindly provided a scan of it for me to study. And by the way, Author Dexter says that this scheme will also work with an S-40, which has a similar plug.

As you can see from the schematic (Figure 1), all that is needed for the project is a 0-1 mA meter and a few small parts. Of course you'll also need some sort of box to house your project – perhaps one of those small sloping-front meter boxes if you can find one.




Fig. 1. Schematic of the S20-R "S"-Meter

Before beginning construction, the value of resistor R3 needs to be verified by experimentation. It is a shunt intended to multiply the meter range to 0-2 mA and must equal the internal resistance of the meter. The value is shown as 100 ohms, which is common, but your meter may be different.

Set up a test circuit with a 15k pot in series with a 9-volt battery, an accurate multimeter, and the project meter with its 100-ohm shunt. Set the pot for maximum resistance before connecting the battery, then adjust the pot, keeping an eye on the project meter to make sure it doesn't go off scale, until the multimeter shows 1 mA.

If the project meter now reads half scale, you're good to go. If not, experiment with the value of R3 (perhaps by adding series or paral-

lel resistors) until you find a value that gives a half-scale reading with a current of 1 mA. Once this is done, the remainder of the construction is straightforward. Add a cable connecting to pins 2, 4 and 5 of a 5-pin plug as shown, insert it into the S20-R's socket, and your meter is ready for use.

Turn on the "S" meter by advancing the r.f. gain all the way until it clicks. Make sure your AVC is turned on (the meter works by measuring AVC voltage) and turn your BFO off. The next step is to zero the meter, which you should do before first using it and at intervals thereafter. To do that, detune the radio so no signal is present or – better – ground the antenna terminals. Then use potentiometer R2 to obtain a zero reading.

With a signal present, the meter will deflect proportionally to its strength. To convert the deflection on the 0-1 scale to "S" units, use the table of Figure 2.

| SIGNAL STRENGTH | MILLIAMMETER DEFLECTION |
|------------------|-------------------------|
| 50 db. above S-9 | 0.87 |
| 45 " " " | 0.85 |
| 40 " " " | 0.83 |
| 35 " " " | 0.80 |
| 30 " " " | 0.78 |
| 25 " " " | 0.76 |
| 20 " " " | 0.73 |
| 15 " " " | 0.70 |
| 10 " " " | 0.66 |
| 5 " " " | 0.64 |
| S-9 | 0.54 |
| S-8 | 0.48 |
| S-7 | 0.41 |
| S-6 | 0.34 |
| S-5 | 0.28 |
| S-4 | 0.20 |
| S-3 | 0.14 |
| S-2 | 0.06 |
| S-1 | 0.02 |

Fig. 2. Meter Reading VS "S" Unit Conversion Chart

According to the author:

"This S-meter does not give flattering indications of signal strength, neither is it especially 'Scotch' in performance. Several hundred tests made by the author in the laboratory and on received signals both on the broadcast and amateur bands (as well as the comparison with S-meter response in a number of competitive receivers) indicate that the calibration data given in the table is fair in every respect."

❖ Our Next Project

Any radio amateur or SWL old enough to be around when World War II surplus first hit

the market – and even those who are younger but fascinated with military gear – will remember the BC-312 HF receiver and its a.c.-operated counterpart, the BC-342. Beautiful in its ugliness and carrying with it an aura of potency and military might, it was the treasured first receiver of many a 1940s era ham, including myself.

The BC-312 will be a "Radio Restorations" project in the not-too-distant future. But for the upcoming project I've chosen the BC-312's much more rare and very interesting cousin – the BC-314 and its a.c.-operated counterpart the BC-344. It's virtually identical, physically, to the BC-312/342, but covers the range 150-1500 kHz as compared with the BC-312's 1500-18000 kHz.

The BC-314/BC-344's two r.f. and two i.f. stages, plus its superb quality coils and other r.f. components, make it a truly hot receiver. Despite its over-70-year-old design, broadcast-band and aeronautical beacon DXers would probably enjoy a logging field day using this vintage set.

The particular radio we're going to work on is an a.c. model, a BC-344. The only difference between it and the dynamotor-powered BC-314 is the power supply installed. As is the case with the BC-312/BC-342, the a.c. model contains a type RA-20 supply; the d.c. model contains dynamotor DM-21.

These supplies were interchangeable and the RA-20 version was commonly available separately during the heyday of surplus availability. So it is not unusual to find a BC-312 or BC-314 with an RA-20 supply installed. I installed one in my own BC-312.

❖ The BC-344 Circuit

As is usual with my communication receiver restoration articles, I'm not going to include the full schematic here. To show it in enough detail to be meaningful would probably take a quarter of a page or more and I would rather use the space for discussion. For our present purposes a verbal description will do just fine, but as we focus on various details of the radio, appropriate sections of the schematic will be shown.

Starting at the antenna, there are two stages of r.f. (each a 6K7). These, along with the separate r.f. oscillator stage (a 6C5), feed a 6L7 mixer (first detector). The 92.5 kHz output of the mixer is amplified by two i.f. amplifier stages (two more 6K7s). The signal from the i.f. amplifiers, along with the output of the 6C5 CW oscillator passes to the 6R7 second detector/first audio amplifier/AVC tube. Finally, the signal is amplified to speaker volume by a 6F6

audio output amplifier. The rectifier tube in the a.c. power supply is a 5W4.

❖ On The Front Panel

One of the first things you might notice about the front panel (Figure 3) is the large right-angle connector at the lower right. It was intended for interconnection of the receiver with other elements of a complete radio system, notably a transmitter.




Fig. 3. Front Panel of the BC-314/BC344

Many hams and other radio hobbyists referred to it as the “ugly plug” and, seeing no use for the connector, removed it, clipping all the leads to it at their points of origin. This left a hole that could be used for a control or other accessory.

Just to the left of the connector is the receiver’s power/mode switch which turns the radio on, selecting either manual or automatic volume control modes depending on how far it is rotated. Under that switch is a “send-receive” switch which, as wired, functions only when the set is used with a companion transmitter.

The top two jacks in the row at the right of the connector, labeled “KEY” and “MCRO” were also, obviously, put there for operation in concert with a companion transmitter. The three jacks below it are supplied for connection of speaker or phones.

Moving to the upper left of the panel, just under the panel lock at the corner, are an antenna connection for coax-type cable and one for a single wire. A binding post for the ground connection is a little to the right of the lower left-hand corner.

The four-position bandswitch is positioned just to the left of the identification plate. The four bands are: 150-260 kHz, 260-450 kHz, 450-820 kHz and 820-1500 kHz. Above the ID plate is the tuning dial which, as you can see, has a shutter that masks off all bands except the one in use. Just to the left of the dial is the “Align Input” knob – which is used to peak the response of the receiver to antennas of different characteristics.

The group of three controls at the upper right includes the volume control (left), CW Oscillator (BFO) “on-off” switch, and CW Oscillator pitch control. In a diagonal line below the volume control are the vernier tuning dial (which on this model is equipped with a lock) and the fast tuning dial. This concludes our quick tour of the front panel.

❖ A Peek Inside

Figure 4 which, like Figure 3, was copied from a military manual, gives us a look down at

the top of the radio as removed from the cabinet. This view will give you a general idea of the layout of the set, though you may not be able to read all of the callouts.

The three tubes on the shelf at the left rear are the first and second r.f. tubes and the first detector. At the right rear, the tubes to the left and right of the i.f. transformer are the first and second i.f. tubes. The tubes on either side of the oblong housing at lower right are the second audio tube (left) and the second detector/first audio tube.

You may be wondering where the r.f. and c.w. oscillator tubes are – as well you might. They’re not visible because each is enclosed in a shielded housing. The r.f. oscillator tube and circuitry is in the oblong box at left; the c.w. oscillator tube is in the oblong box at right.

The reason that the tubes and circuitry are shielded is interesting. The radio direction finding equipment of the era was sensitive enough that, from a reasonable distance, it could pick up even the tiny bit of radiation from these oscillators. That could enable the enemy to pinpoint the location of the radio, which wouldn’t be healthy for the operators!

❖ Possible Enhancements

When it comes to restoring military gear to working order, I’m not a purist. Oh, I wouldn’t drill holes in the panel for extra switches. And I’d probably resist taking out the “ugly plug” (though I did just that with the BC-312 I had as a teen-ager). But if a small and invisible change would enhance performance or convenience I’d be up for it. And there are a few I’m going to consider as I go through this BC-344 restoration.

There are not many enhancements or modifications for the BC-344/BC-314 in the literature. Not covering the amateur bands, these radios didn’t have that much of a following. However, quite a few improvements have been suggested for the almost-electrically-identical BC-312/BC-342 which – as mentioned – is an HF general coverage receiver that was widely used by hams. And I will consider any of these that seem useful and applicable to my set.

The most obvious one, which I’ll defiantly




Fig. 4. Looking Down at the Top of the Radio

do if someone hasn’t already beat me to it, is disconnecting the send-receive switch from its wiring to the “ugly plug” and connecting it, instead, in series with the center tap of the power transformer – so that it can be used to silence the receiver. There are also modifications to the power supply (additional filtering) and audio section aimed at reducing hum. I’ll consider those if the need is apparent.

I definitely like the idea of converting one of the three (!!!) second-audio output jacks to a first audio jack more appropriate for headphone use. And I’m going to look into the changes suggested for enhancing the sensitivity of the r.f. stages. But I probably won’t go for adding a separate r.f. gain control or an “S” meter, since those mods would alter the front panel. We’ll take a first look at our restoration subject next month.

JOIN THE AWA

Antique Wireless Association
The original and largest historical radio-collector group

- Publishes *The AWA Journal*, Marc Ellis, Editor, with:
 - Battery and AC receiver restoration
 - Vacuum-tube history and collecting
 - Old-time amateur-radio contests
 - Communications receivers
 - Free want-sell-swap ads
 - Early television
 - Horn loudspeakers
 - News of U.S. and foreign clubs
- Produces the famous annual Rochester meet
- Maintains unique radio-TV museum

Membership is only \$20 per year in U.S.; \$25.00 elsewhere.
Mail check to:
AWA Membership - P.O. Box 421, Dept. 2 Bloomfield, NY 14469-0421
<http://www.antiquewireless.org>
awamembership@rochester.rr.com (585) 392-3088



Now Transmit & Receive in Ultrasound !!



=ñè= ráiè~JqoQMè~àèAÉáíEññáEè~à~AíáíEè~èíñUÉ=

Ä~âçIPRJQñèl~áíU~NMèò~áÇE~IÇâç~âÇè~àèááíè=

E tF= ~í~QMèòKçí=A~ââáíEè~A~íèl~ááèAíèAÉíèEèl

èçÇEáíèíE~èíUèçláÇèl~è~âÇ~â~áJã~ÇE=èçláÇèKçíçíÇ=

èèEèèíèEèíEèèpmíEèááíEèÇáóA~íè~âÇ~ááèEÁíè~áOè=

NèçâíMè~ñNMè ~íçáEñççíèlNáAáèèAÉíEè~èçíèçèR=

íç~NMNMèEíáíU~íUÉFR40è~èEÁEáíEèèíU~íè~ráíè~JouN=

èEÁEáíEè~íèíí~èçíEè~çáíè~àèááíèè~Çáíèl~Aáíè~íç~O=

átl= íUíè~EááííááO~Açáè~è~Aáípmí~èáOa~áíEèK

~qUáèJÜçíèááíáAáíÇEè~C~ou=éáEòçíè~àèÇíAÉèèl=

_l=A~èEíè~èíèlE~OMíè~OèA~áí~à~âÇèEèáíèèAVKVR=

éáíè~UáèéááOèE~íè~íè~èçááíEè~Aè~OèEè~çíEí~ááè=

A~âçMRJRNTJTPçèèUèEíèíè~JèEíçáííçáè>

Ultra-TR40

qÜÉáí~âpÉí~ççAáÉíèfáA=

www.midnightscience.com

“Sky-Wires & Inhalers” Part 2: From Antenna to Receiver

By Walter Lindenbach

Last time, Bill had just mentioned “radiation resistance” when Chuck had to go home, and he said that that’s the stuff that antennas are built for. In transmitting antennas, it turns electric currents into radio waves or, more generally, electrons into photons.

But Chuck said that he wanted a receiving antenna, so Bill reminded him that antennas work both ways – always. A good antenna – meaning one that has radiation resistance – will turn radio waves into electric currents.

“And those electric currents are radio signals, right?”

“True,” Bill confirmed.

“Good! Now we’re on the right track! But we have to get those electric currents – radio signals – from the antenna to the radio receiver, don’t we?” Then Chuck had another idea. “Hey, maybe we could put the antenna right at the radio receiver. What do you think?”

“Nope,” Bill frowned, “not a good idea. For one thing, the radio will be near things that make electrical noise – QRM, y’know, ham-speak for man-made interference – and there’s enough of that stuff around already.

“Next, buildings are made of stuff that gets in the way of radio signals, that is, the radio signals are *attenuated* by building materials. Walt – y’know, the guy who writes this thing – told me that he lives in a condo building where the windows are *treated* to reduce radio signals of all kinds.”

“Whyever would they do that?”

“Well, do you remember last time we were talking about antennas converting electrons into photons and vice versa? The sun’s radiation is in the form of photons. Radio signals are also in the form of photons. So, to keep the place cooler, the windows are coated to attenuate all photons.”

“Aw bother,” Chuck groaned, “that doesn’t help! So the antenna works better outside, huh? Now what do we do?”

“Well, you remember last time we talked about transmission lines?”

“Aha!” Chuck brightened. “They have a characteristic impedance, the antenna has a characteristic impedance, and so does the receiver antenna connection. So if we get them all matched up with the same characteristic impedance, we get the radio signal from the antenna to the receiver, right?”

“Betcha! Good stuff! One more thing. The transmission line from the antenna to receiver is called a lead-in. Usually, it’s just a wire, but that’s not so good because that’s where a lot of QRM is collected. A shielded transmission line is much better.”

“You mentioned something called RG 58 last time, and you said it is a shielded transmission cable with a characteristic impedance of 50 ohms. Would that do?”

“Yes it sure would,” replied Bill, “and it can do a lot more than that! Let’s turn a transmission line into an antenna.”

❖ Transmission Lines into Antennas

“Y’know Bill, I just got a funny feeling in my leg as if it was being pulled!”

“Well, tell your leg to settle down and pay attention. I’m not kidding! Now look at this. We’re going to see how a transmission line can develop into an antenna where electrons get out of the transmission line and turn into photons – or the other way around.”

Bill took a pad of paper, and began a sketch. He called it Figure 1¹.

“This isn’t a coaxial cable, it’s called a balanced transmission line – like the brown ribbon lead-in for a TV antenna. It’s called 300-ohm twin-lead. 300 ohms is its characteristic impedance – the stuff we were talking about a minute ago.




Figure 1: Transmission Line

“A transmission line is defined as a device with at least two conductors for transmission of electrical energy. The energy is transmitted by current in the conductors *and/or* the electric and magnetic fields between and around the conductors.”

“Really? I can understand the energy being in the conductors and in the fields, but do you really mean ‘or’ in the fields?”

“Chuck, this may be the original chicken-and-egg situation! The electric voltage produces an electrical field between the conductors; the electric current in the conductors produces magnetic fields in and around the conductors. All of these entities are so closely associated that it is impossible to say which causes which. There are theories that include the idea that once – a few pico-pico seconds after the Big Bang, they were separate.

“Once upon a time, I read an article that said all electrical circuits could be described not with wires, but with the electric and magnetic fields, but that this is not done because it would be much more awkward. Still, if that statement is correct, you can see how closely electric voltage and electric fields, and electric current and magnetic

fields, are associated.

“Transmission lines are arranged so that very little energy gets away. That is, almost all of the energy that goes in at one end comes out at the other. But the wires do have resistance, which converts electrical power to heat. This kind of resistance is called ohmic resistance as opposed to radiation resistance which is the stuff that we are going to meet next, and which is the *whole reason* to build antennas.”

Bill went on sketching. “In Figure 2¹, we see a transmission line with the conductors diverging.

This produces a number of effects, but the one we’re interested in is that *energy gets away!* Another effect that we’ll have to consider with our antenna design is that the energy that does not get away is reflected back to the source. That’s over here.” Bill pointed to the left end of the diagram where he had written “Z₁₂”.




Figure 2: Transmission Line Conductors Spread

“You know what, Bill? I think we’re talking about a transmitting antenna again.”

“You know what, Chuck? You’re both right and you’re not right!”

“Oh, for Pete’s sake! Are we going to get another dose of wild and woolly physics?”

“Na, Na, settle down! The reason is very simple: it is not possible to talk about a transmitting antenna without talking about a receiving antenna at the same time – or vice versa.”

“Oh yeah? Here we go viceing and versing again. Do you mean that a receiving antenna has radiation resistance just like a transmitting antenna, but that the radiation resistance does not radiate, it receives?

It turns radio waves into electrical signals in the antenna itself?”

“You got it, man! Right on the money.” Bill picked up the paper pad again. “Now let’s see what happens to our transmission line when it gets turned all the way into an antenna.” And he drew what he called Figure 3¹.




Figure 3: Transmission Line Conductors In Straight Line




Fig 4: Antenna, Lead-in, and Receiver

“Now, if this thing was being used as a transmitting antenna, the RF power from the transmitter would be applied at the terminals marked Z_{13} . Some of it would be turned into radio waves – yes, photons – and go squirting off into space.

“But no, we want a receiving antenna – which is the same thing – but now we can think of the radiation resistance converting radio waves from a radio transmitter and transmitting antenna somewhere else into electric currents which appear at the same terminals, Z_{13} . So we can connect our lead-in from there to the antenna connection of our radio.”

❖ Impedance – Characteristic and Otherwise

“The very cat’s meow!” Chuck spouted gleefully, “Now, are you going to tell me about the $Z_{1,2,3}$ – er – 1, 2, 3 things that you put on the sketches?”

“Will do. First, Z stands for impedance. Yup, we’d better talk about that stuff, because it’s going to get really important before we’re done. What do you know about impedance?”

“Well, let’s see. It’s something like resistance, only different. Yes?”

“Um – well yeah – that’s a start. Impedance is a combination of resistance and reactance – all measured in ohms, which is convenient.

“Now, there are two kinds of reactance: inductive reactance and capacitive reactance. Inductive reactance is produced by things that have – logically – inductance: things like coils, transformers, wires – in fact, anything that conducts current.

“Capacitive reactance is produced by things with – again logically – capacitance, and they are usually capacitors. But there’s more to it than that: any two conductors with an insulator between them, produce capacitance.”

“Uh-huh, now let’s go at this from the other end. Inductors and capacitors have inductance and capacitance which turns into inductive reactance and capacitive reactance, which are both parts of impedance, along with resistance. How’s that?” Chuck looked quite self-satisfied.

“That’s it.”

“Yes, but how does inductance and capacitance turn into reactance?”

“Good,” replied Bill, “I hoped you would ask that. In one word, the answer is: frequency.

Now I was going to show you the equations that relate inductance, capacitance, reactance, and frequency, but I suppose –”

“Yes, yes, yes,” Chuck yelled, “can we get on with the antenna without the math?”

“Well, not entirely, but we’ll skip the reactance equations for now.”

“Whew, that’s a relief! What’s next?”

“Hang on. This is what you have to know. When an AC voltage is applied to an inductor, the inductive reactance increases as the frequency increases. And capacitive reactance is just the reverse: as frequency increases, capacitive reactance decreases.

“Inductive reactance is exactly opposite to capacitive reactance. That means that they subtract one from the other. And, since one increases with frequency and the other decreases with frequency, it is possible to have a circuit where they exactly cancel each other, and there’s nothing left in the circuit but resistance. That’s called *resonance*. Isn’t that neat?”

“Well, I guess so, but what has that got to do with the $Z_{1,2,3}$ things on your sketches?”

“Aha, well first, the little *i* stands for input, and the 1, 2, 3 means that there are three different input impedances because of the different spacing between the wires. In the first case – Figure 1 – the wires are parallel and almost no energy gets away. The wires have inductive reactance, capacitive reactance and, because the wires are not perfect conductors, ohmic resistance.

“The dimensions of the wires, the spacing between them, and the insulating material is such that Z_{11} is 300 ohms. That means that, if you put a 300 ohm resistor at one end, you will see 300 ohms at the other end, no matter the length of cable or the frequency. But, as you found out with an ohmmeter, things are different with DC. First, if there is a 300 ohm resistor at the end of a short length of transmission line, the ohmmeter will read 300 ohms. But if the 300 ohm resistor is at the end of a long piece of transmission line, the resistance will be higher, because the wire in the cable has resistance, too. And, if there is no resistor at the end of the transmission line and it is open, the ohmmeter will indicate an open circuit.

“It is only with high-frequency current that a transmission line of any length with a characteristic impedance of 300 ohms and a 300 ohm resistor connected at one end will appear to have a resistance of 300 ohms at the other end.”

“Now, in the second case – Figure 2 – the wires are diverging at some angle, and some of the RF energy that we put in the at Z_{12} end – if

it’s a transmitting antenna – will turn into radio waves and go off into space. So, we have the same impedance components as in the Figure 1 case plus one more – radiation resistance.

“The Figure 3 case is similar to the Figure 2 case, but the radiation resistance component is larger. In other words, it’s a lot more like an antenna and a lot less like a transmission line.

“But before you get all excited about my talking about transmitting antennas when you’re bent on a receiving antenna, remember they work both ways. In the receiving case, what we call *radiation resistance* is converting radio waves to electrical currents, and the terms $Z_{1,2,3}$ could now be called $Z_{0,1,2,3}$ or output impedance, not input impedance.”

“Okay,” said Chuck, reaching for the paper pad, “now let’s see if I have the general picture straight.” And he began to draw what he called Figure 4.

“So, the antenna transformer has to match the characteristic impedance of the antenna to the transmission cable whose characteristic impedance is 50 ohms. Then, at the other end, the receiver transformer has to match the transmission cable – again 50 ohms – to the receiver input impedance. How’s that?”

“Perfect!” Bill was impressed. “You’ve got the thing cased to the letter! Now, all we need to know is the antenna characteristic impedance and the receiver input impedance. Then, we’ll *make* the transformers to do that.”

“Did you say ‘make’ transformers?” Chuck was wide-eyed. “Can we really do that?”

“Oh yes, ol’ Buddy, we sure can!” Bill replied, “It’s not hard, and certainly not expensive. The great trick is to find out what the transformers are to do. That means what impedance are they to convert to what other impedance, and over what frequency range ... but not tonight.”

“Huh! Now what? Is that nice? You tell me we can make transformers, and then you say ‘not tonight.’ Man, that sounds *terrific!* Come on!”

Bill just pointed to the clock.

“Oh, yeah sure, of course. Okay, next time. Thanks Bill. G’nite.”

“G’nite.”

References and Credits

1: “Radio-Electronic Transmission Fundamentals,” B. Whitfield Griffith, Jr., page 336, McGraw-Hill Book Company Inc., 1962.

Diagrams and graphs were prepared using National Instrument’s program “Multisim,” kindly provided by Analog Devices Inc. Walter Lindenbach can be reached at lindenbachw@shaw.ca

Amateur Radio Satellite Report

Compiled by Larry Van Horn, N5FPW

Some of the information presented here is courtesy of the weekly AMSAT ANS bulletin. The ANS is released worldwide via the AMSAT ANS e-mail reflector and a live radiocast on the AMSAT-NA 20-meter net held each Sunday on 14.282 MHz. Pre-net operations start at 18:00 UTC, with current ANS bulletins transmitted to the eastern U.S. at 19:00 UTC and to the western U.S. at 19:30 UTC. Information is valid as of presstime. For operational purposes be sure to consult the latest information from AMSAT. All communications frequencies are in MHz unless otherwise indicated.

Information on AMSAT-NA is available at www.amsat.org
 Mailing address: AMSAT-NA, 850 Sligo Avenue, Suite 600, Silver Spring, MD 20910-4703
 Voice: 301-589-6062 and 888-322-6728 FAX: 301-608-3410

OPERATIONAL ANALOG AMATEUR SATELLITES

DO-64 Delfi-C3

Catalog number: 32789 Launch Date: April 28, 2008
 Current communications mode: Science mode - beacon only
 Telemetry/Beacon 145.870
 Downlink: 145.880 - 145.920
 Uplink: 435.530 - 435.570
 Official webpage: www.delfic3.nl/

VO-52 HAMSAT

Catalog number: 28650 Launch Date: May 05, 2005
 Current communications mode: U/v - Indian Transponder
 Indian Beacon: 145.859330 CW
 Dutch Beacon: 145.860 12-wpm with CW message
 Mode and Antenna Polarization: V - LHCP and U - RHCP
 Indian Transponder
 Downlink: 145.930 - 145.870 USB/CW
 Uplink: 435.220 - 435.280 LSB/CW
 Dutch Transponder
 Downlink: 145.925 - 145.875 USB/CW
 Uplink: 435.225 - 435.275 LSB/CW
 Note: To know what transponder is switched on listen for the beacon that is active. Each transponder has a different beacon.
 Official webpage: www.amsatindia.org/hamsat.htm

AO-51 ECHO

Catalog number: 28375 Launch date: June 29, 2004
 Current Status: System reload in progress at presstime
 Broadcast identifier: PECHO-11 and BBS identifier: PECHO-12
 Beacon: 435.150
 Mode and Antenna Polarization: T - Linear, V - Linear, U - TX A (usually digital) LHCP/TX B (usually analog) RHCP, L - Linear, S - Linear
 FM Repeater 1
 Downlink: 435.300 FM
 Uplink: 145.920 FM
 FM Repeater 2 (QRP low power only)
 Downlink: 435.150 FM
 Uplink: 145.880 FM
 Analog voice
 Downlinks: 435.300 FM, 435.150 FM, 2401.200 FM
 Uplinks: 145.860 FM, 145.880 USB, 145.920 FM, 1268.700 FM
 Digital
 Downlinks: 435.150 FM 38k4 PBP with 1 watt output,

435.150 FM 9k6 Pacsat broadcast protocol, 2401.200 FM 38k4 AX.25
 Uplinks: 145.860 FM 9k6 PACSAT broadcast protocol, 1268.700 FM 9k6 Pacsat broadcast protocol
 Official webpage: www.amsat.org/amsat-new/echo/

SO-50 SAUDISAT-1C

Catalog number: 27607 Launch date: December 20, 2002
 Current communications mode: V/u
 Mode and Antenna Polarization: V - Linear and U - Linear
 Downlink: 436.795 FM
 Uplink: 145.850 FM - 67.0 Hz PL tone
 Operational note: To switch the transmitter on you need to send a CTCSS tone of 74.4 Hz. The order of operation is (allow for Doppler as necessary): First, transmit on 145.850 with a tone of 74.4 Hz to arm the 10 minute timer on board the spacecraft. Next transmit on 145.850 (FM Voice) using 67.0 Hz to turn the repeater on and off within the 10 minute window. Sending the 74.4 Hz tone again within the 10 minute window will reset the 10 minute timer.
 Official webpage: <http://saudisat.kacst.edu.sa/index.shtml> (not currently functional)

International Space Station (ISS) - ARISS

Catalog number: 25544 Launch date: November 20, 1998
 Callsigns: Belgian - OR4ISS, German - DP0ISS, Russian - RS0ISS/RZ3DZR, United States - NA1SS, Packet Mailbox: RS0ISS-11 and Digipeater callsign - ARISS
 Active Modes: FM Repeater V/u, Voice V/v, BBS V/v, APRS V/v, and SSTV V/v
 Mode and Antenna Polarization: V - Linear and U - Linear
 Digital/APRS (worldwide)
 Downlink: 145.825 FM 1k2 packet
 Packet Uplink: 145.825 FM 1k2 packet
 Voice
 Downlink (worldwide) 145.800 FM
 Uplinks: (Region 1) 145.200 FM/Region 2 and 3 144.490 FM
 Crossband Repeater:
 Downlinks: 145.800 FM and 437.800 FM (Kenwood)
 Uplinks: 1269.650 FM, 437.800 FM, and 145.990 FM - 67.0 Hz PL (Kenwood)
 SSTV
 Downlink: 145.800 FM Robot 36
 Official ARISS webpage: www.rac.ca/ariss
 ISS Fan Club: www.issfanclub.com
 APRS Tracking: www.ariss.net/
 ISS Daily Crew Schedule: <http://spaceflight.nasa.gov/station/timelines>
 Remember that the crew operates on UTC time. Also, not all of the time line is translated from Russian and posted.

FO-29 JAS-2

Catalog number: 24278 Launch Date: August 17, 1996
 Current Status: Recovery
 Callsign: 8J1JCS
 Current communications mode: V/u (Mode JA)
 Beacon: 435.795
 Mode and Antenna Polarization: V - RHCP and U - RHCP
 Voice/CW (Mode JA)
 Downlink: 435.800 - 435.900 CW/USB
 Uplink: 145.900 - 146.000 CW/LSB
 Digital Mode JD
 Downlink: 435.910 1200-baud BPSK or 9600-baud FSK
 Uplinks: 145.850 FM, 145.870 FM, 145.910 FM
 Digital Mode JD
 Downlink: 435.910 1200-baud BPSK or 9600-baud FSK
 Uplinks: 145.850 FM, 145.870 FM, 145.910 FM
 Current operational schedule: www.ne.jp/asahi/m-arai/gkz/satinfo/fo29e.htm
 JARL English webpage: www.jarl.or.jp/English/5_Fuji/ejasmenu.htm
 AMSAT-NA webpage: www.amsat.org/amsat-new/satellites/satInfo.php?satID=5&retURL=/satellites/status.php

Mineo Wakita, JE9PEL, has created a simple decoder program for FO29's CW telemetry downlink available at www.ne.jp/asahi/hamradio/je9pel/fo29cwts.htm

AO-27 AMRAD

Catalog number: 22825 Launch date: September 26, 1993
 Current communications mode: V/u
 Mode and Antenna Polarization: V - Linear and U - Linear
 Downlink: 436.797 FM
 Uplink: 145.850 FM
 Official webpage: www.ao27.org

AO-7 AMSAT OSCAR 7

Catalog number: 07530 Launch Date: November 15, 1974
 Current communications mode: Alternating between mode A and B every 24 hours
 Beacons: 29.502 CW, 145.972 CW, 435.100 CW, 2304.100 CW
 Downlinks: 29.400 - 29.500 CW/USB Mode A (1w PEP), 145.975 - 145.925 CW/USB Mode B (8w PEP), 145.975 - 145.925 CW/USB Mode C (2w PEP)
 Uplinks: 145.850 - 145.950 CW/USB Mode A and 432.125 - 432.175 CW/LSB Mode B
 Official webpage: www.amsat.org/amsat-new/satellites/sat_summary/ao7.php
 AO-7 Logbook and Resource website: www.planetemily.com/ao7/

OPERATIONAL DIGITAL AMATEUR SATELLITES

Pollux (ANDE-2)

Catalog Number: 35694 Launch Date: July 31, 2009
 Downlink: 145.825 1k2 AX.25

Castor (ANDE-2)

Catalog Number: 35693 Launch Date: July 31, 2009
 Downlink: 145.825 1k2 AX.25

BEVO-1/PARADIGM (DRAGONSAT-1)

Catalog Number: 35690 Launch Date: July 31, 2009
 Downlink: 437.325 9k6 GMSK and 437.325 20-wpm CW

AggieSat2 (DRAGONSAT-2)

Catalog Number: 35690 Launch Date: July 31, 2009
 Downlink: 436.250 9k6

CP-6 Polysat

Catalog Number: 35004 Launch Date: May 19, 2009
 Current Status: Not operational. The satellite is not becoming.
 Downlink: 437.365 1k2 AFSK

HAWKSAT 1

Catalog number: 35003 Launch Date: May 19, 2009
 Current Status: Unknown
 Downlink: 437.345?

Pharmasat

Catalog Number: 35002 Launch Date: May 19, 2009
 Current Status: Commissioning
 Downlink: 437.465 1k2 AFSK

ANUSAT

Catalog Number: 34808 Launch Date: April 20, 2009

Current Status: Unknown
Telemetry: 137.400
Downlink: 435.000
Uplink: 145.800

KKS-1 (Tokyo MCIT)

Catalog Number: 33499 Launch Date: January 23, 2009

Callsign: JQ1YYY

Beacon 437.385 AFSK/CW
Downlink: 437.455 AFSK/CW

IARU coordination status: www.amsat.org.uk/iaru/finished_detail.asp?serial=107

AMSAT-NA webpage: www.amsat.org/satellites/satInfo.php?satID=120&retURL=/satellites/status.php

STARS (Kagawa Univ) (Twin Satellites)

Catalog Number: 33498 Launch Date: January 23, 2009

Callsigns: JR5YBN/ JR5YBO

Beacons 437.305 FM/CW and 437.275 FM/CW
Downlinks: 437.485 FM/CW and 437.465 FM/CW

IARU coordination status: www.amsat.org.uk/iaru/finished_detail.asp?serial=99

AMSAT-NA webpage: www.amsat.org/satellites/satInfo.php?satID=121&retURL=/satellites/status.php

SOHLA-1 (Astro Tech)

Catalog Number: 33496 Launch Date: January 23, 2009

Current Status: Commissioning
Proposed Frequencies and Modes

Beacon 437.505 AFSK/CW
Downlink: 437.505 AFSK/CW

IARU coordination status: www.amsat.org.uk/iaru/formal_detail.asp?serial=101

KAGAYAKI (Solan Co.)

Catalog Number: 33495 Launch Date: January 23, 2009

Beacon 437.375 FSK9k6/CW
Downlink: 437.375 FSK9k6/CW

PRISM (Tokyo University)

Catalog Number: 33493 Launch Date: January 23, 2009

Current Status: Operational?

Callsign: JQ1YCX

Beacon 437.250 AFSK/GMSK/CW
Downlink: 437.425 AFSK/GMSK/CW

IARU coordination status: www.amsat.org.uk/iaru/finished_detail.asp?serial=97

AMSAT-NA webpage: www.amsat.org/satellites/satInfo.php?satID=119&retURL=/satellites/status.php

RS-30 Radio Sputnik 30 (Yubileiny)

Catalog Number: 32953 Launch Date: May 23, 2008

Current Modes: Telemetry, audio and images
Downlinks: 435.215 and 435.315

Official website: www.npopm.com/?cid=leoca&caid=43

AMSAT-NA website: www.amsat.org/satellites/satInfo.php?satID=115&retURL=/satellites/status.php

CO-66 Seeds II

Catalog number: 32791 Launch Date: April 28, 2008

Callsign: JQ1YGU

Downlink: 437.485

Project status updates: http://cubesat.aero.cst.nihon-u.ac.jp/english/seeds_2_e.html

IARU coordination status: www.amsat.org.uk/iaru/finished_detail.asp?serial=36

AMSAT-NA webpage: www.amsat.org/satellites/satInfo.php?satID=113&retURL=/satellites/status.php

CanX-2

Catalog number: 32790 Launch Date: April 28, 2008

Status: Operational in range of ground station only

Downlink: 437.478 GFSK

Project status updates: www.utias-sfl.net/nanosatellites/CanX2/

IARU coordination status: www.amsat.org.uk/iaru/finished_detail.asp?serial=46

AAUSAT-II

Catalog number: 32788 Launch Date: April 28, 2008

Downlink: 437.425 1k2 baud packet

Project status updates: www.ausatii.aau.dk/homepage/index.php?language=en&page=home

IARU coordination status: www.amsat.org.uk/iaru/finished_detail.asp?serial=60

Compass-1

Catalog number: 32787 Launch Date: April 28, 2008

Current communications mode: 4k8 MSK packet

Downlink: 437.275 CW and 437.405 Packet

Uplink: 145.980 FM

Project status updates: www.raumfahrt.fh-aachen.de/

IARU coordination status: www.amsat.org.uk/iaru/finished_detail.asp?serial=52

AMSAT-NA webpage: www.amsat.org/satellites/satInfo.php?satID=114&retURL=/satellites/status.php

CO-65 CUTE-1.7+APD II

Catalog number: 32785 Launch Date: April 28, 2008

Current Status: Digipeater

Telemetry beacon 437.2750 CW

Downlink: 437.475 9k6 Packet

Uplink: 1267.600

Project status updates: http://lss.mes.titech.ac.jp/ssp/cute1.7/index_e.html

Command station blog: <http://lss.mes.titech.ac.jp/ssp/cute1.7/blog/>

IARU coordination status: www.amsat.org.uk/iaru/finished_detail.asp?serial=78

AMSAT-NA webpage: www.amsat.org/satellites/satInfo.php?satID=112&retURL=/satellites/status.php

CAPE-1

Catalog Number: 31130 Launch Date: April 17, 2007

Current Status: Intermittent

Callsign: K5USL

Current communications mode: /u

CW Beacon 435.245 CW

Telemetry Downlink: 435.245 9k6 FSK AX.25

Note: Telemetry and CW interchange on the UHF downlink every 30 seconds.

IARU coordination status: www.amsat.org.uk/iaru/finished_detail.asp?serial=72

AMSAT-NA webpage: www.amsat.org/satellites/satInfo.php?satID=94&retURL=/satellites/status.php

CP-3

Catalog Number: 31129 Launch Date: April 17, 2007

Current communications mode: /u

Downlink: 436.845 1k2 AFSK AX.25

GENESAT-1

Catalog Number: 29655 Launch Date: December 16, 2006

Current communications mode: /u

Callsign: KE7EGC

Telemetry Beacon Downlink: 437.0695 1k2 AFSK

Official webpage: www.crestnrp.org/genesat1/ahc.html

CO-58 CubeSat XI-V

Catalog number: 28895 Launch Date: October 27, 2005

Current Status: Operational - CW beacon only

Callsign: JQ1YGW

Current communications mode: /u

Beacon 437.275 CW

Telemetry Downlink: 437.425 1k2 AFSK using AFK protocol

Official webpage: www.space.t.u-tokyo.ac.jp/cubesat/mission/V/

Pictures taken by this satellite, received by Mineo Wakita - JE9PEL: www.ne.jp/asahi/hamradio/je9pel/xivpcte.htm

CO-57 CubeSat XI-IV

Catalog number: 27848 Launch date: June 30, 2003

Current Status: Unknown

Callsign: JQ1YGW

Current communications mode: //u

Beacon 436.8475 CW

Telemetry 437.490 1k2 AFSK

Official webpage: www.space.t.u-tokyo.ac.jp/cubesat/mission/V/

AMSAT-NA webpage: www.amsat.org/satellites/satInfo.php?satID=96&retURL=/satellites/status.php

[satellites/satInfo.php?satID=96&retURL=/satellites/status.php](http://www.amsat.org/satellites/satInfo.php?satID=96&retURL=/satellites/status.php)

CO-56 CUTE-1.7+APD

Catalog number: 28941 Launch date: February 21, 2006

Current Status: Unknown

Callsign: JQ1YPC

Telemetry beacon 437.385 CW

Downlink: 437.470 1k2 FM AX25 or SRLL (active only near Japan?)

Uplink: 1268.500 9k6 GMSK

IARU coordination status: www.amsat.org.uk/iaru/finished_detail.asp?serial=56

Information webpage: <http://lss.mes.titech.ac.jp/ssp/spacerium/cute1blog/>

AO-51 ECHO

Catalog number: 28375 Launch date: June 29, 2004

(See listing in analog section of this report)

QuakeSat

Catalog Number: 27845 Launch Date: June 30, 2003

Current Status: Telemetry transmissions only

Current communications mode: /u telemetry

Downlink: 436.675 9k6 data packet

Quakesat webpage: www.quakefinder.com/services/quakesat-ssite/

CO-55 CUTE-1

Catalog Number: 27844 Launch date: June 30, 2003

Current communications mode: CW downlink (worldwide) and AX25 Packet with uplink command over Japan only

Mode U telemetry Downlink: 437.4000 1k2 AFSK

Mode U telemetry beacon Downlink: 436.8375 CW

AMSAT-NA webpage: www.amsat.org/satellites/satInfo.php?satID=69&retURL=/satellites/status.php

NO-44 PCSAT

Catalog number: 26931 Launch Date: September 30, 2001

Current Status: Telemetry transmissions only

Current communications mode: V/u

General usage

Uplink/Downlink: 145.827 1200 Baud

Special usage

Downlink: 144.390 1200 Baud

PCSAT APRS page: <http://pcsat.aprs.org>

APRS Telemetry Decoder program: www.xciv.org/~iain/aprstm/v1.2/

GO-32 Gurwin TechSat-1B

Catalog number: 25397 Launch Date: July 10, 1998

Current Status: Telemetry transmissions only

Broadcast Callsign: 4XTECH-11 and BBS Callsign: 4XTECH-12

Current communications mode: /u telemetry

Downlink: 435.225 FM (9600-baud FSK) and 435.325 (not currently available due to temperature problems)

Uplinks: 145.850 FM, 145.890 FM, 145.930 FM, 1269.700 FM, 1269.800 FM, 1269.900 FM

More on GO-32 at <http://asri.technion.ac.il/techsat/>

AMSAT-NA webpage: www.amsat.org/satellites/satInfo.php?satID=14&retURL=/satellites/status.php

RS-22 RADIO SPORT 22

Catalog number: 27939 Launch Date: September 27, 2003

Current Status: Operational - 70cm CW only

Current communications mode: /u

Beacon 435.352 and 145.818 (CW)

AMSAT-NA webpage: www.amsat.org/satellites/satInfo.php?satID=76&retURL=/satellites/status.php

International Space Station (ISS) - ARISS

Catalog number: 25544 Launch date: November 20, 1998

(See listing in analog section of this report)

LO-19 LUSAT

Catalog number: 20442 Launch date: January 22, 1990

Current Status: CW beacon only

Broadcast Callsign: LUSAT-11 and BBS: LUSAT-12a

Downlink: 437.125 CW and digital 437.150 SSB (1200-baud RC-BPSK)

Uplinks: 145.840 145.860 145.880 145.900 (all 1200-baud Manchester FSK)

General information and telemetry samples can be found at: www.telecable.es/personales/ea1bcu

The Uniden BCD996XT 21st Century Scanning Technology

By Larry Van Horn, N5FPW, Assistant Editor *Monitoring Times*

Just when I think that our current crop of public safety scanners can't get any better, a new scanner is released that advances the technology even further.

The new Uniden Bearcat BCD996XT base/mobile is truly a 21st century marvel of modern scanning technology. While this new scanner is a lineal descendant of the BCD996T, there are some major differences between them.

Released hot on the heels of the popular Uniden BCD396XT handheld scanner, many of the innovative features included in that scanner and the BCD996D can be found in this new Uniden release. Some of the existing features found in both the BCD396XT and BCD996T have been expanded and updated.

The BCD996XT is a state-of-the-art scanner radio with Trunk Tracker IV and automatic scanning capabilities. You can store in the dynamic memory conventional frequencies such as police, fire/emergency, marine, air, amateur, and other communications. You can store and scan services that use trunked radio systems and more. You can use the scanner's scroll control to quickly select channels and frequencies, and you can automatically program channels in a system using the auto store feature.

❖ Case, Controls and the Antenna

The 996XT case is the same size as its 996T predecessor, measuring 7.2 (W) x 5.9 (D) x 2.2 (H) inches and weighing in at 3.44 lbs without mounting bracket.

There is a multicolor backlight system (user selectable) for the scanner's 1-1/8 by 2-1/8-inch (64 x 128 full dot matrix) liquid crystal display. Colors selectable by the user include white, red, green, yellow, blue, magenta and cyan. You can turn off backlighting or set three levels for each color without going into the scanner menu system by pressing the volume control on the front of the unit. The keyboard backlight also uses the same color and control features that the LCD screen uses.

Controls and switches on the 996XT includes a knurled rotary encoder knob with push switch used for function operations, volume control with power on/off switch and push switch for back light control (see paragraph above), and squelch control with push switch for Close Call mode.

❖ Under the Hood

Looking inside this new scanner I found a world of scanning capability. Here are some

996XT features that BC396T/BCD996T owners will be familiar with (note: specifications are subject to change without notice).

- TrunkTracker IV with control-channel only scanning and I-Call monitoring: Tracks voice traffic on APCO P25, Motorola (analog and P16 mixed mode systems), EDACS (with EDACS ESK support), and LTR trunked systems. The 996XT can decode APCO25 digital audio signals, CTCSS/DCS/NAC decoding and NAC decoding. This unit has the ability to flag each channel as digital, analog, or both (all). This helps when setting up CTCSS/DCS/NAC decoding on a given frequency. The 996XT can also decode fire tone out alerts.
- Supports scanning of rebanded 800 MHz trunk analog radio systems
- Adaptive digital threshold automatically sets the digital decode threshold used to help monitor APCO 25 systems
- Close call RF capture and Close Call temporary store (last 10 hits)
- GPS support for location-based scanning, location alerts, and crows-flight navigation*
- Supported step sizes: 5, 6.25, 7.5, 8.33, 10, 12.5, 15, 20, 25, 50 or 100 kHz
- Multi-site support. You can program all the sites within a trunk system and they can all share one set of talkgroup, saving time and memory space.
- Temporary frequency memory lockouts. You can even temporarily lockout frequencies with birdies and other constant carrier frequencies during searching.
- Ten startup configurations reduce the amount of reloading of pre-programmed frequency loadouts. This is especially useful when traveling or if you just want to monitor something different for a change.
- 12 Service Searches - Public safety, news, ham radio, marine, railroad, air, CB radio, FRS / GMRS, racing, military air, FM broadcast, and special (itinerant frequencies)
- You can perform a scan of the memory channels followed by selected "service" search ranges. You can perform custom searches that let you program up to 10 search ranges. You can also perform a scan of the memory channels followed by up to 10 of these custom service searches. Quick search keys by-pass the menu entirely.
- Frequency/ID AutoStore - automatically store frequencies from a service or limit search into a conventional system or store talk group IDs into a trunked system
- 16 character text tagging for each system, group, channel, talkgroup, search range, and SAME group.
- Compatible with an optional BC-RH96 remote head
- SAME weather alert and weather priority
- Priority scan with priority plus
- Signal strength display
- Adjustable scan delay and adjustable hold (0-255 sec) per system, custom or service search
- Strong signal attenuation
- Independent Alert Tone Volume - lets you set the volume level of the following tones: key beep, emergency alert, channel alert, and close call alert. The unit also has analog and digital automatic gain controls (AGC).
- Repeater reverse and duplicate channel alert
- Broadcast signal ignore while searching (TV and radio

MT FIRST LOOK RATING (0-10 SCALE)

| | |
|------------------------------|----|
| Audio Quality | 10 |
| Audio Levels | 10 |
| Backlight/Display | 10 |
| Ease of Use | 6 |
| Feature Set | 10 |
| Keyboard/Control Layout..... | 9 |
| Overall Construction | 10 |
| Overall Reception | 10 |
| Owners Manual | 6 |
| Sensitivity..... | 9 |
| Selectivity..... | 9 |
| Spectrum Usability | 9 |

- station frequencies, pagers, etc)
- Record output
- Automatic backlight level detection (when used with the "Orange" wire connected to a headlight switched power lead)
- Upgradable firmware
- PC programming and control and wired cloning
- DIN / ISO in-dash mounting with included DIN-E sleeve.

❖ Trunk Tracking Capability

The BCD996XT is a Trunk Tracker IV model scanner. This lets you follow unencrypted conversations on analog Motorola, Motorola mixed mode (analog and digital/3600 baud) systems, Motorola Astro 25 (APCO 25 9600 baud) digital systems, EDACS (wide and narrow), EDACS SCAT, EDACS ESK and LTR trunked radio systems. Trunk systems in VHF, UHF, the new 700 MHz public safety band, 800 and 900 MHz bands can be tracked. This includes some of the trunk systems now being installed by the Department of Defense in the new 380-399.9 MHz LMR sub-band. The scanner can also scan both conventional and trunked systems at the same time.

The BCD996XT also does Motorola control channel trunking. If the scanner is set in this mode, the user can set it up so that it tracks a Motorola trunk system using only control channel data. You do not have to program all of the system's voice channel frequencies into memory in this mode, as long as all possible control channels have been programmed.

❖ What's New

There are several new features and innovations in the 996XT that are unique to this radio. They include:

- Support for P25 conventional channels that include NAC and TGID user differentiation (P25 one-frequency trunk)
- Control channel data output allows the analysis of control channel data without the need to perform invasive modifications to the scanner. This allows you to use certain selected software



SEE More and HEAR More!


With the SR2000A and AR8200MkIII from AOR

SR2000A Color Frequency Monitor

The SR2000A is an ultra-fast spectrum display monitor that lets you SEE received signals in FULL color.

Using the power of FFT (Fast Fourier Transform) algorithms with a sensitive receiver covering 25MHz ~ 3GHz*, the SR2000A features a color monitor that displays up to 40MHz spectrum bandwidth**, a switchable time-lapse "waterfall" display or live video in NTSC or PAL formats.

Ultra sensitive, incredibly fast, yet easy to use with a high quality internal speaker for crisp, clean audio signals. Scans 10MHz in as little as 0.2 seconds! Instantly detects, captures and displays transmitted signals. PC control through RS232C serial port or USB interface. With 12 VDC input, it's perfect for base, mobile or field use.



AR8200MkIII Handheld Receiver



From inter-agency coordination to surveillance, you can't know too much. The world-class AR8200MkIII portable receiver features a TXCO that delivers solid frequency stability and performance not found in most desktop units. With 1,000 alphanumeric memory channels, it covers 500 KHz ~ 3GHz*. Improved RF circuits combine greater sensitivity, resistance to intermod and enhanced Signal to Noise ratio. It offers increased audio frequency response and includes NiMH AA batteries that can be charged while the unit is in use.

Optional internal slot cards expand the AR8200MkIII's capabilities. Choose from Memory Expansion (up to 4,000 memories), CTCSS Squelch and Search, and Tone Eliminator.

The AR8200MkIII offers "all mode" reception that includes "super narrow" FM plus wide and narrow FM in addition to USB, LSB, CW and standard AM and FM modes. It also features true carrier reinsertion in USB and LSB modes and includes a 3KHz SSB filter. The data port can be used for computer control, memory configuration and transfer, cloning or tape recording output.

A special government version, AR8200MkIII IR features infra-red illumination (IR) of the display and operating keys. The IR illumination function is selectable, allowing operation by users wearing night vision apparatus without removing goggles and waiting for the eyes to re-adjust. Ideal for military, law enforcement and surveillance operators.



Authority on Radio
Communications

AOR U.S.A., Inc.
20655 S. Western Ave., Suite 112, Torrance, CA 90501, USA
Tel: 310-787-8615 Fax: 310-787-8619
info@aorusa.com http://www.aorusa.com

* Government version, cellular blocked for US consumer version.
**No audio is available when the frequency span is set to 20MHz or 40MHz.
Specifications subject to change without notice or obligation.

SEE more and HEAR
more with AOR, the
serious choice in
Advanced Technology
Receivers™.

TABLE ONE: BCD996XT FREQUENCY COVERAGE

| Frequency Range (MHz) | Modulation | Step (kHz) | Default |
|-----------------------|------------|------------|---------|
| 25.0000 | 27.9950 | AM | 5.0 |
| 28.0000 | 29.6800 | NFM | 20.0 |
| 29.7000 | 49.9900 | NFM | 10.0 |
| 50.0000 | 53.9800 | NFM | 20.0 |
| 54.0000 | 71.9500 | WFM | 50.0 |
| 72.0000 | 75.9950 | FM | 5.0 |
| 76.0000 | 87.9500 | WF | 50.0 |
| 88.0000 | 107.9000 | FMB | 100.0 |
| 108.0000 | 136.9750 | AM | 25.0 |
| 137.0000 | 143.9875 | NFM | 12.5 |
| 144.0000 | 147.9950 | NFM | 5.0 |
| 148.0000 | 150.7875 | NFM | 12.5 |
| 150.8000 | 161.9950 | NFM | 5.0 |
| 162.0000 | 173.9875 | NFM | 12.5 |
| 174.0000 | 215.9500 | WFM | 50.0 |
| 216.0000 | 224.9800 | NFM | 20.0 |
| 225.0000 | 379.9750 | AM | 25.0 |
| 380.0000 | 512.0000 | NFM | 12.5 |
| 764.0000 | 775.9875 | NFM | 12.5 |
| 794.0000 | 805.9875 | NFM | 12.5 |
| 806.0000 | 823.9875 | NFM | 12.5 |
| 849.0125 | 868.9875 | NFM | 12.5 |
| 894.0125 | 956.0000 | NFM | 12.5 |
| 1240.0000 | 1300.0000 | NFM | 25.0 |

Note: The scanner's frequency coverage is not continuous and does not include the cellular telephone, most of the UHF TV bands, or the 956-1240 MHz frequency range.

packages to analyze trunk radio systems for frequencies, talkgroups, radio IDs and more.

- Independent GPS control of sites and channel groups*
- Fire tone out search with a built-in frequency counter to display the received tones during a tone out.
- Band scope gives a graphic representation of signal activity with a frequency span of 0.2 to 500 MHz and steps from 5 to 100 kHz.
- Multi-color display backlight
- P25 digital NAC decoding
- System/channel number tagging to provide rapid access to a specific system or channel.
- Individual channel volume offset
- Intermediate frequency exchange that changes the IF used for a selected frequency to help avoid image and other mixer-product interference on a frequency.
- Key safe mode that lets you hand the scanner to a novice user and prevent them from modifying the programming.
- Private systems let you flag any system programmed into the scanner so that it cannot be read out or modified by the user.
- Priority ID scan on trunked systems
- Preemptive priority on Motorola analog systems
- Negative channel dropout delay (forced resume)
- Channel alert (using both tones and backlight color)

* A GPS unit is required to use this feature and is not included with the 996XT.

❖ What's in the box?

In addition to the BCD996XT scanner, accessories in the box include an AD1009 AC adapter, cigarette lighter adapter power cord, mobile mounting bracket, DIN-E sleeve, a push on type (BNC) telescopic antenna, PC DB9 serial cable and owner's manual on CD (no printed manual, CD manual not included in our review package).

❖ Rating and Final Thoughts

As with its predecessor, I was particularly impressed with the BCD996XT performance when I conducted a side by side test with my Uniden BCD396T, BCD996T and BC796D scan-

ners. In most cases, sensitivity and selectivity appeared to be slightly better on the BCD996XT.

But those of you who have read this column in the past know that no scanner is perfect, at least in my opinion. My chief complaint with the 996XT and Uniden DMA scanners in general is the steep learning curve. Given this feature-rich scanner and the many systems it can monitor, I do not know how Uniden could simplify this learning curve, given the overall complexity and feature set. On the other hand, from the consumer's point of view this is a serious issue which needs to be addressed. Uniden is not alone: the three major manufacturers (Uniden, GRE and AOR) all face this dilemma, and they need to invest time and staff in making the operating manuals more intuitive. In order to use the full capability of these scanners, one must understand them better, but unfortunately, the manuals by and large hinder that process.

My second complaint is directly tied to the manual itself. I have struggled with trying to quantify my issues with it, and the best I can come up with is to say it is "kludgy." I didn't receive the CD manual that was supposed to be included with the unit, so I could not evaluate if it was any better, but my guess is it wasn't.

So how are you to learn to use this fine piece of radio equipment? Let me offer four pieces of advice to those who purchase this radio: read the manual several times, practice programming the scanner using the examples in the manual, use software to program the radio, and read the manual again and again. You do have the option of going up to various online radio hobby forums and asking specific questions, but this takes time and may not help you in the short run. Maybe what is needed here is a central source for questions and answers – an FAQ type of site.

I also noted that, like its 996T predecessor, the radio defaults to 5 kHz spacing in the 150.8-162.0 MHz public safety band. You can change that spacing, but it still will not match the current bandplan in use, due to the break in spacing around 154.500 MHz. The majority of this band now uses 7.5 kHz spacing with the exception of the break I mentioned above. Other than that, Uniden has come a long way in setting their search steps in line with current spectrum practices.

Finally, while the GPS capability is a neat feature, it is very labor and research intensive to get it up and

operating. I am sure with time, like other aspects of the scanner hobby, information will be shared through the internet to aid hobbyists in programming location information for a variety of radio systems nationwide. But that will be at some point down the road and only a few will probably fully utilize the GPS features in this scanner in the near term.

Bottom line, this is one heck of a scanner. This unit is the most advanced and feature-rich radio scanner ever released by any radio company. No scanner in the marketplace even gets close to the BCD996XT in features, listening capability, and overall performance, especially in its price range. There is a lot of scanning capability loaded into this small package.

So, if you are looking for one unit that does a lot, with the features you could only dream about three years ago, this is it. This is truly a high tech base/mobile scanner for the 21st century.

The Uniden BCD996XT (SCN 21 – www.grove-ent.com/996xt.html) is available from Grove Enterprises (1-800-438-8155 or www.grove-ent.com) for \$499.95 plus shipping and handling.

TABLE TWO: MISCELLANEOUS SPECIFICATIONS

Initialize Memory: Press and hold the "2+9+Hold" keys

Receiver type – Triple Conversion

1st Heterodyne

| | |
|----------------------|---|
| 25.000-319.995 MHz | Upper Heterodyne 1st IF 380.705 ~ 380.800 MHz |
| 320.000-519.995 MHz | Upper Heterodyne 1st IF 265.600 ~ 265.505 MHz |
| 764.000-805.995 MHz | Lower Heterodyne 1st IF 265.500 ~ 265.595 MHz |
| 806.000-1300.000 MHz | Lower Heterodyne 1st IF 380.700 ~ 380.800 MHz |

2nd Heterodyne

| | |
|----------------------|------------------------------------|
| 25.000-319.995 MHz | Lower Heterodyne 2nd IF 10.800 MHz |
| 320.000-805.995 MHz | Upper Heterodyne 2nd IF 10.800 MHz |
| 806.000-1300.000 MHz | Lower Heterodyne 2nd IF 10.800 MHz |

3rd Heterodyne

| | |
|-----------|---------------------------------|
| All Bands | Lower Heterodyne 3rd IF 450 kHz |
|-----------|---------------------------------|

Limits:

Channels: 25,000 maximum; Systems: 500 maximum; Groups per system: 20 maximum; Talkgroups per trunked system: 500 maximum; Channels per conventional system: 1000 maximum; Scan Rate: 100 channels per second (conventional mode); Search Rate: 300 steps per second (on 5 kHz steps); System Quick Key range: 0-99; Group Quick Key range: 0-9; Custom Search Ranges: 10; Startup Keys: 10; System Number Tagging: 999; Channel Number Tagging: 999; Preprogrammed Service Search Bands: 12; Band Scope Span Range: 0.2 MHz To 500 MHz; and Band Scope Step: 5 kHz To 100 kHz.

Operating temperature – Normal -20°C to +60°C; close call -10°C to +60°C; Storage -30°C-+70°C

Scan rate – 100 channels per second (conventional mode)

Search rate – Normal 100 steps per second/Turbo 300 steps per second
Audio output – 3W maximum into 8-ohm speaker; 30mW nominal into 32-ohm stereo headphone

Power Requirements – DC 11.0V to 16.6V via Cigarette Lighter Cord, AC Adapter (AD-1009) all included.

External Jacks:

| |
|---|
| Antenna Jack – BNC Type 50-ohm nominal impedance |
| Phone Jack – 3.5-mm (1/8-inch) Stereo Type |
| External Speaker Jack – 3.5-mm (1/8-inch) Monaural Type |
| Record Out Jack – 3.5-mm (1/8-inch) Stereo Type |
| DC Power Jack – 5.5-mm center pin positive |
| Remote Interface Jack – Four pin mini type |
| GPS Interface Jack – D-sub nine pin (male type) |

Note: Features, specifications, and availability of optional accessories are all subject to change without notice by the manufacturer. Information presented above was based on the test unit provided by the manufacturer. Specifications certificated accordance with FCC Rules and Regulations Part 15 Subpart C as of date of manufacture.

MTX PRESS

**SPECIAL
OFFER
BELOW!**

Going **Green** has never been more exciting!

Before the rising prices of gasoline, and before going “green” became a sales pitch, Monitoring Times created MT Express. The full version of the magazine you’ve come to depend on, in full electronic form. Now going into our 11th year of digital perfection, MT Express is better than ever. You get more with our digital magazine than you could ever have with print. The entire magazine is full color. All of the web links are clickable, so if you see a link to a website that you want to visit, just click on it! Want to email an author? Just click on their email address at the top of their column, and MT Express opens your email program, drops in their address, and is ready for your input! All of this, and it’s even CHEAPER than the regular print version! Plus, you’ll get it faster than you would your print copy, no matter where you are in the world. Now is the time to make the switch to digital. Sure, it’s saving a tree and saving some gas, but it’s also getting you what you need, when you want it. Make the switch today.

For a mere \$19.95 U.S., **MT EXPRESS** gives you *Monitoring Times* magazine

- in PDF format viewable with free software, delivered by FTP
- viewable in **brilliant color** (the **whole** magazine, not just what you see in the print version) on your computer screen
- easily navigated by clicking on the Table of Contents
- printable using your own computer printer
- searchable to find every mention of a topic or station schedule
- importable into your frequency databases
- compatible with software to convert text to audio for sight impaired listeners

Now with
MTXTRA

Not only do you now have the complete *Monitoring Times* magazine, in full color, but for no extra cost, we are now adding **MTXTRA**, which will have a worldwide broadcast guide with **ALL** offered languages, not just English! So no matter where you are in the world, *Monitoring Times* has something just for you!

To find out if this new subscription is the delivery solution for you, you may download a sample issue for free! Just go to <http://www.grove-ent.com> to find out how.

If you order NOW, you will get 14 ISSUES for the price of 12! That’s right, for only \$19.95 you’ll get an EXTRA 2 MONTHS AND MTXTRA! Just mention code MTNOV09 when you place your order!

GROVE

800-438-8155

828-837-9200 fax: 828-837-2216

WWW.GROVE-ENT.COM



What's NEW

Tell them you saw it in Monitoring Times

New Products from MP Antennas

Reviewed by Bob Grove W8JHD

❖ The Super-M Ultra Mobile Antenna

The new MP Antennas Super-M is a unique design. The original Super-M had three straight elements, equally spaced, and angled slightly outward from the base. This new model, however, has more elements for an expanded, continuous frequency coverage.

The manufacturer claims extremely wide-band receive coverage – 25-6000 MHz (6 GHz)! For transmitting, it can accept up to 200 watts of RF power up to 512 MHz, and 100 watts above that frequency. Impedance matching for normal 50 ohm coax is best above 120 MHz, providing an average 1.6:1 to 1.8:1 VSWR continuously through 6000 MHz.

Maximum height is 19 inches, with the top of the cluster of elements flaring out to a 12 inch diameter. Weight (minus the base) is a mere 5 ounces, yet the sturdy stainless-steel elements, firmly locked in place with set screws, provide reliable ruggedness with their low wind load at high road speeds.

The standard NMO mount makes it a ready replacement for professional mobile whip applications. A special magnetic-mount accessory is also available for no-hole attachment to a vehicle.

The new, mobile-mount antenna is sure to draw attention; on a recent vacation trip, it was very clear the folks passing me on the interstate were sizing up the rooftop antenna. It was even more clear – when I parked for shopping, motels, or even at tourist attractions – that this antenna would draw attention and a lot of questions!

Performance

So how did it perform? Very well, indeed. The accompanying chart shows the relative signal strengths when measured on an ATTEN



5011 spectrum analyzer. Signals do fluctuate, so these results are within +/-2 dB after three complete runs through the spectrum.

The competition was shared among five magnetically-attached mobile antennas – the new MP Antennas Super-M Ultra Mobile antenna, the well-designed Austin Spectra, Austin's revered Condor flex antenna, a generic multi-band VHF/UHF flex whip, and a simple 18" whip.

Interpreting the Results

So what do all these numbers tell us? The numbers are actual signal levels in decibels for various signals received at the frequencies shown. The highlighted readings show the strongest responses and the antenna(s) that provided them.



Keep in mind that it takes a 6 dB difference to register one S unit on an S-meter, so one or two dB difference is barely detectable to

the discriminating ear, even on the weakest signals. However, when a signal is mostly buried in noise, ringing it up several dB can make a difference.

In our test, the new MP Antennas Super-M outperformed or equaled the competitors seven out of eleven times across the spectrum. On two more frequencies, it was within 2 dB of the closest competitor – hardly noticeable, if at all. So, in a practical sense, the "listenability factor" equaled or outperformed the other antennas ten out of eleven times.



❖ The Super-M Ultra Base

The Super-M is also available as the Ultra Base for fixed installations. This sturdy yet lightweight (2.1 lb) model includes a drooping ground plane array making the maximum tip-to-tip antenna height 44 inches. The ground plane elements flare out at its base to a 33-inch diameter. The stainless steel wire elements provide a good combination of low wind load and rugged weather durability. It utilizes an NMO mount with a female N connector for the attachment of coax cable.



The clever design is essentially a modified discone with a top cluster of various-length elements to enhance harmonic response, thus dramatically increasing the bandwidth of the antenna over a continuous 100-6000 MHz swath of spectrum. Our transmit test showed it to have excellent performance over the 140-160 and 420-466 MHz ranges. The manufacturer's lab tests show a VSWR averaging 1.2:1 to 1.6:1 over the entire advertised frequency range, with a minor 1.9:1 spike at 200 MHz, and only reaching 3:1 at 50 MHz.

The MP Antennas Super-M Ultra Mobile and Ultra Base are available for \$119.99 and \$199.99 respectively from Grove Enterprises and other MT advertisers.

RELATIVE SIGNAL STRENGTH RECEPTION COMPARISON

| FREQ. MHz | MP Antennas | AUSTIN | CONDOR | MULTI WHIP | 18" WHIP |
|-----------|-------------|--------|--------|------------|----------|
| 38 | 10 | 8 | 20 | 15 | 12 |
| 50 | 25 | 13 | 12 | 9 | 20 |
| 95 | 44 | 38 | 27 | 10 | 35 |
| 103 | 64 | 50 | 60 | 54 | 60 |
| 152 | 32 | 32 | 25 | 27 | 30 |
| 162 | 26 | 15 | 16 | 17 | 20 |
| 463 | 45 | 50 | 42 | 42 | 42 |
| 572 | 20 | 18 | 8 | 12 | 12 |
| 860 | 24 | 23 | 26 | 14 | 26 |
| 882 | 12 | 8 | 14 | 8 | 12 |
| 996 | 16 | 0 | 12 | 6 | 8 |

New MP Antennas

The newest antennas are now at Grove!



The Super-M Ultra Mobile

MP Enterprises claims extremely wideband receive coverage—25-6000 MHz (6 GHz)! For transmitting, it can accept up to 200 watts of RF power at 50 ohms impedance from 120-512 MHz, and 100 watts from 512-6000 MHz. VSWR averages 1.6:1-1.8:1 continuously through 6000 MHz.

Maximum height is 19 inches, with the top of the cluster of elements flaring out to a 12 inch diameter. Weight (less base) is a mere 5 ounces, yet the sturdy, stainless-steel elements, firmly locked in place with set screws, provide reliable ruggedness with their low wind load at high road speeds.

The standard NMO mount makes it a ready replacement for professional mobile whip applications. A strong magnetic-mount with cable is optionally available for no-hole attachment to a vehicle.



The Super-M Ultra Base

For fixed installations this sturdy, yet lightweight (2.1 lbs) model includes a drooping ground plane array, making the maximum tip-to-tip antenna height 44", flaring out at its base to a 33" diameter. The stainless steel wire elements provide a good combination of low wind load and rugged weather durability. It utilizes an NMO mount with a female N connector for the attachment of coax cable.

The top cluster of various-length elements enhances harmonic response, dramatically increasing the bandwidth of the antenna over a continuous 100-6000 MHz swath of spectrum. We performed transmit tests from 140-160 and 420-466 MHz with excellent results. The manufacturer's lab tests show a VSWR averaging 1.2:1 to 1.6:1 over the entire advertised frequency range, with a minor 1.9:1 spike at 200 MHz, and only reaching 3:1 below 50 MHz, providing excellent VHF/UHF performance.

ANT61NMO - Super-M Ultra Mobile, NMO mount - \$109.99

ANT61 - Super-M Ultra Mobile, magnetic mount - \$124.95

ANT61MBS - Super-M Ultra Base - \$199.99

GROVE

800-438-8155

828-837-9200 fax: 828-837-2216

www.grove-ent.com

order@grove-ent.com

7540 Highway 64 West

Brasstown, NC 28902

HEAR. THERE. EVERYWHERE.

RX-320D

LISTEN TO THE WORLD ON YOUR PC! NOW USB READY!

General coverage from 100 kHz – 30 MHz. "Black box" receiver connects to your PC via serial port or USB connector. Your PC provides the operation horsepower. A 12 kHz I-F output is included for decoding DRM transmissions with your PC sound card (user supplies decoding software). Download the actual operating software from our website for a pre-purchase test drive. \$369

RX-340

USED BY GOVERNMENTS WORLDWIDE!

HF SWL receiver, 5 kHz – 30 MHz. IF stage DSP. Sync AM/selectable sideband, SAM, AM, SSB, ISB, CW, FM. Over 90 bandwidth filters, programmable AGC, built-in high stability TCVCXO. Completely remote controllable via RS-232 interface. DRM ready, no modification needed (user supplies decoding software). 90-264 VAC operation. \$4,250

1254

KIT BUILDING IS A WORLD OF FUN!

Build your own HF SWL receiver with our model 1254 shortwave receiver kit. 500 kHz – 30 MHz coverage in 2.5 kHz steps with clarifier control allowing tuning of all frequencies. LED digital readout. AM, SSB, CW capable. Complete step-by-step instructions and all components included. See our website for information on other available kits! \$195



RX-320D



RX-340



1254

1185 Dolly Parton Pkwy., Sevierville, TN 37862 800-833-7373 www.tentec.com

Mon-Fri 8:00-5:30 EST We accept Visa, MC, American Express, and Discover Office: (865) 453-7172 Service: (865) 428-0364

TENTEC

INDEX OF ADVERTISERS

| | |
|---------------------------------|----------------------|
| Antique Wireless..... | 65 |
| AOR..... | Cover 2, 71 |
| Kevin Carey..... | 21 |
| C Crane..... | 55 |
| CIDX..... | 76 |
| Communications Electronics..... | 17 |
| Computer Aided Technology | 25 |
| Grove Enterprises .. | 15, 23, 25, 75, CVR3 |
| ICOM | Cover 4 |
| MT Express..... | 73 |
| NASB | 33 |
| Popular Communications | 63 |
| Robl, Ernest..... | 57 |
| Small Planet Systems | 55 |
| Ten-Tec..... | 75 |
| Universal Radio | 5, 76 |
| WINRADiO..... | 1 |
| Xtal Society..... | 65 |

Stock Exchange

LINE ADS

NON-COMMERCIAL SUBSCRIBER RATES: \$.25 per word. All merchandise must be personal and radio-related.
COMMERCIAL, NON-SUBSCRIBER, AND MULTIPLE SALES RATES: \$1.00 per word. Commercial line ads printed in bold type.

Ads for Stock Exchange must be received 45 days prior to publication date. All ads must be paid in advance to Monitoring Times. Ad copy must be typed for legibility.

1-3/4" SQUARE DISPLAY AD:

\$50 per issue if camera-ready copy or, \$85 if copy to be typeset. Photo-reduction \$5 additional charge. For more information on commercial ads, contact Beth Leinbach, 828-389-4007.

Subscribe to *MT* for as little as \$17.95 (U.S. Second Class Mail)

7540 Hwy. 64 W.; Brasstown, NC 28902
1-800-438-8155 US and Can.; 828-837-9200; Fax 828- 837-2216
e-mail order@grove-ent.com

| | 6 months | One Year | Two Years | Three Years |
|--------------------------------|-----------------------------------|------------------------------------|------------------------------------|------------------------------------|
| Electronic Subscription | <input type="checkbox"/> \$17.95 | <input type="checkbox"/> \$19.95 | <input type="checkbox"/> \$38.90 | <input type="checkbox"/> \$57.85 |
| US Second Class Mail | <input type="checkbox"/> \$32.95 | <input type="checkbox"/> \$32.95 | <input type="checkbox"/> \$59.95 | <input type="checkbox"/> \$89.95 |
| US 1st Class Mail | <input type="checkbox"/> \$32.95 | <input type="checkbox"/> \$59.95 | <input type="checkbox"/> \$119.00 | <input type="checkbox"/> \$179.95 |
| Canada Surface* | <input type="checkbox"/> \$22.95* | <input type="checkbox"/> \$42.95* | <input type="checkbox"/> \$79.95* | <input type="checkbox"/> \$119.95* |
| Canada Air* | <input type="checkbox"/> \$35.95* | <input type="checkbox"/> \$69.95* | <input type="checkbox"/> \$125.95* | <input type="checkbox"/> \$189.95* |
| Foreign International* | <input type="checkbox"/> \$30.95* | <input type="checkbox"/> \$58.95* | <input type="checkbox"/> \$119.95* | <input type="checkbox"/> \$179.95* |
| Foreign Air* | <input type="checkbox"/> \$62.95* | <input type="checkbox"/> \$119.95* | <input type="checkbox"/> \$229.95* | <input type="checkbox"/> \$349.95* |

* All payments must be in US funds drawn on a US bank.

MasterCard, Visa, and Discover Card accepted!



www.SecondHandRadio.com **FREE** classified advertising with photos for used radios & electronics.

Log stations, manage QSLs with Reception Log: www.dxtreme.com

Got something you'd like to sell? Can't find something you've been searching for? *MT* is THE way to buy or sell all of your radio equipment! It's inexpensive and is seen by tens of thousands of fellow hobbyists! Call today to get your listing in the next issue!

MT BLOGS

Blogs offer an opportunity for columnists to share information that does not make their columns. The news might be too timely for deadline, too short, confined to a small geographical area, too far away to be heard in North America, or even off the columnist's regular "beat." Bookmark these blogs for frequent visits!

MT: AMERICAN BANDSCAN

<http://americanbandscan.blogspot.com/> - by Doug Smith

MT: FED FILES

<http://mt-fedfiles.blogspot.com/> - by Chris Parris

MT: MILCOM

<http://mt-milcom.blogspot.com/> - by Larry Van Horn

Larry's Monitoring Post

<http://monitor-post.blogspot.com/> - by Larry Van Horn

MT: SHORTWAVE

<http://mt-shortwave.blogspot.com/> - by Gayle Van Horn

MT: UTILITY WORLD

<http://mt-utility.blogspot.com/> - by Hugh Stegman

Looking for Writers

MT is soliciting feature articles, reviews, and how-to articles covering shortwave broadcasting, utilities, scanning, frequency profiles, construction projects or whatever excites you! Contact Feature Editor Ken Reitz at kenreitz@monitoringtimes.com or write c/o Monitoring Times, 7540 Hwy 64 West, Brasstown, NC 28902.

Join the Club!

Open to hobbyists worldwide, the **CANADIAN INTERNATIONAL DX CLUB** is Canada's national, general coverage radio club serving members since 1962.

For a free sample of our monthly electronic newsletter, **Messenger**, please e-mail CIDX at:

cidxclub@yahoo.com
Web: www.cidx.ca

HUGE 100 PAGE CATALOG

- Shortwave & Ham Gear
- Scanners & RTTY/FAX
- Antennas & Accessories
- Radio Books & CDs.

Send \$1 to



Universal Radio
6830 Americana Pkwy.
Reynoldsburg, OH 43068
Tel. 800 431-3939
www.universal-radio.com

GROVE

**Your Source for Radio Scanners,
Receivers, Accessories,
and Publications**

**Grove means service. You won't find
better customer service anywhere. BUY TODAY!**

Established in 1979 by well-known communications expert Bob Grove, Grove Enterprises has become a world leader in radio monitoring equipment, accessories, and publications.

If you decide you don't like a product, Grove Enterprises doesn't penalize you for it. There is NO restocking fee so long as you call our toll free number for a return authorization within fifteen days of shipment and the item is returned in new condition. Once the item is received we will give you credit toward another item or issue a full refund (less shipping charges). Software cannot be returned if opened.

That's it! No hassle! No negotiations! Just call 1-800-438-8155 and our friendly staff will assist you with a return authorization number.



Shipping/ Handling Charges

| Total Order | Shipping Charges |
|------------------|------------------|
| \$1-\$29.99 | \$3.00 |
| \$30-\$49.99 | \$6.95 |
| \$50-\$99.99 | \$9.95 |
| \$100-\$399.99 | \$13.95 |
| \$400-\$899.99 | \$17.95 |
| \$900-\$1499.99 | \$20.95 |
| \$1500-\$1999.99 | \$24.95 |
| \$2000-\$2499.99 | \$28.95 |
| \$2500+ | \$32.95 |

GROVE

**CALL
TODAY!**

(800) 438-8155

www.grove-ent.com

Grove Enterprises, Inc. - www.grove-ent.com

(800) 438-8155; (828) 837-9200; fax: (828) 837-2216

7540 Hwy 64 W; Brasstown, NC 28902 - email: order@grove-ent.com

GRE

| | | |
|---------|-------|----------|
| PSR-100 | SCN16 | \$99.95 |
| PSR-200 | SCN17 | \$99.95 |
| PSR-300 | SCN13 | \$179.95 |
| PSR-400 | SCN14 | \$179.95 |
| PSR-500 | SCN18 | \$449.95 |
| PSR-600 | SCN19 | \$449.95 |

UNIDEN

| | | |
|----------|-------|----------|
| BCT15X | SCN31 | \$219.95 |
| BCD996XT | SCN21 | \$499.95 |
| BCD396T | SCN47 | \$459.95 |
| BCD396XT | SCN53 | \$499.95 |
| BCD346XT | SCN45 | \$219.95 |
| BC898T | SCN44 | \$194.95 |
| BCT8 | SCN08 | \$162.95 |
| BC246T | SCN46 | \$189.95 |

ICOM

| | | |
|----------|--------|----------|
| R5 Sport | SCN12 | \$174.95 |
| R20 | SCN 20 | \$519.95 |

ALINCO

| | | |
|-----------|-------|----------|
| DJ-X7T | SCN 3 | \$179.95 |
| DJ-X2000T | SCN10 | \$539.95 |
| DJ-X3TD | SCN11 | \$179.95 |

AOR

| | | |
|------------|-------|----------|
| AR8200IIIB | SCN51 | \$629.95 |
|------------|-------|----------|

RAMSEY

| | | |
|-----------------------|-------|----------|
| ABM1 Air Band Monitor | SCN05 | \$149.95 |
|-----------------------|-------|----------|

YAESU

| | | |
|--------|-------|----------|
| VR-500 | SCN06 | \$219.95 |
|--------|-------|----------|

ANTENNAS & CABLES

| | | |
|--|----------|----------|
| Grove Hidden Flex-tenna | ANT49 | \$19.95 |
| Austin Condor | ANT 14 | \$34.95 |
| Grove Scanner Beam III | ANT 03 | \$69.95 |
| Procomm CD144M/BN mag mount antenna | ANT50 | \$19.95 |
| 800 MHz for handhelds | ANT 22 | \$29.95 |
| 800 MHz base w/ right-angle conn. | ANT 23 | \$34.95 |
| OMNI II Scanner | ANT 5 | \$29.95 |
| WiNRADiO AX-71C Discone | ANT01 | \$89.95 |
| Grove Scanner Beam III ANT03 | \$69.95 | |
| WiNRADiO AX-37A Wide-band Log Periodic | ANT28 | \$389.95 |
| WiNRADiO AX-37AM Wide-band Log Periodic | ANT29 | \$499.95 |
| WiNRADiO AX-07B flexible VHF/UHF | ANT47 | \$24.95 |
| WiNRADiO AX-91M magnetic antenna base | ANT48 | \$24.95 |
| Icom AH-8000 Wide-coverage Discone | ANT54 | \$249.95 |
| Grove Flex-tenna HVU | ANT45 | \$14.95 |
| Grove Flex-tenna VU | ANT46 | \$9.95 |
| Professional Wideband Discone | ANT 9 | \$99.95 |
| Scantenna + 50' coax | ANT 7 | \$49.95 |
| Super-M Ultra Base Station | ANT61MBS | \$189.95 |
| Super-M Ultra Mobile antenna w/NMO mount | ANT61NMO | \$109.95 |
| Super-M Ultra Mobile mag mount | ANT61 | \$124.95 |
| Super-M Multiband base antenna | ANT10MBS | \$99.95 |
| Super-M Mobile antennna w/ NMO mount | ANT10NMO | \$79.95 |
| AOR DA3000 Aerial Discone | ANT 11 | \$139.00 |
| AOR MA500 Wide Range | ANT 12 | \$99.00 |
| AOR SA7000 super-wide receiving | ANT 39 | \$229.95 |
| WiNRADiO WR-AX-31C Log-Periodic Antenna | ANT 58 | \$139.95 |
| Grove Universal Telescoping Whip | ANT 6 | \$14.95 |
| Super-M Superior Mobile Antenna | ANT 10 | \$94.95 |
| Create CLP51301N Log-Periodic Antenna | ANT 16 | \$409.95 |
| Create CLP51302N Log-Periodic Antenna | ANT 17 | \$299.95 |
| 50' of RG-6U cable | CBL 50 | \$19.95 |
| 100' of RG-6U cable | CBL 100 | \$24.95 |

MISCELLANEOUS ACCESSORIES

| | | |
|--------------------------------------|-----------|----------|
| UNIDEN UA-72 DC CORD | DCC 19 | \$19.95 |
| Universal Cigarette Adaptor | DCC 3 | \$12.95 |
| Ramsey Broadband Preamp | PRE 2 | \$59.95 |
| Scantcat Gold for Windows | SFT 2W | \$99.95 |
| Scantcat Gold for Windows SE Upgrade | SFT 2SE | \$59.95 |
| Scantcat-Lite Plus | SFT 19 | \$29.95 |
| PAR VHF Intermod Filter 152MHz | FTR 152DS | \$69.95 |
| PAR VHF Intermod Filter 158MHz | FTR 158DS | \$69.95 |
| PAR VHF Intermod Filter 462MHz | FTR 462DS | \$69.95 |
| FM Trap Filter 88-108MHz | FTR-FMDS | \$69.95 |
| PAR NOAA Weather Filter 162 MHz | FTR 162DS | \$69.95 |
| Yaesu SP-8 Speaker | SPK 4 | \$159.95 |
| GRE Superamplifier | PRE 1 | \$59.95 |
| VS6 Mobile Speaker | SPK 7 | \$12.95 |

**Icom has the radio
for the experts...**



IC-R9500 ICOM'S ULTIMATE WIDE BAND RECEIVER

- 0.005 - 3335.000MHz*
- USB, LSB, CW, FSK, FM, WFM, AM
- 1020 Alphanumeric Memory Channels
- P25 (Option UT-122)
- Five Roofing Filters and so much more!

**...or for those just
getting started.**



IC-R75 WIDE BAND RECEIVER

- 0.03 - 60.0 MHz*
- Triple Conversion
- Twin Passband Tuning
- Digital Signal Processing (DSP)

Now bundled with RadioCom 4.5

Icom's black box radios now come bundled with Bonito's RadioCom 4.5 software.



PCR1500
THE "BLACK BOX"

- 0.01 ~ 3299.99 MHz*
- AM, FM, WFM, CW, SSB
- Record and Save Audio as .WAV File
- USB Cable Connection
- Optional DSP



IC-R1500
MOBILE OR PC CONTROL

- 0.01 - 3299.99 MHz*
- AM, FM, WFM, USB, LSB, CW
- 1000 Memory Channels
- Fast Scan
- Optional DSP (UT-106)
- PCR Software Included
- Very Compact Design



PCR2500
DUAL BAND "BLACK BOX"

- 0.01 ~ 3299.99 MHz* (Main)
50 to 1300 MHz* (Sub)
- AM, FM, WFM, CW, SSB
- Opt. APCO 25 and D-STAR
- Dual Wideband Receivers
- Dual Watch PC Window
- Optional DSP



IC-R2500
2 WIDE BAND RX IN 1

- 0.01 - 3299.99 MHz*
- AM, FM, WFM, SSB, CW (Main)
- AM, FM and WFM (Sub)
- 1000 Memory Channels
- Optional D-STAR (UT-118)
- Optional P25 (UT-122)
- Optional DSP

NEW IC-RX7

STYLISH SCANNER WITH SMART INTERFACE

- 0.150 - 1300.000MHz*
- AM, FM, WFM
- 1650 Alphanumeric Memory Channels
- Digital Signal Processing (DSP)
- IPX4 Water Resistant Rating



IC-R5 SPORT

COMPACT WIDE BAND

- 0.5 - 1300.0 MHz*
- AM, FM, WFM
- 1250 Memory Channels
- CTCSS/DTCS Decode
- Weather Alert



IC-R20

ADVANCED WIDE BAND

- 0.150 - 3304.0 MHz*
- AM, FM, WFM, SSB, CW
- 1000 Memory Channels
- Dual Watch Receiver
- 4 Hour Digital Recorder



Contact your favorite Authorized Icom Dealer today!



*Frequency coverage may vary. Refer to owner's manual for exact frequency specs.
©2009 Icom America Inc. The Icom logo is a registered trademark of Icom Inc. All specifications are subject to change without notice or obligation. 30161